

[Extra. ImageJ Macro Language](#)

E.6.3. Macro Functions - Practice

[Course](#) > [Programming Primer](#)> [E.6. Macro Functions](#) > Assessment

E.6.3. Macro Functions - Practice Assessment

Built-in Functions

0 points possible (ungraded)

The ImageJ Macro language has a lot of pre-existing functions that can be found using [Help > Macro Functions...](#) from Fiji, or by visiting [the ImageJ Macro functions Page](#)

Find the correct macro function to use and type it for each question

Suppose we have a hyperstack with 3 channels and 40 timepoints.

What built-in Macro function can access timepoints?

Look at the "Stack." functions



What function returns all the dimensions of an image?

Once found, you can copy it directly from the Macro functions webpage



What function should we run to duplicate channel 2 of our hyperstack?

Try it in Fiji with the Macro recorder on



✖ Incorrect

Variables in Functions

0 points possible (ungraded)

You have a series of images for which you want to duplicate the second channel using.

```
run("Duplicate...", "title=[Channel 2 Copy] duplicate channels=2");
```

Your colleague wants to use it as well, but he needs to duplicate channel 3. You decide it would be easier if the channel to duplicate were in a variable. **How would you write this?**



```
channel = 2;  
run("Duplicate...", "title=[Channel channel Copy] duplicate channels=channel");
```



```
channel = 2;  
run("Duplicate...", "title=[Channel "+channel+" Copy] duplicate channels="+channel);
```



```
channel = 2;  
run("Duplicate...", "title=[Channel +channel+ Copy] duplicate channels="+channel);
```

Submit

 Answers are displayed within the problem

Custom Functions

0 points possible (ungraded)

You have a nice workflow to set the brightness, contrast and LUT for a given channel

```
Stack.setChannel(1);  
run("Red");  
setMinAndMax(20, 235);
```

But it's tedious to copy all three lines and modify them for each channel, so you choose to make a function that encapsulates this functionality.

If you adhere to good coding practices, what would be the name and arguments of this function?



theFunction(a, b, c)



setChannelLUTMinMax(lutName, minValue, maxValue)



setChannelLUTMinMax(channelNumber, lutName, minValue, maxValue)



Submit

i Answers are displayed within the problem