Performance of the SAM ROS 2 Stack on the Jetson Orin Nano

Measurements, analysis and optimization hypotheses

Measurement report of the jxb board campaign of 2026-11-03

Data: 35 recordings with jxb on one Jetson Orin Nano 8 GB (JetPack 7.2.1). Every figure and table is generated from the raw recordings by `docs/measurements/analyze.py`. The derived datasets are in `docs/measurements/data/`, and every quoted number is in `docs/measurements/stats.json`. The system that produced the data is described in `docs/latex/jxb.pdf`.

Abstract

We characterize the performance of the SAM autonomous-driving software stack (ROS 2) on an NVIDIA Jetson Orin Nano 8 GB, using the recordings of a one-day campaign: 35 recordings, 18 of which are valid for analysis. They cover inference benchmarks, the object detector in isolation across three ROS 2 distributions and two run-time modes, the full stack, and Nsight Systems traces. A TensorRT fp16 engine runs the detector model 3.2 times faster than ONNX Runtime's CUDA execution provider (10.8 vs. 35.1 ms median) and needs 3.3 times less energy per inference (164 vs. 548 mJ). INT8 engines reach 9.0 ms and 113 mJ. In the ROS node, the median inference time is 17.15 ms with TensorRT and 46.43 ms with ONNX Runtime; the TensorRT node also uses 0.91 GB less memory and 1.1 W less power. The ROS distribution has no practically relevant effect ($\leq 0.6\,\%$). The median difference between container and native execution (+0.55 ms) is no larger than the difference between two native runs (+0.48 ms). The full stack uses 2.83 CPU cores and 2.11 GB at 8.54 W, but processes only 23–24 of the camera's 30 frames per second. Its GPU is busy 11 % of the time, and the detector slows from 17.1 to 25.1 ms although its kernels overlap with the image pipeline's for only 2.8 % of their duration. Per processed frame, the image pipeline performs 16 device memory allocations and frees (9.1 ms of CUDA API time), uploads 3.1 MB and downloads 4.9 MB. The detector uploads a 7.2 MB float32 tensor that it prepares on the CPU. System memory grows by 213–284 MB/min in the first minutes of a stack run while the processes' resident memory stays flat; a 25-minute follow-up run shows that this growth saturates after about three minutes at 3.0 GB, so there is no leak. From these observations we derive ten falsifiable optimization hypotheses with predicted effects and test procedures; the follow-up settles one of them. The most promising are buffer reuse in the image pipeline, GPU-resident data paths with GPU-side preprocessing, and decoupling the detector from its fixed 5 Hz loop.

Contents

1 Introduction **3**

2 Experimental setup and method **3**
2.1 Platform . . . 3
2.2 Workloads . . . 3
2.3 Instrumentation . . . 4
2.4 Data processing and statistics . . . 4
2.5 The campaign . . . 5

3 Results **5**
3.1 Idle baseline . . . 5
3.2 Inference backends (RQ1) . . . 5
3.3 The detector node (RQ2) . . . 5
3.4 The full stack (RQ3) . . . 7
3.5 Long-duration memory behaviour (follow-up) . . . 8
3.6 Anomalies . . . 9

4 GPU-level analysis **9**

5 Discussion **11**
5.1 Answers to the research questions . . . 11
5.2 A frame-cost model . . . 12
5.3 The observer effect . . . 12

6 Optimization hypotheses (RQ4) **14**

7 Threats to validity **18**

8 Conclusion **19**

A All recordings **19**

B Telemetry before the reset **20**

C Reproduction **20**

1 Introduction

The SAM vehicle runs its perception, planning and control software as a ROS 2 stack on a Jetson Orin module. The platform's resources are tight: 8 GB of memory that CPU and GPU share, six CPU cores, a 25 W power mode and passive cooling. Whether the stack can process its 30 fps camera stream, how much headroom remains for further functions, and where optimization effort pays off are therefore engineering questions with a direct impact on the vehicle's capabilities. This report answers them with measurements. The data was recorded with `jxb`, the cross-development and observability environment described in the companion document (`jxb.pdf`).

We address four research questions:

RQ1 Which inference backend and numeric precision gives the best latency and energy for the SAM detector model on the Orin Nano?

RQ2 Do the ROS 2 distribution (Jazzy, Kilted, Lyrical) or the run-time mode (native, container) affect the detector's performance?

RQ3 What is the resource profile of the full stack, and where are its bottlenecks?

RQ4 Which optimizations are most promising, and how can their effect be tested?

Section 2 describes the setup and the measurement and analysis method, Section 3 the results, Section 4 a GPU-level analysis based on Nsight Systems, and Section 5 discusses them. Section 6 derives optimization hypotheses (RQ4), Section 7 discusses threats to validity.

2 Experimental setup and method

2.1 Platform

Table 1: Hardware and software.

Board	Jetson Orin Nano 8 GB: 6 Arm Cortex-A78AE cores, Ampere GPU (`sm_87`), 7.3 GB usable shared memory, NVMe; 25 W power mode
System	JetPack 7.2.1 (L4T 39.2.1, Ubuntu 24.04), PREEMPT_RT kernel 6.8.12; CUDA 13.2, TensorRT 10.16.2, cuDNN 9.25
Inference	ONNX Runtime 1.31 with CUDA and TensorRT execution providers (built by `jxb` for `sm_87`); `trtexec`
ROS 2	Jazzy (the board's own), Kilted and Lyrical (NVIDIA Isaac ROS Buildfarm) shipped by `jxb`; Lyrical on Ubuntu 26.04 in a container
Containers	runtime images created from the sysroots; GPU via CDI; container runs use Cyclone DDS, native runs the distribution's default (Fast DDS)
Host	x86_64 PC; all builds cross-compiled, all recordings controlled over SSH

2.2 Workloads

- **Inference benchmark.** The SAM detector model S0 (YOLO, s size, fp32, input $1 \times 3 \times 608 \times 960$) and four quantized variants: P1 (post-training quantization), S2 (quantization-aware training), Q4 (fully INT8) and S3 (quantization-aware, n size). The backends are ONNX Runtime with the CPU, CUDA and TensorRT execution providers (EPs), and native TensorRT engines through `trtexec`. Each backend runs 200 iterations after 20 warm-up iterations (CPU: 10 after 2); `trtexec` uses its default measurement duration of about 3 s.
- **Detector node.** SAM's `object_detection` node, fed by `jxb`'s synthetic camera (`jxb_image_pub.py`). The camera publishes a 960×608 road scene at 30 Hz directly on the detector's input topic, so the image pipeline is bypassed. The ONNX Runtime runs use the deployed

`model.onnx`, which is byte-identical (MD5) to the S0 benchmark model. The TensorRT runs use the engines that the benchmark built from S0 (fp16) and S2 (INT8). The node runs inference in a fixed 5 Hz loop.

- **Full stack.** `launch/launch.py module:=parking`: core functions, image pipeline, object detection, parking and traffic lights; 12 processes, or 18 with `use_global_composition:=false`. The synthetic camera publishes 1280 × 800 images and a matching camera info at 30 Hz.

2.3 Instrumentation

All recordings were made with `jxb` and hold the board's measurement lock, so they did not overlap with other users' measurements on the shared board.

- **tegrastats**: CPU, GPU and memory-controller load, memory, temperatures and power rails at a nominal interval of 500 ms. The interval is in fact 1.2 % longer: the benchmark runs' summed wall times exceed the nominal duration of their tegrastats logs by 1.18–1.25 %. Time axes are stretched accordingly where alignment matters.
- **Per-process sampler**: `/proc/<pid>/stat` of every process once per second. Processes are attributed to a session by ancestry (descendants of the session's shell or of its container's init).
- **rosbag2** (MCAP) of selected topics, with numeric topics exported to CSV. The detector publishes its per-frame inference time on `/object_detection/inference_time`.
- **Rate probes** (stack runs only): `ros2 topic hz` on the undistorted image topic and on the detection image topic.
- **Nsight Systems**: CUDA, NVTX, OS runtime, cuBLAS/cuDNN, and process-tree CPU sampling.

2.4 Data processing and statistics

Analysis method

- **Warm-up.** The first five inference samples of a run (the first second at 5 Hz) are excluded and the first inference is reported separately. Telemetry means exclude the first 5 s and the last 3 s of a recording (stack: the first 10 s).
- **Location and uncertainty.** We report medians. Their 95 % confidence intervals come from a moving-block bootstrap [1] with blocks of 10 consecutive samples and 4000 resamples. The blocks preserve the autocorrelation of the time series, which an ordinary bootstrap would ignore and which would make it too optimistic [2].
- **Effect size.** For two samples X, Y, Cliff's $\delta = P(Y > X) - P(Y < X)$ [3]. We call $|\delta| < 0.147$ negligible, < 0.33 small, < 0.474 medium and larger values large [4].
- **Energy per inference.** $E_{\text{inf}} = \bar{P}/r$, with $\bar{P}$ the mean board input power (`VDD_IN`) during the benchmark's measurement loop and r its throughput. $E_{\text{dyn}} = (\bar{P} - P_{\text{idle}})/r$ is the share above idle. Benchmark runs are sequential, so the loop of each run is located at the end of its segment in the stretched tegrastats time axis. A window is accepted only if it is at least 2.5 s long and, for GPU backends, shows a mean GPU load of at least 40 %. This rejects six of the 22 windows, all of them shorter loops.
- **Memory.** "RSS" is the resident set size from `/proc`. Session sums count shared pages once per process and therefore overestimate the physical memory. 1 GB means 1024 MB here, as in the kernel's accounting.
- **Idle baseline.** The idle board is characterized by 7399 tegrastats samples from the tail of a recording after its workload had ended (GPU idle, Section 3.1).

2.5 The campaign

Table 9 in Appendix A lists all 35 recordings. Eighteen are valid for analysis. Nine are failed starts: the shipped Kilted and Lyrical runtimes lacked packages that the SAM launch files use without declaring them (`topic_tools`, `foxglove_bridge`, `osrf_pycommon`). These failures led to the dependency scan and the Python module shipping that `jxb` now performs (`F52`, `F60`, `F61`). One recording ends with a reset of the board (Section 3.6). In one stack recording the image pipeline produced no output, one early recording predates the sampler's ancestry attribution and one lacks its bag; these three are excluded. Two runs were repeated under identical conditions and serve as replicates. A follow-up recording on 2026-11-04 tests hypothesis **H7** (Section 3.5).

3 Results

3.1 Idle baseline

The idle board draws $P_{\text{idle}} = 5.02\,\text{W}$ at its input (standard deviation 0.08 W). Of this, 1.10 W is on the CPU/GPU/CV rail, 1.37 W on the SoC rail and 2.55 W in the rest of the module (memory, I/O, conversion losses). 1.29 GB of memory is in use, the CPU load is 0.3 % and the junction temperature 48.2 °C. Every power figure below should be read against this baseline: even the idle board consumes more than half of the full stack's power.

3.2 Inference backends (RQ1)

Figure 1 and Table 2 show the benchmark. Three results stand out.

TensorRT is the decisive factor. The fp16 engine runs the S0 model in 10.81 ms (median, `trtexec`), 3.2 times faster than ONNX Runtime's CUDA EP (35.08 ms) and 33 times faster than the CPU (354.99 ms). ONNX Runtime's TensorRT EP comes within 10 % of the native engine (11.91 ms), so an application can keep the ONNX Runtime API and still obtain most of the speed-up. The latency distributions of the TensorRT backends are narrow (p99/p50 = 1.11 for `trtexec` fp16) compared with the CPU (1.45).

INT8 gains less than precision suggests. The INT8 engines of the s-sized models need 8.92–9.10 ms, 16–18 % less than fp16. The n-sized S3 model reaches 6.75 ms: on this GPU, model size is the larger lever. Without TensorRT, quantization hurts: the Q/DQ models take 47.3 ms on the CUDA EP (35.1 ms for fp32) and 409–412 ms on the CPU (355 ms), because the quantize and dequantize nodes are executed as such instead of being fused into integer kernels.

Energy follows latency, not power. During the measurement loops, the board draws 12–16 W for every GPU backend (Fig. 2). Faster backends therefore need proportionally less energy per inference: 548 mJ with the CUDA EP, 359 mJ with the fp32 engine, 164 mJ with fp16, 113–120 mJ with INT8 and 81 mJ with the INT8 n-model. Above idle, the fp16 engine needs 109 mJ against 372 mJ for the CUDA EP, a factor of 3.4.

3.3 The detector node (RQ2)

Tables 3 and 4 and Figs. 3 and 4 summarize the detector runs.

Backend. In the node, the median inference time is 46.43 ms with ONNX Runtime's CUDA EP, 17.15 ms with the TensorRT fp16 engine and 15.10 ms with the INT8 engine (Jazzy, native). TensorRT reduces it to 0.369 of the ONNX Runtime value, 95 % CI [0.369, 0.370]. The distributions do not overlap at all (Cliff's $\delta = -1$). The node adds about 6 ms to the engine's own latency with TensorRT (17.15 vs. 10.81 ms; INT8: 15.10 vs. 9.02 ms) and 11 ms with ONNX Runtime (46.43 vs. 35.08 ms). Section 4 traces this overhead to preprocessing on the CPU and the upload of a float32 tensor. TensorRT also changes the node's footprint: 0.53 instead of 1.44 GB of resident memory



Figure 1: Inference latency per model and backend (log scale). Dot: median; tick: p90; end of the line: p99. Colour: backend family; shape: ONNX Runtime or `trtexec`.

(−0.91 GB), 5–8 instead of 15–19 % GPU load, and 5.85 instead of 6.97 W (−1.1 W). Since the node works at a fixed 5 Hz (measured: 5.00 Hz, inter-arrival standard deviation 0.3–0.6 ms), the energy per detection falls from 1.39 to 1.17 J at the board input. Above idle it falls from 0.39 to 0.17 J.

Cold start. The first inference takes 1.50–1.62 s with the CUDA EP, which selects and loads its kernels lazily, but only 34–87 ms with a deserialized TensorRT engine.

Distribution. Between Jazzy and Kilted, the median changes by −0.10 ms (TensorRT, $\delta = -0.37$) and +0.07 ms (ONNX Runtime, $\delta = +0.23$). Both differences are statistically detectable but below 1 % and practically irrelevant. Under Lyrical (Isaac Buildfarm, native) the node's memory, CPU and power match the other distributions (Fig. 4). Its inference times were not recorded, because bag recording failed with the Lyrical runtimes at the time (fixed since, `F68`). Two 25-second verification runs after the fix, outside the campaign, give medians of 17.27 ms for Lyrical on Ubuntu 24.04 and 19.43 ms for Lyrical on Ubuntu 26.04 in its container; the latter difference would need replicates before it can be interpreted.

Run-time mode and replicate. In the container, the median is 0.55 ms higher than natively (95 % CI [0.50, 0.59], $\delta = +0.94$). A second native run under identical conditions, however, differs from the first by +0.48 ms ($\delta = +0.92$), and its resident memory (0.68 GB) equals the container's (Fig. 3b). The container effect is therefore not separable from run-to-run variation. Within this design, the container costs at most about 0.6 ms (3 %) and no measurable memory. The comparison is also confounded by the DDS implementation (Cyclone DDS in the container, Fast DDS natively).

Revision of an earlier conclusion

The system documentation (`jxb.pdf`, based on single runs) reported a container overhead of +0.6 ms and +155 MB. The replicate shows that both differences are within the run-to-run variation of the native configuration.




Figure 2: Energy per inference at the board input for the validated measurement windows. The grey part is the share of the idle power (P_{idle}/r); the coloured part is the energy above idle.

3.4 The full stack (RQ3)

Table 5 and Figs. 5 and 6 characterize the full stack. In every configuration, all processes started and stopped cleanly.

Load. With the TensorRT fp16 detector, the stack runs at 2.83 CPU cores (60 % mean load of the six cores), 2.11 GB summed peak resident memory, 13.8 % mean GPU load and 8.54 W, which is 3.52 W above idle. The maximum junction temperature is 53.0 °C. The composable-node container of the image pipeline dominates with 1.64 cores, 58 % of the session's CPU. It is followed by the measurement and launch tools (0.39 cores), the synthetic camera (0.36), the detector (0.33) and ten other nodes (0.11 together). With ONNX Runtime instead of TensorRT, the stack needs 0.10 cores and 0.81 GB more and draws 1.16 W more, and its GPU load doubles to 29.7 %. In the container the stack is indistinguishable from native execution within single runs: 2.75 cores, 2.07 GB, 8.51 W.

Composition. With one process per node, the session needs 2.36 cores. This configuration ran without bag recorder and rate probes, however: its tools use 0.02 cores instead of 0.39. The image pipeline's own CPU is the same in both arrangements (1.57 vs. 1.64 cores), while its seven separate processes hold 0.74 instead of 0.52 GB. Composition thus saves memory, partly by sharing library pages, but no measurable CPU. This suggests that intra-process communication does not take effect in the composed container (**H2**).

Throughput. The camera delivers 30 frames per second, but lane points are produced at 23.3 Hz, and the Nsight Systems trace (without rate probes) shows the image pipeline processing 24.2 frames per second. A fifth of the frames is lost before the lane detection. The rate probe on the undistorted image topic (`ros2 topic hz`) reports only 19.8–20.5 Hz (Fig. 7). It has to receive every 1280 × 800 image (3 MB) in a separate process, and on the loaded board it under-reports the rate. Detections arrive at the node's 5 Hz.

Detector under load. Inside the stack, the detector's median inference time rises from 17.05 to 25.12 ms (×1.47, CI of the difference [7.59, 8.46] ms) and its p99 to 36.3 ms. With ONNX Runtime it rises from 46.50 to 60.21 ms (×1.30).

Power. Figure 9 decomposes the board power. From idle to the full stack, the CPU/GPU/CV rail grows from 1.10 to 3.25 W (+2.15 W). This is the largest increase, consistent with a CPU-heavy workload. The rest of the module grows by 0.92 W, which we attribute mainly to memory traffic, and the SoC rail by 0.45 W.

Memory growth. In every stack configuration, the system's used memory grows linearly while the stack runs: +284 MB/min natively, +255 MB/min in the container, +215 MB/min with ONNX

Table 2: Inference benchmark. $\bar{P}$: mean board input power in the measurement loop; GPU: mean GPU load in the same window; E_{inf}, E_{dyn}: energy per inference, total and above idle. Missing values: windows rejected by the validity rule of Section 2.4.

Model	Backend	p50 [ms]	p99 [ms]	Rate [1/s]	$\bar{P}$ [W]	GPU [%]	E_{inf} [mJ]	E_{dyn} [mJ]
S0 fp32	ORT CPU	354.99	515.09	2.5	8.54	0	3416	1409
	ORT CUDA EP	35.08	36.14	28.5	15.62	95	548	372
	ORT TensorRT EP fp32	22.55	27.35	43.8	14.05	59	321	206
	ORT TensorRT EP fp16	11.91	14.07	82.1	–	23	–	–
	trtexec fp32	21.87	25.55	45.2	16.22	83	359	248
	trtexec fp16	10.81	11.96	90.9	14.89	71	164	109
P1 PTQ INT8	ORT CPU	409.39	415.86	2.4	8.60	0	3583	1493
	ORT CUDA EP	47.29	47.83	21.1	14.95	91	708	471
	ORT TensorRT EP INT8	9.71	10.80	101.6	–	0	–	–
	trtexec INT8	9.10	9.49	109.1	13.10	71	120	74
S2 QAT INT8	ORT CPU	410.06	415.32	2.4	8.73	0	3636	1545
	ORT CUDA EP	47.34	47.83	21.1	14.82	90	702	465
	ORT TensorRT EP INT8	9.70	10.96	101.5	–	0	–	–
	trtexec INT8	9.02	9.78	110.2	12.44	56	113	67
S3 QAT INT8 (n)	ORT CPU	151.04	156.99	6.6	–	0	–	–
	ORT CUDA EP	26.88	27.32	37.2	13.34	83	359	224
	ORT TensorRT EP INT8	7.38	8.69	134.3	–	0	–	–
	trtexec INT8	6.75	7.18	146.6	11.81	72	81	46
Q4 full INT8	ORT CPU	412.46	428.20	2.4	8.70	0	3623	1533
	ORT CUDA EP	47.83	48.38	20.9	14.88	94	712	472
	ORT TensorRT EP INT8	9.59	10.90	102.4	–	0	–	–
	trtexec INT8	8.92	9.19	111.4	13.31	70	120	75

Runtime and +213 MB/min per node, without bag recorder and probes (Fig. 8). The summed resident memory of the session's processes stays flat (−4 to +11 MB/min). The growth is therefore not process memory, and the bag recorder does not cause it. If it continued linearly, the remaining 4.5 GB would be exhausted within another 16–21 minutes. The follow-up run of Section 3.5 shows that it does not continue (**H7**).

3.5 Long-duration memory behaviour (follow-up)

To decide **H7**, the stack was run for 25 minutes on 2026-11-04 in its TensorRT configuration (Kilted, native, INFO logging as before), without bag recorder and rate probes. Next to the per-process sampler, `jxb` recorded the kernel's memory counters (`/proc/meminfo`) every second. A memory guard would have stopped the launch below 1.2 GB of available memory; it did not fire. All 12 processes ran and stopped cleanly; the session used 2.60 cores, 1.85 GB summed peak resident memory and 8.33 W, and the junction temperature stayed below 55 °C.

The used memory rises steeply during the first two minutes (+322 MB/min) and slower until the third (+34 MB/min), and then stays at 2.99 GB (3057 MB), against 1.17 GB before the start (Fig. 10). From minute 10 on it grows by only 3 MB/min, and the page cache grows by 5 MB/min, as the ROS log files grow. `Shmem` (5 MB), `Slab` and unreclaimable kernel memory stay constant; `MemAvailable` settles at 4.27 GB. The recordings of Section 3.4, two minutes long, captured only this warm-up. The session's resident memory reaches its level within 10 s, so the slower ramp of the used memory is memory outside the processes' resident sets that is allocated while the pipeline warms up. Device memory allocated through the CUDA driver, such as stream-ordered memory pools, is an explanation consistent with this; the counters available without root cannot attribute

Table 3: The detector node with the synthetic camera. Median with 95 % block-bootstrap interval; Det. CPU/RSS: the detector process; GPU and $\bar{P}$: board means; E_{det}: board energy per detection. Runs marked – have no per-frame inference data.

Configuration	n	Median [ms] (95 % CI)	p99 [ms]	Rate [Hz]	Det. CPU [cores]	Det. RSS [GB]	GPU [%]	$\bar{P}$ [W]	E_{det} [J]
Jazzy ORT CUDA EP	199	46.43 (46.40–46.46)	46.9	5.00	0.17	1.44	15.4	6.97	1.39
Jazzy ORT CUDA EP (rep.)	–	–	–	–	0.19	1.43	19.3	7.00	–
Jazzy TRT fp16	207	17.15 (17.14–17.17)	18.3	5.00	0.11	0.53	5.1	5.85	1.17
Jazzy TRT INT8 (QAT)	206	15.10 (15.08–15.12)	16.3	5.00	0.12	0.52	5.5	5.67	1.13
Kilted ORT CUDA EP	202	46.50 (46.47–46.54)	46.9	5.00	0.23	1.44	16.4	7.07	1.41
Kilted TRT fp16	210	17.05 (17.02–17.09)	17.5	5.00	0.14	0.54	7.3	5.91	1.18
Kilted TRT fp16 (rep.)	131	17.53 (17.50–17.55)	18.3	5.00	0.13	0.68	6.6	5.90	1.18
Kilted TRT fp16, container	205	17.60 (17.57–17.63)	18.3	5.00	0.15	0.68	8.1	5.97	1.19
Lyrical ORT CUDA EP	–	–	–	–	0.21	1.55	18.5	6.99	–
Lyrical TRT fp16	–	–	–	–	0.13	0.63	5.8	5.89	–
Lyrical 26.04 TRT fp16, container	–	–	–	–	0.17	0.68	5.0	5.92	–

Table 4: Pairwise comparisons of the detector's inference time: median difference with 95 % block-bootstrap interval, ratio of medians, Cliff's δ (positive: y slower).

Factor	Comparison ($x \to y$)	$\tilde{y} - \tilde{x}$ [ms] (95 % CI)	$\tilde{y}/\tilde{x}$	Cliff's δ	n_x/n_y
backend	ORT CUDA EP → TensorRT fp16 (Jazzy)	-29.28 (-29.31 to -29.25)	0.369	-1.00	199/207
backend	TensorRT fp16 → INT8 (Jazzy)	-2.05 (-2.08 to -2.02)	0.881	-1.00	207/206
distro	Jazzy → Kilted (TensorRT fp16)	-0.10 (-0.14 to -0.06)	0.994	-0.37	207/210
distro	Jazzy → Kilted (ORT CUDA EP)	+0.07 (+0.03 to +0.11)	1.001	+0.23	199/202
mode	native → container (Kilted, TensorRT fp16)	+0.55 (+0.50 to +0.59)	1.032	+0.94	210/205
replicate	run → replicate (Kilted TensorRT fp16)	+0.48 (+0.42 to +0.51)	1.028	+0.92	210/131
load	alone → in the stack (TensorRT fp16)	+8.07 (+7.59 to +8.46)	1.473	+1.00	210/569
load	alone → in the stack (ORT CUDA EP)	+13.71 (+13.18 to +14.23)	1.295	+1.00	202/559

it further.

3.6 Anomalies

The reset. The board reset about 4 s into a run of the detector with ONNX Runtime's CUDA EP inside the Kilted runtime container, while the EP was initializing (`F56`). Table 10 shows the last telemetry before the reset: memory rising from 1.39 to 1.50 GB as the model loads, CPU load up to 44 %, GPU idle, at most 6.7 W and 49–50 °C. At this resolution no thermal or power anomaly precedes the reset. Its cause remains unknown without the kernel's panic log, which requires root.

Long nsys sessions. In two Nsight Systems recordings, the session stayed open long after the workload had ended (508 s and 3800 s). Nsight Systems waits for every process of the profiled tree, including processes that survive the workload. The first case is the launch that died at start (`F62`). For these recordings, telemetry means would be dominated by the idle tail; we restrict the analysis to the GPU-active window. The tail of the second recording provides the idle baseline.

4 GPU-level analysis

The Nsight Systems trace of the full stack (TensorRT fp16, without rate probes) explains the throughput limit. Its GPU-active window lasts 25.9 s and contains 29 440 kernels; the GPU is busy 11.1 % of the window. Figures 11 and 12 and Table 6 summarize it.

The image pipeline is not GPU-bound. It launches seven kernels per frame (image warp




Figure 3: Empirical distribution functions of the detector's per-frame inference time. (a) Backends; (b) TensorRT fp16 across distributions, run-time modes and a replicate; (c, d) the node alone and inside the full stack.

0.95 ms, remap 0.49 ms, a vertical mean-and-threshold step 0.27 ms, . . .), 2.17 ms of GPU time per frame. At that cost the GPU could serve more than 400 frames per second. Instead, each frame costs 14.6 ms of blocking CUDA API time in 36.5 calls. Of these, 16 calls (9.1 ms) allocate or free device memory: seven pairs of `cudaMalloc`/`cudaFree` and one pair of `cudaMallocAsync`/`cudaFreeAsync` per frame. `cudaFree` implicitly synchronizes the device, so these calls also serialize the pipeline. Allocations and frees are balanced in both GPU processes (`cudaMalloc` 4394, `cudaFree` 4397; async 627/627), so the trace shows no device memory leak. Per frame, the pipeline uploads 3.09 MB (one RGB frame) and downloads 4.94 MB (1.6 frames). On a SoC whose CPU and GPU share the same DRAM, these copies move data within the same physical memory. `memcpy` is the hottest CPU function of the image pipeline (12.4 % of its CPU samples), followed by atomic exchange and compare-and-swap primitives, which indicate lock traffic.

The detector's slowdown is not GPU contention. In the stack, an inference takes 196 kernels and 12.2 ms of GPU time, 16 % more than the engine's 10.5 ms GPU compute time in isolation. The detector's kernels overlap with those of the image pipeline for only 44 ms of their 1560 ms (2.8 %), however. Most of the 8 ms increase of the inference time must therefore arise outside the GPU kernels. Candidates are CPU-side pre- and postprocessing on a busy CPU, waits, and memory bandwidth. The detector's CPU profile supports this: besides `memcpy`, OpenCV's float32 channel split and subtraction (`cv::hal::split32s`, `cv::hal::sub32f`) appear among its hottest functions. The node prepares the normalized float32 input on the CPU and uploads it: 7.2 MB per inference, the size of a $1 \times 3 \times 608 \times 960$ float32 tensor.

ONNX Runtime's CUDA EP. In the isolated benchmark, the GPU is busy only 52.6 % of the CUDA EP's active window, against 78.4 % with the TensorRT EP. `cudaMemcpyAsync` takes 962 ms of API time for 672 calls, while the copy engine needs 55 ms for the 430 MB involved: the inputs come from pageable host memory and are staged synchronously. Layout conversions (`nchwToNhwcKernel`) take 6.4 % of the GPU time.




Figure 4: Resources of the detector node per configuration: CPU and resident memory of the detector process, mean GPU load and board power.

Table 5: The full stack (120 s each, Kilted). CPU: session share in cores; RSS: summed peak resident memory; GPU, $\bar{P}$: means after the start-up phase; $P_{\mathrm{dyn}} = \bar{P} - P_{\mathrm{idle}}$; Lanes: lane-point rate (bag); Undist.: median of the rate probe on undistorted images; RAM slope: growth of the system's used memory. *: one process per node, without bag recorder and rate probes.

Configuration	CPU [cores]	RSS [GB]	GPU [%]	$\bar{P}$ [W]	P_{dyn} [W]	Lanes [Hz]	Undist. [Hz]	Inference p50/p99 [ms]	RAM slope [MB/min]
ORT CUDA EP, native	2.93	2.92	29.7	9.70	4.68	23.2	19.8	60.2 / 78.0	215
TRT fp16, native	2.83	2.11	13.8	8.54	3.52	23.3	20.0	25.1 / 36.3	284
TRT fp16, container	2.75	2.07	14.0	8.51	3.50	23.3	20.5	25.3 / 39.9	255
TRT fp16, native, per node*	2.36	1.92	14.3	8.25	3.24	–	–	–	213

5 Discussion

5.1 Answers to the research questions

RQ1. TensorRT engines are the most efficient backend by a wide margin, in latency (3.2× against the CUDA EP) and in energy (3.3×). INT8 adds 16–18 % for the s-sized model; the n-sized INT8 model is the fastest option at 6.75 ms. ONNX Runtime's TensorRT EP retains most of the benefit (+10 % latency) while keeping the ONNX Runtime API. Quantized models must not run without TensorRT.

RQ2. Neither the ROS 2 distribution nor the run-time mode has a practically relevant effect on the detector: distribution effects stay below 1 %, and the container effect (+0.55 ms) is as large as the variation between two native runs (+0.48 ms). The choice between native and container execution, and between Jazzy, Kilted and Lyrical, can therefore be made on functional grounds.

RQ3. The full stack uses less than half of the board's CPU capacity, an eighth of its GPU and a third of its 25 W budget, yet it does not keep up with the camera. The bottleneck is the image pipeline's data handling: device memory allocated and freed several times per frame, frames copied between host and device memory although both are the same DRAM, CPU-side copies and lock traffic. The arithmetic itself costs little. The detector's slowdown in the stack has the same root: it competes for CPU and memory, not for the GPU.




Figure 5: CPU share and peak resident memory of the stack by process category.

Table 6: Cost of one processed frame in the image pipeline (Nsight Systems, full stack, TensorRT fp16).

Quantity (image pipeline, per processed frame)	Value
processed frames in the GPU-active window	627 (24.2 Hz)
GPU kernel time	2.17 ms
CUDA runtime API time (blocking, summed over threads)	14.62 ms
CUDA runtime API calls	36.5
device allocations and frees (`cudaMalloc`, `cudaFree`, async variants)	16.0 calls, 9.11 ms
host-to-device copies	3.09 MB
device-to-host copies	4.94 MB
copy engine time	1.08 ms
share of CPU samples in `memcpy` (leaf)	12.4 %

5.2 A frame-cost model

At 30 Hz, a frame must pass the pipeline every 33.3 ms. The image pipeline spends 2.2 ms of GPU time per frame but 14.6 ms in blocking CUDA calls and, measured by its CPU share, 1.64/24.2 Hz = 68 ms of CPU time per frame across its threads. If the per-frame API time lies on the critical path, it alone takes 44 % of the frame budget. Removing the allocation calls (9.1 ms) would shorten that path by more than the remaining margin to 30 Hz. This is the quantitative basis of **H1**.

5.3 The observer effect

The measurement tools are not free. The bag recorder and the two Python rate probes use 0.37 cores, 13 % of the session's CPU. The probes also add DDS subscribers to large image topics, which costs the publishers copies. The probe on the undistorted images even underestimates the rate it measures. Lightweight probes are therefore a prerequisite for precise A/B experiments on the stack (**H8**). The 1 s per-process sampler costs 0.9–1.1 % of one core.




Figure 6: Board telemetry of three stack runs over time: mean CPU load, GPU load, used memory and board power. The GPU load shows periodic bursts with a period of about 6–7 s; the data does not reveal their cause (the synthetic scene repeats every 2 s).




Figure 7: Rates reported by the rate probes about once per second: (a) undistorted images, (b) detection images.




Figure 8: Used system memory (tegrastats) and summed resident memory of the session's processes during two stack runs, with linear slopes over the steady phase.

6 Optimization hypotheses (RQ4)

Each hypothesis states the observation it rests on, the mechanism, a quantified prediction and an experiment that can falsify it with jxb. Table 7 ranks them by expected benefit and effort.

H1: Reusing device buffers in the image pipeline raises its frame rate

Observation. 16 allocation and free calls per frame, 9.1 ms of blocking API time; `cudaFree` synchronizes the device (Table 6).

Mechanism. Frame-sized buffers are allocated per frame. Preallocating them once (buffer pool, CV-CUDA tensor reuse) or using the stream-ordered allocator with a memory-pool release threshold removes the calls and the implicit synchronization.

Prediction. The allocation calls per frame drop from 16 to about 0; the image pipeline reaches at least 28 Hz with the 30 Hz camera (lane points $\geq$ 28 Hz); its CPU share falls by 10–25 %.

Test. Patch the image processing component; record `jxb trace nsys` (allocations per frame) and `jxb launch --monitor --bag` (lane-point rate, CPU) before and after, three runs each.




Figure 9: Mean board input power split into the measured rails, from the idle board to the full stack.




Figure 10: The 25-minute follow-up run: used memory, summed resident memory of the session, page cache and available memory. The growth seen in the two-minute recordings is a warm-up of about three minutes.

H2: A GPU-resident data path removes most copies and CPU memcpy

Observation. Per frame 3.1 MB host-to-device and 4.9 MB device-to-host; `memcpy` is the image pipeline's hottest CPU function (12.4 %); composition saves no CPU against separate processes.
Mechanism. CPU and GPU share the DRAM, so frames can stay in device-accessible memory (pinned and mapped host memory, or unified memory, see the CUDA for Tegra notes [5]). Between composed nodes they can be passed without serialization through intra-process communication with type adaptation (REP 2007 [6]) or Lyrical's `rosidl::Buffer` CUDA backend.
Prediction. Copy volume per frame below 1 MB; `memcpy` below 3 % of the image pipeline's samples; image pipeline CPU −20 %; "rest of the module" power −0.2 to −0.4 W.
Test. `jxb trace nsys` (copy volume, CPU samples) and `--monitor` (CPU, rails) before and after.




Figure 11: Nsight Systems: top kernels and CUDA runtime API calls by total time in the stack trace (a, b) and in the ONNX Runtime CUDA EP benchmark (c, d). Colour: process role.

H3: Preprocessing on the GPU shortens the detector's node overhead

Observation. About 6 ms between engine latency and node inference time (TensorRT); 7.2 MB float32 upload per inference; OpenCV float32 split and subtract among the detector's hottest functions.
Mechanism. Upload the 8-bit image (1.75 MB at 960 × 608) and convert, normalize and transpose it on the GPU (CV-CUDA or a preprocessing layer in the engine). Models with 8-bit NHWC input, such as SAM's newer YOLO26 models (`F55`), make this the default.
Prediction. Node overhead from 6 to 2–3 ms alone (inference time about 13–14 ms with fp16); a larger gain in the stack, where the CPU is contended (25.1 ms → below 20 ms); detector CPU −0.05 to −0.1 cores.
Test. Bag inference time alone and in the stack; host-to-device volume per inference in nsys.

H4: Scheduling priorities contain the detector's slowdown in the stack

Observation. +8.1 ms median and p99 of 36 ms in the stack, with 2.8 % kernel overlap.
Mechanism. The detector's CPU threads compete with the image pipeline on a PREEMPT_RT kernel. Real-time priorities (`SCHED_FIFO`) and CPU affinity for the detector, and a high-priority CUDA stream for its inference, shorten its waits.
Prediction. In-stack median below 20 ms and p99 below 25 ms, at unchanged total CPU.
Test. Launch the node with `chrt/taskset` as launch prefix; `jxb trace kernel` for the wakeup latency of the detector's threads (needs root); A/B of the bag's inference times.

H5: Decoupling inference from the 5 Hz timer multiplies the detection rate

Observation. The node infers at a fixed 5 Hz; with TensorRT, its GPU is busy only 5–8 % and an inference takes 17 ms.
Mechanism. Event-driven inference on every new frame, or a configurable rate.
Prediction. Detections at the image pipeline's rate (20–30 Hz) for +1.5 to +2.5 W. Alternatively, at 5 Hz, the INT8 n-model lowers the energy per detection.
Test. Rate sweep (5, 10, 15, 20, 30 Hz) with `jxb launch --monitor --bag`: detection rate, inference time, power.




Figure 12: One second of GPU activity in the stack: the image pipeline's per-frame kernel bursts with their copies, and the detector's 5 Hz inferences. The GPU is idle most of the time; gaps in the image pipeline's rhythm are frames it did not process.

H6: TensorRT as the default backend (actionable now)

Observation. −63 % node inference time, −0.91 GB, −1.1 W against the CUDA EP; the TensorRT EP of ONNX Runtime is within 10 % of native engines.
Recommendation. Deploy the fp16 engine, or the ONNX Runtime TensorRT EP with fp16 and an engine cache. Use INT8 if its accuracy is acceptable. Already validated by this campaign.

H7: The memory growth is reclaimable and saturates (tested: confirmed)

Observation. +213 to +284 MB/min of used memory with flat process RSS, with and without bag recorder; balanced device allocations.
Competing explanations. (a) Memory that is not attributed to processes but grows without bound, such as driver or kernel allocations (a leak; out of memory after about 16–21 min). (b) Reclaimable caches or shared memory segments, for example of the DDS transports, which saturate.
Prediction (b). During a 30-minute run the growth flattens, and `MemAvailable` in `/proc/meminfo` stays above 3 GB.
Test. A 30-minute stack run with `/proc/meminfo` (`Cached`, `Shmem`, `Slab`, `MemAvailable`) and `/dev/shm` logged every second next to tegrastats. Because (a) would make the stack fail in the field, this test has the highest priority.
Result (2026-11-04). Explanation (b): the growth saturates after about three minutes at 2.99 GB used memory, `MemAvailable` stays at 4.27 GB, and the remaining growth (3 MB/min) is page cache (Section 3.5).

H8: Lightweight probes reduce the observer effect

Observation. Tools use 0.37 cores; the probe on the image topic under-reports the rate (20 vs. 23–24 Hz).
Mechanism. `ros2 topic hz` already subscribes without deserializing; its cost is the transport of every 3 MB image into the probe process (about a quarter of a core per probe, F70). Measuring on a small per-frame companion topic (the camera info), on downstream topics or at the publisher (ROS 2 topic statistics) avoids that transport. `jxb`'s rate probe (`--rates`) measures all topics in one process with the publishers' reliability.
Prediction. Tools below 0.1 cores; probe rates equal to the lane-point and nsys frame rates.

H9: The power mode can be traded for frame rate or efficiency

Observation. The stack uses 8.5 W of the 25 W mode, and its bottleneck is CPU-side.
Mechanism. Higher CPU clocks (MAXN) speed up the CPU-bound pipeline; a lower mode saves energy where 30 Hz is not needed.
Prediction. Frame rate scales with the CPU clock until H1–H2 remove the bottleneck.
Test. An `nvpmodel` sweep. This changes the shared board's configuration and requires root and the owners' consent.

Table 7: Hypotheses ranked by expected benefit and effort.

Rank		Expected benefit	Effort
1	**H6**	−63 % inference time, −0.9 GB, −1.1 W; validated	configuration
2	**H1**	image pipeline at the camera rate (24 → ≥ 28 Hz)	code change in one component
3	**H3**	detector −3 to −5 ms alone, more in the stack	preprocessing change or model with 8-bit input
4	**H2**	most copies and CPU memcpy removed; lower memory power	design change across components
5	**H5**	4–6× detection rate at +1.5–2.5 W	parameter or callback change
6	**H4**	bounded detector latency under load	launch configuration, root for verification
7	**H8**	more precise experiments	tooling
8	**H9**	frame rate or energy trade-off	board configuration (shared)
9	**H10**	faster CUDA EP	only if ONNX Runtime stays
–	**H7**	tested: no out-of-memory risk, the growth saturates	done (Section 3.5)

H10: If ONNX Runtime stays, pinned input buffers cut the CUDA EP's staging cost

Observation. 1.4 ms per synchronous `cudaMemcpyAsync` from pageable memory; GPU busy 52.6 %.
Mechanism. IOBinding with pinned or device input buffers.
Prediction. CUDA EP latency −3 to −6 ms. Lower priority, given H6.

7 Threats to validity

- **Single runs, one board.** Most configurations were recorded once, on one Orin Nano. The replicates show a run-to-run variation of about 0.5 ms (3 %) in the detector's median and 0.14 GB in its memory. Differences of that size are not conclusive, even when their bootstrap intervals exclude zero, because the interval captures only the variation within a run.
- **Shared hardware.** The measurement lock prevents overlapping measurements, but not every influence of earlier work on the board, for example its thermal state or caches. One stack run started with 0.8 GB more memory in use than the others.
- **Synthetic input.** The synthetic camera replaces real sensors, so detection results and the planning and control chain are not exercised realistically; per-frame costs that depend on image content may differ.
- **Confounding.** Container runs used Cyclone DDS, native runs Fast DDS; the per-node stack run had no bag recorder and no probes.
- **Instrument limits.** tegrastats samples every 0.5 s and its interval drifts by 1.2 %. Energy windows of 2.5–5 s contain few samples, and six windows had to be rejected. Nsight Systems adds overhead to traced CUDA calls, so API times are upper bounds. Summed RSS double counts shared pages.
- **Measurement artefacts.** The Python rate probes load the system and underestimate high rates (Section 5).

8 Conclusion

The measurements show a stack whose computational needs fit the Orin Nano comfortably: with TensorRT, the detector needs 17 ms per frame, and the full stack uses less than half of the CPU, an eighth of the GPU and a third of the power budget. They also show that the stack does not reach its input rate, because data handling rather than computation limits it: per-frame device allocations, copies within shared memory, CPU-side preprocessing and lock traffic. The ROS distribution and the run-time mode are not performance factors. The hypotheses of Section 6 turn these findings into experiments; each can be run and evaluated with the same tools that produced this report. The first of them, a long-duration memory test, has already ruled out a memory leak; buffer reuse in the image pipeline (**H1**) and GPU-side preprocessing (**H3**) are the next.

A All recordings

Time	Kind	Label	Profile	Mode	Wall [s]	rc	Status
02:13	nsys	ort-cuda	jazzy	–	23	0	valid
02:14	tegrastats	idle	jazzy	–	5	0	3 samples only
02:22	nsys	ort-trt16	jazzy	–	385	130	interrupted (rc 130); kernel data valid, span recomputed
15:07	launch	od-jazzy-native	jazzy	native	29	124	excluded: sampler without ancestry markers, concurrent HIL load counted (F53)
15:12	launch	od-ort-jazzy-native	jazzy	native	45	124	valid (replicate); bag without CSV export
15:15	bench	s0-fp32	jazzy	–	790	0	valid
15:29	bench	int8	jazzy	–	2108	0	valid
19:57	launch	od-onnx-jazzy-native	jazzy	native	65	124	excluded: no bag (topics passed as one argument)
20:00	launch	od-onnx-jazzy-native	jazzy	native	51	124	valid
20:01	launch	od-trt-fp16-jazzy-native	jazzy	native	50	124	valid
20:02	launch	od-trt-int8-qat-jazzy-native	jazzy	native	50	124	valid
20:04	launch	od-onnx-kilted-native	kilted	native	6	1	failed start: topic_tools missing (F52)
20:04	launch	od-trt-fp16-kilted-native	kilted	native	6	1	failed start: topic_tools missing (F52)
20:10	launch	od-onnx-kilted-native	kilted	native	51	124	valid
20:11	launch	od-trt-fp16-kilted-native	kilted	native	50	124	valid
20:19	launch	od-onnx-kilted-container	–	–	–	–	board reset during ORT CUDA EP initialization in the container (F56)
20:23	launch	od-trt-fp16-kilted-container	kilted	container	51	124	valid
20:24	launch	od-onnx-lyrical-isaac-native	lyrical-isaac	native	6	1	failed start: osrf_pycommon missing (F61)
20:24	launch	od-trt-fp16-lyrical-isaac-native	lyrical-isaac	native	6	1	failed start: osrf_pycommon missing (F61)
20:28	launch	od-v2check-kilted-native	kilted	native	36	124	valid (replicate after the lifecycle rework)
20:31	launch	stack-parking-onnx-kilted-native	kilted	native	8	1	failed start: foxglove_bridge missing (F60)
20:31	launch	stack-parking-trt-fp16-kilted-native	kilted	native	8	1	failed start: foxglove_bridge missing (F60)
20:31	launch	stack-parking-trt-fp16-kilted-container	kilted	container	10	1	failed start: foxglove_bridge missing (F60)
20:31	nsys	stack-parking-trt16-kilted	kilted	–	592	0	launch died at start (foxglove_bridge); nsys waited 508 s for the process tree (F62)
20:43	launch	stack-parking-onnx-kilted-native	kilted	native	127	124	invalid: image pipeline produced no output (diagnostics stale)
20:45	launch	stack-parking-trt-fp16-kilted-native	kilted	native	127	124	valid
20:54	launch	stack-parking-trt-fp16-kilted-container	kilted	container	129	124	valid
21:46	launch	od-onnx-lyrical-isaac-native	lyrical-isaac	native	7	1	failed start: osrf_pycommon missing (F61)
21:46	launch	od-trt-fp16-lyrical-isaac-native	lyrical-isaac	native	7	1	failed start: osrf_pycommon missing (F61)

Time	Kind	Label	Profile	Mode	Wall [s]	rc	Status
21:59	launch	od-trt-fp16-lyrical-container	lyrical	container	67	137	container needed SIGKILL at shutdown (rc 137); no bag
22:01	launch	od-onnx-lyrical-isaac-native	lyrical-isaac	native	46	124	valid; bag storage failed on Lyrical
22:02	launch	od-trt-fp16-lyrical-isaac-native	lyrical-isaac	native	46	124	valid; bag storage failed on Lyrical
22:03	launch	stack-parking-onnx-kilted-native	kilted	native	127	124	valid
22:05	launch	stack-parking-trt-fp16-kilted-native-nodes	kilted	native	127	124	valid; no bag, no rate probes
22:07	nsys	stack-parking-trt16-kilted	kilted	–	3846	0	valid; GPU active 7.5–36 s, session open for 3800 s afterwards

Table 9: All recordings of the campaign (times are the host's local time).

B Telemetry before the reset

Table 10: The last tegrastats samples before the board reset (ONNX Runtime CUDA EP in the Kilted container).

t [s]	RAM [MB]	CPU mean [%]	GPU [%]	VDD_IN [mW]	T_j [°C]
0.0	1388	19	0	5750	49.6
0.5	1385	8	0	5560	49.4
1.0	1394	18	0	5781	49.3
1.5	1401	19	0	5891	49.8
2.0	1408	43	0	6369	49.8
2.5	1422	41	0	6568	50.0
3.0	1436	32	0	6409	49.4
3.5	1469	21	0	6210	49.5
4.0	1501	44	0	6687	49.5

C Reproduction

The raw recordings are in `traces/nano-lab/` on the measurement host; they are not part of the repository. To regenerate every figure, table and number of this report:

`python3 docs/measurements/analyze.py` then `latexmk -pdf docs/latex/measurements.tex`

New recordings are made with `jxb launch --monitor --bag`, `jxb trace nsys` and `jxb trace bench`; their directories can be added to the run lists at the top of the analysis script.

References

[1] H. R. Künsch. The jackknife and the bootstrap for general stationary observations. *The Annals of Statistics*, 17(3):1217–1241, 1989.

[2] B. Efron and R. J. Tibshirani. *An Introduction to the Bootstrap*. Chapman & Hall, 1993.

[3] N. Cliff. Dominance statistics: ordinal analyses to answer ordinal questions. *Psychological Bulletin*, 114(3):494–509, 1993.

[4] J. Romano, J. D. Kromrey, J. Coraggio and J. Skowronek. Appropriate statistics for ordinal level data: should we really be using t-test and Cohen's d for evaluating group differences on the NSSE and other surveys? Annual meeting of the Florida Association of Institutional Research, 2006.

[5] NVIDIA. *CUDA for Tegra* (memory management on integrated GPUs). https://docs.nvidia.com/cuda/cuda-for-tegra-appnote/

[6] ROS 2. *REP 2007: Type Adaptation Feature*. https://ros.org/reps/rep-2007.html

[7] NVIDIA. *Nsight Systems User Guide*. https://docs.nvidia.com/nsight-systems/UserGuide/