



```
ROUTER
*Jul 17 07:35:34.132: %SYS-5-CONFIG_I: Configured from console by console
R1#conf t
Enter configuration commands, one per line. End with CNTL/Z.
R1(config)#ip domain-name sathish.com
R1(config)#username cisco privilege 15 secret cisco@123
R1(config)#crypto key generate rsa
The name for the keys will be: R1.sathish.com
Choose the size of the key modulus in the range of 360 to 4096 for your
General Purpose Keys. Choosing a key modulus greater than 512 may take
a few minutes.
How many bits in the modulus [512]: 2048
% Generating 2048 bit RSA keys, keys will be non-exportable...
[OK] (elapsed time was 8 seconds)

R1(config)#
R1(config)#
*Jul 17 07:37:57.890: %SSH-5-ENABLED: SSH 1.99 has been enabled
R1(config)#ip ssh version 2
R1(config)#line vty 0
R1(config-line)#transport input ssh
R1(config-line)#login local
R1(config-line)#exit
R1(config)#
```



```
QEMU (Win)
50.0.0.1 - PuTTY
login as: cisco
Using keyboard-interactive authentication.
Password:

R1#
R1#
R1#sh ip in brief
% Ambiguous command: "sh ip in brief"
R1#sh ip int brief
Interface                IP-Address      OK? Method Status      Prot
Ethernet0/0              50.0.0.1        YES manual up          up
Ethernet0/1              unassigned      YES TFTP  down        down
Ethernet0/2              unassigned      YES TFTP  down        down
Ethernet0/3              unassigned      YES TFTP  down        down

R1#
```