GEARBOX

SERIES	A - Series Bevel Gearboxes
SIZE	60 - Mn2=2800Nm/Tn2=24800LbIn
REDUCTIONS	4 - 4 Reduction Stages
VERSION	UH60 - Hollow O/P Shaft Dia. 60mm
GEAR RATIO	500.3
INPUT CONFIGURATION	P90 - Metric Motor Adaptor IEC 90
MOUNTING POSITION	B3

MOTOR

PRODUCT SERIES	BXN - AC IE3 Three Phase Motor
SIZE	90S - IEC 90
POLE NUMBER	4 - 4 Poles
WINDING	WD3 - Winding Type 3
DEGREE OF PROTECTION	IP56 - Not for Brake Motors
INSULATION CLASS	CLF - Standard Insulation Class
MOTOR EXECUTION	B5 - B5 Motor Mounting Flange

GEARMOTOR OPTIONS

TERMINAL BOX POSITION	S - Terminal Box Positiont 180°

TECHNICAL DATA

Measurement Internat. System	METRIC
n2 Output Speed [min-1]	N/A
Mn2 Output rated torque [Nm]	N/A
Rn2 Output OHL [N]	N/A
Gearb.Mom.Inert.(•10-4) [kgm2]	N/A
sf Service factor	N/A
Voltage [V]	220/380 Δ/Y
Pn Motor Nominal Power [kW]	1.1
Pn Motor Nominal Power [Hp]	1.5
Pn-60 Motor Nominal Power [kW]	1.1
Pn-60 Motor Nominal Power [Hp]	1.5
I0 [A]	2.64/1.52
In Nominal Current [A]	4.34/2.51
Cosφ	0.78
n Motor Speed [min-1]	1448
Efficiency Class	IE3
η100 Efficiency 100% [%]	84.1
η75 Efficiency 75% [%]	85.9
η50 Efficiency 50% [%]	83.5

KVA code	J
Starting Current	7.3
Starting Torque	2.4
Mean Breakway Torque	2.9
Voltage 60Hz [V]	255/440 Δ/Y
I0 60Hz [A]	2.4/1.38
In Nominal Current 60Hz [A]	3.82/2.21
Cosφ 60Hz	0.75
n Motor Speed 60Hz [min-1]	1755
η100 Efficiency 100% 60Hz [%]	86.5
η75 Efficiency 75% 60Hz [%]	86.6
η50 Efficiency 50% 60Hz [%]	83.5
KVA code 60Hz	L
Starting Current 60Hz	8.5
Starting Torque 60Hz	2.7
Mn Motor Nominal Torque [Nm]	7.3
Tn Motor Nom. Torque [lb-in]	64.6
Mn Motor Nom. Torque 60Hz [Nm]	6.0
Tn Mot. Nom.Torq. 60Hz [lb-in]	53.1
Jm Mot.momen.of inertia[kgcm2]	31.76

Gearmotor Weight [Kg]	105.6
Oil Quantity [l]	8.000
Output Shaft Dimensions	Ø60 G7 mm