



SBK_WRIST_BLATER_II_PCB V0					
Description	Dimensions / Value	Qté	Supplier	Part Number	Comments
PCB	57 x 58 x 1.6mm	1	SBK	SBK_WRIST_BLATER_II_PCB V0	Email me for inquiries
Arduino Nano Every with 2x male header 1x15	Arduino Nano Every	1	Digikey, Mouser	ABX00033	
DFPlayer Mini with 2x male header 1x08	DFR0299	1	Digikey, Mouser	DFR0299	
Micro SD card	Recommended Class 4 128 MB min. (for sound effects and a few music tracks only) 16 GB max (unlimited music tracks !)	1	Amazon		Size up to your taste : for the sound effects and few tracks, a 128MB is sufficient. If you want to put a lot of music tracks, well you can go up to 16GB.
LTK5128 5W mono Amp module	12x15x1.6mm	1	Amazon	5W 5128 mono amplifier module	
Female header	Female 2.54mm 1x08	2	Amazon	Male and femal 2.54 headers kit	You can buy a kit on Amazon to cover all your
Female header	Female 2.54mm 1x15	2			
Male header	Male 2.54mm 1x06	1			
Male header	Male 2.54mm 1x02	1			
Male header	Male 2.54mm 1x01	3			
Male header	Male 2.54mm 2x08	1			
Male header	Male 2.54mm 2x03	2			
JST XH254 terminal male plug	JST-XH 2.54mm male terminal, THT, 1x05	1	Amazon	JST-XH 2.54mm kit	You can buy a kit on Amazon to cover all your needs for this project.
JST XH254 terminal male plug	JST-XH 2.54mm male terminal, THT, 1x03	1			
JST XH254 terminal male plug	JST-XH 2.54mm male terminal, THT, 1x02	5			
Resistor 1/4W	10k THT 1/4W	2	Amazon	resistors kit	You can buy a kit on Amazon to cover all your needs for this project.
	4K7 THT 1/4W	2			
	1k THT 1/4W	1			
	470 THT 1/4W	3			
	150 THT 1/4W (for fire button yellow led)	1			
Ceramic capacitor	0.1uF - 5mm between pins	3	Amazon	0.1uF 104 multilayer Ceramic Capacitor	
Low ESR Electrolytic Capacitor	220 uF 10V 6mm dia x 7mm, 2.5mm between pins	1	Digikey, Mouser, Amazon	220 uF 10V 6mm dia x 7mm	This capacitor is under the board, there is other size, but the 7mm high is more convenient to fit under the board.
Low ESR Electrolytic Capacitor	3300 uF 10V 13mm dia x 20mm, 5mm between pins	1	Digikey, Mouser, Amazon	3300 uF	Various size available, but max diameter is 13mm. You should also try to have a 20mm high version.
trimmer pot	50K, 3362P Serie, P503, THT	1	Amazon	trim pot kit	
MOSFET	BS170 TO-92 NMOS	2	Amazon	BS170 TO-92	

Bar Meter PCBs					
Description	Dimensions / Value	Qté	Supplier	Part Number	Comments
Bar meter driver PCB	54.1*20.4mm	1	SBK	SBK_WB_BG_xx_DR_PCB V0	xx = SA -> Common Anode xx = SK -> Common Cathode
Bar meter PCB	47.2x20.4mm	1	SBK	SBK_WB_BG_28SEG_PCB V0	Fits both SA or SK bar meter
Leds driver chip	MAX7221 DIP-24	1	Digikey, Mouser, Amazon	MAX7221 DIP-24	Can find knock off on Amazon or Aliexpress..
Bar Meter 28segments yellow	BL28-3005xx04Y	1	Aliexpress	BL28-3005xx04Y	Must fit your driver PCB : xx = SA -> Common Anode xx = SK -> Common Cathode Can find various sellers on Aliexpress, I do not recommend one in particular...
JST XH254 terminal male plug	JST-XH 2.54mm male terminal, THT, 1x05	1	Amazon	JST-XH 2.54mm kit	You can buy a kit on Amazon to cover all your needs for this project.
Male header	Male 2.54mm 1x06	1	Amazon	Male and femal 2.54 headers kit	You can buy a kit on Amazon to cover all your needs for this project.
Male header	Male 2.54mm 1x05	1			
Male header	Male 2.54mm 1x02	1			
Resistor 1/4W	27kOhms	1	Amazon	27kOhms 1/4W resistor	You won't find those easily in a kit...
Ceramic capacitor	0.1uF - 5mm between pins	3	Amazon	0.1uF 104 multilayer Ceramic Capacitor	
Capacitor	10uF 10V 4mm dia x 7mm, 1.5mm between pins	1	Digikey, Mouser, Amazon	10 uF 25V 4x7mm	6.3V is the minimum for this capacitor.

Câbles and jumpers					
Description	Dimensions / Value	Qté	Supplier	Part Number	Comments
Bar meter jumper connector	JST-XH254 5pins female-female 10-15 cm	1	Amazon, Aliexpress	JST-XH254 5pins female-female 10-15 cm	10cm is a little short, 20 is a little long, 15cm rarely available unfortunately
Potentiometer connector plug	Dupont female plug 1x03	2	Amazon, Aliexpress	Dupont kit	You can try to build a kit from this link for your needs. You can take longer pre-clamp wire and cut them in half to make 2 wires...
Switches and buttons connector plug	Dupont female plug 2x06	1			
Wires for potentiometer, switches and buttons	Dupon female pre-clamp wire 20cm	18	Amazon, Aliexpress	JST-XH254 jumper	You can try to make your jumper out of a kit like that.
Leds Strip jumper connector	Female JST-XH254 3pins to wire jumper 20cm	1			
Speaker connector	Female JST-XH254 2pins to wire jumper 20cm	1			
Smoke vacuum pump connector	Female JST-XH254 2pins to wire jumper 20cm	1			
Smoke fan connector	Female JST-XH254 2pins to wire jumper 20cm	1			
Batterie connector	Female JST-XH254 2pins to wire jumper 20cm	1			

Accessories					
Description	Dimensions / Value	Qté	Supplier	Part Number	Comments
Toggle switch	Blue mini MTS-101 2-pin SPST	4	Amazon	Blue mini MTS-101 SPST	Could also be MTS-102 3pin SPDT
Push button with yellow led indicator	R16-503 16mm Momentary Push Button 4pin Yellow	1	Amazon, Digikey, Mouser	R16-503 16mm Momentary Push Button 4pin Yellow	Be carefull, choose Momentory and 4 pins...
Speaker	2 inches 5W 4Ohms	1	Amazon, Aliexpress	Link for reference only 	I do not recommend any speaker. Foot print must match this :
Potentiometer	B10K, 15mm shaft	2	Amazon	B10K 15mm shaft	For the hue control in the Clippard valve, potentiometer pins could have to be bent or cut to fit inside...
Mini vacuum pump (for smoke)	5VDC, less then 500mA	1	Amazon, Aliexpress	No model number 	Must fit these dimensions to fit in the Clippard Valve
Fan (for smoke)	3006 or 3007, 2pins, 5VDC, less then 500mA	1	Amazon	3006 5v 2pin fan	3006 are more expensive then 3007 fan...