

Currently we have a SM30 view for table NACH called ZV_NACH.

It is used for mass changes of the messages.

Unfortunately, SAP did some changes on table NACH for the S4Hana System and field VAKEY was removed from table NACH.

HPC fixed the view on the Hana System so it can be used without errors but in is not super useful anymore because we can not see for which combination the message is customized for.

Therefore, we need a new program/view which basically does the same as the SM30 view. But we need to add and build the VAKEY again.

We want to have all fields from table NACH (S4Hana) + custom field for VAKEY.

PA1: field VAKEY (Variabler Key) exists in NACH

NACH: Anzeige der gefundenen Einträge

PA1

Zu durchsuchende Tabelle: NACH Detaildaten für Nachrichten

Anzahl Treffer: 1

Laufzeit: 0 Maximale Trefferzahl: 500

NrKondSatz	Angelegt von	Angelegt am	V	Tab	Apl	Kart	Variabler Key
0000003524	NHS001321	16.07.2015	B	011	V3	ZRCP	1100ZF2

SA2: VAKEY is missing in table NACH. But we can rebuild it in our program.

For that we need to check which condition table is needed. In this case it would be B011. Then read that table using KNUMH.

Concatenate the field values of the table in order (ignore field KAPPL, KSCHL and KNUMH when doing this). So, in this case it would be VKORG and FKART. (But of course every table has different fields.)

Since we are building the VAKEY ourselves, Marius said it would be helpful for him to have a space between the values. In this example, we expect the value of the VAKEY field in our program to be “1100 ZF2”.

The image displays two screenshots of SAP search results. The left screenshot shows a search for 'NACH' with 500 hits. The right screenshot shows a search for 'B011' with 239 hits, and a detailed view of a specific entry with '1100 ZF2' in the VAKEY field.

NACH: Anzeige der gefundenen Einträge

Zu durchsuchende Tabelle: NACH
Anzahl Treffer: 500
Laufzeit: 0
Maximale Trefferzahl: 500

NrKondSatz	Angelegt von	Angelegt am	V Tab	Apl KArt	Gültig ab	Gültig bis
0000003524	NHS001321	16.07.2015	B 011	V3 ZRCP		
0000003525	NHS001321	16.07.2015	B 011	V3 ZRCP		
0000003526	NHS001321	16.07.2015	B 011	V3 ZRCP		
0000003527	NHS001321	16.07.2015	B 011	V3 ZRCP		
0000003532	NHS001321	16.07.2015	B 011	V3 ZRCP		
0000003563	NHS001321	16.07.2015	B 011	V3 ZRCP		
0000003564	NHS001321	16.07.2015	B 011	V3 ZRCP		
0000003565	NHS001321	16.07.2015	B 011	V3 ZRCP		
0000003566	NHS001321	16.07.2015	B 011	V3 ZRCP		
0000003568	NHS001321	16.07.2015	B 011	V3 ZRCP		

B011: Anzeige der gefundenen Einträge

Zu durchsuchende Tabelle: B011
Anzahl Treffer: 239
Laufzeit: 0
Maximale Trefferzahl: 500

Apl Nach	VkO... FkArt	NrKondSatz	Zähler
V3 ZRCP	1100 ZF2	0000003524	1