

COMPONENT VALUES

All resistors are 1/2 watt, 5% unless otherwise specified.

R	1	4,700 ohms	113472	R23	1,000 ohms, 10%	112102
R	2	4,700 ohms	113472	R24	4,700 ohms	115472
R	3	30,000 ohms	113303	R25	1 watt, 10%	113103
R	4	150 ohms	113151	R26	10,000 ohms	112223
R	5	100,000 ohms	113104	R27	22,000 ohms, 10%	128004
R	6	1,000 ohms	113102	R28	0.47 ohms	113030
R	7	1,500 ohms	113152	R29	2 watt, 10%	112102
R	8	270 ohms	113271	C 1	5 mfd, tantalum	282505
R	9	4,700 ohms	113472	C 2	150 pf mica	245151
R	10	3,900 ohms	113392	C 3	250 mfd, 40v,	283267
R	11	10,000 ohms	113103	C 4	35 mfd, 20v,	283356
R	12	10,000 ohms	113103	C 5	250 mfd, 16v,	283257
R	13	100 ohms	103101	C 6	47 mfd, 10v,	282505
R	14	100 ohms	103101	C 7	3300 mfd, 50v,	283338
R	15	470 ohms	113472	C 8	0.1 mfd, 100v,	264104
R	16	300 ohms	120301	C 9	1000 mfd, 100v,	284108
R	17	300 ohms	120301	C 10	50 mfd, 25v,	283516
R	18	4.7 ohms	120301	C 11	500 mfd, 100v,	284507
R	19	6,200 ohms	113622	C 12	3300 mfd, 100v,	284338
R	20	1,000 ohms, 10%	112102	C 13	68 pf disc	237680
R	21	1,200 ohms	113122	C 14	0.01 mfd, 100v,	244104
R	22	3,900 ohms	116392	C 15	27 pf disc	244271
R		1 watt, 5%		C 16	.01 mfd, 1000 v,	228103

Q	1	BC108A	130-180 Beta	572683
Q	2	2N5320	160-260 Beta, 90 V _{rev} , r = 5KΩ	572002
Q	3	TIP31C		577031
Q	4	TIP32C		567032
Q	5	2N3772	571844, 40-90 Beta @ 1 A	338-1
Q	6	2N3772	571844 Red Dot, 60-90 Beta @ 1 A	338-2
Q	7	2N4037	100-250 Beta, 90 V _{rev} , r = 5KΩ	564671
Q	8	2N5320	100-140 Beta, 90 V _{rev} , r = 5KΩ	574003
Q	9	2N4347	25-50 Beta @ 1 A, 110 V _{rev}	574844

D	1	zener diode, 5.1 volt, 5%, 400 mw.	540405
D	2	silicon diode, 0.8 volt drop @ 140 ma.	544015
D	3	silicon diode, 0.8 volt drop @ 140 ma.	544015
D	4	silicon diode, 3 amperes, 200 prv.	544322
D	5	silicon diode, 3 amperes, 200 prv.	544322
D	6	silicon diode, 3 amperes, 200 prv.	544322
D	7	silicon diode, 3 amperes, 200 prv.	544322
D	8	silicon diode, 1N4003	544012
D	9	silicon diode, 1N4003	544012
D	10	zener diode, 58 volt, 2%, 1 watt	540158
D	11	silicon diode, 1N4003	544012
D	12	silicon diode, 1N4003	544012
T	1	Dynaco FA-704 power transformer	464001
S	1	DPDT lighted switch	334001
F	1	fuse 3 amp slo-blo	342030
F	2	fuse 1.5 amp slo-blo (alternate)	342015
L	1	74 inches of #16 insulated wire	319997

VOLTAGE TEST POINTS

Measured with VTVM. 120 or 240 volt 60 cycle AC line, 8 ohm load, shorted input. All voltages are DC unless specified AC.

Left PC-14	Right PC-14	PC-15
#1 72	#1 0	#1 -21
#2 37	#2 36	#2 -21
#3 <0.5	#3 <0.5	#3 72
#4 37	#4 37	#4 72
#5 72	#5 72	#5 71
#6 36	#6 36	#6 0
#7 36	#7 36	#7 -20
#8 36	#8 36	#8 } 70 AC*
#9 71	#9 71	#9 }
#10 71	#10 71	
#11 0	#11 0	
#12 0	#12 0	
#13 0	#13 0	
#14 36	#14 37	
#15 0	#15 72	

*Measured between eyelets located on circuit board edge

