PIFI DAC V2.0 configuration with different Operating System

OSMC
Select My OSMC -> Hardware Support -> Sound Overlay -> hifiberry-dac-overlay
Reboot
Settings -> System -> Audio -> Audio output device ->
ALSA:Default(snd_rpi_hifiberry_dacplus Analog)

Volumio
At time of setup, enable I2S DAC select Hifiberry Dac Plus
Even from settings, playback this can be done

Xbian
ssh xbian (username-xbian, password raspberry)
sudo nano /etc/modules.xbian
Comment the line
#snd_bcm2835
Save it (ctrl+x, y, Enter)
sudo nano /boot/config.txt
Locate and remove comment(#) from
dtoverlay=hifiberry-dacplus
Save it (ctrl+x, y, Enter)
sudo reboot
Settings -> System -> Audio -> Audio output device ->
ALSA:Default(snd_rpi_hifiberry_dacplus Analog)

LIBREELEC

ssh (username : root, password : libreelec)
mount -o remount,rw /flash
nano /flash/config.txt
add given line -
dtoverlay=hifiberry-dacplus
Save it (ctrl+x, y, Enter)
sudo reboot
amixer -c 0 set Digital 80%