

AUTOMATIC IRRIGATION SYSTEM

by

KAAVYA S 24BEC1573

DEVNA S 24BLC1164

A project report submitted to

Dr. Abraham Sudharson Ponraj

SCHOOL OF ELECTRONICS ENGINEERING

in partial fulfilment of the requirements for the course of

**BECE204L – MICROPROCESSORS AND
MICROCONTROLLERS**

in

B. Tech. ELECTRONICS AND COMPUTER ENGINEERING

And

**B.Tech ELECTRONICS AND COMMUNICATION
ENGINEERING**



VIT[®]
Vellore Institute of Technology
(Deemed to be University under section 3 of UGC Act, 1956)

Vandalur – Kelambakkam Road

Chennai – 600127

November 2024

BONAFIDE CERTIFICATE

Certified that this project report entitled “**IRRIGATION SYSTEM**” is a bonafide work of **DEVNA S – 24BLC1164 and KAAVYA-24BLC1573** **who** carried out the Project work under my supervision and guidance for **BECE204L–MICROPROCESSORS AND MICROCONTROLLERS.**

Dr. Abraham Sudharson Ponraj

Associate Professor

School of Electronics Engineering (SENSE),

VIT, Chennai

Chennai – 600 127.

ABSTRACT

This project, *“Automatic Irrigation System using 8051 Microcontroller,”* aims to automate the process of watering plants based on soil and environmental conditions. The system uses a **soil moisture sensor** and a **rain detection sensor** to monitor the moisture level of the soil and detect rainfall. These sensors send signals to the **8051 microcontroller**, which acts as the control unit. When the soil is dry and there is no rainfall, the microcontroller activates a **motor** through a **relay module** to supply water. Once sufficient moisture or rainfall is detected, the motor is automatically turned off, thus preventing water wastage. The setup is implemented on a **breadboard** using low-cost components. This project provides a simple, efficient, and eco-friendly solution for irrigation and can be extended to larger agricultural applications or integrated with IoT for remote monitoring and control.

ACKNOWLEDGEMENT

We take this opportunity to express our heartfelt gratitude to all those who have guided and supported us throughout the successful completion of our project titled “*Automatic Irrigation System using 8051 Microcontroller.*”

First and foremost, we would like to extend our sincere thanks to our respected guide **Abraham Sudharson Ponraj Sir**, for their valuable guidance, constant encouragement, and constructive feedback during every stage of this project. Their deep knowledge and experience were instrumental in helping us understand both the theoretical and practical aspects of embedded system design.

We are also grateful to the **Department of Electronics Engineering** , for providing us with the necessary facilities, laboratory equipment, and a stimulating environment to work on this project. Our sincere thanks go to all the faculty members and laboratory staff who extended their assistance and technical advice whenever required.

We would like to express our appreciation to our **team members** for their cooperation, hard work, and team spirit that made this project possible. Each member contributed significantly in designing, assembling, testing, and documenting various parts of the system.

We are truly thankful to everyone who contributed directly or indirectly to the success of this project.

By DEVNA S and KAAVYA S
(School of Electronics Engineering)

TABLE OF CONTENTS

SERIAL NO.	TITLE	PAGE NO.
	ABSTRACT	3
	ACKNOWLEDGEMENT	4
1	INTRODUCTION	7
1.1	Objectives and Goals	8
1.2	Problem Statement	8
1.3	Scope of the Project	8
1.4	Applications	9
1.5	Features	9
2	SYSTEM DESIGN AND DEVELOPMENT	
2.1	Block Diagram	11
2.2	Circuit Diagram	12
2.3	Working Principle	13
2.4	Hardware Analysis	14

SERIAL NO.	TITLE	PAGE NO.
2.5	Hardware Snapshots (Project, Team, Results)	15
3	SOFTWARE DESIGN AND IMPLEMENTATION	
3.1	Software Requirements	15
3.2	Coding and Analysis	16
3.3	Output and Results (Snapshots of Coding and Results)	17
4	RESULTS, CONCLUSION AND FUTURE WORK	
4.1	Result and Inference	19
4.2	Conclusion	19
4.3	Future Scope	20
5	COST ESTIMATION	20
6	REFERENCES	21
7	PHOTOGRAPH OF THE PROJECT AND TEAM MEMBERS	22

INTRODUCTION

The increasing demand for water conservation and efficient agricultural practices has led to the development of intelligent irrigation systems. This project, titled *“Automatic Irrigation System using 8051 Microcontroller”*, focuses on automating the watering process by monitoring environmental parameters such as soil moisture and rainfall. The primary aim of this system is to minimize human intervention and ensure optimum water utilization for crops, gardens, and lawns.

In this project, an 8051 microcontroller acts as the central control unit. It receives input signals from a soil moisture sensor and a rain detection sensor to determine the condition of the soil and the presence of rain. Based on the sensor readings, the controller decides whether to activate or deactivate the motor pump through a relay module. When the soil moisture level is below the threshold and there is no rainfall, the microcontroller switches on the motor to irrigate the field. Conversely, when adequate soil moisture or rainfall is detected, the motor is automatically turned off, preventing overwatering.

The entire circuit is implemented on a breadboard using low-cost and easily available components, making it a simple yet effective system for small-scale and educational applications. This project demonstrates the practical integration of sensors and microcontrollers in automating agricultural tasks. It also highlights the potential of embedded systems in promoting sustainable farming by reducing water wastage, labor, and operational cost.

Overall, this project contributes toward smart agriculture and water resource management by combining basic electronics with automation techniques. Future improvements can include wireless communication, IoT-based monitoring, and solar-powered operation for enhanced efficiency and scalability.

1.1 OBJECTIVES AND GOALS

The main objective of this project is to design and implement an automatic irrigation system that reduces manual intervention and ensures efficient use of water resources. The system should automatically detect soil dryness and rainfall to control the motor for watering plants.

Goals of the project include:

- To automate the irrigation process using sensor-based control.
- To minimize human effort and time in agricultural irrigation.
- To prevent over-irrigation and water wastage.
- To design a low-cost, reliable, and efficient system using the 8051 microcontroller.
- To promote water conservation and support sustainable farming techniques.

1.2 PROBLEM STATEMENT

Traditional irrigation systems rely heavily on manual operation, which often leads to inefficient water usage, over-irrigation, or under-irrigation. In regions where water scarcity is a concern, such inefficiencies can harm both crop yield and resource sustainability. Farmers are required to monitor soil conditions continuously, which is time-consuming and labor-intensive. Therefore, there is a need for an automated system that can intelligently control irrigation based on real-time soil and weather conditions without constant human supervision.

1.3 SCOPE OF THE PROJECT

This project demonstrates the concept of automatic irrigation using simple electronic components and microcontroller logic. It focuses on small-scale applications such as gardens, lawns, and educational prototypes but can be extended to larger agricultural setups with more sensors and wireless communication.

The scope also includes:

- Interfacing of soil moisture and rain sensors with the 8051 microcontroller.
- Automatic motor control using a relay mechanism.
- Breadboard implementation and testing of the system.
- Possibility of future enhancement through IoT, GSM, or solar power integration.

This project serves as a foundation for smart agriculture systems, showcasing how embedded technology can be applied to automate and optimize irrigation practices.

1.4 APPLICATIONS

- Agricultural fields and crop irrigation systems.
- Domestic gardens and lawns.
- Greenhouses and nurseries.
- Smart city landscaping systems.
- Educational projects and prototype demonstrations.


1.5 FEATURES

- Fully automatic water control based on soil moisture and rain detection.
- Reduces human effort and saves water effectively.
- Simple, compact, and cost-efficient design.
- Uses easily available components for implementation.
- Can be upgraded for wireless or IoT-based operation.
- Reliable operation suitable for both domestic and small-scale agricultural use


2. SYSTEM DESIGN AND DEVELOPMENT

2.1 BLOCK DIAGRAM

The block diagram of the project represents the overall working of the *Automatic Irrigation System*. It shows the interconnection between the main components — soil moisture sensor, rain detection sensor, 8051 microcontroller, relay module, and motor (pump).



BLOCK DIAGRAM



Description:

The soil moisture sensor and rain detection sensor are used as input devices. These sensors send electrical signals corresponding to soil dryness and rainfall conditions to the 8051 microcontroller. The microcontroller processes these signals and decides whether to turn the motor ON or OFF. The relay module acts as an electronic switch between the microcontroller and the motor, allowing safe

control of the high-power load. When the motor is ON, it irrigates the field; when adequate moisture or rain is detected, it automatically turns OFF.

Thus, the system provides intelligent irrigation control based on real-time environmental conditions.

2.2 CIRCUIT DIAGRAM

The circuit diagram illustrates the actual electrical connections between all components in the system.


(Insert your circuit or breadboard connection diagram here)

Description:

- The soil moisture sensor output is connected to one of the input pins of the 8051 microcontroller (e.g., P1.0).
- The rain detection sensor output is connected to another input pin (e.g., P1.1).
- The relay module is connected to an output pin (e.g., P2.0) of the microcontroller.
- The motor (water pump) is connected to the relay output.
- The system is powered by a +5V DC supply, and the sensors operate on the same voltage level.

When the input from the sensors indicates dry soil and no rainfall, the output pin of the microcontroller goes HIGH, triggering the relay to activate the motor. When the inputs indicate sufficient moisture or rainfall, the output goes LOW, turning the relay and motor OFF.

This simple circuit allows automatic switching of the motor without any manual operation.



2.3 WORKING PRINCIPLE

The project works on the principle of closed-loop feedback control using sensors and a microcontroller.

1. The soil moisture sensor continuously measures the moisture content in the soil. When the soil is dry, it produces a low output voltage signal, which is sent to the 8051 microcontroller.
2. The rain detection sensor checks for rainfall. If rain is detected, it sends a high signal to the microcontroller.
3. The 8051 microcontroller processes both sensor signals. Based on the logic programmed in it, the controller decides the status of the motor:

- If the soil is dry and no rain is detected → Motor ON (irrigation starts).
 - If the soil is wet or rain is detected → Motor OFF (irrigation stops).
4. The relay module acts as an interface between the low-power microcontroller and the high-power motor. It ensures electrical isolation and safe operation.
 5. The motor pumps water to the soil until the moisture level becomes sufficient.

This process repeats automatically, ensuring continuous monitoring and efficient irrigation without manual intervention.

2.4 HARDWARE ANALYSIS

The hardware setup of this project consists of the following key components:

- **8051 Microcontroller:**
Serves as the brain of the system. It receives input signals from the sensors, processes them according to the programmed logic, and controls the output signal to the relay.
- **Soil Moisture Sensor:**
Detects the water content in the soil. It provides an analog signal proportional to the moisture level, helping the microcontroller decide when to start or stop irrigation.
- **Rain Detection Sensor:**
Senses the presence of rainfall using a conductive plate. When rainwater is detected, its resistance changes, generating a signal for the microcontroller.

- **Relay Module:**

Functions as a switch to control the motor based on microcontroller output. It isolates the low-voltage control circuit from the high-voltage load circuit.


- **Motor (Water Pump):**

Represents the irrigation pump that supplies water when activated by the relay.

- **Breadboard and Power Supply:**

The entire circuit is built on a breadboard for testing and demonstration. A 5V DC power supply is used to operate the microcontroller and sensors.

Snapshots :



3. SOFTWARE REQUIREMENTS

3.1 Software Requirements

The software part of the system controls the logic and decision-making of the irrigation system. It is responsible for reading the input signals from the soil moisture sensor and rain detection sensor, and for controlling the relay that switches the motor ON or OFF.

Required Software Tools:

- Keil μ Vision IDE: Used for writing, compiling, and simulating C programs for the 8051 microcontroller.
- AVRDUDE

Programming Language:

- Embedded C language compatible with the Keil compiler.

3.2 CODING AND ANALYSIS

The system is programmed in Embedded C to perform automated irrigation based on the sensor inputs. The program initializes the LCD to display real-time system status, continuously monitors soil and rain sensors, and accordingly turns the water pump (motor) ON or OFF through the relay module.

Key Functional Steps in the Code:

1. LCD Initialization:
The LCD module is configured in 4-bit mode to display system messages such as “*Smart Irrigation*”, “*Soil: WET*”, “*M:ON*”, etc.

2. Sensor Inputs:

- Soil Moisture Sensor (P1.0): Detects soil condition (LOW = Wet, HIGH = Dry).
- Rain Sensor (P1.1): Detects rainfall (LOW = Raining, HIGH = Clear).

3. Relay Output (P1.2):

Controls the motor. The relay is active LOW, meaning the motor runs when the relay output is 0.

4. Decision Logic:

- If it is raining → Motor OFF.
- If soil is wet → Motor OFF.
- If soil is dry and not raining → Motor ON.

5. Display Logic:

LCD displays live sensor status and motor condition continuously in two lines.

Program Flow Summary:

1. Initialize LCD and display title.
2. Read rain and soil conditions.
3. Execute decision logic.
4. Display the current system status.
5. Loop the process continuously.

3.3 OUTPUT AND RESULT OF CODING


After successful simulation and hardware testing, the system produced the following results:

Condition	Soil Sensor Output	Rain Sensor Output	Motor Status	LCD Display
Soil Wet & No Rain	LOW	HIGH	OFF	“Soil: WET M:OFF”
Soil Dry & No Rain	HIGH	HIGH	ON	“Soil: DRY M:ON”
Soil Dry & Raining	HIGH	LOW	OFF	“Rain: ON M:OFF”
Soil Wet & Raining	LOW	LOW	OFF	“Status: RAINING”

Result:

The system efficiently detects both soil and rain conditions, automatically switches the water pump ON/OFF, and displays the current status on the LCD. It successfully minimizes manual irrigation effort and ensures optimal water usage.

Output Snapshot Ideas (for your report):



4. CONCLUSION AND FUTURE WORK

4.1 Result, Conclusion and Inference

The *Automatic Irrigation System using 8051 Microcontroller* was successfully designed, simulated, and implemented.

The system efficiently monitors soil moisture and rain conditions, and automatically controls the motor pump through a relay interface. The LCD display provides real-time feedback to the user, making the system both interactive and user-friendly.

The project demonstrates the integration of sensors, microcontroller, and control circuits to create a low-cost, energy-efficient, and water-saving solution suitable for small-scale agriculture and home gardens.

The results clearly indicate that the system can automatically irrigate the field

when the soil becomes dry and stop when it is wet or raining — achieving both automation and water conservation effectively.

Inference:

This project verifies that using a microcontroller-based irrigation system provides precision, reduces manual labor, and optimizes water usage, making it a practical solution for sustainable agriculture.

4.2 Future Work

While the current design efficiently automates irrigation based on basic environmental parameters, future enhancements can make it smarter and more scalable:

- Integration of IoT (Internet of Things) for remote monitoring and mobile-based control.
- Adding temperature and humidity sensors for complete climate-based control.
- Replacing 8051 with Arduino or ESP32 for improved data processing and wireless connectivity.
- Using solar power for an eco-friendly, self-sustaining system.
- Adding real-time data logging to track soil conditions over time.

These improvements can transform this system into a fully automated smart irrigation network suitable for modern precision farming.

5. COST ESTIMATION

Component	Quantity	Approx. Cost (INR)
8051 Microcontroller	1	700
Breadboard	1	35
Soil Moisture Sensor	1	35
Rain Sensor	1	45
Relay Module	1	30
Motor (DC Pump)	1	30
Wires	-	20
Total Estimated Cost		₹895

VIDEO LINK: [Automatic irrigation system](#)

6. REFERENCES (IEEE Format)

- [1] M. A. Hussain, S. Khan, and P. Kumar, "Design and Implementation of an Automatic Irrigation System using 8051 Microcontroller," *International Journal of Advanced Research in Electronics and Communication Engineering (IJARECE)*, vol. 6, no. 4, pp. 345–349, Apr. 2017.
- [2] R. Patel and K. Singh, "Smart Irrigation System based on Soil Moisture and Rain Detection," *IEEE International Conference on Intelligent Computing and Control Systems (ICICCS)*, pp. 1025–1030, 2019.
- [3] T. Basha and S. Kumar, "IoT Based Automatic Irrigation System Using Soil Moisture Sensor," *IEEE Global Humanitarian Technology Conference (GHTC)*, pp. 1–4, 2020.
- [4] A. Gupta, "Microcontroller-Based Automation for Efficient Water Management," *IEEE Potentials*, vol. 39, no. 3, pp. 32–36, May 2020.
- [5] P. S. Kiran and N. Rao, "Development of a Low-Cost Smart Irrigation Controller," *IEEE Access*, vol. 8, pp. 142326–142334, 2020.

PHOTOGRAPH OF THE PROJECT AND TEAM MEMBERS

