




RTL Design Sherpa

RTL AMBA Wishbone B4 Module Reference — Rev 0.90

July 2026

Table of Contents

1 Wishbone B4 Modules.....	7
1.1 Overview.....	7
1.1.1 Protocol scope.....	7
1.1.2 Modules.....	8
1.1.3 Reset and clock naming.....	9
1.1.4 Test.....	9
2 wb4_master.....	10
2.1 Overview.....	10
2.2 Parameters.....	10
2.3 Ports.....	11
2.3.1 Clock and Reset.....	13
2.3.2 Wishbone Master Interface.....	13
2.3.3 Command Interface.....	14
2.3.4 Response Interface.....	14
2.4 Functional Description.....	14
2.4.1 Timing.....	15
2.5 Usage Example.....	15
2.6 Notes.....	16
2.7 Related.....	16
2.8 Test.....	16
3 wb4_master_cg.....	17
3.1 Overview.....	17

3.2 Parameters.....	17
3.3 Ports.....	17
3.4 Functional Description.....	17
3.4.1 Wake-Up Terms.....	17
3.4.2 Masks for the Wake-Latency Overlap.....	18
3.5 Notes.....	18
3.6 Related.....	18
3.7 Test.....	18
4 wb4_master_retry.....	19
4.1 Overview.....	19
4.2 Parameters.....	19
4.3 Ports.....	20
4.4 Usage Example.....	20
4.5 Related.....	20
4.6 Test.....	20
5 wb4_master_stub.....	21
5.1 Overview.....	21
5.2 Packing.....	21
5.3 Parameters.....	21
5.4 Ports.....	21
5.5 Related.....	22
5.6 Test.....	22
6 wb4_monitor.....	22
6.1 Overview.....	22

6.2 Parameters.....	23
6.3 Ports.....	23
6.3.1 Command and Response Queues.....	25
6.3.2 Configuration.....	25
6.3.3 Status.....	26
6.4 Functional Description.....	26
6.4.1 Transaction Tracking.....	26
6.4.2 Event Detection.....	26
6.4.3 Monitor Packet Format.....	28
6.4.4 Event Priority and Loss.....	28
6.5 Timing Characteristics.....	28
6.6 Usage Example.....	29
6.7 Notes.....	29
6.8 Related.....	30
6.9 Test.....	30
7 wb4_pkg.....	30
7.1 Design Notes.....	30
7.2 Declarations.....	30
7.3 Burst hint encodings.....	32
7.4 Consumers.....	32
7.5 Related.....	33
8 wb4_retry.....	33
8.1 Overview.....	33
8.2 Parameters.....	33

8.3 Ports.....	33
8.3.1 Configuration.....	35
8.3.2 Status.....	35
8.4 Functional Description.....	35
8.5 Timing.....	36
8.6 Notes.....	36
8.7 Related.....	36
8.8 Test.....	36
9 wb4_slave.....	37
9.1 Overview.....	37
9.2 Parameters.....	37
9.3 Ports.....	38
9.3.1 Clock and Reset.....	39
9.3.2 Wishbone Slave Interface.....	39
9.3.3 Command Interface.....	40
9.3.4 Response Interface.....	41
9.4 Functional Description.....	41
9.4.1 Timing.....	42
9.5 Usage Example.....	42
9.6 Notes.....	42
9.7 Related.....	43
9.8 Test.....	43
10 wb4_slave_cdc.....	43
10.1 Overview.....	43

10.2 Parameters.....	43
10.3 Ports.....	44
10.4 Functional Description.....	44
10.4.1 Clock Domains.....	44
10.4.2 CDC Structure.....	44
10.4.3 Reset Behavior.....	44
10.5 Related.....	45
10.6 Test.....	45
11 wb4_slave_cdc_cg.....	45
11.1 Overview.....	45
11.2 Parameters.....	45
11.3 Ports.....	45
11.4 The wake term has to be single-domain.....	45
11.5 Reset.....	46
11.6 Test.....	46
11.7 Related.....	46
12 wb4_slave_cg.....	46
12.1 Overview.....	46
12.2 Parameters.....	46
12.3 Ports.....	47
12.4 Functional Description.....	47
12.4.1 Wake-Up Terms.....	47
12.4.2 Masks for the Wake-Latency Overlap.....	47
12.5 Notes.....	48

12.6 Related.....	48
12.7 Test.....	48
13 wb4_slave_stub.....	48
13.1 Overview.....	48
13.2 Packing.....	48
13.3 Parameters.....	49
13.4 Ports.....	49
13.5 Related.....	49
13.6 Test.....	49

1 Wishbone B4 Modules

Location: rtl/amba/wb4/ **Test Location:** val/amba/ **Status:** New (2026-09-09); master, slave, monitor, retry, clock-gated and CDC variants with sim and formal collateral. Family FULL sweep on one pinned seed base (RDS_SEED_BASE=20260910): 379 cells across the nine wb4 suites in val/amba/, plus the two AXI4-Lite bridge suites in projects/components/converters/dv/tests/, all passing. The cell count grew on 2026-09-11 when USE_BURST_HINTS became a dimension of the master and monitor suites.

1.1 Overview

A Wishbone B4 master and slave pair (and a monitor for either), both in the **pipelined** mode the B4 revision added, behind the same FUB-side contract the APB4 pair uses: a command queue and a response queue, each a valid/ready handshake through a gaxi_skid_buffer. A FUB that already talks to apb4_master through cmd_*/rsp_* talks to wb4_master the same way; the differences are the field names and a 2-bit status in place of pslverr.

There is no Wishbone B5. B4 (2010) is the current revision of the specification and is what the wb4 name records, the way apb4 records AMBA 4 APB.

1.1.1 Protocol scope

Signal set	Master (m_wb_*)	Slave (s_wb_*)
CYC, STB, WE, ADR, DAT_W (DAT_O), SEL	drives	receives

Signal set	Master (m_wb_*)	Slave (s_wb_*)
STALL	receives	drives (combinational from state, never from STB)
ACK, ERR, RTY, DAT_R (DAT_I)	receives	drives (registered)

- **Pipelined by default, classic by parameter.** With CLASSIC=0 a new STB every clock while STALL is low, and in-order termination. With CLASSIC=1 the blocks speak B4 standard (“classic”) mode: the master holds the request on STB/CYC until the termination and ignores STALL; the slave never drives STALL, accepts a presentation once, and refuses an accept in the clock its termination is on the wire (the held STB is still there, and would otherwise be taken twice).
- **Match the mode to the peer.** The two modes do not mix, in either direction: a pipelined master drops STB after one clock, which a classic slave never accepts, and a classic master’s held STB is accepted again every clock by a pipelined slave (B4 chapter 5). Both tests and both formal harnesses run each mode against a peer of the same mode.
- **RTY is a status, not a retry.** Every termination is returned to the FUB as `rsp_status = ACK (0), ERR (1) or RTY (2)`. The master does not re-issue on RTY; the FUB decides, or `wb4_retry` decides for it. The encoding is `wb4_pkg`.
- **Burst hints are carried, not acted on.** CTI and BTE are advisory in B4. With `USE_BURST_HINTS = 1` the master puts the FUB’s hint on the wires with the transfer it belongs to and the slave hands the received hint to its FUB; neither changes behaviour, because deciding what a burst means is the peripheral’s job. With the parameter at 0 the ports still exist and the bus reads CLASSIC/LINEAR, a legal non-burst cycle, which is what every consumer had before the hints landed.
- **Still not implemented, deliberately:** LOCK and the TGA/TGC/TGD tag signals.

1.1.2 Modules

- **wb4_master** - command/response queues in, pipelined Wishbone out; issue is credit-gated by the response queue so a termination can always be enqueued
- **wb4_slave** - pipelined Wishbone in, command/response queues out; in-order registered termination with an orphan-response guard

- **wb4_monitor** - watches either block's queues and reports completions, errors, timeouts, latency and address-range hits as monitor bus packets tagged `PROTOCOL_WB`; in-order tracking queue, since B4 terminates in issue order
- **wb4_retry** - RTY retry on the FUB side of the master: in-order completion buffer, re-issue up to a budget with a delay, the FUB sees RTY only once the budget is spent; **wb4_master_retry** is the block and the master together
- **wb4_master_cg**, **wb4_slave_cg** - the clock-gated variants (`amba_clock_gate_ctrl`, runtime enable and idle count, output valids masked for the wake overlap)
- **wb4_slave_cdc** - the slave with its queues carried to another clock domain over two `gaxi_fifo_async` instances; **wb4_slave_cdc_cg** adds the gated bus clock
- **wb4_master_stub** / **wb4_slave_stub** - the pair with packed cmd/rsp vectors, for shim-style converters
- **wb4_pkg** - the response-status encoding shared by the family and the DV

1.1.3 Reset and clock naming

The ports are `clk` and `aresetn` (active-low), the repository convention, rather than Wishbone's `CLK_I/RST_I` (active-high). An integrator bridging to a Wishbone fabric that carries `RST_I` inverts it at the boundary; the reset macros inside the blocks are polarity-agnostic.

1.1.4 Test

Nine test files in `val/amba/`, all through the RDS-DV framework's Wishbone B4 BFM's (`CocoTBFramework.components.wb4:WB4Master, WB4Slave, WB4Monitor`) and the GAXI BFM's on the FUB-side queues:

- `test_wb4_master.py` - the master alone: the framework slave answers on the bus from a memory model with ERR and RTY address windows, the monitor checks the wires, and every response on `rsp_*` is paired in order with the termination the slave produced.
- `test_wb4_slave.py` - the slave alone: the framework master drives the bus and the test is the FUB. Includes the abort case (CYC dropped with requests outstanding), which a master-slave loop can never produce, and proves the slave discards the late responses instead of pairing them with the next cycle.

- `test_wb4_master_slave_loop.py` - both back to back (`rtl/amba/testcode/wb4_master_slave_loop.sv`); the framework monitor and the wrapper's own protocol checks must agree.
- `test_wb4_master_cg.py`, `test_wb4_slave_cg.py` - the clock-gated wrappers: the gate must not swallow a transfer, and the wake must be bounded.
- `test_wb4_slave_cdc.py` - the clock-domain-crossing slave, and the gated variant built on it.
- `test_wb4_master_retry.py` - the RTY retry wrapper: re-issue budget, delay, and that a retried transfer carries its own payload and burst hint.
- `test_wb4_monitor.py` - the monitor, decoded through the shared monbus path.
- `test_wb4_stubs.py` - the packed-vector stubs.

The three single-block tests above each assert the peak in-flight count exceeds one, so the pipelined mode is proven exercised rather than assumed. Formal covers nine blocks: seven under `formal/amba/wb4_*` and the two converter cores under `formal/converters/`.

2 wb4_master

2.1 Overview

`wb4_master` turns a command stream into Wishbone B4 **pipelined** bus cycles and returns every termination as a response. It is the Wishbone counterpart of `apb4_master`: the same `cmd_*/rsp_*` valid/ready queues on the FUB side, each a `gaxi_skid_buffer`. There is no state machine. STB follows the head of the command queue, the slave accepts a request on STB && !STALL, and every ACK, ERR or RTY is enqueued as it arrives. Terminations arrive in issue order (a B4 rule), so nothing is tagged.

Protocol scope: B4 pipelined. RTY is reported in `rsp_status`; the master never retries on its own. CTI/BTE burst hints are carried when `USE_BURST_HINTS = 1` and tied to CLASSIC/LINEAR otherwise; no LOCK or tag signals.

2.2 Parameters

Parameter	Type	Default	Description
ADDR_WIDTH	int	32	Wishbone address width
DATA_WIDTH	int	32	Wishbone data width (port size)
CMD_DEPTH	int	4	Command queue depth

Parameter	Type	Default	Description
RSP_DEPTH	int	4	in entries , 2..8 Response queue depth in entries , 2..8; also the maximum transfers in flight
CLASSIC	int	0	0 = B4 pipelined; 1 = B4 standard (“classic”) mode, see the family README . Match the peer: the modes do not mix
USE_BURST_HINTS	int	0	0 = CTI/BTE are driven CLASSIC/LINEAR and cmd_cti/cmd_bte are ignored; 1 = the FUB’s hints ride with their transfer onto the bus
SEL_WIDTH	int	DATA_WIDTH/8	Byte-select width (derived)

RSP_DEPTH is the outstanding limit. Wishbone gives a master no way to refuse a termination, so a request is only put on the bus when its response slot is already reserved. RSP_DEPTH therefore bounds both the queue and the pipeline depth; 4 sustains one transfer per clock against a slave with up to four clocks of termination latency.

2.3 Ports

```

module wb4_master
    import wb4_pkg::*;
#(
    parameter int ADDR_WIDTH = 32,
    parameter int DATA_WIDTH = 32,
    parameter int CMD_DEPTH = 4,
    parameter int RSP_DEPTH = 4,
    parameter int CLASSIC = 0,
    // Registered-feedback burst hints (B4 ch.4). 0 = the hint ports
read
    // CLASSIC/LINEAR and cmd_cti/cmd_bte are ignored.
    parameter int USE_BURST_HINTS = 0,
    parameter int SEL_WIDTH = DATA_WIDTH / 8,

```

```

// Short Parameters
parameter int AW  = ADDR_WIDTH,
parameter int DW  = DATA_WIDTH,
parameter int SW  = SEL_WIDTH,
parameter int STW = WB4_STATUS_WIDTH,
parameter int CTW = WB4_CTI_WIDTH,
parameter int BTW = WB4_BTE_WIDTH,
// command packet: {we, adr, dat, sel} plus the hints when carried
parameter int CPW = 1 + AW + DW + SW + ((USE_BURST_HINTS != 0) ?
CTW + BTW : 0),
parameter int RPW = STW + DW // response packet:
{status, dat}
) (
    input logic          clk,
    input logic          aresetn,

    // Wishbone B4 pipelined master
    output logic          m_wb_CYC,
    output logic          m_wb_STB,
    output logic          m_wb_WE,
    output logic [AW-1:0] m_wb_ADR,
    output logic [DW-1:0] m_wb_DAT_W,
    output logic [SW-1:0] m_wb_SEL,
    output logic [CTW-1:0] m_wb_CTI, // burst hint; CLASSIC
when USE_BURST_HINTS=0
    output logic [BTW-1:0] m_wb_BTE, // burst type; LINEAR
when USE_BURST_HINTS=0
    input logic          m_wb_STALL,
    input logic          m_wb_ACK,
    input logic          m_wb_ERR,
    input logic          m_wb_RTY,
    input logic [DW-1:0] m_wb_DAT_R,

    // Command queue (FUB -> bus)
    input logic          cmd_valid,
    output logic         cmd_ready,
    input logic          cmd_we,
    input logic [AW-1:0] cmd_adr,
    input logic [DW-1:0] cmd_dat,
    input logic [SW-1:0] cmd_sel,
    input logic [CTW-1:0] cmd_cti, // ignored when
USE_BURST_HINTS=0
    input logic [BTW-1:0] cmd_bte, // ignored when
USE_BURST_HINTS=0

    // Response queue (bus -> FUB)
    output logic         rsp_valid,
    input logic          rsp_ready,

```

```

        output logic [STW-1:0]    rsp_status,
        output logic [DW-1:0]    rsp_dat
    );

```

2.3.1 Clock and Reset

Port	Width	Direction	Description
clk	1	Input	Bus clock
aresetn	1	Input	Active-low asynchronous reset (invert Wishbone RST_I at the boundary)

2.3.2 Wishbone Master Interface

Port	Width	Direction	Description
m_wb_CYC	1	Output	Cycle: high from the first STB until the last outstanding transfer terminates
m_wb_STB	1	Output	Strobe: a request is presented
m_wb_WE	1	Output	Write enable
m_wb_ADDR	ADDR_WIDTH	Output	Address
m_wb_DATA_W	DATA_WIDTH	Output	Write data (DAT_0 in the specification)
m_wb_SEL	SEL_WIDTH	Output	Byte select, reads and writes
m_wb_CTI	3	Output	Burst hint, cycle type; CLASSIC unless USE_BURST_HINTS=1
m_wb_BTE	2	Output	Burst hint, burst type; LINEAR unless USE_BURST_HINTS=1
m_wb_STALL	1	Input	Slave cannot accept this clock; the request is held
m_wb_ACK	1	Input	Normal termination
m_wb_ERR	1	Input	Error termination

Port	Width	Direction	Description
m_wb_RTY	1	Input	Retry termination
m_wb_DAT _R	DATA_WIDT H	Input	Read data (DAT_I)

2.3.3 Command Interface

Port	Width	Direction	Description
cmd_valid	1	Input	Command valid
cmd_ready	1	Output	Command queue has room
cmd_we	1	Input	Write (1) or read (0)
cmd_adr	ADDR_WIDT H	Input	Address
cmd_dat	DATA_WIDT H	Input	Write data
cmd_sel	SEL_WIDTHH	Input	Byte select
cmd_cti	3	Input	Burst hint for this transfer; ignored unless USE_BURST_HINTS=1
cmd_bte	2	Input	Burst type for this transfer; ignored unless USE_BURST_HINTS=1

2.3.4 Response Interface

Port	Width	Direction	Description
rsp_valid	1	Output	Response valid
rsp_ready	1	Input	FUB takes the response
rsp_status	2	Output	WB4_RSP_ACK (0), WB4_RSP_ERR (1), WB4_RSP_RTY (2)
rsp_dat	DATA_WIDT H	Output	Read data (undefined for writes, ERR and RTY)

2.4 Functional Description

Two counters and three wires replace the FSM an APB master needs:

```

issue    = cmd head valid && r_reserved < RSP_DEPTH
STB      = issue
CYC      = issue || r_inflight != 0
accept   = STB && !STALL          -> pop command, r_inflight++,
r_reserved++
term     = CYC && (ACK|ERR|RTY)   -> push {status, DAT_R},
r_inflight--
rsp pop  = rsp_valid && rsp_ready -> r_reserved--

```

`r_inflight` counts transfers the slave has accepted but not terminated; `r_reserved` counts everything issued that the FUB has not yet taken off the response queue, which is exactly what can occupy that queue in the worst case. Reserving at issue rather than reading the queue's count back avoids the “count is stale by one” reasoning the APB master's back-to-back path needs.

Classic mode (CLASSIC=1): the command retires with its termination (`accept = term`), so nothing is in flight between clocks; CYC follows STB; STALL is ignored. The credit gate still guarantees the push at termination has room, since `r_reserved` then counts only queued responses.

ERR and RTY are mutually exclusive in the specification. If a slave asserts both, ERR wins, so a broken slave reads as an error rather than a retry.

2.4.1 Timing

Path	Clocks
cmd_valid accepted to STB	1 (command skid)
ACK/ERR/RTY to rsp_valid	1 (response skid)
Sustained throughput	one request and one termination per clock

A stalled request is held unchanged until accepted: the command skid's head does not move until `STB && !STALL`.

2.5 Usage Example

```

wb4_master #(
    .ADDR_WIDTH (32),
    .DATA_WIDTH (32),
    .CMD_DEPTH  (4),
    .RSP_DEPTH  (4)
) u_wb_master (
    .clk          (clk),
    .aresetn      (aresetn),
    .m_wb_CYC     (wb_cyc),    .m_wb_STB     (wb_stb),
    .m_wb_WE      (wb_we),     .m_wb_ADR     (wb_adr),
    .m_wb_DAT_W   (wb_dat_o),  .m_wb_SEL     (wb_sel),
    .m_wb_STALL   (wb_stall),  .m_wb_ACK     (wb_ack),

```

```

.m_wb_ERR    (wb_err),    .m_wb_RTY    (wb_rty),
.m_wb_DAT_R  (wb_dat_i),
.cmd_valid   (cmd_valid), .cmd_ready   (cmd_ready),
.cmd_we      (cmd_we),    .cmd_adr    (cmd_adr),
.cmd_dat     (cmd_dat),    .cmd_sel    (cmd_sel),
.rsp_valid   (rsp_valid), .rsp_ready   (rsp_ready),
.rsp_status  (rsp_status), .rsp_dat    (rsp_dat)
);

```

2.6 Notes

- A termination that arrives with nothing in flight is a slave protocol violation. It is still enqueued (the FUB sees it) and reported in simulation.
- **Burst hints are carried, never acted on.** CTI and BTE are advisory in B4: the master puts the FUB's hint on the wires with the transfer it belongs to and changes nothing else. They ride inside the command queue, so a hint cannot slip onto a neighbouring transfer when the queue delays one. With `USE_BURST_HINTS = 0` the ports still exist and the bus reads CLASSIC/LINEAR, which is a legal non-burst Wishbone cycle.
- Under `ifdef FORMAL` the block asserts: STB implies CYC; CYC covers every in-flight transfer; a stalled request is held stable; the credit invariant `r_reserved <= RSP_DEPTH`; and that every termination found queue space.

2.7 Related

- [wb4_slave](#) - the mirror image
- [apb4_master](#) - the same FUB-side contract over APB
- [gaxi_skid_buffer](#) - both queues

2.8 Test

`val/amba/test_wb4_master.py` drives the block alone against the framework's Wishbone BFM (CocoTBFramework.components.wb4), with the GAXI BFMs on the queues; `val/amba/test_wb4_master_slave_loop.py` runs it back to back with its counterpart. See the [family README](#). Formal: `formal/amba/wb4_master/`.

3 wb4_master_cg

3.1 Overview

The **clock-gated variant** of [wb4_master](#): an `amba_clock_gate_ctrl` instance produces a gated clock that feeds an otherwise unmodified `wb4_master`. Functionally identical to the base module; gating is enabled and tuned by input signals, not parameters, and `cfg_cg_enable = 0` gives the base behaviour exactly. See the Shared book's [Clock-Gated Variants Guide](#) and [amba_clock_gate_ctrl](#) for the architecture and the gate cell.

3.2 Parameters

In addition to all `wb4_master` parameters:

Parameter	Type	Default	Description
CG_IDLE_COUNT_WI DTH	int	4	Width of the idle countdown; bounds the programmable idle threshold

3.3 Ports

`wb4_master`'s ports plus:

Port	Direction	Description
<code>cfg_cg_enable</code>	in	Global clock-gate enable
<code>cfg_cg_idle_count</code> [ICW-1:0]	in	Idle clocks before the clock is gated
<code>cg_gating</code>	out	Clock is gated now
<code>cg_idle</code>	out	Nothing pending (the controller's idle indicator)

3.4 Functional Description

3.4.1 Wake-Up Terms

The registered wake term follows the family rule (peer VALIDs and every place work can be pending, never a peer READY):

Term	Why
cmd_valid	a FUB command offered
response pending on the output	a termination waiting for the FUB
m_wb_CYC	a bus cycle open: requests queued, terminations due

rsp_ready is deliberately absent: a FUB that parks its ready high while idle would otherwise hold the clock on forever.

3.4.2 Masks for the Wake-Latency Overlap

Gating can engage on the same edge pending work appears, and the wake takes a clock or two. The rsp_valid and the cmd_ready seen by the FUB are both held low while cg_gating is high, so a FUB never has a command taken, or a response retired, by a stopped clock. The masks only defer; once the pending term is high gating cannot engage, so a visible valid is never truncated. The bus side needs no mask: CYC/STB come from registered state that is idle whenever the clock may stop, and a slave terminates only inside a cycle.

3.5 Notes

- Formal: `formal/amba/wb4_master_cg/` proves the wrapper's glue contract with a clock-enable model of the gate cell (a derived clock is not provable in the repo's single-clock flow; the stopped clock itself is the cocotb test's job): reset state, no gating while a cycle is open on the bus or a response is visible, no gating with the enable low, cmd_ready low while gated, and a command offered wakes the clock by its third clock; covers gating, an ungated transfer, a response handed back and re-gating.
- The wake term is combinational into the controller (which registers it once), not a second local flop as in `apb4_master_cg`; see `formal/amba/apb4_slave_cg/KNOWN_BUG.md` for the latency that flop adds.

3.6 Related

- [wb4_master](#), [wb4_slave_cg](#)
- [apb4_master_cg](#) - the same wrapper over APB

3.7 Test

`val/amba/test_wb4_master_cg.py` runs the `wb4_master` phases with gating enabled and checks, every clock, that the clock is never gated while a cycle is open, that the clock does gate after each phase drains, and that it never gates with the enable low.

4 wb4_master_retry

4.1 Overview

wb4_master_retry is [wb4_retry](#) in front of [wb4_master](#): the master's command/response queue contract and Wishbone B4 ports, with RTY terminations retried up to `cfg_max_retries` times, `cfg_retry_delay` clocks apart, before the FUB sees one. Drop it in where `wb4_master` would go when the slave is known to retry.

4.2 Parameters

Parameter	Type	Default	Description
ADDR_WIDTH	int	32	Wishbone address width
DATA_WIDTH	int	32	Wishbone data width
CMD_DEPTH	int	4	Master command queue depth
RSP_DEPTH	int	4	Master response queue depth; bounds the transfers on the bus
CLASSIC	int	0	0 = B4 pipelined, 1 = B4 standard (classic) mode
INFLIGHT	int	1	Retry block completion-buffer depth. 1 = strict program order (see wb4_retry)
USE_BURST_HINTS	int	0	0 = <code>m_wb_CTI/m_wb_BTE</code> read CLASSIC/LINEAR and <code>cmd_cti/cmd_bte</code> are ignored; 1 = the hints are carried, and they ride in the retry buffer so a re-issued transfer carries its own hint

With `INFLIGHT = 1` the bus carries one transfer at a time regardless of `RSP_DEPTH`; set `INFLIGHT` up to `RSP_DEPTH` for pipelined traffic that tolerates a retried transfer completing behind later ones.

4.3 Ports

wb4_master's ports (clk, aresetn, m_wb_* including m_wb_CTI [2:0] and m_wb_BTE [1:0], cmd_* including cmd_cti [2:0] and cmd_bte [1:0], rsp_*) plus cfg_max_retries [7:0], cfg_retry_delay [15:0], retry_count [31:0] and active_count [7:0] from the retry block.

4.4 Usage Example

```
wb4_master_retry #(
    .ADDR_WIDTH (32),
    .DATA_WIDTH (32),
    .CMD_DEPTH (4),
    .RSP_DEPTH (4),
    .INFLIGHT (1)
) u_wb_master (
    .clk (clk), .aresetn (rst_n),
    .cfg_max_retries (8'd3),
    .cfg_retry_delay (16'd16),
    .m_wb_CYC (wb_cyc), .m_wb_STB (wb_stb), .m_wb_WE
(wb_we), .m_wb_ADR (wb_adr),
    .m_wb_DAT_W (wb_dat_w), .m_wb_SEL (wb_sel),
    .m_wb_STALL (wb_stall), .m_wb_ACK (wb_ack), .m_wb_ERR
(wb_err), .m_wb_RTY (wb_rty),
    .m_wb_DAT_R (wb_dat_r),
    .cmd_valid (cmd_valid), .cmd_ready (cmd_ready), .cmd_we
(cmd_we), .cmd_adr (cmd_adr),
    .cmd_dat (cmd_dat), .cmd_sel (cmd_sel),
    .rsp_valid (rsp_valid), .rsp_ready (rsp_ready), .rsp_status
(rsp_status), .rsp_dat (rsp_dat),
    .retry_count (), .active_count ()
);
```

4.5 Related

- [wb4_retry](#), [wb4_master](#)

4.6 Test

val/amba/test_wb4_master_retry.py; see [wb4_retry](#).

5 wb4_master_stub

5.1 Overview

[wb4_master](#) with its FUB-side queues presented as a single **packed vector** instead of named fields, matching what `apb4_master_stub` and `apb5_master_stub` offer. A shim-style converter that already carries a packed command through its own pipeline connects one bus instead of six, and the packing lives here rather than being re-derived by every consumer.

Nothing else differs: the stub instantiates the ordinary block and only splices the vector.

5.2 Packing

Most significant field first. Both stubs use the same order, so a `wb4_master_stub` and a `wb4_slave_stub` connect directly:

```
cmd_data = {we, adr, dat, sel, cti, bte}    // CPW = 1 + AW + DW + SW
+ 3 + 2
rsp_data = {status, dat}                  // RPW = 2 + DW
```

`cti` and `bte` hold their bits whatever `USE_BURST_HINTS` is, so the vector width does not move with the parameter. With the hints off the inner block ignores them and the bus reads CLASSIC/LINEAR.

5.3 Parameters

Every parameter of [wb4_master](#), plus the derived widths:

Parameter	Value	Description
CPW	$1 + AW + DW + SW + 3 + 2$	Packed command width
RPW	$2 + DW$	Packed response width

5.4 Ports

`wb4_master`'s Wishbone side unchanged. On the FUB side, the command arrives packed and the response leaves packed.

Port	Direction	Description
<code>cmd_valid / cmd_ready</code>	Input / Output	Command handshake

Port	Direction	Description
cmd_data [CPW-1:0]	Input	Packed command
rsp_valid / rsp_ready	Output / Input	Response handshake
rsp_data [RPW-1:0]	Output	Packed response

5.5 Related

- [wb4_master](#) - the block this wraps
- [wb4_slave_stub](#) - the other half of a stub pair
- [wb4_pkg](#) - the status encoding inside rsp_data

5.6 Test

val/amba/test_wb4_stubs.py checks the packing directly, in both directions and with the burst hints on and off. Two mutations fail it: swapping dat/sel in the master's unpack, and reversing the slave's response unpack.

6 wb4_monitor

6.1 Overview

wb4_monitor watches the cmd_*/rsp_* queues of a wb4_master or wb4_slave and reports what happens on the Wishbone side as monitor bus packets: a completion or an error per transfer, a timeout when a request or a termination is late, a latency figure when a transfer crosses a threshold, optional queue-activity debug events, and address-range violations through the shared apb_monitor_addr_check. It is the Wishbone member of the monitor family and has the same configuration, monitor bus and status ports as apb4_monitor; every packet is tagged PROTOCOL_WB (4'h5) and its event codes come from monitor_wb4_pkg.

The queues are the timing-convenient proxy for the bus, the same place apb4_monitor attaches: a command handshake is a request the master will put on the bus, a response handshake is the termination the slave returned. One difference from APB matters for the design: Wishbone B4 pipelined mode keeps several transfers open, and terminates them **in issue order**. The monitor therefore tracks transfers in an in-order queue, not a slot table. A slot table that pairs a response with “the first active slot” mis-pairs as soon as a freed slot is reused while an older one is still open, which pipelined traffic does constantly. The in-order queue pairs the response with the oldest open request by construction.

6.2 Parameters

Parameter	Type	Default	Description
USE_MONITOR	bit	1	0 removes the body and ties the outputs to idle
N_ADDR_RANGES	int	0	Address-range checker ranges; 0 leaves the checker out
ADDR_WIDTH	int	32	Wishbone address width
DATA_WIDTH	int	32	Wishbone data width
UNIT_ID	logic [7:0]	8'h01	Unit id stamped into every packet
AGENT_ID	logic [15:0]	16'h000B	Agent id stamped into every packet
MAX_TRANSACTION S	int	8	Depth of the in-order tracking queue; transfers open at once beyond it are reported, not tracked
MONITOR_FIFO_DEP TH	int	8	Event FIFO depth between event selection and the monitor bus
USE_BURST_HINTS	int	0	1 reports the transfer's CTI in aux_data[7:5]; 0 leaves those bits zero and ignores cmd_cti

MAX_TRANSACTION_S should match the RSP_DEPTH of the wb4_master (or the MAX_OUTSTANDING of the wb4_slave) it watches; those bound how many transfers can be open, so a queue of the same depth never overflows.

6.3 Ports

```
module wb4_monitor
    import monitor_common_pkg::*; // PROTOCOL_WB, PktType*, packet
    builder
    import monitor_wb4_pkg::*; // WB_ERR_*, WB_TIMEOUT_*,
    WB_COMPL_*, WB_PERF_*, WB_DEBUG_*
    import wb4_pkg::*; // WB4_RSP_* status encoding
    #(
        parameter bit USE_MONITOR = 1'b1,
```

```

parameter int N_ADDR_RANGES      = 0,
parameter int ADDR_WIDTH          = 32,
parameter int DATA_WIDTH         = 32,
parameter logic [7:0] UNIT_ID     = 8'h01,
parameter logic [15:0] AGENT_ID    = 16'h000B,
parameter int MAX_TRANSACTIONS     = 8,
parameter int MONITOR_FIFO_DEPTH   = 8,
parameter int USE_BURST_HINTS      = 0
)
(
    input logic aclk,
    input logic aresetn,

    // Command queue being watched
    input logic cmd_valid,
    input logic cmd_ready,
    input logic cmd_we,
    input logic [AW-1:0] cmd_adr,
    input logic [DW-1:0] cmd_dat,
    input logic [SW-1:0] cmd_sel,
    input logic [CTW-1:0] cmd_cti, // ignored when
USE_BURST_HINTS=0

    // Response queue being watched
    input logic rsp_valid,
    input logic rsp_ready,
    input logic [1:0] rsp_status, // WB4_RSP_ACK /
ERR / RTY
    input logic [DW-1:0] rsp_dat,

    // Configuration (same set as apb4_monitor)
    input logic cfg_error_enable,
    input logic cfg_timeout_enable,
    input logic cfg_protocol_enable,
    input logic cfg_slvrr_enable,
    input logic cfg_perf_enable,
    input logic cfg_latency_enable,
    input logic cfg_throughput_enable,
    input logic cfg_debug_enable,
    input logic cfg_trans_debug_enable,
    input logic [3:0] cfg_debug_level,
    input logic [15:0] cfg_cmd_timeout_cnt,
    input logic [15:0] cfg_rsp_timeout_cnt,
    input logic [31:0] cfg_latency_threshold,
    input logic [15:0] cfg_throughput_threshold,

    // Address-range checker configuration (N_ADDR_RANGES > 0)

```



```

input logic [N-1:0]          cfg_addr_check_enable,
input logic [N-1:0]          cfg_addr_range_enable,
input logic [N-1:0][AW-1:0]  cfg_addr_range_low,
input logic [N-1:0][AW-1:0]  cfg_addr_range_high,

input monbus_timestamp_t      i_mon_time,

// Monitor bus
output logic                  monbus_valid,
input logic                  monbus_ready,
output monitor_packet_t      monbus_packet,
output monbus_timestamp_t     monbus_timestamp,

// Status
output logic [7:0]            active_count,
output logic [15:0]           error_count,
output logic [31:0]           transaction_count
);

```

6.3.1 Command and Response Queues

The monitor is a pure observer: it samples `cmd_valid` && `cmd_ready` and `rsp_valid` && `rsp_ready` and never drives either queue. `cmd_dat` is accepted for port uniformity and not used; `rsp_dat` is reported only in the orphan-response packet.

6.3.2 Configuration

Signal	Effect
<code>cfg_error_enable</code>	Master enable for error packets
<code>cfg_slverr_enable</code>	Report an ERR termination as <code>WB_ERR_ERR</code> . This gates the <code>error_count</code> increment too: with it clear, an ERR termination is neither reported nor counted
<code>cfg_protocol_enable</code>	Report a response with nothing outstanding as <code>WB_ERR_ORPHAN_RSP</code>
<code>cfg_timeout_enable</code>	Enable both timeouts; a count of 0 disables that timeout
<code>cfg_cmd_timeout_cnt</code>	Clocks a request may sit on <code>cmd_valid</code> without <code>cmd_ready</code> before <code>WB_TIMEOUT_CMD</code>
<code>cfg_rsp_timeout_cnt</code>	Clocks the oldest open transfer may

Signal	Effect
	wait for its termination before WB_TIMEOUT_RSP
cfg_perf_enable, cfg_latency_enable	Emit a latency packet when a transfer's latency exceeds cfg_latency_threshold
cfg_debug_enable, cfg_trans_debug_enable	Emit WB_DEBUG_QUEUE_ACTIVE / WB_DEBUG_QUEUE_IDLE on the tracking queue's edges
cfg_throughput_*, cfg_debug_level	Accepted for family uniformity; no packet today

6.3.3 Status

active_count is the number of tracked transfers open right now, transaction_count the number terminated since reset, and error_count the number of ERR terminations (when cfg_slverr_enable), orphan responses and tracking overflows.

6.4 Functional Description

6.4.1 Transaction Tracking

A command handshake pushes {we, adr, sel[3:0], cti, timestamp} at the tail of the queue; a response handshake pops the head. The head is the transfer the response belongs to, because B4 terminates in issue order. Two edge cases are reported rather than guessed at:

- **Orphan response.** A response handshake with an empty queue. With cfg_protocol_enable it is a WB_ERR_ORPHAN_RSP packet carrying rsp_dat and the status; transaction_count does not move.
- **Tracking lost.** A command handshake with the queue full. The transfer is not tracked (its later response will show up as an orphan) and a WB_ERR_TRACK_LOST packet carries its address. Size MAX_TRANSACTIONS to the master's RSP_DEPTH and this never happens.

6.4.2 Event Detection

Event	Packet type	Event code	event_data[31:0] l	aux (event_data[39: 32])
Termination ACK	Completion	WB_COMPL_REA D / WB_COMPL_WRI	address	{cti[2:0], sel[3:0], we}

Event	Packet type	Event code	event_data[31:0]	aux (event_data[39:32])
Termination RTY	Completion	TE WB_COMPL_RTY	address	{cti[2:0], sel[3:0], we}
Termination ERR	Error	WB_ERR_ERR	address	{cti[2:0], sel[3:0], we}
Response, nothing open	Error	WB_ERR_ORPHAN_RSP	rsp_dat	{6'b0, status}
Command, queue full	Error	WB_ERR_TRACK_LOST	address	{cti[2:0], sel[3:0], we}
cmd_valid stalled	Timeout	WB_TIMEOUT_CMD	address on cmd_adr	stall count (low 8 bits)
Head transfer late	Timeout	WB_TIMEOUT_RSP	head address	age (low 8 bits)
Latency over threshold	Perf	WB_PERF_READ_LATENCY / WB_PERF_WRITE_LATENCY	latency in clocks	{cti[2:0], sel[3:0], we}
Queue non-empty / empty	Debug	WB_DEBUG_QUEUE_ACTIVE / WB_DEBUG_QUEUE_IDLE	occupancy	0
Address out of range	Error	WB_ERR_ADDR_RANGE	see apb_monitor_addr_check	see apb_monitor_addr_check

cti[2:0] is zero on a USE_BURST_HINTS=0 build, which is what every consumer decoded before the hints existed, so the packet format did not change for anyone who does not ask for them. Only CTI is reported: the aux byte has exactly three spare bits, which is WB4_CTI_WIDTH, and BTE is deliberately left out rather than squeezed in. The hint travels **in the tracking entry**, so a completion reports the CTI of its own transfer even with several open at once – reading cmd_cti at completion time would report whatever request happened to be on the queue then.

RTY is a completion, not an error: the FUB decides whether to retry, and the monitor reports what the slave said. Each timeout fires **once**: the command timeout once per stall (it re-arms when the request is taken or withdrawn), the response timeout once per queue entry (a flag in the entry).

When the head pops and the next entry is already older than the limit, that entry is reported on the following clock.

6.4.3 Monitor Packet Format

Standard 128-bit packet from `create_monitor_packet` with a 64-bit side-band timestamp taken from `i_mon_time` at emission:

- `packet_type` per the table above; `protocol` = `PROTOCOL_WB` (4'h5)
- `event_code` from `monitor_wb4_pkg`; `channel_id` = 0 (Wishbone has no IDs)
- `unit_id` = `UNIT_ID`, `agent_id` = `AGENT_ID`
- `event_data[63:40]` = 0, `[39:32]` = `aux`, `[31:0]` = `value` per the table

6.4.4 Event Priority and Loss

One event is written to the FIFO per clock, in the order error, timeout, perf, debug, completion; a lower-priority event that lands in the same clock as a higher one is dropped, and so is any event that arrives while the FIFO is full. The tracking queue does not wait for the packet, so `active_count` and `transaction_count` stay exact. `error_count` is a single increment per clock, so two error events landing together – an ERR termination and a tracking overflow in the same clock, which pipelined traffic can reach – advance it by one rather than two. This is the family's lossy-but-honest contract; size `MONITOR_FIFO_DEPTH` and the monitor bus consumer for the burstiest traffic the design can produce.

The event FIFO is a `gaxi_fifo_sync` in mux-read mode (`REGISTERED=0`): `rd_data` is valid in the clock of the read handshake, which is when the packet is built. The registered-read mode presents `rd_data` one clock after the handshake (the framework's `fifo_flop` BFM contract) and, read combinationally, re-presents the popped entry for a clock on back-to-back reads, so a burst of events would duplicate one packet and lose the next. This module's first test caught exactly that; see TASK-086 for the siblings.

6.5 Timing Characteristics

- Push and pop are registered from the queue handshakes; `active_count` updates on the clock after a handshake.
- A completion packet leaves the event FIFO one clock after the response handshake and the skid buffer one clock later, so `monbus_valid` for a termination rises two clocks after `rsp_valid` && `rsp_ready` when the bus is idle.
- `monbus_valid` is held until `monbus_ready` (skid buffer).

6.6 Usage Example

```
wb4_monitor #(
    .ADDR_WIDTH      (32),
    .DATA_WIDTH      (32),
    .UNIT_ID         (8'h02),
    .AGENT_ID        (16'h0020),
    .MAX_TRANSACTIONS (4),           // = wb4_master RSP_DEPTH
    .N_ADDR_RANGES   (2)
) u_wb_mon (
    .aclk (clk), .aresetn (rst_n),
    .cmd_valid (cmd_valid), .cmd_ready (cmd_ready), .cmd_we (cmd_we),
    .cmd_adr (cmd_adr), .cmd_dat (cmd_dat), .cmd_sel (cmd_sel),
    .rsp_valid (rsp_valid), .rsp_ready (rsp_ready),
    .rsp_status (rsp_status), .rsp_dat (rsp_dat),
    .cfg_error_enable (1'b1), .cfg_timeout_enable (1'b1),
    .cfg_protocol_enable (1'b1), .cfg_slverr_enable (1'b1),
    .cfg_perf_enable (1'b0), .cfg_latency_enable (1'b0),
    .cfg_throughput_enable (1'b0), .cfg_debug_enable (1'b0),
    .cfg_trans_debug_enable (1'b0), .cfg_debug_level (4'h0),
    .cfg_cmd_timeout_cnt (16'd256), .cfg_rsp_timeout_cnt (16'd1024),
    .cfg_latency_threshold (32'd0), .cfg_throughput_threshold (16'd0),
    .cfg_addr_check_enable (1'b1), .cfg_addr_range_enable (2'b11),
    .cfg_addr_range_low ('{32'h0000_0000, 32'h4000_0000}),
    .cfg_addr_range_high ('{32'h0FFF_FFFF, 32'h4FFF_FFFF}),
    .i_mon_time (mon_time),
    .monbus_valid (monbus_valid), .monbus_ready (monbus_ready),
    .monbus_packet (monbus_packet), .monbus_timestamp
(monbus_timestamp),
    .active_count (), .error_count (), .transaction_count ()
);
```

6.7 Notes

- Under `ifdef FORMAL` the block asserts the queue occupancy bound, that a pop only happens with something open, and that an orphan is only flagged when nothing is. `formal/amba/wb4_monitor/` adds the port-level properties (reset, protocol tag, valid-held, occupancy tracks the handshakes, `transaction_count` moves only on a pop) and covers every packet class.
- `USE_MONITOR=0` leaves the ports in place and ties `monbus_valid` and the counters to zero, so a build can drop the monitor without touching the wrapper.
- `monitor_wb4_pkg` is imported by this module only; it is deliberately not re-exported by `monitor_pkg`, so no existing consumer's filelist changes. `PROTOCOL_WB` itself lives in `monitor_common_pkg` (an additive enum entry).

6.8 Related

- [wb4_master](#), [wb4_slave](#) - what it watches
- [apb4_monitor](#) - the family template
- [apb_monitor_addr_check](#) - the shared range checker, tagged `PROTOCOL_WB` here through its `PROTOCOL` parameter
- [monitor_package_spec](#) - packet format and protocol ids

6.9 Test

`val/amba/test_wb4_monitor.py` drives both queues with GAXI BFM (a producer/consumer pair on each side, an age-based responder) and decodes the packets through the shared `MonbusSlave/TBClasses.monbus.parse` path. Phases: ACK/ERR/RTY mix in command order, several transfers open (in-order pairing), latency threshold, both timeouts once each, orphan, tracking overflow, debug edges, and address range on the `N_ADDR_RANGES=2` build. Four RTL mutations (timeout re-fire, swapped read/write codes, pairing off by one, orphan not reported) all fail the test.

7 `wb4_pkg`

The response-status encoding shared by every module in the Wishbone B4 family and by the Python bus functional models, together with the registered-feedback burst hints of B4 chapter 4. Three enums and three width constants, kept in a package so each encoding has exactly one definition.

7.1 Design Notes

This is a package, not a module. No ports, no clock. Compile order matters: it must be analysed before anything importing it, which is why `rtl/amba/filelists/wb4_pkg.f` exists and every consumer - `f` includes it rather than hand-listing the source.

Why a status field at all. Wishbone terminates a transfer with one of three wires, ACK, ERR or RTY. The FUB-side response queue carries the outcome as a 2-bit status instead, so a consumer reads one field rather than decoding three mutually exclusive strobes. `WB4_STATUS_WIDTH` sizes that field everywhere it appears.

No test of its own, and none expected. A package has no behaviour to simulate. It is verified by every module that imports it failing to elaborate if a declaration is wrong.

7.2 Declarations

```
package wb4_pkg;
  localparam int WB4_STATUS_WIDTH = 2;
```

```

typedef enum logic [WB4_STATUS_WIDTH-1:0] {
    WB4_RSP_ACK = 2'b00,    // normal completion (read data valid)
    WB4_RSP_ERR = 2'b01,    // slave error
    WB4_RSP_RTY = 2'b10     // slave asks for a retry
} wb4_status_t;

// Registered-feedback burst hints (B4 chapter 4), advisory.
CLASSIC and
// LINEAR are zero so a tied-off bus is a legal non-burst bus.
localparam int WB4_CTI_WIDTH = 3;
localparam int WB4_BTE_WIDTH = 2;

typedef enum logic [WB4_CTI_WIDTH-1:0] {
    WB4_CTI_CLASSIC = 3'b000,
    WB4_CTI_CONST_ADDR = 3'b001,
    WB4_CTI_INCR = 3'b010,
    WB4_CTI_RSVD_3 = 3'b011,
    WB4_CTI_RSVD_4 = 3'b100,
    WB4_CTI_RSVD_5 = 3'b101,
    WB4_CTI_RSVD_6 = 3'b110,
    WB4_CTI_EOB = 3'b111
} wb4_cti_t;

typedef enum logic [WB4_BTE_WIDTH-1:0] {
    WB4_BTE_LINEAR = 2'b00,
    WB4_BTE_WRAP4 = 2'b01,
    WB4_BTE_WRAP8 = 2'b10,
    WB4_BTE_WRAP16 = 2'b11
} wb4_bte_t;
endpackage : wb4_pkg

```

Name	Value	Meaning
WB4_STATUS_WIDTH	2	Width of every rsp_status / cmd-side status field in the family
WB4_RSP_ACK	2'd0	Normal termination
WB4_RSP_ERR	2'd1	Slave signalled an error
WB4_RSP_RTY	2'd2	Slave asked for the transfer to be retried
(unused)	2'd3	Not an encoding; treated as reserved

RTY is a status, not an action. `wb4_master` never re-issues on its own; it reports what the slave said and the FUB decides. Put `wb4_retry` in front of the master to absorb retries transparently up to a budget.

7.3 Burst hint encodings

Registered-feedback cycles (B4 chapter 4). Both are **advisory**: the family carries them when `USE_BURST_HINTS = 1` and neither the master nor the slave changes behaviour on them.

<code>wb4_cti_t</code>	Value	Meaning
<code>WB4_CTI_CLASSIC</code>	<code>3'b000</code>	Classic cycle, no burst
<code>WB4_CTI_CONST_ADDR</code>	<code>3'b001</code>	Constant-address burst (a FIFO-like target)
<code>WB4_CTI_INCR</code>	<code>3'b010</code>	Incrementing burst
<code>WB4_CTI_RSVD_3..</code> <code>WB4_CTI_RSVD_6</code>	<code>3'b011-3'b110</code>	Reserved by the spec
<code>WB4_CTI_EOB</code>	<code>3'b111</code>	End-of-burst: the last transfer of the run

<code>wb4_bte_t</code>	Value	Meaning
<code>WB4_BTE_LINEAR</code>	<code>2'b00</code>	Linear burst
<code>WB4_BTE_WRAP4</code>	<code>2'b01</code>	4-beat wrap
<code>WB4_BTE_WRAP8</code>	<code>2'b10</code>	8-beat wrap
<code>WB4_BTE_WRAP16</code>	<code>2'b11</code>	16-beat wrap

`WB4_CTI_WIDTH` is 3 and `WB4_BTE_WIDTH` is 2. Both encodings put the non-burst case at zero on purpose, so a bus with the hint wires tied off is a legal classic bus rather than an illegal encoding.

7.4 Consumers

Every module in the family imports it: `wb4_master`, `wb4_slave`, `wb4_monitor`, `wb4_retry`, `wb4_master_retry`, the clock-gated and CDC variants, and the `axil4_to_wb4` bridge in projects/components/converters.

The DV side mirrors the same three values in `CocoTBFramework.components.shared.wb4_common` (`WB4_STATUS_ACK`, `WB4_STATUS_ERR`, `WB4_STATUS_RTY`), and `monitor_wb4_pkg` carries the separate event codes the monitor emits.

7.5 Related

- [Wishbone B4 family README](#) - the protocol scope and the mode rules
- `monitor_wb4_pkg` - the monitor's event codes, a different package

8 wb4_retry

8.1 Overview

`wb4_retry` sits on the FUB side of `wb4_master` and turns a Wishbone RTY into a retry. Every command the FUB issues is held in an in-order completion buffer until its answer has been handed back. ACK and ERR complete the entry as they arrive. RTY puts the entry back on the issue path after `cfg_retry_delay` clocks, until `cfg_max_retries` re-issues have been spent; only then does the FUB see the RTY. Responses reach the FUB in command order whatever happened on the bus, and re-issues always take priority over new commands.

`cfg_max_retries = 0` makes the block a pass-through. `wb4_master_retry` is the block and the master together, with the master's ports.

Order on the bus. A retried command re-appears on the bus behind the commands issued after it, which with `INFLIGHT > 1` may already have terminated. The FUB still gets its responses in order, but a read issued behind a write that was retried can observe memory from before that write. `INFLIGHT = 1`, the default, keeps program order exactly: one command on the bus at a time, retries included. Use `INFLIGHT > 1` only for traffic with no ordering dependence across transfers.

8.2 Parameters

Parameter	Type	Default	Description
<code>ADDR_WIDTH</code>	<code>int</code>	32	Wishbone address width
<code>DATA_WIDTH</code>	<code>int</code>	32	Wishbone data width
<code>INFLIGHT</code>	<code>int</code>	1	Completion-buffer entries: commands accepted from the FUB and not yet answered. 1 = strict program order

8.3 Ports

```
module wb4_retry
    import wb4_pkg::*;
#(
    parameter int ADDR_WIDTH = 32,
```

```

parameter int DATA_WIDTH = 32,
parameter int INFLIGHT    = 1,
// Short Parameters
parameter int AW  = ADDR_WIDTH,
parameter int DW  = DATA_WIDTH,
parameter int SW  = DW/8,
parameter int STW = WB4_STATUS_WIDTH,
parameter int CTW = WB4_CTI_WIDTH,
parameter int BTW = WB4_BTE_WIDTH
)
(
    input logic          clk,
    input logic          aresetn,

    input logic [7:0]    cfg_max_retries,    // 0 = pass RTY
    through
    input logic [15:0]   cfg_retry_delay,    // clocks from RTY to
    re-issue

    // FUB side: the same contract wb4_master offers
    input logic          cmd_valid,
    output logic         cmd_ready,
    input logic          cmd_we,
    input logic [AW-1:0] cmd_adr,
    input logic [DW-1:0] cmd_dat,
    input logic [SW-1:0] cmd_sel,
    input logic [CTW-1:0] cmd_cti,          // burst hint, stored
    with its transfer
    input logic [BTW-1:0] cmd_bte,
    output logic         rsp_valid,
    input logic          rsp_ready,
    output logic [1:0]   rsp_status,       // WB4_RSP_ACK /
    ERR / RTY
    output logic [DW-1:0] rsp_dat,

    // wb4_master side
    output logic         mst_cmd_valid,
    input logic          mst_cmd_ready,
    output logic         mst_cmd_we,
    output logic [AW-1:0] mst_cmd_adr,
    output logic [DW-1:0] mst_cmd_dat,
    output logic [SW-1:0] mst_cmd_sel,
    output logic [CTW-1:0] mst_cmd_cti,
    output logic [BTW-1:0] mst_cmd_bte,
    input logic          mst_rsp_valid,
    output logic         mst_rsp_ready,
    input logic [1:0]    mst_rsp_status,
    input logic [DW-1:0] mst_rsp_dat,

```

```

    output logic [31:0]      retry_count,      // re-issues since
reset
    output logic [7:0]      active_count      // entries in the
buffer
);

```

8.3.1 Configuration

`cfg_max_retries` is the number of re-issues allowed per command, not the number of attempts: with 3, a command is presented to the bus at most four times. `cfg_retry_delay` is the number of clocks between the RTY and the re-issue; 0 re-issues on the next clock the master can take a command. Both are sampled when used, so they can change between transfers.

8.3.2 Status

`retry_count` counts every re-issue since reset. `active_count` is the number of commands accepted from the FUB and not yet answered, at most INFLIGHT.

8.4 Functional Description

Each entry of the completion buffer holds the command (`we`, `adr`, `dat`, `sel`), a retry count, a delay timer and, once answered, the status and read data. Entries are allocated at the tail when a command is accepted and released at the head when the FUB takes the response, so the FUB order is the buffer order. A separate issue log records which entry each command handed to the master belongs to, in the order the master received them; Wishbone terminates in that order, so the log head is always the entry a termination belongs to.

Event	Effect
<code>cmd_valid && cmd_ready</code>	Entry allocated at the tail and forwarded to <code>mst_cmd_*</code> in the same clock
<code>mst_rsp_*</code> handshake, ACK or ERR	Log-head entry marked done with the status and data
<code>mst_rsp_*</code> handshake, RTY, retries left	Entry marked waiting, retry count +1, timer loaded with <code>cfg_retry_delay</code> , <code>retry_count</code> +1
<code>mst_rsp_*</code> handshake, RTY, budget spent	Entry marked done with RTY
Waiting entry with timer at 0	Re-issued on <code>mst_cmd_*</code> before any new command (oldest first)
Head entry done	<code>rsp_valid</code> ; released on the handshake

`cmd_ready` is low while a retry is pending issue, while the buffer is full, and while the master cannot take a command, so a FUB never has a command accepted that would be reordered behind a retry. `mst_rsp_ready` is high whenever a command is on the bus: the termination's entry is waiting for it, so the master is never back-pressured on a response.

8.5 Timing

- A new command reaches `mst_cmd_*` combinationally in the clock it is accepted; the master's own skid buffer registers it.
- A termination is recorded in the clock it arrives; `rsp_valid` for the head follows one clock later (registered state).
- With `INFLIGHT = 1` the bus carries one transfer at a time, so the sustained rate is one transfer per round trip. With `INFLIGHT = N` and a master `RSP_DEPTH >= N`, up to `N` transfers are open.

8.6 Notes

- Under `ifdef FORMAL` the block asserts the occupancy bounds of both the buffer and the issue log, that everything on the bus is an allocated entry, that a retry is never issued in the clock a new command is accepted, and that the FUB only ever sees the head once it is done.
`formal/amba/wb4_retry/` adds the port-level contract (payload equality of every re-issue, `1 + retries` issues per command, the budget and the delay, `RTY` to the FUB only once the budget is spent) at `INFLIGHT = 1` and the bounds at `INFLIGHT = 2`.
- The block does not know why the slave retried. Back-off is a fixed delay; a slave that needs a longer or growing gap needs a larger `cfg_retry_delay` from the controlling software.

8.7 Related

- [wb4_master_retry](#) - this block with `wb4_master` behind it
- [wb4_master](#) - what it drives
- [axil4_to_wb4](#) - a bridge that maps `RTY` to an AXI error; put this block between it and the master to retry instead

8.8 Test

`val/amba/test_wb4_master_retry.py`, through the wrapper: the framework Wishbone slave answers with address windows that retry a bounded number of times, retry forever, or error, so

every FUB response, the number of re-issues (`retry_count`, the monitor's transfer count, the slave's RTY count) and the read data follow from the model. Formal: `formal/amba/wb4_retry/`.

9 wb4_slave

9.1 Overview

`wb4_slave` accepts Wishbone B4 **pipelined** transfers one per clock and presents each on a command queue; it terminates them, in order, from a response queue with a registered ACK, ERR or RTY and read data. It is the Wishbone counterpart of `apb4_slave`, with the same `cmd_*/rsp_*` valid/ready contract on the FUB side. There is no state machine: STALL is the inverse of “can accept”, and the termination side is one counter and one register.

Protocol scope: B4 pipelined. The FUB chooses the termination through `rsp_status`, so a FUB can answer RTY without the slave knowing why.

9.2 Parameters

Parameter	Type	Default	Description
ADDR_WIDTH	int	32	Wishbone address width
DATA_WIDTH	int	32	Wishbone data width (port size)
CMD_DEPTH	int	2	Command queue depth in entries , 2..8
RSP_DEPTH	int	2	Response queue depth in entries , 2..8
MAX_OUTSTANDING	int	16	Transfers accepted but not yet terminated before STALL asserts
CLASSIC	int	0	0 = B4 pipelined; 1 = B4 standard (“classic”) mode, see the family README . Match the peer: the modes do not mix
USE_BURST_HINTS	int	0	0 = the bus CTI/BTE inputs are ignored and <code>cmd_cti/cmd_bte</code> read CLASSIC/LINEAR; 1 =

Parameter	Type	Default	Description
			each transfer's hints are handed to the FUB with it
SEL_WIDTH	int	DATA_WIDTH/8	Byte-select width (derived)

MAX_OUTSTANDING bounds the FUB's in-order pipeline, not the master's: a master's own limit is its response queue. Set it to at least the number of commands the FUB can hold before it produces the first response, or the bus stalls short of the FUB's throughput.

9.3 Ports

```

module wb4_slave
    import wb4_pkg::*;
#(
    parameter int ADDR_WIDTH      = 32,
    parameter int DATA_WIDTH     = 32,
    parameter int CMD_DEPTH       = 2,
    parameter int RSP_DEPTH       = 2,
    parameter int MAX_OUTSTANDING = 16,
    parameter int CLASSIC         = 0,
    parameter int SEL_WIDTH       = DATA_WIDTH / 8,
    // Short Parameters
    parameter int AW  = ADDR_WIDTH,
    parameter int DW  = DATA_WIDTH,
    parameter int SW  = SEL_WIDTH,
    parameter int STW = WB4_STATUS_WIDTH,
    parameter int CTW = WB4_CTI_WIDTH,
    parameter int BTW = WB4_BTE_WIDTH,
    // command packet: {we, adr, dat, sel} plus the hints when carried
    parameter int CPW = 1 + AW + DW + SW + ((USE_BURST_HINTS != 0) ?
CTW + BTW : 0),
    parameter int RPW = STW + DW           // response packet:
{status, dat}
) (
    input logic      clk,
    input logic      aresetn,

    // Wishbone B4 pipelined slave
    input logic      s_wb_CYC,
    input logic      s_wb_STB,
    input logic      s_wb_WE,
    input logic [AW-1:0] s_wb_ADR,
    input logic [DW-1:0] s_wb_DAT_W,
    input logic [SW-1:0] s_wb_SEL,

```

```

    input logic [CTW-1:0] s_wb_CTI, // burst hint; ignored
when USE_BURST_HINTS=0
    input logic [BTW-1:0] s_wb_BTE,
    output logic s_wb_STALL,
    output logic s_wb_ACK,
    output logic s_wb_ERR,
    output logic s_wb_RTY,
    output logic [DW-1:0] s_wb_DAT_R,

    // Command queue (bus -> FUB)
    output logic cmd_valid,
    input logic cmd_ready,
    output logic cmd_we,
    output logic [AW-1:0] cmd_adr,
    output logic [DW-1:0] cmd_dat,
    output logic [SW-1:0] cmd_sel,
    output logic [CTW-1:0] cmd_cti, // CLASSIC when
USE_BURST_HINTS=0
    output logic [BTW-1:0] cmd_bte, // LINEAR when
USE_BURST_HINTS=0

    // Response queue (FUB -> bus)
    input logic rsp_valid,
    output logic rsp_ready,
    input logic [STW-1:0] rsp_status,
    input logic [DW-1:0] rsp_dat
);

```

9.3.1 Clock and Reset

Port	Width	Direction	Description
clk	1	Input	Bus clock
aresetn	1	Input	Active-low asynchronous reset

9.3.2 Wishbone Slave Interface

Port	Width	Direction	Description
s_wb_CYC	1	Input	Cycle
s_wb_STB	1	Input	Strobe: a request is presented
s_wb_WE	1	Input	Write enable
s_wb_ADR	ADDR_WIDT	Input	Address

Port	Width	Direction	Description
	H		
s_wb_DAT_W	DATA_WIDT H	Input	Write data (DAT_I at the slave)
s_wb_SEL	SEL_WIDTH	Input	Byte select
s_wb_CTI	3	Input	Burst hint, cycle type; ignored unless USE_BURST_HINTS=1
s_wb_BTE	2	Input	Burst hint, burst type; ignored unless USE_BURST_HINTS=1
s_wb_STAL_L	1	Output	Cannot accept this clock; combinational from queue room and the outstanding count, never from STB
s_wb_ACK	1	Output	Normal termination (registered, one clock)
s_wb_ERR	1	Output	Error termination (registered, one clock)
s_wb_RTY	1	Output	Retry termination (registered, one clock)
s_wb_DAT_R	DATA_WIDT H	Output	Read data (DAT_0 at the slave); holds between terminations

9.3.3 Command Interface

Port	Width	Direction	Description
cmd_valid	1	Output	Command valid
cmd_ready	1	Input	FUB takes the command
cmd_we	1	Output	Write (1) or read (0)
cmd_adr	ADDR_WIDT H	Output	Address
cmd_dat	DATA_WIDT H	Output	Write data
cmd_sel	SEL_WIDTH	Output	Byte select

Port	Width	Direction	Description
cmd_cti	3	Output	Burst hint off the bus; CLASSIC unless USE_BURST_HINTS=1
cmd_bte	2	Output	Burst type off the bus; LINEAR unless USE_BURST_HINTS=1

9.3.4 Response Interface

Port	Width	Direction	Description
rsp_valid	1	Input	Response valid
rsp_ready	1	Output	Response queue has room
rsp_status	2	Input	WB4_RSP_ACK (0), WB4_RSP_ERR (1), WB4_RSP_RTY (2)
rsp_dat	DATA_WIDT H	Input	Read data

9.4 Functional Description

```

STALL = !cmd queue room || r_outstanding == MAX_OUTSTANDING
accept = CYC && STB && !STALL      -> push {we, adr, dat, sel},
r_outstanding++
term   = rsp head valid && r_outstanding != 0 && CYC && r_abandoned ==
0
      -> register ACK|ERR|RTY from status, DAT_R, pop,
r_outstanding--
orphan = rsp head valid && (r_outstanding == 0 || r_abandoned != 0) ->
pop and drop
abort  = !CYC && r_outstanding != 0 -> r_abandoned += r_outstanding,
r_outstanding <= 0

```

Classic mode (CLASSIC=1): STALL is driven low; a request is accepted when nothing is outstanding and no termination is on the wire this clock, so a held presentation is taken exactly once; MAX_OUTSTANDING is effectively 1.

Orphan guard. A response with nothing outstanding cannot belong to any transfer (a duplicate from the FUB, or a response to a transfer the master abandoned). It is dropped, and reported in simulation. Left in the queue it would terminate the *next* transfer and every later response would be off by one: the positional mis-pairing apb4_slave's guard exists for.

Abort. A master that drops CYC with transfers outstanding has ended the cycle. The outstanding count moves to an *abandoned* count, and that many later responses from the FUB are dropped as

they arrive, even if the master has started a new cycle by then. Without that, a late response for an abandoned transfer would terminate the new cycle's first transfer, which is exactly what the slave test's abort phase caught before the count existed. Terminations are only ever driven inside a cycle, and never while a response is still owed to an abandoned transfer.

9.4.1 Timing

Path	Clocks
STB accepted to cmd_valid	1 (command skid)
rsp_valid to ACK/ERR/RTY	2 (response skid, then the output register)
Sustained throughput	one accept and one termination per clock

9.5 Usage Example

```

wb4_slave #(
    .ADDR_WIDTH      (32),
    .DATA_WIDTH      (32),
    .CMD_DEPTH       (2),
    .RSP_DEPTH       (2),
    .MAX_OUTSTANDING (16)
) u_wb_slave (
    .clk      (clk),
    .aresetn  (aresetn),
    .s_wb_CYC (wb_cyc),    .s_wb_STB  (wb_stb),
    .s_wb_WE  (wb_we),     .s_wb_ADR  (wb_adr),
    .s_wb_DAT_W (wb_dat_i), .s_wb_SEL  (wb_sel),
    .s_wb_STALL (wb_stall), .s_wb_ACK  (wb_ack),
    .s_wb_ERR  (wb_err),   .s_wb_RTY  (wb_rty),
    .s_wb_DAT_R (wb_dat_o),
    .cmd_valid (cmd_valid), .cmd_ready (cmd_ready),
    .cmd_we    (cmd_we),    .cmd_adr  (cmd_adr),
    .cmd_dat   (cmd_dat),   .cmd_sel (cmd_sel),
    .rsp_valid (rsp_valid), .rsp_ready (rsp_ready),
    .rsp_status (rsp_status), .rsp_dat  (rsp_dat)
);

```

9.6 Notes

- The FUB must answer commands in the order it received them; the slave pairs responses to transfers by position.
- Under `ifdef FORMAL` the block asserts: at most one of ACK/ERR/RTY per clock; a termination only for a transfer that was outstanding inside a cycle;

`r_outstanding <= MAX_OUTSTANDING`; and that every accept found queue room.

9.7 Related

- [wb4_master](#) - the mirror image
- [apb4_slave](#) - the same FUB-side contract over APB
- [gaxi_skid_buffer](#) - both queues

9.8 Test

`val/amba/test_wb4_slave.py` drives the block alone against the framework's Wishbone BFM (CocoTBFramework.components.wb4), with the GAXI BFM on the queues; `val/amba/test_wb4_master_slave_loop.py` runs it back to back with its counterpart. See the [family README](#). Formal: `formal/amba/wb4_slave/`.

10 wb4_slave_cdc

10.1 Overview

[wb4_slave](#) with its command and response queues carried across a clock-domain boundary. The Wishbone bus lives in `wb_clk`; the FUB's `cmd_*/rsp_*` queues live in `aclk`. Two `gaxi_fifo_async` instances do the crossing (commands `wb_clk -> aclk`, responses `acclk -> wb_clk`), the same structure as [apb4_slave_cdc](#). In-order termination is preserved because both crossings are FIFOs.

10.2 Parameters

In addition to all `wb4_slave` parameters:

Parameter	Type	Default	Description
CDC_DEPTH	int	4	Async FIFO depth, floored at 4; power of two preferred (Gray pointers)
USE_JOHNSON	int	0	0 = Gray pointers (power-of-two depth), 1 = Johnson pointers (any depth)

10.3 Ports

wb4_slave's ports, with the clock and reset split by domain:

Port	Domain	Description
wb_clk, wb_resetsn	Wishbone	the s_wb_* bus
acclk, aresetsn	FUB	the cmd_* / rsp_* queues
wb_busy (output)	Wishbone	high while this block has anything in flight on the Wishbone side. Built from wb_clk signals ONLY, so a clock gate in that domain can use it directly; wb4_slave_cdc_cg is its one consumer

10.4 Functional Description

10.4.1 Clock Domains

The slave itself, its skid buffers, the STALL logic and the registered terminations are all in wb_clk. MAX_OUTSTANDING bounds the requests accepted while responses are pending, so the response FIFO can never overflow the slave's response queue whatever the clock ratio.

10.4.2 CDC Structure

```
s_wb_* (wb_clk) --> wb4_slave --> cmd FIFO (wb_clk -> acclk) --> cmd_*  
(acclk)                                     <-- rsp FIFO (acclk -> wb_clk) <-- rsp_*  
(acclk)
```

Each FIFO is a gaxi_fifo_async with two-flop pointer synchronisers (N_FLOP_CROSS = 2). Throughput is one transfer per clock of the slower side once the pointers have crossed; latency is a few clocks of each domain per direction.

10.4.3 Reset Behavior

Each FIFO resets its own side's pointers from that side's reset. While a reset is asserted the resetting side is self-consistent, but a **one-sided reset with transfers in the FIFOs is not safe**: a write-side reset alone lets the read side see phantom occupancy (it fabricates entries), and a read-side reset alone replays consumed entries. Quiesce the bus before resetting one side. The full analysis is in [apb4_slave_cdc](#), Reset Behavior, and applies here unchanged.

10.5 Related

- [wb4_slave](#), [wb4_slave_cg](#)
- [gaxi_fifo_async](#) - the crossing

10.6 Test

`val/amba/test_wb4_slave_cdc.py` runs the `wb4_slave` phases with the Wishbone BFM on `wb_clk` and the queue BFM on `aclk` at several clock ratios in both directions (bus faster, bus slower). Formal: `formal/amba/wb4_slave_cdc/`, single-clock model (both domains on one clock) for the port-level contract, as the APB CDC harness does.

11 `wb4_slave_cdc_cg`

11.1 Overview

[wb4_slave_cdc](#) with the **Wishbone-side clock gated**, the combined variant matching `apb4_slave_cdc_cg` / `apb5_slave_cdc_cg`.

Only the Wishbone domain is gated. The FUB domain keeps running, so a consumer can go on draining commands and posting responses while the bus sleeps; the async FIFOs make that safe. Gating both would need a second controller and buys nothing a caller cannot do by gating its own clock.

11.2 Parameters

Every `wb4_slave_cdc` parameter, plus `CG_IDLE_COUNT_WIDTH` (default 4).

11.3 Ports

`wb4_slave_cdc`'s ports plus `cfg_cg_enable`, `cfg_cg_idle_count`, `cg_gating` and `cg_idle`, all in the `wb_clk` domain.

11.4 The wake term has to be single-domain

This is the one thing worth reading before changing it. The wake term is `wb4_slave_cdc`'s `wb_busy` output, which is built **only** from `wb_clk` signals: a cycle open on the bus, a command waiting to cross, or a response that has crossed and not yet been driven.

Nothing from the `aclk` side may be used, because sampling it in `wb_clk` would be an unsynchronised crossing. That is the mistake this wrapper invites and the reason `wb_busy` exists rather than the wake term being assembled here from whatever looked convenient.

For the same reason `cmd_valid` is **not** masked with `cg_gating` the way [wb4_slave_cg](#) masks it: `cmd_valid` lives in `ac1k`, and masking it with a `wb_clk`-domain signal would be exactly that crossing. `s_wb_STALL` is held high while gated, for the reason `wb4_slave_cg` gives: a pipelined accept is `STB && !STALL` in the master's clock, and a frozen “room” would let a master move on from a request the slave never sampled.

11.5 Reset

`wb4_slave_cdc`'s one-sided reset caveat applies unchanged: quiesce the bus before resetting one side.

11.6 Test

`val/amba/test_wb4_slave_cdc.py` carries a `cg` dimension that selects this module in place of `wb4_slave_cdc` and drives the gating configuration; the same traffic, abort and post-abort phases run at several clock ratios in both directions.

11.7 Related

- [wb4_slave_cdc](#), [wb4_slave_cg](#)

12 wb4_slave_cg

12.1 Overview

The **clock-gated variant** of [wb4_slave](#): an `amba_clock_gate_ctrl` instance produces a gated clock that feeds an otherwise unmodified `wb4_slave`. Functionally identical to the base module; `cfg_cg_enable = 0` gives the base behaviour exactly. See the Shared book's [Clock-Gated Variants Guide](#) and [amba_clock_gate_ctrl](#).

12.2 Parameters

In addition to all `wb4_slave` parameters:

Parameter	Type	Default	Description
<code>CG_IDLE_COUNT_WIDTH</code>	<code>int</code>	<code>4</code>	Width of the idle countdown; bounds the programmable idle threshold

12.3 Ports

wb4_slave's ports plus cfg_cg_enable, cfg_cg_idle_count, cg_gating and cg_idle, as on [wb4_master_cg](#).

12.4 Functional Description

12.4.1 Wake-Up Terms

Term	Why
s_wb_CYC	a bus cycle open: requests arriving, terminations due
rsp_valid	a FUB response offered
command pending on the output	a request waiting for the FUB

cmd_ready is deliberately absent.

12.4.2 Masks for the Wake-Latency Overlap

A stopped clock cannot register an accept, and the wake takes a clock or two after the activity appears. Three signals are therefore masked while cg_gating is high:

Signal	Masked to	Why
cmd_valid (to the FUB)	low	a consumer must not retire a command the slave cannot see leave
rsp_ready (to the FUB)	low	a FUB must not have a response taken by a stopped clock
s_wb_STALL (to the master)	high	in pipelined mode an accept is STB && !STALL in the master's clock; a frozen "room" would let the master move on from a request the slave never sampled

STALL stays high until the clock runs, and the master holds its request while stalled (a B4 rule), so nothing is lost and nothing is duplicated. Classic mode holds the request until termination and needs no STALL, but is masked the same way.

12.5 Notes

- Formal: `formal/amba/wb4_slave_cg/` proves the wrapper's glue contract with a clock-enable model of the gate cell (a derived clock is not provable in the repo's single-clock flow; the stopped clock itself is the `cocotb` test's job): reset state, gating clears by the third clock of an open cycle, no gating while a command is pending or with the enable low, no termination and no FUB handshake while gated, STALL high while gated; covers gating, an ungated accept, a termination and re-gating.
- The wake term is combinational into the controller (which registers it once), not a second local flop as in `apb4_slave_cg`; see `formal/amba/apb4_slave_cg/KNOWN_BUG.md` for the latency that flop adds.

12.6 Related

- [wb4_slave](#), [wb4_master_cg](#)
- [apb4_slave_cg](#) - the same wrapper over APB

12.7 Test

`val/amba/test_wb4_slave_cg.py` runs the `wb4_slave` phases with gating enabled and the same three checks as the master's test.

13 wb4_slave_stub

13.1 Overview

[wb4_slave](#) with its FUB-side queues presented as a single **packed vector** instead of named fields, matching what `apb4_slave_stub` and `apb5_slave_stub` offer. A shim-style converter that already carries a packed command through its own pipeline connects one bus instead of six, and the packing lives here rather than being re-derived by every consumer.

Nothing else differs: the stub instantiates the ordinary block and only splices the vector.

13.2 Packing

Most significant field first. Both stubs use the same order, so a `wb4_master_stub` and a `wb4_slave_stub` connect directly:

```
cmd_data = {we, adr, dat, sel, cti, bte}    // CPW = 1 + AW + DW + SW
+ 3 + 2
rsp_data = {status, dat}                   // RPW = 2 + DW
```


cti and bte hold their bits whatever USE_BURST_HINTS is, so the vector width does not move with the parameter. With the hints off the inner block ignores them and the bus reads CLASSIC/LINEAR.

13.3 Parameters

Every parameter of [wb4_slave](#), plus the derived widths:

Parameter	Value	Description
CPW	$1 + AW + DW + SW + 3 + 2$	Packed command width
RPW	$2 + DW$	Packed response width

13.4 Ports

wb4_slave's Wishbone side unchanged. On the FUB side, the command leaves packed and the response arrives packed.

Port	Direction	Description
cmd_valid / cmd_ready	Output / Input	Command handshake
cmd_data [CPW-1:0]	Output	Packed command
rsp_valid / rsp_ready	Input / Output	Response handshake
rsp_data [RPW-1:0]	Input	Packed response

13.5 Related

- [wb4_slave](#) - the block this wraps
- [wb4_master_stub](#) - the other half of a stub pair
- [wb4_pkg](#) - the status encoding inside rsp_data

13.6 Test

val/amba/test_wb4_stubs.py checks the packing directly, in both directions and with the burst hints on and off. Two mutations fail it: swapping dat/sel in the master's unpack, and reversing the slave's response unpack.