EXPERIMENT:8

PERFORMANCE ANALYSIS OF FM SYSTEM UNDER GAUSSIAN

WHITE NOISE USING MATLAB

AIM:

1. To generate a Frequency Modulated (FM) signal in MATLAB using the specified carrier and message signal parameters.


2. To introduce Additive White Gaussian Noise (AWGN) into the generated FM signal and simulate the effect of a noisy communication channel using MATLAB.

3. To analyze the effect of AWGN on the transmitted FM signal by comparing the original and noisy FM signals using time-domain and frequency-domain analysis.

CODE:

```
clc; clear; close all;
fs=100000; t=0:1/fs:0.02;
fm=500; fc=5000; kf=100;
m=cos(2*pi*fm*t);
c=cos(2*pi*fc*t);
FM=cos(2*pi*fc*t+2*pi*kf*cumsum(m)/fs);
% Add 10 dB Gaussian Noise
noise=sqrt(mean(FM.^2)/10)*randn(size(FM));
noisy=FM+noise;
figure;
subplot(4,1,1); plot(t,m); title('Message Signal'); grid on;
subplot(4,1,2); plot(t,c); title('Carrier Signal'); grid on;
subplot(4,1,3); plot(t,FM); title('FM Signal'); grid on;
subplot(4,1,4); plot(t,noisy); title('FM with Gaussian Noise'); grid on;
```

OUTPUT:



RESULT:

1. Generated and visualized an FM signal using specified carrier and message signal parameters.

2. Introduced AWGN into the FM signal at a specified signal-to-noise ratio (SNR).

3. Compared clean and noisy FM signals in the time domain.

4. Computed the FFT and compare the frequency-domain characteristics of the clean and noisy FM signals.

5. Evaluated the influence of AWGN on the quality and spectral characteristics of the transmitted FM signal.