skkmigas PERTAMINA EP	**PERTAMINA EP REGIONAL 1 ZONA 4**	POG

ELECTRICAL CABLE SCHEDULE	No. Dok. : TMBP-SP001-EL-SCH-D101 Rev. : A Halaman : 1 dari 8

NAMA PEMILIK PROYEK : **PT PERTAMINA EP**

NAMA PROYEK : **JASA PEMBANGUNAN FASILITAS PRODUKSI STASIUN PENGUMPUL (SP) TANJUNG MIRING BARAT & KARANGAN TIMUR**

LOKASI : **SP TANJUNG MIRING BARAT & KARANGAN TIMUR - FIELD LIMAU**

NO. KONTRAK : **SA02035383B**

REV.	TGL.	DESKRIPSI	DISIAPKAN	DIPERIKSA	DISETUJUI	DIPERIKSA	DISETUJUI
A	09/01/2026	Issued For Review	FN	AS	MR		
			PT. PROSYMPAC OIL & GAS			PT. PERTAMINA EP	

TABEL REVISI

Rev.	Tanggal	Deskripsi

COMMENT RESPONSE SHEET

No.	Page	Company's Comment	Contractor's Response	Remarks

DED PENGEMBANGAN FASILITAS PRODUKSI TANJUNG MIRING BARAT & KARANGAN TIMUR

ELECTRICAL CABLE SCHEDULE

Doc No: TMBP-SP001-EL-SCH-D101
Rev: A
Date: 09-01-26

No	CABLE NO	LOAD		CABLE DESCRIPTION				ROUTE						CABLE GLAND				REMARKS
								FROM			TO			FROM		TO		
		APACITY KW(KVA	VOLTAGE(V)	SIZE(mm2)	CABLE TYPE	OD(mm)	LENGTH(M)	EQUIPMENT NUMBER	EQUIPMENT NAME	UIPMENTLOCATI	EQUIPMENT NUMBER	EQUIPMENT NAME	QUIPMENTLOCATION	TYPE	SIZE	TYPE	SIZE	
A	GAS ENGINE GENERATOR 01 (GEG-001)																	
1	P-GEG-001-001-R	455	400	10-300	P1	37,97	92	GEG-001	Gas Engine Generator #1	D6	SWGMCC-001A	0.4kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	non-Ex	M40	non-Ex	M40	
2	P-GEG-001-001-S	455	400	10-300	P1	37,97	92	GEG-001	Gas Engine Generator #1	D6	SWGMCC-001A	0.4kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	non-Ex	M40	non-Ex	M40	
3	P-GEG-001-001-T	455	400	10-300	P1	37,97	92	GEG-001	Gas Engine Generator #1	D6	SWGMCC-001A	0.4kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	non-Ex	M40	non-Ex	M40	
4	P-GEG-001-001-N	455	400	10-300	P1	37,97	92	GEG-001	Gas Engine Generator #1	D6	SWGMCC-001A	0.4kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	non-Ex	M40	non-Ex	M40	
5	P-GEG-001-002-R	455	400	10-300	P1	37,97	92	GEG-001	Gas Engine Generator #1	D6	SWGMCC-001A	0.4kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	non-Ex	M40	non-Ex	M40	
6	P-GEG-001-002-S	455	400	10-300	P1	37,97	92	GEG-001	Gas Engine Generator #1	D6	SWGMCC-001A	0.4kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	non-Ex	M40	non-Ex	M40	
7	P-GEG-001-002-T	455	400	10-300	P1	37,97	92	GEG-001	Gas Engine Generator #1	D6	SWGMCC-001A	0.4kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	non-Ex	M40	non-Ex	M40	
8	P-GEG-001-002-N	455	400	10-300	P1	37,97	92	GEG-001	Gas Engine Generator #1	D6	SWGMCC-001A	0.4kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	non-Ex	M40	non-Ex	M40	
9	P-GEG-001-003-R	455	400	10-300	P1	37,97	92	GEG-001	Gas Engine Generator #1	D6	SWGMCC-001A	0.4kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	non-Ex	M40	non-Ex	M40	
10	P-GEG-001-003-S	455	400	10-300	P1	37,97	92	GEG-001	Gas Engine Generator #1	D6	SWGMCC-001A	0.4kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	non-Ex	M40	non-Ex	M40	
11	P-GEG-001-003-T	455	400	10-300	P1	37,97	92	GEG-001	Gas Engine Generator #1	D6	SWGMCC-001A	0.4kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	non-Ex	M40	non-Ex	M40	
12	P-GEG-001-003-N	455	400	10-300	P1	37,97	92	GEG-001	Gas Engine Generator #1	D6	SWGMCC-001A	0.4kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	non-Ex	M40	non-Ex	M40	
13	C-GCP-GEG-001-001			60-15	P2	14,50	92	LCP-GEG-001	Local Control Panel GEG 001	D6	GCP-GEG-001	Generator Control Panel GEG 001	D6	non-Ex	M20	non-Ex	M20	ALARM & SHUTDOWN STATUS INDICATION
14	C-GCP-GEG-001-002			120-15	P2	17,00	92	LCP-GEG-001	Local Control Panel GEG 001	D6	GCP-GEG-001	Generator Control Panel GEG 001	D6	non-Ex	M20	non-Ex	M20	ART/STOP COMMAND EMERGENCY STOP SPEED ADJUSMENT VOLTAGE RHEOSTA
15	SH-GCP-GEG-001-001		230	20-25	P2	18,00	97	LCP-GEG-001	Local Control Panel GEG 001	D6	GCP-GEG-001	Generator Control Panel GEG 001	D6	non-Ex	M20	non-Ex	M20	Space Heater
16	CT-GCP-GEG-001-001-R		230	20-25	P2	18,00	92	LCP-GEG-001	Local Control Panel GEG 001	D6	GCP-GEG-001	Generator Control Panel GEG 001	D6	non-Ex	M20	non-Ex	M20	CT - R
17	CT-GCP-GEG-001-001-S		230	20-25	P2	18,00	92	LCP-GEG-001	Local Control Panel GEG 001	D6	GCP-GEG-001	Generator Control Panel GEG 001	D6	non-Ex	M20	non-Ex	M20	CT- S
18	CT-GCP-GEG-001-001-T		230	20-25	P2	18,00	92	LCP-GEG-001	Local Control Panel GEG 001	D6	GCP-GEG-001	Generator Control Panel GEG 001	D6	non-Ex	M20	non-Ex	M20	CT- T
19	PT-GCP-GEG-001-001-R		230	20-25	P2	18,00	92	LCP-GEG-001	Local Control Panel GEG 001	D6	GCP-GEG-001	Generator Control Panel GEG 001	D6	non-Ex	M20	non-Ex	M20	PT - R
20	PT-GCP-GEG-001-001-S		230	20-25	P2	18,00	92	LCP-GEG-001	Local Control Panel GEG 001	D6	GCP-GEG-001	Generator Control Panel GEG 001	D6	non-Ex	M20	non-Ex	M20	PT - R
21	PT-GCP-GEG-001-001-T		230	20-25	P2	18,00	92	LCP-GEG-001	Local Control Panel GEG 001	D6	GCP-GEG-001	Generator Control Panel GEG 001	D6	non-Ex	M20	non-Ex	M20	PT - R
22	NCT-GCP-GEG-001-001		230	20-4	P1	19,02	92	LCP-GEG-001	Local Control Panel GEG 001	E6	SWGMCC-001A	0.4kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	D6	non-Ex	M20	non-Ex	M20	Neutral CT
23	SH-GCP-GEG-001-001		230	20-25+G	P2	20,10	25	NLP-001	Normal Lighting Panel	D6	GCP-GEG-001	Generator Control Panel GEG 001	D6	non-Ex	M20	non-Ex	M20	Aux Supply 230 VAC (Heater & Lampu Panel)
24	CHG-GCP-GEG-001-001		230	20-25+G	P2	20,10	25	NLP-001	Normal Lighting Panel	D6	GCP-GEG-001	Generator Control Panel GEG 001	D6	non-Ex	M20	non-Ex	M20	230 VAC for battery charger GCP
25	BATT-GEG-001-001		230	20-25+G	P1	20,10	32	GEG-001	Gas Engine Generator #1	D6	GCP-GEG-001	Generator Control Panel GEG 001	D6	non-Ex	M20	non-Ex	M20	Supply for Battery (From GCP- Battery Charger - GEG)
26	VT-GCP-MCC-001-001		230	40-25	P2	15,30	35	SWG/MCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	GCP-GEG-001	Generator Control Panel GEG 001	D6	non-Ex	M20	non-Ex	M20	VT Meassuring
27	VT-GCP-MCC-001-002		230	40-25	P2	15,32	35	SWG/MCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	GCP-GEG-001	Generator Control Panel GEG 001	D6	non-Ex	M20	non-Ex	M20	VT Protection
28	CT-GCP-MCC-001-001		230	40-25	P2	25,96	35	SWG/MCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	GCP-GEG-001	Generator Control Panel GEG 001	D6	non-Ex	M20	non-Ex	M20	CT Meassuring
29	CT-GCP-MCC-001-002		230	40-25	P2	25,96	35	SWG/MCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	GCP-GEG-001	Generator Control Panel GEG 001	D6	non-Ex	M20	non-Ex	M20	CT Protection
30	ST-GCP-MCC-001-002			240-1,5	P2	30,50	35	SWG/MCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	GCP-GEG-001	Generator Control Panel GEG 001	D6	non-Ex	M32	non-Ex	M32	MCC Status (Open Class Trip)
31	COMM-GCP001-GCP002			LAN	-	15,5	10	GCP-GEG-001	Generator Control Panel GEG 001	D6	GCP-GEG-001	Generator Control Panel GEG 002	D6	non-Ex	M20	non-Ex	M20	LAN Communication (Fungsi Situation)
B	GAS ENGINE GENERATOR 02 (GEG-002)																	
1	P-GEG-002-004-R	455	400	10-300	P1	37,97	89	GEG-002	Gas Engine Generator #2	D6	SWGMCC-001A	0.4kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	non-Ex	M40	non-Ex	M40	
2	P-GEG-002-004-S	455	400	10-300	P1	37,97	89	GEG-002	Gas Engine Generator #2	D6	SWGMCC-001A	0.4kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	non-Ex	M40	non-Ex	M40	
3	P-GEG-002-004-T	455	400	10-300	P1	37,97	89	GEG-002	Gas Engine Generator #2	D6	SWGMCC-001A	0.4kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	non-Ex	M40	non-Ex	M40	
4	P-GEG-002-004-N	455	400	10-300	P1	37,97	89	GEG-002	Gas Engine Generator #2	D6	SWGMCC-001A	0.4kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	non-Ex	M40	non-Ex	M40	
5	P-GEG-002-005-R	455	400	10-300	P1	37,97	89	GEG-002	Gas Engine Generator #2	D6	SWGMCC-001A	0.4kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	non-Ex	M40	non-Ex	M40	
6	P-GEG-002-005-S	455	400	10-300	P1	37,97	89	GEG-002	Gas Engine Generator #2	D6	SWGMCC-001A	0.4kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	non-Ex	M40	non-Ex	M40	
7	P-GEG-002-005-T	455	400	10-300	P1	37,97	89	GEG-002	Gas Engine Generator #2	D6	SWGMCC-001A	0.4kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	non-Ex	M40	non-Ex	M40	
8	P-GEG-002-005-N	455	400	10-300	P1	37,97	89	GEG-002	Gas Engine Generator #2	D6	SWGMCC-001A	0.4kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	non-Ex	M40	non-Ex	M40	
9	P-GEG-002-006-R	455	400	10-300	P1	37,97	89	GEG-002	Gas Engine Generator #2	D6	SWGMCC-001A	0.4kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	non-Ex	M40	non-Ex	M40	
10	P-GEG-002-006-S	455	400	10-300	P1	37,97	89	GEG-002	Gas Engine Generator #2	D6	SWGMCC-001A	0.4kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	non-Ex	M40	non-Ex	M40	
11	P-GEG-002-006-T	455	400	10-300	P1	37,97	89	GEG-002	Gas Engine Generator #2	D6	SWGMCC-001A	0.4kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	non-Ex	M40	non-Ex	M40	
12	P-GEG-002-006-N	455	400	10-300	P1	37,97	89	GEG-002	Gas Engine Generator #2	D6	SWGMCC-001A	0.4kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	non-Ex	M40	non-Ex	M40	
13	C-GCP-GEG-002-001			60-15	P2	14,50	89	LDP-GEG-002	Local Control Panel GEG 002	D6	GCP-GEG-002	Generator Control Panel GEG 002	D6	non-Ex	M20	non-Ex	M20	ALARM & SHUTDOWN STATUS INDICATION
14	C-GCP-GEG-002-002			120-15	P2	17,00	89	LDP-GEG-002	Local Control Panel GEG 002	D6	GCP-GEG-002	Generator Control Panel GEG 002	D6	non-Ex	M20	non-Ex	M20	ART/STOP COMMAND EMERGENCY STOP SPEED ADJUSMENT VOLTAGE RHEOSTA
15	SH-GCP-GEG-002-001		230	20-25	P2	18,00	95	LDP-GEG-002	Local Control Panel GEG 002	D6	GCP-GEG-002	Generator Control Panel GEG 002	D6	non-Ex	M20	non-Ex	M20	Space Heater
16	CT-GCP-GEG-002-001-R		230	20-25	P2	18,00	89	LDP-GEG-002	Local Control Panel GEG 002	D6	GCP-GEG-002	Generator Control Panel GEG 002	D6	non-Ex	M20	non-Ex	M20	CT - R
17	CT-GCP-GEG-002-001-S		230	20-25	P2	18,00	89	LDP-GEG-002	Local Control Panel GEG 002	D6	GCP-GEG-002	Generator Control Panel GEG 002	D6	non-Ex	M20	non-Ex	M20	CT- S
18	CT-GCP-GEG-002-001-T		230	20-25	P2	18,00	89	LDP-GEG-002	Local Control Panel GEG 002	D6	GCP-GEG-002	Generator Control Panel GEG 002	D6	non-Ex	M20	non-Ex	M20	CT- T
19	PT-GCP-GEG-002-001-R		230	20-25	P2	18,00	89	LDP-GEG-002	Local Control Panel GEG 002	D6	GCP-GEG-002	Generator Control Panel GEG 002	D6	non-Ex	M20	non-Ex	M20	PT - R
20	PT-GCP-GEG-002-001-S		230	20-25	P2	18,00	89	LDP-GEG-002	Local Control Panel GEG 002	D6	GCP-GEG-002	Generator Control Panel GEG 002	D6	non-Ex	M20	non-Ex	M20	PT - R
21	PT-GCP-GEG-002-001-T		230	20-25	P2	18,00	89	LDP-GEG-002	Local Control Panel GEG 002	D6	GCP-GEG-002	Generator Control Panel GEG 002	D6	non-Ex	M20	non-Ex	M20	PT - R
22	NCT-GCP-GEG-001-001		230	20-4	P1	19,02	89	LDP-GEG-002	Local Control Panel GEG 002	E6	SWGMCC-001A	0.4kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	D6	non-Ex	M20	non-Ex	M20	Neutral CT
23	SH-GCP-GEG-001-002		230	20-25+G	P2	20,10	25	NDP-001	Normal Lighting Panel	D6	GCP-GEG-002	Generator Control Panel GEG 002	D6	non-Ex	M20	non-Ex	M20	Aux Supply 230 VAC (Heater & Lampu Panel)
24	CHG-GCP-GEG-001-002		230	20-25+G	P2	20,10	25	NDP-001	Normal Lighting Panel	D6	GCP-GEG-002	Generator Control Panel GEG 002	D6	non-Ex	M20	non-Ex	M20	230 VAC for battery charger GCP
25	BATT-GEG-001-001		230	20-25+G	P1	20,10	25	GEG-002	Gas Engine Generator #2	D6	GCP-GEG-002	Generator Control Panel GEG 002	D6	non-Ex	M20	non-Ex	M20	Supply for Battery (From GCP- Battery Charger - GEG)
26	VT-GCP-MCC-001-001		230	40-25	P2	15,30	35	SWGMCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	GCP-GEG-002	Generator Control Panel GEG 002	D6	non-Ex	M20	non-Ex	M20	VT Meassuring
27	VT-GCP-MCC-001-002		230	40-25	P2	15,30	35	SWGMCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	GCP-GEG-002	Generator Control Panel GEG 002	D6	non-Ex	M20	non-Ex	M20	VT Protection
28	CT-GCP-MCC-001-001		230	40-25	P2	15,30	35	SWGMCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	GCP-GEG-002	Generator Control Panel GEG 002	D6	non-Ex	M20	non-Ex	M20	CT Meassuring
29	CT-GCP-MCC-001-002		230	40-25	P2	15,30	35	SWGMCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	GCP-GEG-002	Generator Control Panel GEG 002	D6	non-Ex	M20	non-Ex	M20	CT Protection
30	ST-GCP-MCC-001-002			240-1,5	P2	30,50	35	SWGMCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	GCP-GEG-002	Generator Control Panel GEG 002	D6	non-Ex	M32	non-Ex	M32	MCC Status (Open Class Trip)
31	COMM-GCP002=EDG001			LAN	-	18,50	10	GCP-GEG-002	Generator Control Panel GEG 002	D6	GCP-GEG-001	Generator Control Panel DEG 001	D6	non-Ex	M20	non-Ex	M20	LAN Communication (Fungsi Situation)
C	EMERGENCY DIESEL GENERATOR (EDG-001)																	
1	P-DEG-001-001-R	520	400	10-300	P1	37,57	95	DEG-001	Diesel Engine Generator #1	D6	SWGMCC-001B	0.4kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	non-Ex	M40	non-Ex	M40	
2	P-DEG-001-001-S	520	400	10-300	P1	37,57	95	DEG-001	Diesel Engine Generator #1	D6	SWGMCC-001B	0.4kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	non-Ex	M40	non-Ex	M40	
3	P-DEG-001-001-T	520	400	10-300	P1	37,57	95	DEG-001	Diesel Engine Generator #1	D6	SWGMCC-001B	0.4kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	non-Ex	M40	non-Ex	M40	
4	P-DEG-001-001-N	520	400	10-300	P1	37,57	95	DEG-001	Diesel Engine Generator #1	D6	SWGMCC-001B	0.4kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	non-Ex	M40	non-Ex	M40	
5	P-DEG-001-002-R	520	400	10-300	P1	37,57	95	DEG-001	Diesel Engine Generator #1	D6	SWGMCC-001B	0.4kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	non-Ex	M40	non-Ex	M40	
6	P-DEG-001-002-S	520	400	10-300	P1	37,57	95	DEG-001	Diesel Engine Generator #1	D6	SWGMCC-001B	0.4kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	non-Ex	M40	non-Ex	M40	
7	P-DEG-001-002-T	520	400	10-300	P1	37,57	95	DEG-001	Diesel Engine Generator #1	D6	SWGMCC-001B	0.4kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	non-Ex	M40	non-Ex	M40	
8	P-DEG-001-002-N	520	400	10-300	P1	37,57	95	DEG-001	Diesel Engine Generator #1	D6	SWGMCC-001B	0.4kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	non-Ex	M40	non-Ex	M40	
9	P-DEG-001-003-R	520	400	10-300	P1	37,57	95	DEG-001	Diesel Engine Generator #1	D6	SWGMCC-001B	0.4kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	non-Ex	M40	non-Ex	M40	
10	P-DEG-001-003-S	520	400	10-300	P1	37,57	95	DEG-001	Diesel Engine Generator #1	D6	SWGMCC-001B	0.4kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	non-Ex	M40	non-Ex	M40	
11	P-DEG-001-003-T	520	400	10-300	P1	37,57	95	DEG-001	Diesel Engine Generator #1	D6	SWGMCC-001B	0.4kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	non-Ex	M40	non-Ex	M40	
12	P-DEG-001-003-N	520	400	10-300	P1	37,57	95	DEG-001	Diesel Engine Generator #1	D6	SWGMCC-001B	0.4kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	non-Ex	M40	non-Ex	M40	
13	C-GCP-DEG-001-001			50-15	P2	14,50	95	LCP-DEG-001	Local Control Panel DEG 001	D6	GCP-GEG-001	Generator Control Panel DEG 001	D6	non-Ex	M20	non-Ex	M20	ALARM & SHUTDOWN STATUS INDICATION
14	C-GCP-DEG-001-002			120-15	P2	17,00	95	LCP-DEG-001	Local Control Panel DEG 001	D6	GCP-GEG-001	Generator Control Panel DEG 001	D6	non-Ex	M20	non-Ex	M20	ART/STOP COMMAND EMERGENCY STOP SPEED ADJUSMENT VOLTAGE RHEOSTA
15	SH-GCP-DEG-001-001		230	20-25	P2	18,00	100	LCP-DEG-001	Local Control Panel DEG 001	D6	GCP-GEG-001	Generator Control Panel DEG 001	D6	non-Ex	M20	non-Ex	M20	Space Heater

skkmigas PERTAMINA EP

DED PENGEMBANGAN FASILITAS PRODUKSI TANJUNG MIRING BARAT & KARANGAN TIMUR

POG

ELECTRICAL CABLE SCHEDULE

Doc No: TMBP-SP001-EL-SCH-D101
Rev: A
Date 09-01-26

No	CABLE NO	LOAD		CABLE DESCRIPTION				ROUTE						CABLE GLAND				REMARKS
								FROM			TO			FROM		TO		
		APACITY KW(KVA	VOLTAGE(V)	SIZE(mm2)	CABLE TYPE	OD(mm)	LENGTH(M)	EQUIPMENT NUMBER	EQUIPMENT NAME	UIPMENTLOCATI	EQUIPMENT NUMBER	EQUIPMENT NAME	QUIPMENTLOCATION	TYPE	SIZE	TYPE	SIZE	
16	CT-GCP-DEG-001-001-R		230	20-25	P2	18,00	95	LCP-DEG-001	Local Control Panel DEG 001	D6	GCP-DEG-001	Generatbr Control Panel DEG 001	D6	non-Ex	M20	non-Ex	M20	CT - R
17	CT-GCP-DEG-001-001-S		230	20-25	P2	18,00	95	LCP-DEG-001	Local Control Panel DEG 001	D6	GCP-DEG-001	Generatbr Control Panel DEG 001	D6	non-Ex	M20	non-Ex	M20	CT - S
18	CT-GCP-DEG-001-001-T		230	20-25	P2	18,00	95	LCP-DEG-001	Local Control Panel DEG 001	D6	GCP-DEG-001	Generatbr Control Panel DEG 001	D6	non-Ex	M20	non-Ex	M20	CT - T
19	PT-GCP-DEG-001-001-R		230	20-25	P2	18,00	95	LCP-DEG-001	Local Control Panel DEG 001	D6	GCP-DEG-001	Generatbr Control Panel DEG 001	D6	non-Ex	M20	non-Ex	M20	PT - R
20	PT-GCP-DEG-001-001-S		230	20-25	P2	18,00	95	LCP-DEG-001	Local Control Panel DEG 001	D6	GCP-DEG-001	Generatbr Control Panel DEG 001	D6	non-Ex	M20	non-Ex	M20	PT - R
21	PT-GCP-DEG-001-001-T		230	20-25	P2	18,00	95	LCP-DEG-001	Local Control Panel DEG 001	D6	GCP-DEG-001	Generatbr Control Panel DEG 001	D6	non-Ex	M20	non-Ex	M20	PT - R
22	NCT-GDP-DEG-001-001		230	20-4	P1	19,02	95	LCP-DEG-001	Local Control Panel DEG 001	E6	SWGMCC-001B	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	D6	non-Ex	M20	non-Ex	M20	Neutral CT
23	SH-GCP-DEG-001-002		230	20-25+G	P2	20,10	25	NLP-001	Normal Lighting Panel	D6	GCP-DEG-001	Generatbr Control Panel DEG 001	D6	non-Ex	M20	non-Ex	M20	Aux Supply 230 VAC (Heater & Lampu Panel)
24	CHG-GCP-DEG-001-001		230	20-25+G	P2	20,10	25	NLP-001	Normal Lighting Panel	D6	GCP-DEG-001	Generatbr Control Panel DEG 001	D6	non-Ex	M20	non-Ex	M20	230 VAC for battery charger GCP
25	BATT-DEG-001-001		230	20-25+G	P1	20,10	25	DEG-001	Diesel Engine Generator # 1	D6	GCP-DEG-001	Generatbr Control Panel DEG 001	D6	non-Ex	M20	non-Ex	M20	Supply for Battery (From GCP- Battery Charger - GEG)
26	VT-GCP-MCC-001-001		230	40-25	P2	15,30	35	SWGMCC-001B	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	GCP-DEG-001	Generatbr Control Panel DEG 001	D6	non-Ex	M20	non-Ex	M20	VT Meassuring
27	VT-GCP-MCC-001-002		230	40-25	P2	15,30	35	SWGMCC-001B	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	GCP-DEG-001	Generatbr Control Panel DEG 001	D6	non-Ex	M20	non-Ex	M20	VT Protection
28	CT-GCP-MCC-001-001		230	40-25	P2	15,30	35	SWGMCC-001B	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	GCP-DEG-001	Generatbr Control Panel DEG 001	D6	non-Ex	M20	non-Ex	M20	CT Meassuring
29	CT-GCP-MCC-001-002		230	40-25	P2	15,30	35	SWGMCC-001B	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	GCP-DEG-001	Generatbr Control Panel DEG 001	D6	non-Ex	M20	non-Ex	M20	CT Protection
30	ST-GCP-MCC-001-002			240-1.5	P2	30,50	35	SWGMCC-001B	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	GCP-DEG-001	Generatbr Control Panel DEG 001	D6	non-Ex	M32	non-Ex	M32	MCC Status (Open Class Trip)
31	COMM-GCP001-GCP003			LAN	-	18,50	10	GCP-GEG-001	Generatbr Control Panel GEG 001	D6	GCP-DEG-001	Generatbr Control Panel DEG 001	D6	non-Ex	M20	non-Ex	M20	LAN Communication (Fungsi Situation)
D	**MASTER GENERATOR CONTROL PANEL (MGCP-001)**																	
1	C-MGCP-001-001			120-1.5	P2	17,00	95	GCP-GEG-001	Generatbr Control Panel GEG 001	D6	MGCP-001	Master Generator Control Panel 001	D6	non-Ex	M20	non-Ex	M20	Sinkron and Command
2	C-MGCP-001-002			120-1.5	P2	17,00	95	GCP-GEG-001	Generatbr Control Panel GEG 001	D6	MGCP-001	Master Generator Control Panel 001	D6	non-Ex	M20	non-Ex	M20	Sinkron and Command
3	C-MGCP-001-003			120-1.5	P2	17,00	95	GCP-GEG-001	Generatbr Control Panel GEG 001	D6	MGCP-001	Master Generator Control Panel 001	D6	non-Ex	M20	non-Ex	M20	Sinkron and Command
4	SH-GCP-DEG-001-002		230	20-25+G	P2	20,10	25	NLP-001	Normal Lighting Panel	D6	MGCP-001	Master Generator Control Panel 001	D6	non-Ex	M20	non-Ex	M20	Aux Supply 230 VAC (Heater & Lampu Panel)
E	**0.4 kV LOW VOLTAGE SWITCHGEAR & MCC BUS A**																	
1	P-P-002A-001	2.2	400	30-4+G	P2	19,72	114	SWGMCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	P-002A	Test Pump TMB - A	D5	non-Ex	M20	Ex	M20	
2	C-P-002A-001			120-1.5	P2	17,50	114	SWGMCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	P-002A	Test Pump TMB - A	D5	non-Ex	M20	Ex	M20	LCS (Start Stop Indicator Star/Stop)
3	P-P-003A-001																	
4	C-P-003A-001	3	400	30-4+G	P2	19,72	123	SWGMCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	P-003A	Test Pump TMB - A	D5	non-Ex	M20	Ex	M20	
				120-1.5	P2	17,00	123	SWGMCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	P-003A	Test Pump TMB - A	D5	non-Ex	M20	Ex	M20	LCS (Start Stop Indicator Star/Stop)
5	P-P-003B-001																	
6	C-P-003B-001	3	400	30-4+G	P2	19,72	118	SWGMCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	P-003B	Test Pump TMB - B	D5	non-Ex	M20	Ex	M20	
				120-1.5	P2	17,00	118	SWGMCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	P-003B	Test Pump TMB - B	D5	non-Ex	M20	Ex	M20	LCS (Start Stop Indicator Star/Stop)
7	P-P-005A-001	0.56	400	30-4+G	P2	19,72	145	SWGMCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	P-006A	KOD Pump - A	D6	non-Ex	M20	Ex	M20	
8	C-P-005A-001			120-1.5	P2	17,00	145	SWGMCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	P-006A	KOD Pump - A	C4	non-Ex	M20	Ex	M20	LCS (Start Stop Indicator Star/Stop)
9	P-P-006B-001	0.56	400	30-4+G	P2	19,72	145	SWGMCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	P-006B	KOD Pump - B	D5	non-Ex	M20	Ex	M20	
10	C-P-006B-001			120-1.5	P2	17,00	145	SWGMCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	P-006B	KOD Pump - B	D6	non-Ex	M20	Ex	M20	LCS (Start Stop Indicator Star/Stop)
11	P-P-021-001	0.37	400	30-4+G	P2	19,72	140	SWGMCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	P-021	KOD Sump Pump	D6	non-Ex	M20	Ex	M20	
12	C-P-021-001			120-1.5	P2	17,00	140	SWGMCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	P-021	KOD Sump Pump	D6	non-Ex	M20	Ex	M20	LCS (Start Stop Indicator Star/Stop)
13	P-P-007A-001	1.1	400	30-4+G	P2	19,72	153	SWGMCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	P-007A	Closed Drain Pump - A	D6	non-Ex	M20	Ex	M20	
14	C-P-007A-001			120-1.5	P2	17,00	153	SWGMCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	P-007A	Closed Drain Pump - A	D5	non-Ex	M20	Ex	M20	LCS (Start Stop Indicator Star/Stop)
15	P-P-007B-001	1.1	400	30-4+G	P2	19,72	158	SWGMCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	P-007B	Closed Drain Pump - B	D6	non-Ex	M20	Ex	M20	
16	C-P-007B-001			120-1.5	P2	17,00	158	SWGMCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	P-007B	Closed Drain Pump - B	D6	non-Ex	M20	Ex	M20	LCS (Start Stop Indicator Star/Stop)
17	P-P-018-001	0.56	400	30-4+G	P2	19,72	160	SWGMCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	P-018	Closed Drain Sump Pump	D6	non-Ex	M20	Ex	M20	
18	C-P-018-001			120-1.5	P2	17,00	160	SWGMCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	P-018	Closed Drain Sump Pump	D6	non-Ex	M20	Ex	M20	LCS (Start Stop Indicator Star/Stop)
19	P-P-019-001	1.5	400	30-4+G	P2	19,72	233	SWGMCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	P-019	Water Sump Pump	C4	non-Ex	M20	Ex	M20	
20	C-P-019-001			120-1.5	P2	17,00	233	SWGMCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	P-019	Water Sump Pump	C4	non-Ex	M20	Ex	M20	LCS (Start Stop Indicator Star/Stop)
21	P-P-040-001	0.75	400	30-4+G	P2	19,72	200	SWGMCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	P-040	Storage Test Sump Pump - DEG	C4	non-Ex	M20	Ex	M20	

skkmigas PERTAMINA EP

DED PENGEMBANGAN FASILITAS PRODUKSI TANJUNG MIRING BARAT & KARANGAN TIMUR

PGG

ELECTRICAL CABLE SCHEDULE

Doc No: TMBP-SP001-EL-SCH-D101
Rev: A
Date: 09-01-26

No	CABLE NO	LOAD		CABLE DESCRIPTION				ROUTE						CABLE GLAND				REMARKS
								FROM			TO			FROM		TO		
		APACITY KW[KVA	VOLTAGE(V)	SIZE(mm2)	CABLE TYPE	OD(mm)	LENGTH(M)	EQUIPMENT NUMBER	EQUIPMENT NAME	UIPMENTLOCATI	EQUIPMENT NUMBER	EQUIPMENT NAME	QUIPMENTLOCATION	TYPE	SIZE	TYPE	SIZE	
22	P-P-039-001	1,1	400	30-4+G	P2	25,18	273	SWGMCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	P-039	Manufbid Chemical Tranfer Pump	C3	non-Ex	M25	Ex	M25	
23	C-P-039-001			120-1,5	P2	17,00	273	SWGMCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	P-039	Manufbid Chemical Tranfer Pump	C3	non-Ex	M20	Ex	M20	LCS (Start, Stop Indicator Start/Stop)
24	P-UPS-001A-001	[30]	400	40-10+G	P2	25,15	43	SWGMCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	UPS-011A	AC UPS System Normal	E6	non-Ex	M25	non-Ex	M25	
25	P-NLF-001-001	[12,20]	400	40-10+G	P2	25,15	43	SWGMCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	NLP-001	Normal Lighting Panel Small Power DB	E6	non-Ex	M25	non-Ex	M25	
26	P-DHC-002-001	[2,35]	400	40-10+G	P2	25,15	123	SWGMCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	NLP-002	Crane for Electric Chain Host for Test & Transfer Pump Shelter	D6	non-Ex	M25	non-Ex	M25	
27	P-OHC-005-001	[11,18]	400	40-10+G	P2	25,15	117	SWGMCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	OHC-005	Crane for Electric Chain Host instrument At Package Shelter	D6	non-Ex	M25	non-Ex	M25	
28	P-OHC-006-001	[2,35]	400	40-10+G	P2	25,15	322	SWGMCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	OHC-005	Crane for Electric Chain Host for Fire Water Pump Shelter	C5	non-Ex	M25	non-Ex	M25	
29	P-OHC-007-001	[2,35]	400	40-10+G	P2	25,15	237	SWGMCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	OHC-005	Crane for Electric Chain Host for Oil Sneker Shelter	D6	non-Ex	M25	non-Ex	M25	
30	P-OHC-008-001	[2,35]	400	40-10+G	P2	25,15	224	SWGMCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	OHC-005	Crane for Electric Chain Host for Gross Transfer Pump Shelter	C6	non-Ex	M25	non-Ex	M25	
31	P-WO-001-001	[29,41]	400	40-10+G	P2	25,15	89	SWGMCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	WO-001	Welding Outlet for GEG & EDG Sneker	C6	non-Ex	M25	non-Ex	M25	
32	P-WO-002-001	[29,41]	400	40-20+G	P1	30,74	133	SWGMCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	WO-002	Welding Outlet for Instrument Past Soulding	C6	non-Ex	M32	non-Ex	M32	
33	P-WO-004-001	[29,41]	400	40-20+G	P1	30,74	145	SWGMCC-001A	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS A	E6	WO-004	Welding Outlet for KOD Drum Shelter	C6	non-Ex	M32	non-Ex	M32	

skkmigas PERTAMINA EP

DED PENGEMBANGAN FASILITAS PRODUKSI
TANJUNG MIRING BARAT & KARANGAN TIMUR

POG

ELECTRICAL CABLE SCHEDULE

Doc No : TMBP-SP001-EL-SHC-D101
Rev : A
Date : 09-01-2026

No	CABLE NO	LOAD		CABLE DESCRIPTION				ROUTE						CABLE GLAND				REMARKS
		CAPACITY KW [KVA]	VOLTAGE (V)	SIZE (mm2)	CABLE TYPE	OD (mm)	LENGTH (M)	FROM			TO			FROM		TO		
								EQUIPMENT NUMBER	EQUIPMENT NAME	EQUIPMENT LOCATION	EQUIPMENT NUMBER	EQUIPMENT NAME	EQUIPMENT LOCATION	TYPE	SIZE	TYPE	SIZE	
F	0.42 V LOW VOLTAGE SWITCHGEAR & MCC BUS B																	
1	P-SS-P-001A-001	90	400	32-95-G	P1	43,71	20	SWG-MCC-001B	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	SS-P-001A	Panel SS For Gross Transfer Pump - A	E8	non-Ex	M50	Ex	M50	
2	F-F-001A-001	90	400	33-95-G	P1	43,71	219	SS-P-001A	Panel SS For Gross Transfer Pump - A	E6	P-001A	Gross Transfer Pump - A	C5	non-Ex	M50	Ex	M50	
3	C-P-001A-001			12C-15	P2	47	219	SWG-MCC-001B	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	P-001A	Gross Transfer Pump - A	C5	non-Ex	M20	Ex	M20	LCS (Start Stop Indicator Start Stop Emergency Stop
4	C-P-001A-002			4C-15	P2	42,5	219	SWG-MCC-001B	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	P-001A	Gross Transfer Pump - A	C5	non-Ex	M20	Ex	M20	Arrester
5	SHF-D001A-001		230	2C-4	P2	49,02	219	SWG-MCC-001B	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	P-001A	Gross Transfer Pump - A	C5	non-Ex	M20	Ex	M20	Space Heater
6	P-SS-P-001B-001	90	400	3C-54-G	P1	43,71	20	SWG-MCC-001B	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	SS-P-001B	Panel SS For Gross Transfer Pump - B	E8	non-Ex	M50	Ex	M50	
7	F-F-001B-001	90	400	3C-55-G	P1	43,71	213	SS-P-001B	Panel SS For Gross Transfer Pump - B	E6	P-001B	Gross Transfer Pump - B	C5	non-Ex	M50	Ex	M50	
8	C-P-001B-001			12C-15	P2	47	213	SWG-MCC-001B	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	P-001B	Gross Transfer Pump - B	C5	non-Ex	M20	Ex	M20	LCS (Start Stop Indicator Start Stop Emergency Stop
9	C-P-001B-002			4C-15	P2	42,5	213	SWG-MCC-001B	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	P-001B	Gross Transfer Pump - B	C5	non-Ex	M20	Ex	M20	Arrester
10	SHF-D001B-001		230	2C-4	P2	49,02	213	SWG-MCC-001B	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	P-001B	Gross Transfer Pump - B	C5	non-Ex	M20	Ex	M20	Space Heater
11	P-P-023-001	0,37	400	3C-4-G	P2	49,72	242	SWG-MCC-001B	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	P-023	Gross Sump Pump	C5	non-Ex	M20	Ex	M20	
12	C-P-023-001			12C-15	P2	47	242	SWG-MCC-001B	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	P-023	Gross Sump Pump	C5	non-Ex	M20	Ex	M20	LCS (Start Stop Indicator Start/Stop)
13	P-C-001A-001	[52,24]	400	4C-95-G	P1	43,72	184	SWG-MCC-001B	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	C-001A	Instrument Air Compressor - A	E7	non-Ex	M50	non-Ex	M50	
14	P-C-001B-001	[38,24]	400	4C-25-G	P1	43,72	180	SWG-MCC-001B	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	C-001B	Instrument Air Compressor - B	E7	non-Ex	M50	non-Ex	M50	
15	P-P-008A-001	0,75	400	3C-4-G	P2	49,72	150	SWG-MCC-001B	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	P-008A	Deep Well Pump - A	E4	non-Ex	M20	Ex	M20	
16	C-P-008A-001			12C-15	P2	47	150	SWG-MCC-001B	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	P-008A	Deep Well Pump - A	E4	non-Ex	M20	Ex	M20	LCS (Start Stop Indicator Start/Stop)
17	P-P-008B-001	0,75	400	3C-4-G	P2	49,72	147	SWG-MCC-001B	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	P-008B	Deep Well Pump - B	E4	non-Ex	M20	Ex	M20	
18	C-P-008B-001			12C-15	P2	47	147	SWG-MCC-001B	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	P-008B	Deep Well Pump - B	E4	non-Ex	M20	Ex	M20	LCS (Start Stop Indicator Start/Stop)
19	P-P-016A-001	0,37	400	3C-4-G	P2	49,72	178	SWG-MCC-001B	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	P-016A	Booster Pump - A	E7	non-Ex	M20	Ex	M20	
20	C-P-016A-001			12C-15	P2	47	178	SWG-MCC-001B	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	P-016A	Booster Pump - A	E7	non-Ex	M20	Ex	M20	LCS (Start Stop Indicator Start/Stop)
21	P-P-016B-001	0,37	400	3C-4-G	P2	49,72	175	SWG-MCC-001B	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	P-016B	Booster Pump - B	E7	non-Ex	M20	Ex	M20	
22	C-P-016B-001			12C-15	P2	47	175	SWG-MCC-001B	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	P-016B	Booster Pump - B	E7	non-Ex	M20	Ex	M20	LCS (Start Stop Indicator Start/Stop)
23	P-P-017A-001	0,37	400	3C-4-G	P2	49,72	176	SWG-MCC-001B	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	P-017A	Water Distribution Pump - A	D7	non-Ex	M20	non-Ex	M20	
24	C-P-017A-001			12C-15	P2	47	176	SWG-MCC-001B	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	P-017A	Water Distribution Pump - A	D7	non-Ex	M20	non-Ex	M20	LCS (Start Stop Indicator Start/Stop)
25	P-P-017B-001	0,37	400	3C-4-G	P2	49,72	173	SWG-MCC-001B	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	P-017B	Water Distribution Pump - B	D7	non-Ex	M20	non-Ex	M20	
26	C-P-017B-001			12C-15	P2	47	173	SWG-MCC-001B	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	P-017B	Water Distribution Pump - B	D7	non-Ex	M20	non-Ex	M20	LCS (Start Stop Indicator Start/Stop)
27	P-P-051-001	[2,52]	400	4C-10-G	P2	25,16	307	SWG-MCC-001B	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	P-051	Jockes Pump	C2	non-Ex	M25	non-Ex	M25	
28	P-UPS-001B-001	[30]	400	4C-10-G	P2	25,16	42	SWG-MCC-001B	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	UPS-001B	AC UPS	E8	non-Ex	M25	non-Ex	M25	
29	P-UPS-001C-001	[30]	400	4C-10-G	P2	25,16	43	SWG-MCC-001B	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	UPS-001C	AC UPS (By Pass)	E8	non-Ex	M25	non-Ex	M25	
30	P-ELP-001-001	[53,82]	400	4C-10-G	P1	34,5	45	SWG-MCC-001B	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	ELP-001	Emergency Lighting Panel and Small Power DB	E8	non-Ex	M40	non-Ex	M40	
31	P-OHC-001-001	[11,12]	400	4C-10-G	P2	25,16	92	SWG-MCC-001B	0.4 kV LOW VOLTAGE SWITCHGEAR AND MCC BUS B	E6	OHC-001	Overead For GEG Shelter	C9	non-Ex	M25	non-Ex	M25	
G	AC UPS																	
1	P-BAT-UPS-001-001	100 Ah	220	2C-50-G	P4	29,52	30	DB-BAT-UPS-001	MCCB BOX BATTERY	E6	BAT-UPS-001	Batery UPS	E8	non-Ex	M32	non-Ex	M32	
2	P-DB-BAT-UPS-001-001	100 Ah	220	2C-50-G	P4	29,52	30	UPS-001	AC UPS	E6	DB-BAT-UPS-001	MCCB BOX BATTERY	E6	non-Ex	M32	non-Ex	M32	
H	DB UPS																	
1	P-TMBP-PCS-001-001	[1,13]	230	2C-25	P4	15,34	30	DB-UPS-001	Dst. Board UPS	E6	PP-PCS-401	Process Control System (PCS)	E8	non-Ex	M20	non-Ex	M20	
2	P-TMBP-PCS-001-002	[1,13]	230	2C-25	P4	15,34	30	DB-UPS-001	Dst. Board UPS	E6	PP-PCS-401	Process Control System (PCS)	E8	non-Ex	M20	non-Ex	M20	
3	P-TMBP-ESS-002-001	[1,13]	230	2C-25	P4	15,34	30	DB-UPS-001	Dst. Board UPS	E6	PP-PCS-401	Emergency Shutdown System (ESS) / Fire Gas System (FGS)	E8	non-Ex	M20	non-Ex	M20	
4	P-TMBP-ESS-002-002	[1,13]	230	2C-25	P4	15,34	30	DB-UPS-001	Dst. Board UPS	E6	PP-PCS-401	Emergency Shutdown System (ESS) / Fire Gas System (FGS)	E8	non-Ex	M20	non-Ex	M20	
5	P-TMBP-CCTV-003-001	[1,13]	230	2C-25	P4	15,34	30	DB-UPS-001	Dst. Board UPS	E6	TMBP-CCTV-003	CCTV System	E8	non-Ex	M20	non-Ex	M20	
6	P-TMBP-NVR-004-001	[0,35]	230	2C-25	P4	15,34	30	DB-UPS-001	Dst. Board UPS	E6	TMBP-CCTV-004	Network Video Recorder	E8	non-Ex	M20	non-Ex	M20	
7	P-TMBP-PABX-005-001	[1,18]	230	2C-25	P4	15,34	30	DB-UPS-001	Dst. Board UPS	E6	TMBP-PABX-005	Foreawa Automatic Branch Exchange	E8	non-Ex	M20	non-Ex	M20	
8	P-TMBP-PAGA-006-001	[0,24]	230	2C-25	P4	15,34	30	DB-UPS-001	Dst. Board UPS	E6	TMBP-PAGA-006	Public Address & General Alarm	E8	non-Ex	M20	non-Ex	M20	
9	P-TMBP-PACR-007-001	[0,35]	230	2C-25	P4	15,34	30	DB-UPS-001	Dst. Board UPS	E6	TMBP-FCAP-007	Server / Historian / Network	E8	non-Ex	M20	non-Ex	M20	
10	P-TMBP-SHN-001-001	[0,52]	230	2C-25	P4	15,34	30	DB-UPS-001	Dst. Board UPS	E6	TMBP-SHN-001	Fire Control Panel	E8	non-Ex	M20	non-Ex	M20	
11	P-TMBP-AUX-001-001	[0,35]	230	2C-25	P4	15,34	30	DB-UPS-001	Dst. Board UPS	E6	TMBP-AUX-001	Auxiliary Console	E8	non-Ex	M20	non-Ex	M20	
12	P-TMBP-EWS-001-001	[0,71]	230	2C-25	P4	15,34	30	DB-UPS-001	Dst. Board UPS	E6	TMBP-EWS-001	Engineering Work Station (PC)	E8	non-Ex	M20	non-Ex	M20	
13	P-TMBP-OWS-001-001	[0,71]	230	2C-25	P4	15,34	30	DB-UPS-001	Dst. Board UPS	E6	TMBP-OWS-001	PCS Operator Work Station (PC)	E8	non-Ex	M20	non-Ex	M20	
14	P-TMBP-OWS-002-001	[0,71]	230	2C-25	P4	15,34	30	DB-UPS-001	Dst. Board UPS	E6	TMBP-OWS-002	ESD / FGS Operator Work Station (PC)	E8	non-Ex	M20	non-Ex	M20	
15	P-TMBP-OWS-003-001	[0,35]	230	2C-25	P4	15,34	30	DB-UPS-001	Dst. Board UPS	E6	TMBP-OWS-003	Modules Display Operator Work Station	E8	non-Ex	M20	non-Ex	M20	

skkmigas PERTAMINA EP

DED PENGEMBANGAN FASILITAS PRODUKSI
TANJUNG MIRING BARAT & KARANGAN TIMUR

POG

ELECTRICAL CABLE SCHEDULE

Doc No : TMBP-SP001-EL-SHC-D101
Rev : A
Date : 09-01-2026

No	CABLE NO	LOAD		CABLE DESCRIPTION				ROUTE						CABLE GLAND				REMARKS
								FROM			TO			FROM		TO		
		CAPACITY KW [KVA]	VOLTAGE (V)	SIZE (mm2)	CABLE TYPE	OD (mm)	LENGTH (M)	EQUIPMENT NUMBER	EQUIPMENT NAME	EQUIPMENT LOCATION	EQUIPMENT NUMBER	EQUIPMENT NAME	EQUIPMENT LOCATION	TYPE	SIZE	TYPE	SIZE	
16	P-TMBP-PRT-001-001	[0.02]	230	2C-25	P4	15.34	30	DB-UPS-001	Dist. Board UPS	E6	TMBP-PRT-001	Color Printer	E6	nonEx	M20	nonEx	M20	
17	P-TMBP-PRT-002-001	[0.05]	230	2C-25	P4	15.34	30	DB-UPS-001	Dist. Board UPS	E6	TMBP-PRT-002	Doc Matrik Printer	E6	nonEx	M20	nonEx	M20	
18	P-TMBP-PC-CCTV-001-001	[0.02]	230	2C-25	P4	15.34	30	DB-UPS-001	Dist. Board UPS	E6	TMBP-PC-CCTV-001	PC for CCTV Station	E6	nonEx	M20	nonEx	M20	
19	P-TMBP-PC-CCTV-001-002	[0.02]	230	2C-25	P4	15.34	30	DB-UPS-001	Dist. Board UPS	E6	TMBP-PC-CCTV-001	PC for CCTV Security	E6	nonEx	M20	nonEx	M20	
20	P-TMBP-PC-CCTV-001-003	[0.35]	230	2C-25	P4	15.34	30	DB-UPS-001	Dist. Board UPS	E6	TMBP-PC-CCTV-001	CCTV Monitor 24	E6	nonEx	M20	nonEx	M20	
21	P-TMBP-FTZ-C-001-001	[0.05]	230	2C-25	P4	15.34	30	DB-UPS-001	Dist. Board UPS	E6	TMBP-PTZ-C-001	PTZ Controler	E6	nonEx	M20	nonEx	M20	
22	P-TMBP-LCP-008-001	[0.52]	230	2C-25	P4	15.34	30	DB-UPS-001	Dist. Board UPS	E6	TMBP-LCP-008	RE Panel	E6	nonEx	M20	nonEx	M20	
23	P-TMBP-LCP-009-001	[0.52]	230	2C-25	P4	15.34	30	DB-UPS-001	Dist. Board UPS	E6	TMBP-LCP-009	Distribution Panel	E6	nonEx	M20	nonEx	M20	
24	P-TMBP-PT-002-001	[0.02]	230	2C-25	P4	15.34	30	DB-UPS-001	Dist. Board UPS	E6	TMBP-PT-002	Ultrasonic Flow Faster (DB Panel at Instrument Panel	E6	nonEx	M20	nonEx	M20	
25	P-TMBP-FTZ-001-001	[0.07]	230	2C-25	P4	15.34	30	DB-UPS-001	Dist. Board UPS	E6	TMBP-PTZ-001	PTZ Camera (1.25) (DB Panel at Instrument Panel)	E6	nonEx	M20	nonEx	M20	
26	P-TMBP-FTZ-002-001	[0.07]	230	2C-25	P4	15.34	30	DB-UPS-001	Dist. Board UPS	E6	TMBP-PTZ-002	PTZ Camera (DB Panel at Instrument Panel)	E6	nonEx	M20	nonEx	M20	
27	P-TMBP-FTZ-003-001	[0.07]	230	2C-25	P4	15.34	30	DB-UPS-001	Dist. Board UPS	E6	TMBP-PTZ-003	PTZ Camera (DB Panel at Instrument Panel)	E6	nonEx	M20	nonEx	M20	
28	P-TMBP-FTZ-004-001	[0.07]	230	2C-25	P4	15.34	30	DB-UPS-001	Dist. Board UPS	E6	TMBP-PTZ-004	PTZ Camera (DB Panel at Instrument Panel)	E6	nonEx	M20	nonEx	M20	
29	P-TMBP-FTZ-005-001	[0.07]	230	2C-25	P4	15.34	30	DB-UPS-001	Dist. Board UPS	E6	TMBP-PTZ-005	PTZ Camera (DB Panel at Instrument Panel)	E6	nonEx	M20	nonEx	M20	
30	P-TMBP-FIX-001-001	[0.07]	230	2C-25	P4	15.34	30	DB-UPS-001	Dist. Board UPS	E6	TMBP-FCIX-001	For Camera	E6	nonEx	M20	nonEx	M20	
31	P-TMBP-FIX-002-001	[0.07]	230	2C-25	P4	15.34	30	DB-UPS-001	Dist. Board UPS	E6	TMBP-FCIX-002	For Camera	E6	nonEx	M20	nonEx	M20	
32	P-TMBP-FIX-003-001	[0.07]	230	2C-25	P4	15.34	30	DB-UPS-001	Dist. Board UPS	E6	TMBP-FCIX-003	For Camera	E6	nonEx	M20	nonEx	M20	
33	P-SPK-001L2-001	[0.02]	230	2C-25	P4	15.34	30	DB-UPS-001	Dist. Board UPS	E6	SPK-001L2	Speaker Indoor	E6	nonEx	M20	nonEx	M20	
34	P-SPK-001L6-001	[0.02]	230	2C-25	P4	15.34	30	DB-UPS-001	Dist. Board UPS	E6	SPK-003L2	Speaker Outdoor (DB Panel at Instrument Panel)	E6	nonEx	M20	nonEx	M20	
35	P-GCP-GEG-001-001	[0.35]	230	2C-25	P4	15.34	20	DB-UPS-001	Dist. Board UPS	E6	GCP-GEG-001	GCP Gas Engine Generator - 001	D5	nonEx	M20	nonEx	M20	
36	P-GCP-GEG-002-001	[0.35]	230	2C-25	P4	15.34	20	DB-UPS-001	Dist. Board UPS	E6	GCP-GEG-002	GCP Gas Engine Generator - 002	D5	nonEx	M20	nonEx	M20	
37	P-MGCP-001-001	[0.35]	230	2C-25	P4	15.34	25	DB-UPS-001	Dist. Board UPS	E6	MASTER GCP	Master Generator Control Panel	D5	nonEx	M20	nonEx	M20	
38	P-GCP-DEG-001-001	[0.35]	230	2C-25	P4	15.34	25	DB-UPS-001	Dist. Board UPS	E6	GCP-EDG-001	GCP Engineering Diesel Generator - 001	D5	nonEx	M20	nonEx	M20	
39	P-SWGMCC-001-001	[0.24]	230	2C-25	P4	15.34	15	DB-UPS-001	Dist. Board UPS	E6	LV SWGR	LV Switchgear	E6	nonEx	M20	nonEx	M20	
40	P-TMBP-C-P-001-001	[0.34]	230	2C-25	P4	15.34	110	DB-UPS-001	Dist. Board UPS	E6	TMBP-LCP-001	Local Control Panel For Air Compressor	E7	nonEx	M20	nonEx	M20	
41	P-TMBP-LCP-003-001	[0.24]	230	2C-25	P4	15.34	95	DB-UPS-001	Dist. Board UPS	E6	TMBP-LCP-003	Local Control Panel for Gas Engine Generator - 001	E7	nonEx	M20	nonEx	M20	
42	P-TMBP-LCP-004-001	[0.24]	230	2C-25	P4	15.34	95	DB-UPS-001	Dist. Board UPS	E6	TMBP-LCP-004	Local Control Panel for Gas Engine Generator - 002	E7	nonEx	M20	nonEx	M20	
43	P-TMBP-LCP-005-001	[0.24]	230	2C-25	P4	15.34	92	DB-UPS-001	Dist. Board UPS	E6	TMBP-LCP-005	Local Control Panel for Diesel Engine Generator - 001	E7	nonEx	M20	nonEx	M20	
44	P-TMBP-LCP-006-001	[0.24]	230	2C-25	P4	15.34	110	DB-UPS-001	Dist. Board UPS	E6	TMBP-LCP-006	Local Control Panel Air Dryer Package	E7	nonEx	M20	nonEx	M20	

NOTE :
1 Ukuran Cable Gland mengacu pada Data Vendor
2 Overall Diameter Cable mengacu pada katalog kabel yang digunakan pada dokumen TMBP-01-EL-CA-103-Cable Calculation

TIPE KABEL	DESKRIPSI	PENERAPAN KABEL
P1	Multicore CULFESVOSSWAFYCFR power cable 600/1000 V voltage pada stranded copper conductor, XLPE insulation, Galstar Steel Wire Armour (Same (RC50330.3 CAT A thermoset cor pounds sheath	Kabel dengan ukuran 16mm² dan diatasnya untuk feeder utama dan feeder motor
P2	Multicore CLLUOLPERVOSSVEFVC-FR power cable, vailge grade stranded copper conductor XLPE insulation Galster Steel Wire 25WE Fantast (F Ria conference ECOS CAT CF VC compounds sheat	Kabel dengan ukuran 10mm² can dibawahnya untuk kebutuhan penerangan daya rendah dan remote kontrol di luar ruangan (outdoor)
P3	Multicore CUXEFEL SEGSWSLSZHFR power cable, 500300 V voltage grade stendere anar XLPE ration, Gavezed Steel Wire Brand (640) Force Putardant EC60332.3, CAT A thermoset compounds shaath	Kabel dengan ukuran 10mm² dan dibawahnya untuk kebutuhan pengerangan dengan daya dan remote kontrol dalam ruangan motor
P4	Multicore CUMGTIX FEPIC GSWBFVC-FR po vetage grade fre resistant incorros Mica Gress Tape Galvanizad Steel Wire Sad SWS) Fire Restart (F Hard EC 60332.3 CAT A thermoset compounds shaath	Kabel untuk sistem distribusi tenaji UPS
F3	Twisted trad ortbr FTD cable application PVC-HRnded clase mickel clated copper off reed upper TOWE overall screen, PVCARE of test grey or white dereafrcds max tamperture 130°C	Kabel Resistance Inspector Director
G	Single care PVC sected conductor 150 V voltage gradu stranded copper constuctor Pene Fatantwas EC 50332	Kabel untuk kepetuan system grounding