skkmigas PERTAMINA EP	**PERTAMINA EP REGIONAL 1 ZONA 4**	POG

INSTRUMENT CABLE SCHEDULE	No. Dok. : TMBP-SP001-IN-SCH-D101 Rev. : A Halaman : 1 dari 9

NAMA PEMILIK PROYEK : **PT PERTAMINA EP**

NAMA PROYEK : **JASA PEMBANGUNAN FASILITAS PRODUKSI STASIUN PENGUMPUL (SP) TANJUNG MIRING BARAT & KARANGAN TIMUR**

LOKASI : **SP TANJUNG MIRING BARAT & KARANGAN TIMUR - FIELD LIMAU**

NO. KONTRAK : **SA02035383B**

REV.	TGL.	DESKRIPSI	DISIAPKAN	DIPERIKSA	DISETUJUI	DIPERIKSA	DISETUJUI
A	05/01/2026	Issued For Review	MHP	AS	RTN		
			PT. PROSYMPAC OIL & GAS			PT. PERTAMINA EP	

TABEL REVISI

Rev.	Tanggal	Deskripsi

COMMENT RESPONSE SHEET

No.	Page	PERUSAHAAN's Comment	Contractor's Response	Remarks

DAFTAR ISI

TABEL REVISI **2**
COMMENT RESPONSE SHEET **3**
DAFTAR ISI **4**

INSTRUMENT CABLE SCHEDULE

PROJECT : DED JASA PEMBANGUNAN FASILITAS PRODUKSI STASIUN PENGUMPUL (SP) TANJUNG MIRING BARAT & KARANGAN TIMUR
OWNER : PT. PERTAMINA HULU ROKAN
LOCATION : LAPANGAN TANJUNG MIRING BARAT DAN KARANGAN TIMUR
DOC. NO : TMBP-SP001-IN-SCH-D101
REVISION : A

No	CABLE NO.	FROM				TO				VOLTAGE GRADE	CABLE TYPE	DESCRIPTION	O.D (mm)	LENGTH (m)	DRUM NO.	REMARKS
		Tag No.	DESCRIPTION	LOCATION	GLAND SIZE	Tag No.	DESCRIPTION	LOCATION	GLAND SIZE							
1	PIT-V001-002	PIT-V001-002	PRESSURE TRANSMITTER	Field	1/2" NPT	JB-AP-01	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	45	1PR-AN-FL-DR1	
2	LIT-V001-003	LIT-V001-003	LEVEL TRANSMITTER	Field	1/2" NPT	JB-AP-01	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	45	1PR-AN-FL-DR1	
3	PY-V001-002	PY-V001-002	I/P CONVERTER	Field	1/2" NPT	JB-AP-01	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	45	1PR-AN-FL-DR1	
4	ZIT-V001-002	ZIT-V001-002	POSITION TRANSMITTER	Field	1/2" NPT	JB-AP-01	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	45	1PR-AN-FL-DR1	
5	FIT-V001-001	FIT-V001-001	FLOW TRANSMITTER	Field	1/2" NPT	JB-AP-01	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	45	1PR-AN-FL-DR1	
6	LY-V001-003	LY-V001-003	I/P CONVERTER	Field	1/2" NPT	JB-AP-01	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	39	1PR-AN-FL-DR1	
7	ZIT-V001-003	ZIT-V001-003	POSITION TRANSMITTER	Field	1/2" NPT	JB-AP-01	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	39	1PR-AN-FL-DR1	
8	TT-V001-001	TT-V001-001	TEMPERATURE TRANSMITTER	Field	1/2" NPT	JB-AP-01	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	45	1PR-AN-FL-DR1	
9	TT-V003-001	TT-V003-001	TEMPERATURE TRANSMITTER	Field	1/2" NPT	JB-AP-01	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	34	1PR-AN-FL-DR1	
10	PIT-V003-002	PIT-V003-002	PRESSURE TRANSMITTER	Field	1/2" NPT	JB-AP-01	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	34	1PR-AN-FL-DR1	
11	PY-V003-002	PY-V003-002	I/P CONVERTER	Field	1/2" NPT	JB-AP-01	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	34	1PR-AN-FL-DR1	
12	ZIT-V003-002	ZIT-V003-002	POSITION TRANSMITTER	Field	1/2" NPT	JB-AP-01	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	34	1PR-AN-FL-DR1	
13	LIT-V003-003	LIT-V003-003	LEVEL TRANSMITTER	Field	1/2" NPT	JB-AP-01	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	34	1PR-AN-FL-DR1	
14	FIT-V003-001	FIT-V003-001	FLOW TRANSMITTER	Field	1/2" NPT	JB-AP-01	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	34	1PR-AN-FL-DR1	
15	LY-V003-003	LY-V003-003	I/P CONVERTER	Field	1/2" NPT	JB-AP-01	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	34	1PR-AN-FL-DR1	
16	ZIT-V003-003	ZIT-V003-003	POSITION TRANSMITTER	Field	1/2" NPT	JB-AP-01	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	34	1PR-AN-FL-DR1	
17	PIT-V002-002	PIT-V002-002	PRESSURE TRANSMITTER	Field	1/2" NPT	JB-AP-01	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	41	1PR-AN-FL-DR1	
18	LIT-V002-003	LIT-V002-003	LEVEL TRANSMITTER	Field	1/2" NPT	JB-AP-01	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	41	1PR-AN-FL-DR1	
19	PY-V002-002	PY-V002-002	I/P CONVERTER	Field	1/2" NPT	JB-AP-01	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	41	1PR-AN-FL-DR1	
20	ZIT-V002-002	ZIT-V002-002	POSITION TRANSMITTER	Field	1/2" NPT	JB-AP-01	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	41	1PR-AN-FL-DR1	
21	**JBAP-01-01**	**JB-AP-01**	**Analog PCS Junction Box**	**Field**	**M40**	**PCS-001**	**PCS Cabinet**	**C/R**	**M32**	**300/500**	**XLPE**	**24 Pr#1.5mm^2 / IS-OS / FL / ANALOG**	**36.9**	**130**	**24PR-AN-FL-DR1**	
22	LY-V002-003	LY-V002-003	I/P CONVERTER	Field	1/2" NPT	JB-AP-02	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	39	1PR-AN-FL-DR1	
23	ZIT-V002-003	ZIT-V002-003	POSITION TRANSMITTER	Field	1/2" NPT	JB-AP-02	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	39	1PR-AN-FL-DR1	
24	FIT-V002-001	FIT-V002-001	FLOW TRANSMITTER	Field	1/2" NPT	JB-AP-02	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	39	1PR-AN-FL-DR1	
25	PIT-V004-002	PIT-V004-002	PRESSURE TRANSMITTER	Field	1/2" NPT	JB-AP-02	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	30	1PR-AN-FL-DR1	
26	PY-V004-002	PY-V004-002	I/P CONVERTER	Field	1/2" NPT	JB-AP-02	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	32	1PR-AN-FL-DR1	
27	ZIT-V004-002	ZIT-V004-002	POSITION TRANSMITTER	Field	1/2" NPT	JB-AP-02	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	32	1PR-AN-FL-DR2	
28	LIT-V004-003	LIT-V004-003	LEVEL TRANSMITTER	Field	1/2" NPT	JB-AP-02	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	31	1PR-AN-FL-DR2	
29	FIT-V004-001	FIT-V004-001	FLOW TRANSMITTER	Field	1/2" NPT	JB-AP-02	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	30	1PR-AN-FL-DR2	
30	LY-V004-003	LY-V004-003	I/P CONVERTER	Field	1/2" NPT	JB-AP-02	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	30	1PR-AN-FL-DR2	
31	ZIT-V004-003	ZIT-V004-003	POSITION TRANSMITTER	Field	1/2" NPT	JB-AP-02	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	30	1PR-AN-FL-DR2	
32	TT-V004-001	TT-V004-001	TEMPERATURE TRANSMITTER	Field	1/2" NPT	JB-AP-02	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	41	1PR-AN-FL-DR2	
33	TT-V004-001	TT-V004-001	TEMPERATURE TRANSMITTER	Field	1/2" NPT	JB-AP-02	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	32	1PR-AN-FL-DR2	
34	PIT-V005-001	PIT-V005-001	PRESSURE TRANSMITTER	Field	1/2" NPT	JB-AP-02	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	19	1PR-AN-FL-DR2	
35	LIT-V005-002	LIT-V005-002	LEVEL TRANSMITTER	Field	1/2" NPT	JB-AP-02	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	22	1PR-AN-FL-DR2	
36	TT-V005-001	TT-V005-001	TEMPERATURE TRANSMITTER	Field	1/2" NPT	JB-AP-02	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	19	1PR-AN-FL-DR2	
37	PY-V005-001	PY-V005-001	I/P CONVERTER	Field	1/2" NPT	JB-AP-02	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	12	1PR-AN-FL-DR2	
38	ZIT-V005-001	ZIT-V005-001	POSITION TRANSMITTER	Field	1/2" NPT	JB-AP-02	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	12	1PR-AN-FL-DR2	
39	LY-V005-002	LY-V005-002	I/P CONVERTER	Field	1/2" NPT	JB-AP-02	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	23	1PR-AN-FL-DR2	
40	ZIT-V005-002	ZIT-V005-002	POSITION TRANSMITTER	Field	1/2" NPT	JB-AP-02	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	23	1PR-AN-FL-DR2	
41	FIT-FG001-001	FIT-FG001-001	FLOW TRANSMITTER	Field	1/2" NPT	JB-AP-02	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	19	1PR-AN-FL-DR2	
42	PIT-FG001-003	PIT-FG001-003	PRESSURE TRANSMITTER	Field	1/2" NPT	JB-AP-02	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	24	1PR-AN-FL-DR2	
43	**JBAP-02-01**	**JB-AP-02**	**Analog PCS Junction Box**	**Field**	**M40**	**PCS-001**	**PCS Cabinet**	**C/R**	**M32**	**300/500**	**XLPE**	**24 Pr#1.5mm^2 / IS-OS / FL / ANALOG**	**36.9**	**130**	**24PR-AN-FL-DR1**	
44	PIT-KRG-001	PIT-KRG-001	PRESSURE TRANSMITTER	Field	1/2" NPT	JB-AP-03	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	46	1PR-AN-FL-DR2	
45	PIT-KRG-002	PIT-KRG-002	PRESSURE TRANSMITTER	Field	1/2" NPT	JB-AP-03	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	46	1PR-AN-FL-DR2	
46	PIT-TMB-001	PIT-TMB-001	PRESSURE TRANSMITTER	Field	1/2" NPT	JB-AP-03	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	45	1PR-AN-FL-DR2	
47	PIT-TMB-002	PIT-TMB-002	PRESSURE TRANSMITTER	Field	1/2" NPT	JB-AP-03	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	45	1PR-AN-FL-DR2	
48	FIT-P008-001A	FIT-P008-001A	ROTAMETER TRANSMITTER	Field	1/2" NPT	JB-AP-03	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	13	1PR-AN-FL-DR2	
49	FIT-P008-001B	FIT-P008-001B	ROTAMETER TRANSMITTER	Field	1/2" NPT	JB-AP-03	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	12	1PR-AN-FL-DR2	
50	**JBAP-03-01**	**JB-AP-03**	**Analog PCS Junction Box**	**Field**	**M32**	**PCS-001**	**PCS Cabinet**	**C/R**	**M32**	**300/500**	**XLPE**	**12 Pr#1.5mm^2 / IS-OS / FL / ANALOG**	**27.1**	**143**	**12PR-AN-FL-DR1**	
51	LIT-T003-001	LIT-T003-001	LEVEL TRANSMITTER	Field	1/2" NPT	JB-AP-04	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	66	1PR-AN-FL-DR2	
52	PDIT-T003-001	PDIT-T003-001	PRESSURE DIFF. TRANSMITTER	Field	1/2" NPT	JB-AP-04	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	55	1PR-AN-FL-DR2	
53	LIT-T004-001	LIT-T004-001	LEVEL TRANSMITTER	Field	1/2" NPT	JB-AP-04	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	64	1PR-AN-FL-DR2	
54	PDIT-T004-001	PDIT-T004-001	PRESSURE DIFF. TRANSMITTER	Field	1/2" NPT	JB-AP-04	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	54	1PR-AN-FL-DR2	
55	LIT-PN001-002	LIT-PN001-002	LEVEL TRANSMITTER	Field	1/2" NPT	JB-AP-04	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	135	1PR-AN-FL-DR2	
56	PIT-P019-001	PIT-P019-001	PRESSURE TRANSMITTER	Field	1/2" NPT	JB-AP-04	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	135	1PR-AN-FL-DR3	
57	**JBAP-04-01**	**JB-AP-04**	**Analog PCS Junction Box**	**Field**	**M32**	**PCS-001**	**PCS Cabinet**	**C/R**	**M32**	**300/500**	**XLPE**	**12 Pr#1.5mm^2 / IS-OS / FL / ANALOG**	**27.1**	**51**	**12PR-AN-FL-DR1**	
58	LIT-T005-002A	LIT-T005-002A	LEVEL TRANSMITTER	Field	1/2" NPT	JB-AP-07	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	68	1PR-AN-FL-DR4	
59	LIT-T005-002B	LIT-T005-002B	LEVEL TRANSMITTER	Field	1/2" NPT	JB-AP-07	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	68	1PR-AN-FL-DR4	
60	LIT-T006-002A	LIT-T006-002A	LEVEL TRANSMITTER	Field	1/2" NPT	JB-AP-07	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	47	1PR-AN-FL-DR4	
61	LIT-T006-002B	LIT-T006-002B	LEVEL TRANSMITTER	Field	1/2" NPT	JB-AP-07	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	32	1PR-AN-FL-DR4	
62	FIT-P001-001	FIT-P001-001	FLOW TRANSMITTER	Field	1/2" NPT	JB-AP-07	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	54	1PR-AN-FL-DR4	
63	PDIT-P001-001	PDIT-P001-001	PRESSURE DIFF. TRANSMITTER	Field	1/2" NPT	JB-AP-07	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	84	1PR-AN-FL-DR4	
64	VIT-P001-001A	VIT-P001-001A	VIBRATION TRANSMITTER	Field	1/2" NPT	JB-AP-07	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	54	1PR-AN-FL-DR4	
65	VIT-P001-001B	VIT-P001-001B	VIBRATION TRANSMITTER	Field	1/2" NPT	JB-AP-07	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	84	1PR-AN-FL-DR4	
66	**JBAP-07-01**	**JB-AP-07**	**Analog PCS Junction Box**	**Field**	**M32**	**PCS-001**	**PCS Cabinet**	**C/R**	**M32**	**300/500**	**XLPE**	**12 Pr#1.5mm^2 / IS-OS / FL / ANALOG**	**27.1**	**155**	**12PR-AN-FL-DR1**	

INSTRUMENT CABLE SCHEDULE

PROJECT : DED JASA PEMBANGUNAN FASILITAS PRODUKSI STASIUN PENGUMPUL (SP) TANJUNG MIRING BARAT & KARANGAN TIMUR
OWNER : PT. PERTAMINA HULU ROKAN
LOCATION : LAPANGAN TANJUNG MIRING BARAT DAN KARANGAN TIMUR
DOC. NO : TMBP-SP001-IN-SCH-D101
REVISION : A

No	CABLE NO.	FROM				TO				VOLTAGE GRADE	CABLE TYPE	DESCRIPTION	O.D (mm)	LENGTH (m)	DRUM NO.	REMARKS
		Tag No.	DESCRIPTION	LOCATION	GLAND SIZE	Tag No.	DESCRIPTION	LOCATION	GLAND SIZE							
67	LIT-V006-001	LIT-V006-001	LEVEL TRANSMITTER	Field	1/2" NPT	JB-AP-08	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	23	1PR-AN-FL-DR4	
68	LIT-V006-002	LIT-V006-002	LEVEL TRANSMITTER	Field	1/2" NPT	JB-AP-08	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	24	1PR-AN-FL-DR4	
69	PIT-V006-001	PIT-V006-001	PRESSURE TRANSMITTER	Field	1/2" NPT	JB-AP-08	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	22	1PR-AN-FL-DR4	
70	TT-V006-001	TT-V006-001	TEMPERATURE TRANSMITTER	Field	1/2" NPT	JB-AP-08	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	21	1PR-AN-FL-DR4	
71	PIT-V006-002	PIT-V006-002	PRESSURE TRANSMITTER	Field	1/2" NPT	JB-AP-08	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	12	1PR-AN-FL-DR4	
72	TT-V006-002	TT-V006-002	TEMPERATURE TRANSMITTER	Field	1/2" NPT	JB-AP-08	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	12	1PR-AN-FL-DR4	
73	FIT-V006-002	FIT-V006-002	FLOW TRANSMITTER	Field	1/2" NPT	JB-AP-08	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	18	1PR-AN-FL-DR4	
74	PIT-P006-001A	PIT-P006-001A	PRESSURE TRANSMITTER	Field	1/2" NPT	JB-AP-08	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	26	1PR-AN-FL-DR4	
75	PIT-P006-002A	PIT-P006-002A	PRESSURE TRANSMITTER	Field	1/2" NPT	JB-AP-08	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	26	1PR-AN-FL-DR4	
76	PIT-P006-001B	PIT-P006-001B	PRESSURE TRANSMITTER	Field	1/2" NPT	JB-AP-08	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	26	1PR-AN-FL-DR4	
77	PIT-P006-002B	PIT-P006-002B	PRESSURE TRANSMITTER	Field	1/2" NPT	JB-AP-08	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	26	1PR-AN-FL-DR4	
78	PIT-V007-001	PIT-V007-001	PRESSURE TRANSMITTER	Field	1/2" NPT	JB-AP-08	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	33	1PR-AN-FL-DR4	
79	LIT-V007-001	LIT-V007-001	LEVEL TRANSMITTER	Field	1/2" NPT	JB-AP-08	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	33	1PR-AN-FL-DR5	
80	LIT-V007-002	LIT-V007-002	LEVEL TRANSMITTER	Field	1/2" NPT	JB-AP-08	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	33	1PR-AN-FL-DR5	
81	TT-V007-001	TT-V007-001	TEMPERATURE TRANSMITTER	Field	1/2" NPT	JB-AP-08	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	31	1PR-AN-FL-DR5	
82	PIT-P007-001A	PIT-P007-001A	PRESSURE TRANSMITTER	Field	1/2" NPT	JB-AP-08	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	34	1PR-AN-FL-DR5	
83	PIT-P007-002A	PIT-P007-002A	PRESSURE TRANSMITTER	Field	1/2" NPT	JB-AP-08	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	34	1PR-AN-FL-DR5	
84	PIT-P007-001B	PIT-P007-001B	PRESSURE TRANSMITTER	Field	1/2" NPT	JB-AP-08	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	34	1PR-AN-FL-DR5	
85	PIT-P007-002B	PIT-P007-002B	PRESSURE TRANSMITTER	Field	1/2" NPT	JB-AP-08	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	34	1PR-AN-FL-DR5	
86	**JBAP-08-01**	**JB-AP-08**	**Analog PCS Junction Box**	**Field**	**M32**	**PCS-001**	**PCS Cabinet**	**C/R**	**M32**	**300/500**	**XLPE**	**24 Pr#1.5mm^2 / IS-OS / FL / ANALOG**	**36.9**	**102**	**24PR-AN-FL-DR1**	
87	PIT-P017-001	PIT-P017-001	PRESSURE TRANSMITTER	Field	1/2" NPT	JB-AP-09	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	15	1PR-AN-FL-DR5	UTILITY WATER SYSTEM
88	LIT-T017-001	LIT-T017-001	LEVEL TRANSMITTER	Field	1/2" NPT	JB-AP-09	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	15	1PR-AN-FL-DR5	
89	**JBAP-09-01**	**JB-AP-09**	**Analog PCS Junction Box**	**Field**	**M32**	**PCS-001**	**PCS Cabinet**	**C/R**	**M32**	**300/500**	**XLPE**	**6 Pr#1.5mm^2 / IS-OS / FL / ANALOG**	**20.7**	**136**	**6PR-AN-FL-DR1**	
90	PDIT-T019-001	PDIT-T019-001	PRESSURE DIFF. TRANSMITTER	Field	1/2" NPT	JB-AP-10	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	15	1PR-AN-FL-DR5	
91	FIT-F006-001	FIT-F006-001	FLOW TRANSMITTER	Field	1/2" NPT	JB-AP-10	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	21	1PR-AN-FL-DR5	
92	LIT-T019-001	LIT-T019-001	LEVEL TRANSMITTER	Field	1/2" NPT	JB-AP-10	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	20	1PR-AN-FL-DR5	
93	ZIT-V008-002	ZIT-V008-002	POSITION TRANSMITTER	Field	1/2" NPT	JB-AP-10	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	36	1PR-AN-FL-DR5	FUEL GAS SYSTEM
94	PY-V008-002	PY-V008-002	I/P CONVERTER	Field	1/2" NPT	JB-AP-10	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	33	1PR-AN-FL-DR5	FUEL GAS SYSTEM
95	PIT-V008-001	PIT-V008-001	PRESSURE TRANSMITTER	Field	1/2" NPT	JB-AP-10	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	33	1PR-AN-FL-DR5	FUEL GAS SYSTEM
96	PIT-V008-002	PIT-V008-002	PRESSURE TRANSMITTER	Field	1/2" NPT	JB-AP-10	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	33	1PR-AN-FL-DR5	FUEL GAS SYSTEM
97	LIT-V008-003	LIT-V008-003	LEVEL TRANSMITTER	Field	1/2" NPT	JB-AP-10	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	33	1PR-AN-FL-DR5	FUEL GAS SYSTEM
98	PDIT-F001-001A	PDIT-F001-001A	PRESSURE DIFF. TRANSMITTER	Field	1/2" NPT	JB-AP-10	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	33	1PR-AN-FL-DR5	FUEL GAS SYSTEM
99	LIT-F001-001A	LIT-F001-001A	LEVEL TRANSMITTER	Field	1/2" NPT	JB-AP-10	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	33	1PR-AN-FL-DR5	FUEL GAS SYSTEM
100	PDIT-F001-001B	PDIT-F001-001B	PRESSURE DIFF. TRANSMITTER	Field	1/2" NPT	JB-AP-10	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	33	1PR-AN-FL-DR5	FUEL GAS SYSTEM
101	LIT-F001-001B	LIT-F001-001B	LEVEL TRANSMITTER	Field	1/2" NPT	JB-AP-10	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	33	1PR-AN-FL-DR5	FUEL GAS SYSTEM
102	ZIT-V008-003	ZIT-V008-003	POSITION TRANSMITTER	Field	1/2" NPT	JB-AP-10	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	33	1PR-AN-FL-DR5	FUEL GAS SYSTEM
103	LY-V008-003	LY-V008-003	I/P CONVERTER	Field	1/2" NPT	JB-AP-10	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	33	1PR-AN-FL-DR5	FUEL GAS SYSTEM
104	TT-F001-001	TT-F001-001	TEMPERATURE TRANSMITTER	Field	1/2" NPT	JB-AP-10	Analog PCS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS / FL / SWA / ANALOG	11.8	33	1PR-AN-FL-DR5	FUEL GAS SYSTEM
105	**JBAP-10-01**	**JB-AP-10**	**Analog PCS Junction Box**	**Field**	**M32**	**PCS-001**	**PCS Cabinet**	**C/R**	**M32**	**300/500**	**XLPE**	**24 Pr#1.5mm^2 / IS-OS / FL / ANALOG**	**36.9**	**114**	**24PR-AN-FL-DR1**	
106	ZSO-V001-001	ZSO-V001-001	OPEN POSITION SWITCH	Field	1/2"	JB-DP-01	Digital PCS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FL / SWA / DIGITAL	11.0	48	2CR-DI-FL-DR1	
107	ZSC-V001-001	ZSC-V001-001	CLOSE POSITION SWITCH	Field	1/2"	JB-DP-01	Digital PCS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FL / SWA / DIGITAL	11.0	48	2CR-DI-FL-DR1	
108	ZSO-V001-002	ZSO-V001-002	OPEN POSITION SWITCH	Field	1/2"	JB-DP-01	Digital PCS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FL / SWA / DIGITAL	11.0	40	2CR-DI-FL-DR1	
109	ZSC-V001-002	ZSC-V001-002	CLOSE POSITION SWITCH	Field	1/2"	JB-DP-01	Digital PCS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FL / SWA / DIGITAL	11.0	40	2CR-DI-FL-DR1	
110	ZSO-V002-001	ZSO-V002-001	OPEN POSITION SWITCH	Field	1/2"	JB-DP-01	Digital PCS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FL / SWA / DIGITAL	11.0	44	2CR-DI-FL-DR1	
111	ZSC-V002-001	ZSC-V002-001	CLOSE POSITION SWITCH	Field	1/2"	JB-DP-01	Digital PCS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FL / SWA / DIGITAL	11.0	44	2CR-DI-FL-DR1	
112	ZSO-V002-002	ZSO-V002-002	OPEN POSITION SWITCH	Field	1/2"	JB-DP-01	Digital PCS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FL / SWA / DIGITAL	11.0	33	2CR-DI-FL-DR1	
113	ZSC-V002-002	ZSC-V002-002	CLOSE POSITION SWITCH	Field	1/2"	JB-DP-01	Digital PCS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FL / SWA / DIGITAL	11.0	33	2CR-DI-FL-DR1	
114	ZSO-V003-001	ZSO-V003-001	OPEN POSITION SWITCH	Field	1/2"	JB-DP-01	Digital PCS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FL / SWA / DIGITAL	11.0	33	2CR-DI-FL-DR1	
115	ZSC-V003-001	ZSC-V003-001	CLOSE POSITION SWITCH	Field	1/2"	JB-DP-01	Digital PCS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FL / SWA / DIGITAL	11.0	33	2CR-DI-FL-DR1	
116	ZSO-V003-002	ZSO-V003-002	OPEN POSITION SWITCH	Field	1/2"	JB-DP-01	Digital PCS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FL / SWA / DIGITAL	11.0	32	2CR-DI-FL-DR1	
117	ZSC-V003-002	ZSC-V003-002	CLOSE POSITION SWITCH	Field	1/2"	JB-DP-01	Digital PCS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FL / SWA / DIGITAL	11.0	32	2CR-DI-FL-DR1	
118	ZSO-V004-001	ZSO-V004-001	OPEN POSITION SWITCH	Field	1/2"	JB-DP-01	Digital PCS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FL / SWA / DIGITAL	11.0	30	2CR-DI-FL-DR1	
119	ZSC-V004-001	ZSC-V004-001	CLOSE POSITION SWITCH	Field	1/2"	JB-DP-01	Digital PCS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FL / SWA / DIGITAL	11.0	30	2CR-DI-FL-DR1	
120	**JBDP-01-01**	**JB-DP-01**	**Digital PCS Junction Box**	**Field**	**M32**	**PCS-001**	**PCS Cabinet**	**C/R**	**M32**	**300/500**	**XLPE**	**40 Cr#1.5mm^2 / OS / FL / DIGITAL**	**34.1**	**134**	**40CR-DI-FL-DR1**	
121	ZSO-V004-002	ZSO-V004-002	OPEN POSITION SWITCH	Field	1/2"	JB-DP-02	Digital PCS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FL / SWA / DIGITAL	11.0	28	2CR-DI-FL-DR1	
122	ZSC-V004-002	ZSC-V004-002	CLOSE POSITION SWITCH	Field	1/2"	JB-DP-02	Digital PCS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FL / SWA / DIGITAL	11.0	28	2CR-DI-FL-DR1	
123	ZSO-V005-001	ZSO-V005-001	OPEN POSITION SWITCH	Field	1/2"	JB-DP-02	Digital PCS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FL / SWA / DIGITAL	11.0	25	2CR-DI-FL-DR1	
124	ZSC-V005-001	ZSC-V005-001	CLOSE POSITION SWITCH	Field	1/2"	JB-DP-02	Digital PCS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FL / SWA / DIGITAL	11.0	25	2CR-DI-FL-DR1	
125	ZSO-V005-002	ZSO-V005-002	OPEN POSITION SWITCH	Field	1/2"	JB-DP-02	Digital PCS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FL / SWA / DIGITAL	11.0	15	2CR-DI-FL-DR1	
126	ZSC-V005-002	ZSC-V005-002	CLOSE POSITION SWITCH	Field	1/2"	JB-DP-02	Digital PCS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FL / SWA / DIGITAL	11.0	15	2CR-DI-FL-DR1	
127	ZSO-V005-003	ZSO-V005-003	OPEN POSITION SWITCH	Field	1/2"	JB-DP-02	Digital PCS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FL / SWA / DIGITAL	11.0	12	2CR-DI-FL-DR1	
128	ZSC-V005-003	ZSC-V005-003	CLOSE POSITION SWITCH	Field	1/2"	JB-DP-02	Digital PCS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FL / SWA / DIGITAL	11.0	12	2CR-DI-FL-DR1	
129	**JBDP-02-01**	**JB-DP-02**	**Digital PCS Junction Box**	**Field**	**M32**	**PCS-001**	**PCS Cabinet**	**C/R**	**M32**	**300/500**	**XLPE**	**24 Cr#1.5mm^2 / OS / FL / DIGITAL**	**29.1**	**134**	**24CR-DI-FL-DR1**	

INSTRUMENT CABLE SCHEDULE

PROJECT : DED JASA PEMBANGUNAN FASILITAS PRODUKSI STASIUN PENGUMPUL (SP) TANJUNG MIRING BARAT & KARANGAN TIMUR
OWNER : PT. PERTAMINA HULU ROKAN
LOCATION : LAPANGAN TANJUNG MIRING BARAT DAN KARANGAN TIMUR
DOC. NO : TMBP-SP001-IN-SCH-D101
REVISION : A

No	CABLE NO.	FROM				TO				VOLTAGE GRADE	CABLE TYPE	DESCRIPTION	O.D (mm)	LENGTH (m)	DRUM NO.	REMARKS
		Tag No.	DESCRIPTION	LOCATION	GLAND SIZE	Tag No.	DESCRIPTION	LOCATION	GLAND SIZE							
130	ZSO-V008-001	ZSO-V008-001	OPEN POSITION SWITCH	Field	1/2"	JB-DP-03	Digital PCS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FL / SWA / DIGITAL	11.0	33	2CR-DI-FL-DR1	FUEL GAS SYSTEM
131	ZSC-V008-001	ZSC-V008-001	CLOSE POSITION SWITCH	Field	1/2"	JB-DP-03	Digital PCS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FL / SWA / DIGITAL	11.0	33	2CR-DI-FL-DR1	FUEL GAS SYSTEM
132	ZSO-V008-002	ZSO-V008-002	OPEN POSITION SWITCH	Field	1/2"	JB-DP-03	Digital PCS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FL / SWA / DIGITAL	11.0	33	2CR-DI-FL-DR1	FUEL GAS SYSTEM
133	ZSC-V008-002	ZSC-V008-002	CLOSE POSITION SWITCH	Field	1/2"	JB-DP-03	Digital PCS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FL / SWA / DIGITAL	11.0	33	2CR-DI-FL-DR1	FUEL GAS SYSTEM
134	ZSO-Z002-002	ZSO-Z002-002	OPEN POSITION SWITCH	Field	1/2"	JB-DP-03	Digital PCS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FL / SWA / DIGITAL	11.0	33	2CR-DI-FL-DR1	FUEL GAS SYSTEM
135	ZSC-Z002-002	ZSC-Z002-002	CLOSE POSITION SWITCH	Field	1/2"	JB-DP-03	Digital PCS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FL / SWA / DIGITAL	11.0	33	2CR-DI-FL-DR1	FUEL GAS SYSTEM
136	ZSO-Z002-001	ZSO-Z002-001	OPEN POSITION SWITCH	Field	1/2"	JB-DP-03	Digital PCS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FL / SWA / DIGITAL	11.0	33	2CR-DI-FL-DR1	FUEL GAS SYSTEM
137	ZSC-Z002-001	ZSC-Z002-001	CLOSE POSITION SWITCH	Field	1/2"	JB-DP-03	Digital PCS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FL / SWA / DIGITAL	11.0	33	2CR-DI-FL-DR1	FUEL GAS SYSTEM
138	**JBDP-03-01**	**JB-DP-03**	**Digital PCS Junction Box**	**Field**	**M32**	**PCS-001**	**PCS Cabinet**	**C/R**	**M32**	**300/500**	**XLPE**	**24 Cr#1.5mm^2 / OS / FL / DIGITAL**	**29.1**	**134**	**24CR-DI-FL-DR1**	
139	LCP-Z005-01	LCP-Z-005	IAS PACKAGE (AIR DYER PANEL)	Field	M20	PCS-001	PCS Cabinet	C/R	M20	300/500	RS485	4 Pr#0.15mm^2 / FL / SWA / ANALOG	18.40	158	4PR-485-FL-DR1	
140	LCP-Z006-01	LCP-Z-006	IAS PACKAGE (AIR COMPRESSOR PANEL)	Field	M20	PCS-001	PCS Cabinet	C/R	M20	300/500	RS485	4 Pr#0.15mm^2 / FL / SWA / ANALOG	18.40	161	4PR-485-FL-DR1	
141																
142	LCP-GEG001-01	LCP-GEG-01	GAS ENGINE GENERATOR	Field	M20	PCS-001	PCS Cabinet	C/R	M20	300/500	RS485	4 Pr#0.15mm^2 / FL / SWA / ANALOG	18.40	152	4PR-485-FL-DR1	
143	LCP-GEG002-02	LCP-GEG-02	GAS ENGINE GENERATOR	Field	M20	PCS-001	PCS Cabinet	C/R	M20	300/500	RS485	4 Pr#0.15mm^2 / FL / SWA / ANALOG	18.40	145	4PR-485-FL-DR1	
144	LCP-DEG001-01	LCP-DEG-01	DIESEL ENGINE GENERATOR	Field	M20	PCS-001	PCS Cabinet	C/R	M20	300/500	RS485	4 Pr#0.15mm^2 / FL / SWA / ANALOG	18.40	130	4PR-485-FL-DR1	
145	PCS-001-01	PCS-001	PCS CABINET	C/R	M20	ESS-001	ESS Cabinet	C/R	M20	300/500	RS485	4 Pr#0.15mm^2 / FL / SWA / ANALOG	18.40	30	4PR-485-FL-DR1	
146	P-008A-C1	P-008A	DEEP WELL PUMP	Field	M25	PCS-001	PCS Cabinet	C/R	M25	300/500	XLPE	12 Cr#1.5mm^2 / OS / FL / DIGITAL	20.2	142	12CR-DI-FL-DR1	
147	P-008B-C1	P-008B	DEEP WELL PUMP	Field	M25	PCS-001	PCS Cabinet	C/R	M25	300/500	XLPE	12 Cr#1.5mm^2 / OS / FL / DIGITAL	20.2	140	12CR-DI-FL-DR1	
148	MCC-P001A-C1	P-001A	Gross Transfer Pump	E/R (MCC)	M25	PCS-001	PCS Cabinet	C/R	M25	300/500	XLPE	12 Cr#1.5mm^2 / OS / FL / DIGITAL	20.2	28	12CR-DI-FL-DR2	
149	MCC-P001B-C1	P-001B	Gross Transfer Pump	E/R (MCC)	M25	PCS-001	PCS Cabinet	C/R	M25	300/500	XLPE	12 Cr#1.5mm^2 / OS / FL / DIGITAL	20.2	28	12CR-DI-FL-DR2	
150	MCC-P002A-C1	P-002A	Test Pump TMB	E/R (MCC)	M25	PCS-001	PCS Cabinet	C/R	M25	300/500	XLPE	12 Cr#1.5mm^2 / OS / FL / DIGITAL	20.2	28	12CR-DI-FL-DR2	
151	MCC-P003A-C1	P-003A	Test Pump KRG	E/R (MCC)	M25	PCS-001	PCS Cabinet	C/R	M25	300/500	XLPE	12 Cr#1.5mm^2 / OS / FL / DIGITAL	20.2	28	12CR-DI-FL-DR2	
152	MCC-P003B-C1	P-003B	Test Pump KRG	E/R (MCC)	M25	PCS-001	PCS Cabinet	C/R	M25	300/500	XLPE	12 Cr#1.5mm^2 / OS / FL / DIGITAL	20.2	28	12CR-DI-FL-DR2	
153	MCC-P006A-C1	P-006A	K.O Drum Pump	E/R (MCC)	M25	PCS-001	PCS Cabinet	C/R	M25	300/500	XLPE	12 Cr#1.5mm^2 / OS / FL / DIGITAL	20.2	28	12CR-DI-FL-DR2	
154	MCC-P006B-C1	P-006B	K.O Drum Pump	E/R (MCC)	M25	PCS-001	PCS Cabinet	C/R	M25	300/500	XLPE	12 Cr#1.5mm^2 / OS / FL / DIGITAL	20.2	28	12CR-DI-FL-DR2	
155	MCC-P007A-C1	P-007A	Closed Drain Pump	E/R (MCC)	M25	PCS-001	PCS Cabinet	C/R	M25	300/500	XLPE	12 Cr#1.5mm^2 / OS / FL / DIGITAL	20.2	28	12CR-DI-FL-DR2	
156	MCC-P007B-C1	P-007B	Closed Drain Pump	E/R (MCC)	M25	PCS-001	PCS Cabinet	C/R	M25	300/500	XLPE	12 Cr#1.5mm^2 / OS / FL / DIGITAL	20.2	28	12CR-DI-FL-DR2	
157	MCC-P019-C1	P-019	Water Sump Pit Pump	E/R (MCC)	M25	PCS-001	PCS Cabinet	C/R	M25	300/500	XLPE	12 Cr#1.5mm^2 / OS / FL / DIGITAL	20.2	28	12CR-DI-FL-DR2	
158	MCC-P017A-C1	P-017A	Water Distribution Pump	E/R (MCC)	M25	PCS-001	PCS Cabinet	C/R	M25	300/500	XLPE	12 Cr#1.5mm^2 / OS / FL / DIGITAL	20.2	28	12CR-DI-FL-DR2	
159	MCC-P017B-C1	P-017B	Water Distribution Pump	E/R (MCC)	M25	PCS-001	PCS Cabinet	C/R	M25	300/500	XLPE	12 Cr#1.5mm^2 / OS / FL / DIGITAL	20.2	28	12CR-DI-FL-DR2	
160	LIT-V001-001	LIT-V001-001	LEVEL TRANSMITTER	Field	1/2"	JB-AE-01	Analog ESD Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS-OS / FR / SWA / ANALOG	13.5	45	1PR-AN-FR-DR1	
161	PIT-V001-001	PIT-V001-001	PRESSURE TRANSMITTER	Field	1/2"	JB-AE-01	Analog ESD Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS-OS / FR / SWA / ANALOG	13.5	45	1PR-AN-FR-DR1	
162	PIT-V003-001	PIT-V003-001	PRESSURE TRANSMITTER	Field	1/2"	JB-AE-01	Analog ESD Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS-OS / FR / SWA / ANALOG	13.5	34	1PR-AN-FR-DR1	
163	LIT-V003-001	LIT-V003-001	LEVEL TRANSMITTER	Field	1/2"	JB-AE-01	Analog ESD Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS-OS / FR / SWA / ANALOG	13.5	34	1PR-AN-FR-DR1	
164	PIT-V002-001	PIT-V002-001	PRESSURE TRANSMITTER	Field	1/2"	JB-AE-01	Analog ESD Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS-OS / FR / SWA / ANALOG	13.5	41	1PR-AN-FR-DR1	
165	LIT-V002-001	LIT-V002-001	LEVEL TRANSMITTER	Field	1/2"	JB-AE-01	Analog ESD Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS-OS / FR / SWA / ANALOG	13.5	41	1PR-AN-FR-DR1	
166	PIT-V004-001	PIT-V004-001	PRESSURE TRANSMITTER	Field	1/2"	JB-AE-01	Analog ESD Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS-OS / FR / SWA / ANALOG	13.5	30	1PR-AN-FR-DR1	
167	LIT-V004-001	LIT-V004-001	LEVEL TRANSMITTER	Field	1/2"	JB-AE-01	Analog ESD Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS-OS / FR / SWA / ANALOG	13.5	30	1PR-AN-FR-DR1	
168	LIT-V005-001	LIT-V005-001	LEVEL TRANSMITTER	Field	1/2"	JB-AE-01	Analog ESD Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS-OS / FR / SWA / ANALOG	13.5	16	1PR-AN-FR-DR1	
169	**JBAE-01-01**	**JB-AE-01**	**Analog ESD Junction Box**	**Field**	**M32**	**ESS-001**	**ESS Cabinet**	**C/R**	**M32**	**300/500**	**XLPE**	**12 Pr#1.5mm^2 / IS-OS / FR / SWA / ANALOG**	**36.5**	**130**	**12PR-AN-FR-DR1**	
170	LIT-T003-002	LIT-T003-002	LEVEL TRANSMITTER	Field	1/2"	JB-AE-02	Analog ESD Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS-OS / FR / SWA / ANALOG	13.5	67	1PR-AN-FR-DR1	
171	LIT-T004-002	LIT-T004-002	LEVEL TRANSMITTER	Field	1/2"	JB-AE-02	Analog ESD Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS-OS / FR / SWA / ANALOG	13.5	65	1PR-AN-FR-DR1	
172	PIT-P002-001A	PIT-P002-001A	PRESSURE TRANSMITTER	Field	1/2"	JB-AE-02	Analog ESD Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS-OS / FR / SWA / ANALOG	13.5	42	1PR-AN-FR-DR1	
173	PIT-P002-002A	PIT-P002-002A	PRESSURE TRANSMITTER	Field	1/2"	JB-AE-02	Analog ESD Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS-OS / FR / SWA / ANALOG	13.5	42	1PR-AN-FR-DR1	
174	PIT-P003-001B	PIT-P003-001B	PRESSURE TRANSMITTER	Field	1/2"	JB-AE-02	Analog ESD Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS-OS / FR / SWA / ANALOG	13.5	46	1PR-AN-FR-DR1	
175	PIT-P003-002B	PIT-P003-002B	PRESSURE TRANSMITTER	Field	1/2"	JB-AE-02	Analog ESD Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS-OS / FR / SWA / ANALOG	13.5	46	1PR-AN-FR-DR1	
176	PIT-P003-001A	PIT-P003-001A	PRESSURE TRANSMITTER	Field	1/2"	JB-AE-02	Analog ESD Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS-OS / FR / SWA / ANALOG	13.5	51	1PR-AN-FR-DR1	
177	PIT-P003-002A	PIT-P003-002A	PRESSURE TRANSMITTER	Field	1/2"	JB-AE-02	Analog ESD Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS-OS / FR / SWA / ANALOG	13.5	51	1PR-AN-FR-DR1	
178	LIT-V008-002	LIT-V008-002	LEVEL TRANSMITTER	Field	1/2"	JB-AE-02	Analog ESD Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS-OS / FR / SWA / ANALOG	13.5	114	1PR-AN-FR-DR1	
179	LIT-PN002-001	LIT-PN002-001	LEVEL TRANSMITTER	Field	1/2"	JB-AE-02	Analog ESD Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS-OS / FR / SWA / ANALOG	13.5	105	1PR-AN-FR-DR2	
180	**JBAE-02-01**	**JB-AE-02**	**Analog ESD Junction Box**	**Field**	**M32**	**ESS-001**	**ESS Cabinet**	**C/R**	**M32**	**300/500**	**XLPE**	**12 Pr#1.5mm^2 / IS-OS / FR / SWA / ANALOG**	**36.5**	**51**	**12PR-AN-FR-DR1**	
181	LIT-T005-001A	LIT-T005-001A	LEVEL TRANSMITTER	Field	1/2"	JB-AE-03	Analog ESD Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS-OS / FR / SWA / ANALOG	13.5	74	1PR-AN-FR-DR2	
182	LIT-T005-001B	LIT-T005-001B	LEVEL TRANSMITTER	Field	1/2"	JB-AE-03	Analog ESD Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS-OS / FR / SWA / ANALOG	13.5	74	1PR-AN-FR-DR2	
183	LIT-T006-001A	LIT-T006-001A	LEVEL TRANSMITTER	Field	1/2"	JB-AE-03	Analog ESD Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS-OS / FR / SWA / ANALOG	13.5	48	1PR-AN-FR-DR2	
184	LIT-T006-001B	LIT-T006-001B	LEVEL TRANSMITTER	Field	1/2"	JB-AE-03	Analog ESD Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS-OS / FR / SWA / ANALOG	13.5	26	1PR-AN-FR-DR2	
185	PIT-P001-001A	PIT-P001-001A	PRESSURE TRANSMITTER	Field	1/2"	JB-AE-03	Analog ESD Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS-OS / FR / SWA / ANALOG	13.5	36	1PR-AN-FR-DR2	
186	PIT-P001-002A	PIT-P001-002A	PRESSURE TRANSMITTER	Field	1/2"	JB-AE-03	Analog ESD Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS-OS / FR / SWA / ANALOG	13.5	36	1PR-AN-FR-DR2	
187	PIT-P001-001B	PIT-P001-001B	PRESSURE TRANSMITTER	Field	1/2"	JB-AE-03	Analog ESD Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS-OS / FR / SWA / ANALOG	13.5	30	1PR-AN-FR-DR2	
188	PIT-P001-002B	PIT-P001-002B	PRESSURE TRANSMITTER	Field	1/2"	JB-AE-03	Analog ESD Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / IS-OS / FR / SWA / ANALOG	13.5	30	1PR-AN-FR-DR2	
189	**JBAE-03-01**	**JB-AE-03**	**Analog ESD Junction Box**	**Field**	**M32**	**ESS-001**	**ESS Cabinet**	**C/R**	**M32**	**300/500**	**XLPE**	**12 Pr#1.5mm^2 / IS-OS / FR / SWA / ANALOG**	**36.5**	**155**	**12PR-AN-FR-DR1**	
190	SDY-V001-001	SDY-V001-001	SOLENOID VALVE	Field	1/2"	JB-DE-01	Digital ESD Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FR / SWA / DIGITAL	13.5	49	2CR-DI-FR-DR1	
191	SDY-V001-002	SDY-V001-002	SOLENOID VALVE	Field	1/2"	JB-DE-01	Digital ESD Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FR / SWA / DIGITAL	13.5	40	2CR-DI-FR-DR1	

INSTRUMENT CABLE SCHEDULE

PROJECT : DED JASA PEMBANGUNAN FASILITAS PRODUKSI STASIUN PENGUMPUL (SP) TANJUNG MIRING BARAT & KARANGAN TIMUR
OWNER : PT. PERTAMINA HULU ROKAN
LOCATION : LAPANGAN TANJUNG MIRING BARAT DAN KARANGAN TIMUR
DOC. NO : TMBP-SP001-IN-SCH-D101
REVISION : A

No	CABLE NO.	FROM				TO				VOLTAGE GRADE	CABLE TYPE	DESCRIPTION	O.D (mm)	LENGTH (m)	DRUM NO.	REMARKS
		Tag No.	DESCRIPTION	LOCATION	GLAND SIZE	Tag No.	DESCRIPTION	LOCATION	GLAND SIZE							
192	SDY-V002-001	SDY-V002-001	SOLENOID VALVE	Field	1/2"	JB-DE-01	Digital ESD Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FR / SWA / DIGITAL	13.5	44	2CR-DI-FR-DR1	
193	SDY-V002-002	SDY-V002-002	SOLENOID VALVE	Field	1/2"	JB-DE-01	Digital ESD Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FR / SWA / DIGITAL	13.5	33	2CR-DI-FR-DR1	
194	SDY-V003-001	SDY-V003-001	SOLENOID VALVE	Field	1/2"	JB-DE-01	Digital ESD Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FR / SWA / DIGITAL	13.5	34	2CR-DI-FR-DR1	
195	SDY-V003-002	SDY-V003-002	SOLENOID VALVE	Field	1/2"	JB-DE-01	Digital ESD Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FR / SWA / DIGITAL	13.5	31	2CR-DI-FR-DR1	
196	SDY-V004-001	SDY-V004-001	SOLENOID VALVE	Field	1/2"	JB-DE-01	Digital ESD Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FR / SWA / DIGITAL	13.5	30	2CR-DI-FR-DR1	
197	SDY-V004-002	SDY-V004-002	SOLENOID VALVE	Field	1/2"	JB-DE-01	Digital ESD Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FR / SWA / DIGITAL	13.5	28	2CR-DI-FR-DR1	
198	SDY-V005-001	SDY-V005-001	SOLENOID VALVE	Field	1/2"	JB-DE-01	Digital ESD Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FR / SWA / DIGITAL	13.5	25	2CR-DI-FR-DR1	
199	SDY-V005-002	SDY-V005-002	SOLENOID VALVE	Field	1/2"	JB-DE-01	Digital ESD Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FR / SWA / DIGITAL	13.5	15	2CR-DI-FR-DR1	
200	BDY-V005-001	BDY-V005-001	SOLENOID VALVE	Field	1/2"	JB-DE-01	Digital ESD Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FR / SWA / DIGITAL	13.5	12	2CR-DI-FR-DR1	
201	**JBDE-01-01**	**JB-DE-01**	**Digital ESD Junction Box**	**Field**	**M32**	**ESS-001**	**ESS Cabinet**	**C/R**	**M32**	**300/500**	**XLPE**	**40 Cr#1.5mm^2 / OS / FR / SWA / DIGITAL**	**29.1**	**134**	**40CR-DI-FR-DR1**	
202	SDY-V008-001	SDY-V008-001	SOLENOID VALVE	Field	1/2"	JB-DE-02	Digital ESD Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FR / SWA / DIGITAL	13.5	33	2CR-DI-FR-DR1	FUEL GAS SYSTEM
203	SDY-V008-002	SDY-V008-002	SOLENOID VALVE	Field	1/2"	JB-DE-02	Digital ESD Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FR / SWA / DIGITAL	13.5	33	2CR-DI-FR-DR1	FUEL GAS SYSTEM
204	SDY-Z002-002	SDY-Z002-002	SOLENOID VALVE	Field	1/2"	JB-DE-02	Digital ESD Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FR / SWA / DIGITAL	13.5	33	2CR-DI-FR-DR1	FUEL GAS SYSTEM
205	SDY-Z002-001	SDY-Z002-001	SOLENOID VALVE	Field	1/2"	JB-DE-02	Digital ESD Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FR / SWA / DIGITAL	13.5	33	2CR-DI-FR-DR1	FUEL GAS SYSTEM
206	**JBDE-02-01**	**JB-DE-02**	**Digital ESD Junction Box**	**Field**	**M32**	**ESS-001**	**ESS Cabinet**	**C/R**	**M32**	**300/500**	**XLPE**	**24 Cr#1.5mm^2 / OS / FR / SWA / DIGITAL**	**22.3**	**114**	**24CR-DI-FR-DR1**	
207	MCC-P001A-C2	P-001A	Gross Transfer Pump	E/R (MCC)	1/2"	ESS-001	ESS Cabinet	C/R	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FR / SWA / DIGITAL	13.1	27	2CR-DI-FR-DR1	
208	MCC-P001B-C2	P-001B	Gross Transfer Pump	E/R (MCC)	1/2"	ESS-001	ESS Cabinet	C/R	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FR / SWA / DIGITAL	13.1	27	2CR-DI-FR-DR1	
209	MCC-P002A-C2	P-002A	Test Pump TMB	E/R (MCC)	1/2"	ESS-001	ESS Cabinet	C/R	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FR / SWA / DIGITAL	13.1	27	2CR-DI-FR-DR1	
210	MCC-P003A-C2	P-003A	Test Pump KRG	E/R (MCC)	1/2"	ESS-001	ESS Cabinet	C/R	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FR / SWA / DIGITAL	13.1	27	2CR-DI-FR-DR1	
211	MCC-P003B-C2	P-003B	Test Pump KRG	E/R (MCC)	1/2"	ESS-001	ESS Cabinet	C/R	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FR / SWA / DIGITAL	13.1	27	2CR-DI-FR-DR1	
212	MCC-P006A-C2	P-006A	K.O Drum Pump	E/R (MCC)	1/2"	ESS-001	ESS Cabinet	C/R	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FR / SWA / DIGITAL	13.1	27	2CR-DI-FR-DR1	
213	MCC-P006B-C2	P-006B	K.O Drum Pump	E/R (MCC)	1/2"	ESS-001	ESS Cabinet	C/R	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FR / SWA / DIGITAL	13.1	27	2CR-DI-FR-DR1	
214	MCC-P007A-C2	P-007A	Closed Drain Pump	E/R (MCC)	1/2"	ESS-001	ESS Cabinet	C/R	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FR / SWA / DIGITAL	13.1	27	2CR-DI-FR-DR1	
215	MCC-P007B-C2	P-007B	Closed Drain Pump	E/R (MCC)	1/2"	ESS-001	ESS Cabinet	C/R	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FR / SWA / DIGITAL	13.1	27	2CR-DI-FR-DR1	
216	MCC-P016A-C1	P-016A	Booster Pump	E/R (MCC)	1/2"	ESS-001	ESS Cabinet	C/R	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FR / SWA / DIGITAL	13.1	27	2CR-DI-FR-DR1	
217	MCC-P016B-C1	P-016B	Booster Pump	E/R (MCC)	1/2"	ESS-001	ESS Cabinet	C/R	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FR / SWA / DIGITAL	13.1	27	2CR-DI-FR-DR1	
218	GD-011	GD-011	GAS DETECTOR	Field	M20	JB-AF-01	Analog FGS Junction Box	Field	M20	300/500	XLPE	1 Tr#1.5mm^2 / IS / FR / SWA / ANALOG	16.0	97	1TR-AN-FR-DR1	
219	GD-012	GD-012	GAS DETECTOR	Field	M20	JB-AF-01	Analog FGS Junction Box	Field	M20	300/500	XLPE	1 Tr#1.5mm^2 / IS / FR / SWA / ANALOG	16.0	107	1TR-AN-FR-DR1	
220	GD-013	GD-013	GAS DETECTOR	Field	M20	JB-AF-01	Analog FGS Junction Box	Field	M20	300/500	XLPE	1 Tr#1.5mm^2 / IS / FR / SWA / ANALOG	16.0	26	1TR-AN-FR-DR1	
221	GD-014	GD-014	GAS DETECTOR	Field	M20	JB-AF-01	Analog FGS Junction Box	Field	M20	300/500	XLPE	1 Tr#1.5mm^2 / IS / FR / SWA / ANALOG	16.0	36	1TR-AN-FR-DR1	
222	GD-015	GD-015	GAS DETECTOR	Field	M20	JB-AF-01	Analog FGS Junction Box	Field	M20	300/500	XLPE	1 Tr#1.5mm^2 / IS / FR / SWA / ANALOG	16.0	48	1TR-AN-FR-DR1	
223	GD-016	GD-016	GAS DETECTOR	Field	M20	JB-AF-01	Analog FGS Junction Box	Field	M20	300/500	XLPE	1 Tr#1.5mm^2 / IS / FR / SWA / ANALOG	16.0	74	1TR-AN-FR-DR1	
224	GD-017	GD-017	GAS DETECTOR	Field	M20	JB-AF-01	Analog FGS Junction Box	Field	M20	300/500	XLPE	1 Tr#1.5mm^2 / IS / FR / SWA / ANALOG	16.0	73	1TR-AN-FR-DR1	
225	FD-005	FD-005	FLAME DETECTOR	Field	M20	JB-AF-01	Analog FGS Junction Box	Field	M20	300/500	XLPE	1 Tr#1.5mm^2 / IS / FR / SWA / ANALOG	16.0	25	1TR-AN-FR-DR1	
226	**JBAF-01-01**	**JB-AF-01**	**Analog FGS Junction Box**	**Field**	**M32**	**ESS-001**	**ESS Cabinet**	**C/R**	**M32**	**300/500**	**XLPE**	**12 Tr#1.5mm^2 / IS-OS / FR / SWA / ANALOG**	**41.0**	**155**	**12TR-AN-FR-DR1**	
227	GD-001	GD-001	GAS DETECTOR	Field	M20	JB-AF-02	Analog FGS Junction Box	Field	M20	300/500	XLPE	1 Tr#1.5mm^2 / IS / FR / SWA / ANALOG	16.0		1TR-AN-FR-DR1	
228	GD-002	GD-002	GAS DETECTOR	Field	M20	JB-AF-02	Analog FGS Junction Box	Field	M20	300/500	XLPE	1 Tr#1.5mm^2 / IS / FR / SWA / ANALOG	16.0		1TR-AN-FR-DR1	
229	GD-003	GD-003	GAS DETECTOR	Field	M20	JB-AF-02	Analog FGS Junction Box	Field	M20	300/500	XLPE	1 Tr#1.5mm^2 / IS / FR / SWA / ANALOG	16.0		1TR-AN-FR-DR1	
230	GD-004	GD-004	GAS DETECTOR	Field	M20	JB-AF-02	Analog FGS Junction Box	Field	M20	300/500	XLPE	1 Tr#1.5mm^2 / IS / FR / SWA / ANALOG	16.0		1TR-AN-FR-DR1	
231	GD-005	GD-005	GAS DETECTOR	Field	M20	JB-AF-02	Analog FGS Junction Box	Field	M20	300/500	XLPE	1 Tr#1.5mm^2 / IS / FR / SWA / ANALOG	16.0		1TR-AN-FR-DR1	
232	GD-006	GD-006	GAS DETECTOR	Field	M20	JB-AF-02	Analog FGS Junction Box	Field	M20	300/500	XLPE	1 Tr#1.5mm^2 / IS / FR / SWA / ANALOG	16.0		1TR-AN-FR-DR2	
233	FD-001	FD-001	FLAME DETECTOR	Field	M20	JB-AF-02	Analog FGS Junction Box	Field	M20	300/500	XLPE	1 Tr#1.5mm^2 / IS / FR / SWA / ANALOG	16.0		1TR-AN-FR-DR2	
234	FD-002	FD-002	FLAME DETECTOR	Field	M20	JB-AF-02	Analog FGS Junction Box	Field	M20	300/500	XLPE	1 Tr#1.5mm^2 / IS / FR / SWA / ANALOG	16.0		1TR-AN-FR-DR2	
235	**JBAF-02-01**	**JB-AF-02**	**Analog FGS Junction Box**	**Field**	**M32**	**ESS-001**	**ESS Cabinet**	**C/R**	**M32**	**300/500**	**XLPE**	**12 Tr#1.5mm^2 / IS-OS / FR / SWA / ANALOG**	**41.0**	**51**	**12TR-AN-FR-DR1**	
236	GD-007	GD-007	GAS DETECTOR	Field	M20	JB-AF-03	Analog FGS Junction Box	Field	M20	300/500	XLPE	1 Tr#1.5mm^2 / IS / FR / SWA / ANALOG	16.0	42	1TR-AN-FR-DR2	
237	GD-010	GD-010	GAS DETECTOR	Field	M20	JB-AF-03	Analog FGS Junction Box	Field	M20	300/500	XLPE	1 Tr#1.5mm^2 / IS / FR / SWA / ANALOG	16.0	152	1TR-AN-FR-DR2	
238	GD-018	GD-018	GAS DETECTOR	Field	M20	JB-AF-03	Analog FGS Junction Box	Field	M20	300/500	XLPE	1 Tr#1.5mm^2 / IS / FR / SWA / ANALOG	16.0	145	1TR-AN-FR-DR2	
239	FD-003	FD-003	FLAME DETECTOR	Field	M20	JB-AF-03	Analog FGS Junction Box	Field	M20	300/500	XLPE	1 Tr#1.5mm^2 / IS / FR / SWA / ANALOG	16.0	92	1TR-AN-FR-DR2	
240	FD-004	FD-004	FLAME DETECTOR	Field	M20	JB-AF-03	Analog FGS Junction Box	Field	M20	300/500	XLPE	1 Tr#1.5mm^2 / IS / FR / SWA / ANALOG	16.0	75	1TR-AN-FR-DR2	
241	FD-006	FD-006	FLAME DETECTOR	Field	M20	JB-AF-03	Analog FGS Junction Box	Field	M20	300/500	XLPE	1 Tr#1.5mm^2 / IS / FR / SWA / ANALOG	16.0	70	1TR-AN-FR-DR2	
242	**JBAF-03-01**	**JB-AF-03**	**Analog FGS Junction Box**	**Field**	**M32**	**ESS-001**	**ESS Cabinet**	**C/R**	**M32**	**300/500**	**XLPE**	**12 Tr#1.5mm^2 / IS-OS / FR / ANALOG**	**41.0**	**51**	**12TR-AN-FR-DR1**	
243	LHD-005	LHD-005	LINE HEAT DETECTOR	Field	M20	JB-AF-04	Analog FGS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / OS / FR / SWA / ANALOG	13.1	26	1PR-AN-FR-DR2	
244	LHD-006	LHD-006	LINE HEAT DETECTOR	Field	M20	JB-AF-04	Analog FGS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / OS / FR / SWA / ANALOG	13.1	48	1PR-AN-FR-DR2	
245	LHD-007	LHD-007	LINE HEAT DETECTOR	Field	M20	JB-AF-04	Analog FGS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / OS / FR / SWA / ANALOG	13.1	74	1PR-AN-FR-DR2	
246	LHD-008	LHD-008	LINE HEAT DETECTOR	Field	M20	JB-AF-04	Analog FGS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / OS / FR / SWA / ANALOG	13.1	74	1PR-AN-FR-DR2	
247	**JBAF-04-01**	**JB-AF-04**	**Analog FGS Junction Box**	**Field**	**M32**	**ESS-001**	**ESS Cabinet**	**C/R**	**M32**	**300/500**	**XLPE**	**12 Cr#1.5mm^2 / OS / FR / SWA / ANALOG**	**16.5**	**155**	**12CR-DI-FR-DR1**	
248	LHD-001	LHD-001	LINE HEAT DETECTOR	Field	M20	JB-AF-05	Analog FGS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / OS / FR / SWA / ANALOG	13.1	67	1PR-AN-FR-DR3	
249	LHD-002	LHD-002	LINE HEAT DETECTOR	Field	M20	JB-AF-05	Analog FGS Junction Box	Field	M20	300/500	XLPE	1 Pr#1.5mm^2 / OS / FR / SWA / ANALOG	13.1	65	1PR-AN-FR-DR3	
250	**JBAF-05-01**	**JB-AF-05**	**Analog FGS Junction Box**	**Field**	**M32**	**ESS-001**	**ESS Cabinet**	**C/R**	**M32**	**300/500**	**XLPE**	**12 Cr#1.5mm^2 / OS / FR / SWA / ANALOG**	**16.5**	**51**	**12CR-DI-FR-DR1**	
251	MAC-001	MAC-001	MANUAL ALARM CALL POINT	Field	M20	JB-DF-01	Digital FGS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FR / SWA / ANALOG	13.1	107	2CR-DI-FR-DR2	
252	MAC-002	MAC-002	MANUAL ALARM CALL POINT	Field	M20	JB-DF-01	Digital FGS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FR / SWA / ANALOG	13.1	40	2CR-DI-FR-DR2	

INSTRUMENT CABLE SCHEDULE

PROJECT : DED JASA PEMBANGUNAN FASILITAS PRODUKSI STASIUN PENGUMPUL (SP) TANJUNG MIRING BARAT & KARANGAN TIMUR
OWNER : PT. PERTAMINA HULU ROKAN
LOCATION : LAPANGAN TANJUNG MIRING BARAT DAN KARANGAN TIMUR
DOC. NO : TMBP-SP001-IN-SCH-D101
REVISION : A

No	CABLE NO.	FROM				TO				VOLTAGE GRADE	CABLE TYPE	DESCRIPTION	O.D (mm)	LENGTH (m)	DRUM NO.	REMARKS
		Tag No.	DESCRIPTION	LOCATION	GLAND SIZE	Tag No.	DESCRIPTION	LOCATION	GLAND SIZE							
253	MAC-003	MAC-003	MANUAL ALARM CALL POINT	Field	M20	JB-DF-01	Digital FGS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FR / SWA / ANALOG	13.1	131	2CR-DI-FR-DR2	
254	HRN-001	HRN-001	HORN / SOUNDER	Field	M20	JB-DF-01	Digital FGS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FR / SWA / ANALOG	13.1	107	2CR-DI-FR-DR2	
255	HRN-002	HRN-002	HORN / SOUNDER	Field	M20	JB-DF-01	Digital FGS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FR / SWA / ANALOG	13.1	40	2CR-DI-FR-DR2	
256	HRN-003	HRN-003	HORN / SOUNDER	Field	M20	JB-DF-01	Digital FGS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FR / SWA / ANALOG	13.1	131	2CR-DI-FR-DR2	
257	BCN-001	BCN-001	BEACON / STROBE LIGHT	Field	M20	JB-DF-01	Digital FGS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FR / SWA / ANALOG	13.1	107	2CR-DI-FR-DR2	
258	BCN-002	BCN-002	BEACON / STROBE LIGHT	Field	M20	JB-DF-01	Digital FGS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FR / SWA / ANALOG	13.1	40	2CR-DI-FR-DR2	
259	BCN-003	BCN-003	BEACON / STROBE LIGHT	Field	M20	JB-DF-01	Digital FGS Junction Box	Field	M20	300/500	XLPE	2 Cr#1.5mm^2 / OS / FR / SWA / ANALOG	13.1	131	2CR-DI-FR-DR2	
260	**JBDF-01-01**	**JB-DF-01**	**Digital FGS Junction Box**	**Field**	**M32**	**ESS-001**	**ESS Cabinet**	**C/R**	**M32**	**300/500**	**XLPE**	**24 Cr#1.5mm^2 / OS / FR / SWA / DIGITAL**	**22.3**	**102**	**24CR-DI-FR-DR1**	
261	**LCP-X000-01**	**LCP-X-000**	**LCP Foam Panel**	**Field**	**M32**	**ESS-001**	**ESS Cabinet**	**C/R**	**M32**	**300/500**	**XLPE**	**24 Cr#1.5mm^2 / OS / FR / SWA / DIGITAL**	**22.3**	**75**	**24CR-DI-FR-DR1**	
262	**LCP-X000-02**	**LCP-X-000**	**LCP Foam Panel**	**Field**	**M32**	**ESS-001**	**ESS Cabinet**	**C/R**	**M32**	**300/500**	**XLPE**	**24 Cr#1.5mm^2 / OS / FR / SWA / DIGITAL**	**22.3**	**75**	**24CR-DI-FR-DR1**	
263	**FACP-000-01**	**FACP-X-000**	**Fire Alarm Control Panel**	**C/R**	**M20**	**ESS-001**	**ESS Cabinet**	**C/R**	**M20**	**300/500**	**RS485**	**4 Pr#0.51mm^2 / FL / SWA / ANALOG**	**18.4**	**35**	**4PR-485-FL-DR1**	
264	**FACP-000-02**	**FACP-X-000**	**Fire Alarm Control Panel**	**C/R**	**M40**	**ESS-001**	**ESS Cabinet**	**C/R**	**M40**	**300/500**	**XLPE**	**40 Cr#1.5mm^2 / OS / FR / SWA / DIGITAL**	**34.4**	**35**	**40CR-DI-FR-DR1**	