EN

SPECIFICATIONS:

Number of keys: 68(Hot-swappable Mechanical Switch)
Numbers of Multifunction Keys: 16
Materials: Aluminum Alloy Body, PBT+ABS Keycaps
Interface: Type-C
Mode: Wired/Bluetooth/2.4G
Bluetooth Name: Flow2-68@Lofree
Dimensions: 341.2X107X21.5mm

Diagram:



① Battery Indicator
Charging:Indicator on breathing white
Charged:Indicator always on white
Battery<20%:Indicator on breathing red
Battery<5%:Indicator flashing till off
② Type-C Interface
Wired/Charging port
③ Side Touch Switch
Volume Control:
Slide up to increase volume, slide down to decrease.
Screen Brightness:
Hold the fn key — slide up to brighten, slide down to dim.
To enable or disable the touch function:
Press and hold (Fn + Space) for 3 seconds.
④ Caps Lock Indicator(White)/Status Indicator(Blue)
· Caps Lock Indicator(White)
Indicator white light enabled: Caps lock on
Indicator white light disabled: Caps lock off
· Bluetooth/2.4G Pairing Indicator(Blue)
During Bluetooth/2.4G pairing, Indicator blinks slowly for 1 min, after successfully paired, Indicator keeps on for 3s.
During device switching, Indicator flashes for 3s, after successfully paired, Indicator keeps on for 3s.
· Bluetooth reconnection
During Bluetooth reconnection, the indicator keeps blinking. After reconnection, the indicator keeps on for 3 seconds, and then recovers to the previous state.
⑤ Mode Switch
✕:OFF/ Wired Mode/ Wireless Mode

Detailed Operation

Wired Connection:

❶ Toggle the mode switch to

❷ Connect the keyboard to the device with attached Type C cable to complete the wired connection mode.

Bluetooth Connection:

❶ Toggle the mode switch to

❷ Long Press fn+Q/fn+W/fn+E until indicator blinks slowly on Blue.

❸ Find and pair "Flow2-68@Lofree" on your list of paired devices.

❹ Status Indicator:
Indicator keeps on for 3s and turns off.



❺ fn+Q/fn+W/fn+E = Switch Bluetooth Device



2.4GWireless Mode:

❶ Toggle the mode switch to

❷ Insert the 2.4G receiver into the USB port of the device.

❸ Press fn+R for 1 second to enter 2.4G mode.

❹ Status Indicator(Blue light):
Indicator flashes quickly, after successful connection, the indicator keeps on for 3s and turns off.

Note: MAC/IOS system devices do not support multimedia functions under 2.4G & USB connection.

❺ If 2.4G connection fails, hold fn+R for 3s until the indicator shows slow blue flashing. Replug the receiver, successful pairing is confirmed when the blue light stays solid for 3s before turning off.

Use of Ambient Light:

fn + ←/→ : Steady/Breathe/Off

System Switch

fn + N — fn+N is to trigger the corresponding system function key of windows/Android

fn + M — fn+M is to trigger the corresponding system function key of Mac/IOS

Restore Factory Settings

fn + shift + ←

Press and hold (Fn + Left Shift + Backspace) for 3 seconds. The power indicator will flash red 3 times, indicating the reset was successful.

Function Key Switch

The top row number keys default to number input, and can be switched to function keys by pressing Fn + Tab.

Multifunction Keys

fn + 1……del = Multimedia Key

	Mac	Windows
fn+1	Screen BR -	
fn+2	Screen BR +	
fn+3	Multi-Screen	
fn+4	Search	
fn+5	Backlit -	
fn+6	Backlit +	
fn+7	Prev Song	
fn+8	Play/Pause	
fn+9	Next Song	
fn+0	Mute	
fn+-	VOL-	
fn+=	VOL+	
fn+ctrl	/	Menu
fn+del	/	Lock
fn+home	Page up	
fn+end	Page down	

Using VIA

1.Please contact customer support to request the configuration file.
2.Visit the official VIA website:https://usevia.app/
3.Connect your device and upload the file to start. If needed, basic VIA usage instructions are available from support.

Note: VIA only supports wired connections.

NAME AND CONTENT OF HAZARDOUS SUBSTANCES IN PRODUCT:

Harmful Elements	Hazardous substances					
	Lead (Pb)	Mercury (Hg)	Cadmium (Cd)	Hexavalent Chromium (Cr6+)	Polybrominated Biphenyls (PBB)	Polybrominated Diphenyl Ethers (PBDE)
Plastic Components	O	O	O	O	O	O
Circuit Board Assembly	O	O	O	O	O	O
Silicone Components	O	O	O	O	O	O
Spare Parts	O	O	O	O	O	O

This table is prepared in accordance with the provisions of SJ/T 11364.
The classification and marking of this product was performed in accordance with the EU directive 2011/65/EU and the revised directive 2015/863/EU.
O:Indicates that the said hazardous substance contained in all the homogeneous materials for this component is below the limit requirement in GB/T 26572.
X:Indicates that this hazardous substance contained in at least one of the homogeneous materials used for this part is above the limit requirement in GB/T 26572.

ENVIRONMENTAL PROTECTION INSTRUCTIONS:

The hazardous substances contained in the electronic parts of this product will not leak or change under normal use conditions fora period often years. During the same period, the electronic components of this product with not cause serious environmental pollution or serious damage to human health or property whilt the products are being used by the consumer.
According to the Chinese electronic industry standard SJ/T 11364-2014 and retated Chinese government regulations, this product and some of its internal or external components may have an environmentally-friendly use period mark, depending on the component and component manufacturer; the mark lifespan on the product and its components may vary. The expiration date on the component takes precedence over any conflicted or different UFUP labels on the product.

Warning:

- If the battery is not replaced properly, there may be leakage or explosion and personal injury hazards.
- Do not use the battery when there is leakage, discoloration, deformation, or any other abnormality.
- Do not leave the battery in a discharged or unused state for a long time.
- Do not short-circuit the product
- Battery life varies with usage. Used batteries should be disposed of in accordance with local laws or thrown away in trash cans for recycling electronic devices.
- If any liquid accidentally enters the product, please immediately disconnect the power supply and remove the product. Continue to use the product may cause fire or electric shock. Please contact the agent or the nearest customer service center for inspection and maintenance.

FCC Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
-- Reorient or relocate the receiving antenna.
-- Increase the separation between the equipment and receiver.
-- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
-- Consult the dealer or an experienced radio/TV technician for help.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:
(1)This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

FCC Radiation Exposure Statement

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

IC Caution:

· English:
This device complies with Innovation, Science and Economic Development Canada licence-exempt RSS standard(s). Operation is subject to the following two conditions:
(1)This device may not cause interference, and
(2)This device must accept any interference, including interference that may cause undesired operation of the device.
The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.

· French:
Cet appareil est conforme aux normes RSS exemptées de licence d'innovation, sciences et développement économique Canada. L'exploitationestautorisée aux deux conditions suivantes:
(1)l'appareil ne doit pas produire de brouillage, et
(2)l'utilisateur de l'appareildoit accepter tout brouillageradioélectriqueaubi, mêmes le brouillagest susceptible d'encomprometter le fonctionnement.
Le matériel a été évalué pour répondre aux exigences générales d'exposition aux radiofréquences. Le dispositif peut être utilisé dans des conditions d'exposition portables illimitées.