Lay out the parts.

Printed parts

1 base + 1 lid + 1 fit coupon. Print STLs already have bed orientation.

Board retention

4 × M3 × 6 screws; 4 × M3 washers, nominal 0.5 mm thick.

Case retention

4 × M3 × 10 screws from below; 4 adhesive feet, nominal 8 × 2 mm.

Status optics

1 lens, 64 × 32 × 1; reverse black mask; 2 clear Ø3 × 24.6 rods.

OLED module

1 Adafruit 326 QT; 4 × M2 × 6 screws; 4 × M2 washers; 1 four-wire harness.

Power switch

1 C&K D102J12S215HQA candidate; 2 insulated leads with matching quick-connects.

Prepare a ruler, suitable hand screwdriver, M3/M2 taps, crimp tool and multimeter. Try actual hardware on the coupon before printing the whole case.