

5G-NR Waveform Configuration Summary

Generated from `toolbox.signalgen/config_signal_master_5waveforms.m`

Common parameters. All waveforms use $\Delta f = 60$ kHz, $NFFT = 2048$, $Nslots = 4$, oversampling factor $ovs = 4$, final sampling rate $f_{sovs} = 491.52$ MHz, 256-QAM, central subcarrier disabled, per-carrier clipping disabled, BPideal spectrum shaping, and 491520 generated samples.

ID	Carriers	NPRB	Nominal BW	Effective BW	Foff	Occupied span	Passband mask edges	EVM after CFR	NMSE after vs before CFR
1	1	[6]	[5 MHz]	[4.32 MHz]	[0 MHz]	4.32 MHz centered	[-0.008789, 0.008789]	11.3878%	-17.9964 dB
2	1	[6]	[5 MHz]	[4.32 MHz]	[-77.5 MHz]	5 MHz channel at lower 160 MHz edge	[-0.324870, -0.307292]	11.3055%	-18.0518 dB
3	1	[6]	[5 MHz]	[4.32 MHz]	[77.5 MHz]	5 MHz channel at upper 160 MHz edge	[0.307292, 0.324870]	11.3055%	-18.0515 dB
4	2	[24, 24]	[20, 20] MHz	[17.28, 17.28] MHz	[-70, 70] MHz	157.28 MHz edge-to-edge	[-0.320312, -0.25], [0.25, 0.320312]	[10.1533, 10.0848]%	[-23.7395, -23.7395] dB
5	2	[107, 107]	[80, 80] MHz	[77.04, 77.04] MHz	[-40, 40] MHz	157.04 MHz edge-to-edge	[-0.319743, -0.00651], [0.00651, 0.319743]	[7.0156, 6.29893]%	[-29.1362, -29.1362] dB
6	1	[24]	[20 MHz]	[17.28 MHz]	[0 MHz]	17.28 MHz centered	[-0.035156, 0.035156]	6.00781%	-23.3934 dB
7	1	[65]	[50 MHz]	[46.8 MHz]	[0 MHz]	46.8 MHz centered	[-0.095215, 0.095215]	3.99399%	-26.8996 dB
8	1	[135]	[100 MHz]	[97.2 MHz]	[0 MHz]	97.2 MHz centered	[-0.197754, 0.197754]	3.18679%	-28.9795 dB

Notes. The passband mask edges are normalized to Nyquist, i.e. to $f_{sovs}/2 = 245.76$ MHz, matching the format consumed by `spectrumMask` and `clipping_PAPR_ICF`. EVM was measured after CFR using `analiza_medidas_5GNR_v6`. NMSE was computed directly between the CFR output and the pre-CFR waveform, after mean removal and power normalization. Multi-carrier values are reported per carrier.