• Other Settings

```
        Others
  ▣  VGA  ⇕  ⟳  ▭↑

      <Off Timer>
```

All of the icons shown in the ScreenManager "Other" menu are described below.

	Function
Off Timer ``` Others ▣ VGA ⇕ ⟳ ▭↑ ◉Enable 12H ○Disable ```	Automatically Turns off the Monitor **What is Off Timer** The Off Timer function allows the user to set the time in which the monitor will be in operation, called the "On Period" and automatically shifts the operation into the "Power Off" mode when the set "On Period" expires. The Off Timer function was created to reduce after-image characteristics that are particular to LCD monitors when the monitor screen is left on for a long period without use. 1) Select the "Off Timer" icon and press the Enter button to display "Off Timer" select menu. 2) Select "Enable . and press the Enter button. 3) Press the right/left button to adjust how long (1 to 23 hours) the monitor should be in the "On Period". Then, press the enter button to return to the "others" menu. Advance notice (indicator; flashing green) will be given 15 minutes before the monitor will automatically turn off and enter the "Power Off" modes. **To Delay Entering Power Off** To delay entering the "Power Off" mode, press any button on the front panel located to the left of the LED light during the advance notice period. The monitor will continue to operate for an additional 90 minutes. There will be another advance notice for 15 minutes as described. Delayed entrance into the "Power Off" period can be extended as many times as desired. • The Off Timer function will work while PowerManager is active, but there would be no advance notice before the monitor's power switches off.