

Dashen Bank TV Kiosk — Administrator Setup Guide

Version: 2.0

Audience: Branch IT / Field Technicians / Head Office IT

estimated time: 10 minutes per TV/PC

Applies to: Windows 10 / Windows 11 PCs connected to TV via HDMI

1. Purpose

This guide explains how to set up a branch TV/PC so that it:

1. **Auto-logs in** to Windows (no password prompt)
2. **Never sleeps** or turns the screen off
3. **Auto-launches** Google Chrome in fullscreen kiosk mode
4. **Displays** the correct branch's exchange rate dashboard automatically

After setup, the operator only needs to power the PC on. Everything else happens automatically.

2. Prerequisites

#	Requirement	How to check
1	Windows 10 or 11	Settings → System → About
2	Google Chrome installed	Open Chrome — must open
3	PC connected to TV via HDMI	TV shows PC desktop
4	Network / internet access	Open Chrome → visit <code>http://localhost:3000</code>
5	Backend server reachable	Dashboard loads in browser
6	Admin rights on the PC	Required to run the setup script
7	Branch code available	e.g., JIM001, ADD001, 054

Before starting, confirm the following on the target PC:

⚠️ **If any of the above is missing, do not proceed.** Fix the prerequisite first.

🔧 3. Setup Process — Step by Step

Step 3.1 — Open PowerShell as Administrator

Two ways to do this:

Method A — Keyboard shortcut (fastest):

1. Press **Windows key + X** on the keyboard
2. From the menu, select:
 - **Windows PowerShell (Admin)**
 - or **Windows Terminal (Admin)** — on Windows 11
3. If prompted "**Do you want to allow this app to make changes?**" → click **Yes**

Method B — Start menu:

1. Click **Start**
2. Type **PowerShell**
3. Right-click **Windows PowerShell** → **Run as administrator**
4. Click **Yes** on the UAC prompt

✓ **Confirm success:** The window title bar should say "**Administrator: Windows PowerShell**"

Step 3.2 — Navigate to the Project Folder

In the Administrator PowerShell window, type:

```
powershell
cd C:\xampp\htdocs\digitalSigage
```

Press **Enter**.

✓ **Confirm success:** The prompt now shows:

text

PS C:\xampp\htdocs\digitalSigage>

Step 3.3 — Allow Script Execution (One-Time)

Type:

powershell

`Set-ExecutionPolicy Bypass -Scope Process -Force`

Press **Enter**.

This allows the script to run **only in this session** — it doesn't change any permanent policy.

✓ **Confirm success:** No error appears. Prompt returns immediately.

Step 3.4 — Run the Setup Script

Type:

powershell

`.\setup-tv-kiosk.ps1`

Press **Enter**.

The script starts and displays:

text

```
=====
DASHEN BANK TV DASHBOARD - KIOSK SETUP
=====
```

Step 3.5 — Answer the Prompts

The script asks **four** questions. Answer them exactly as follows.

◆ Prompt 1: Branch Code

text

Enter branch code (e.g., JIM001):

Type the **branch code** for this TV, then press **Enter**.

Examples:

- Jimma Main Branch → JIM001
- Addis Bole Branch → ADD001
- Hawassa Branch → HAW001
- Mekelle Branch → MEK001
- Or the numeric code you have assigned → 054

⚠ **Important:** The code must match exactly what is stored in the backend database (`branches.code`).

◆ Prompt 2: Server URL

text

Enter server URL (default: `http://localhost:3000`):

Two options:

Scenario

What to type

Testing on this PC only

Press **Enter** (uses `http://localhost:3000`)

Production (recommended)

Type the server's LAN IP, e.g. `http://192.168.1.100:3000` then press Enter

⚠️ **For 900 branches:** Always use the **head-office server IP** or the **public domain**, e.g. `https://tv.dashenbank.com` — never `localhost`, because each branch's PC is a different machine.

Example for production:

text

Enter server URL (default: `http://localhost:3000`): `http://192.168.1.100:3000`

◆ Prompt 3: Windows Password

text

Enter Windows password for 'SEID':

Type the **Windows login password** of the account that will auto-login.

⚠️ Two key notes:

1. The cursor does **not move** as you type (masked input) — this is normal.
2. If the account has **no password**, press **Enter** without typing anything (not recommended — auto-login may not work).

Press **Enter** after typing.

◆ Prompt 4: Launch Now?

text

Launch the dashboard right now? (y/n):

Answer	Result
y	Chrome opens immediately in kiosk mode with the dashboard
n	Setup completes but does not launch — will auto-launch on next login

For first-time setup: type `y` and press Enter.

Step 3.6 — Verify Success

The script prints:

text

```
=====
      SETUP COMPLETE
=====
```

What was configured:

- Auto-login on boot
- Sleep and screen-off disabled
- Chrome kiosk launches on login

Branch dashboard URL:

`http://192.168.1.100:3000/?branch=JIM001`

If you typed `y` at the last prompt, Chrome now opens **fullscreen** showing the branch dashboard.

□ 4. Post-Setup Verification

Complete these four checks after the script finishes.

✓ **Check 1 — Dashboard is displaying**

The TV should show:

- Dashen Bank logo
- Live exchange rates
- Video panel (if a video is active)
- Scrolling footer ticker
- Branch name in the footer

✓ **Check 2 — Correct branch is shown**

Look at the footer of the TV:

- Should show the branch name you configured (e.g., "Jimma Main Branch")
- ✗ If it shows "**Unknown Branch**" in red → the branch code is wrong or missing in the database

✓ **Check 3 — Chrome is in kiosk mode**

- There is **no** address bar
- There are **no** tabs
- There is **no** close button
- The dashboard fills the entire screen

Press **F11** to test — it should do nothing (already fullscreen).

✓ **Check 4 — Auto-start works**

1. Close Chrome: press **Alt + F4**
2. Restart the PC: **Start** → **Power** → **Restart**
3. **Do not touch anything** — wait 30 seconds

Expected result: The PC boots, logs in, opens Chrome in kiosk mode, and displays the dashboard — with no user interaction.

Symptom	Cause	Fix
"Please run this script as Administrator"	PowerShell not elevated	Close → reopen as Admin (Step 3.1)
"Chrome not found"	Chrome not installed	Install from https://www.google.com/chrome/
Script won't run — "cannot be loaded because running scripts is disabled"	Execution policy	Run Step 3.3 again
Chrome opens but shows "Unknown Branch"	Wrong branch code or missing in DB	Check <code>branches.code</code> in the database
Chrome opens but dashboard is blank	Server not reachable	Test <code>http://SERVER:3000</code> in Chrome first
Auto-login doesn't work after restart	Wrong password or policy	Re-run the script — password may have a typo
Screen still sleeps	Power policy blocked by IT	Contact Head Office IT — may need Group Policy change
Chrome crashes or hangs after days	Long-running browser	Reboot the PC once a week (or schedule a nightly restart)

🔧 5. Troubleshooting

🔄 6. Changing the Branch Code Later

If a TV is moved to a different branch or the branch code changes:

1. Open PowerShell as Administrator
2. Run:

```
powershell
Remove-Item "$env:APPDATA\Microsoft\Windows\Start Menu\Programs\Startup\DashenTVKiosk
.lnk" -Force
Unregister-ScheduledTask -TaskName "DashenTVKiosk" -Confirm:$false
Remove-Item "C:\dashen-tv-kiosk.bat" -Force
```

3. Re-run the setup script:

```
powershell
cd C:\xampp\htdocs\digitalSigage
Set-ExecutionPolicy Bypass -Scope Process -Force
.\setup-tv-kiosk.ps1
```

4. Enter the new branch code at the first prompt.

7. Undoing / Removing Kiosk Mode

If you need to disable auto-launch:

```
powershell
Remove-Item "$env:APPDATA\Microsoft\Windows\Start Menu\Programs\Startup\DashenTVKiosk
.lnk" -Force
Unregister-ScheduledTask -TaskName "DashenTVKiosk" -Confirm:$false
```

This stops the kiosk from launching. Windows will boot to the desktop normally.

#	Task	Done
---	------	------

1	Verify Chrome installed	☐
2	Verify server reachable in browser	☐
3	Open PowerShell as Administrator	☐
4	Run <code>cd C:\xampp\htdocs\digitalSigage</code>	☐
5	Run <code>Set-ExecutionPolicy Bypass -Scope Process -Force</code>	☐
6	Run <code>.\setup-tv-kiosk.ps1</code>	☐
7	Enter branch code	☐
8	Enter server URL (default or IP)	☐
9	Enter Windows password	☐
10	Type <code>y</code> to launch dashboard	☐
11	Confirm correct branch name in footer	☐
12	Restart PC and confirm auto-launch	☐
13	Confirm kiosk mode (no browser bars)	☐
14	Confirm screen does not sleep	☐
15	Log setup in rollout tracker	☐

8. Rollout Checklist — Per Branch

Print this checklist for each TV/PC you configure.

📞 9. Escalation

If setup fails after two attempts, contact:

Level	Contact	When
L3	Seid Mohammed	0985192541

Provide the following when escalating:

- Branch code
- PC name / serial number
- Screenshot of error

- Console output from the PowerShell window
-

10. Appendix — Full Script Reference

Script location: `C:\xampp\htdocs\digitalSigage\setup-tv-kiosk.ps1`

What the script configures:

Component	Where	Purpose
Auto-login	Registry: <code>HKLM\...\Winlogon</code>	Skip Windows password screen
Power policy	<code>powercfg</code>	Disable sleep, hibernate, screen-off
Chrome launcher	<code>C:\dashen-tv-kiosk.bat</code>	Batch file that opens Chrome in kiosk mode
Startup shortcut	<code>%APPDATA%\...\Startup\</code>	Runs the batch on login
Task Scheduler	<code>DashenTVKiosk</code>	More reliable alternative to Startup folder

Chrome flags used in the batch file:

Flag	Purpose
<code>--kiosk</code>	Fullscreen, no browser UI
<code>--noerrdialogs</code>	Hide "restore pages" popups
<code>--disable-infobars</code>	Hide "Chrome is being controlled" banner
<code>--disable-session-crashed-bubble</code>	Hide crash recovery dialog
<code>--incognito</code>	Fresh session each boot