

KAM Label Printing Guide

Version: 1.0

Prepared for: KAM (KORT Asset Management System)

Applies to: Thermal label printing with TSC printers (including TSC 400 Pro)

1. Prerequisites

- Printer installed and visible in Windows Devices & Printers.
- Correct label media loaded (for example, 50 x 25 mm).
- Printer driver installed from TSC official package.
- KAM app updated with thermal-print label sizing changes.

2. Configure Label Settings in KAM

Go to: Settings > Labels and Barcode.

Set Label Size to your media size (50x25, 60x40, or 80x50).

Set Print Margin (mm) according to your printer calibration (usually 1 to 2 mm).

Enable or disable Barcode and QR as needed.

Save changes.

3. Configure TSC 400 Pro in Windows

Open: Control Panel > Devices and Printers > TSC 400 Pro > Printing Preferences.

Set page/stock size exactly equal to your KAM label size.

Set orientation (portrait/landscape) to match label feed direction.

Set margins to minimum allowed by driver.

Disable scaling options in driver if available.

Run printer calibration from driver utility if labels shift.

4. Print Labels from KAM

Open an asset and click Print Label, or use bulk label printing.

In browser print dialog:

- Select printer: TSC 400 Pro
- Scale: 100% (Actual Size)
- Margins: None or Minimum
- Headers/Footers: Off
- Background graphics: Off (unless required)

Print a single test label first, then run bulk prints.

5. Server Commands After Deployment

Run these from the Laravel directory that contains the artisan file:

```
php artisan optimize:clear
```

```
php artisan view:cache
```

```
php artisan config:cache
```

```
php artisan route:cache
```

```
php artisan queue:restart
```

If route:cache fails because of Closure routes, use: `php artisan route:clear`

6. Quick Troubleshooting

Issue: Could not open input file: artisan

Fix: cd into the correct Laravel directory, then run artisan commands.

Issue: Label prints too large/small

Fix: Ensure both Windows printer media size and KAM Label Size match exactly.

Issue: Content is cut off

Fix: Lower Print Margin in KAM or recalibrate printer media sensor.

Issue: Misalignment between labels

Fix: Run gap/calibration from TSC utility; verify label pitch and gap settings.

7. Recommended Baseline for 50 x 25 mm

KAM Label Size: 50x25

KAM Print Margin: 1 mm or 2 mm

Windows Driver Paper Size: 50 x 25 mm

Browser Scale: 100%

Print test: 1 label before bulk jobs