Comptia A+

TROUBLESHOOTING AND HELPDESK

DAY4

TASKS:1

Open your desktop or laptop, locate the RAM slots, and remove and re-insert the RAM module to simulate reseating — then document each step you took and any issues you observed during the process.

RESULT

- Shut down the computer.
- Disconnect the power cable and remove the battery (if using a laptop with a removable battery).
- Press the power button for a few seconds to discharge any remaining power.
- Open the computer case or laptop back cover.
- Locate the **RAM slots** on the motherboard.
- Push the clips on both sides of the RAM module to release it.
- Carefully remove the RAM module.
- Check for dust or dirt and clean gently if necessary.
- Reinsert the RAM module firmly into the slot until both clips lock automatically.
- Close the computer case.
- Reconnect the power and start the computer.
- Verify that the system boots normally.

Comptia A+

TASKS:2

.Create a troubleshooting checklist for diagnosing a faulty GPU in a gaming PC, including at least 5 steps from initial symptom identification to confirming the fix. Think about display issues, driver checks, and physical connections.

RESULT

Step	Action
1	Check if the monitor displays a blank screen, artifacts, or "No Signal."
2	Verify that the monitor cable is securely connected to the graphics card.
3	Remove and firmly reinsert the GPU into the PCIe slot.
4	Check that all GPU power connectors are properly connected.
5	Update or reinstall the graphics driver.
6	Test the GPU in another PC or test another GPU in the same PC.
7	Confirm that the display works correctly after the fix.

TASKS:3

Simulate a storage issue by unplugging and replugging a SATA or NVMe drive (SSD/HDD) on a test system, then describe the error messages or BIOS indicators you see before and after reconnecting.

Comptia A+

RESULT

PROCEDURE:-

1. Turn off the computer.
2. Disconnect the power cable.
3. Open the computer case.
4. Disconnect the SATA cable from the HDD/SSD (or remove the NVMe SSD).
5. Turn on the computer.

BEFORE RECONNECTING:-

1. **No Boot Device Found**
2. **Operating System Not Found**
3. **Boot Device Not Detected**
4. Storage drive not listed in BIOS
5. Turn off the computer again.
6. Reconnect the SATA cable or reinstall the NVMe SSD.
7. Restart the computer.

AFTER RECONNECTING:-

- The BIOS detects the SSD/HDD.
- The operating system starts normally.

Comptia A+

TASKS:4

Given a scenario where a PC randomly restarts, list which component (RAM, GPU, storage) you would check first and explain your reasoning, then outline the specific diagnostic steps you would perform for that component.

RESULT

First I check RAM because RAM is one of the most common causes of random restarts. A loose or faulty RAM module can lead to system crashes, restart loops, or blue screen errors.

STEPS TO RESOLVE PROBLEM:-

1. Turn off the computer and disconnect the power.
2. Open the computer case.
3. Remove the RAM module.
4. Check for dust or damage.
5. Reinsert the RAM securely.
6. If there are multiple RAM modules, test one module at a time.
7. Restart the computer and observe whether the restart issue is resolved.