```
#include <WiFi.h>
#include <HTTPClient.h>
#include <Wire.h>
#include <DHT.h>
#include <OneWire.h>
#include <DallasTemperature.h>
#include <BH1750.h>

#define DHTPIN 4
#define DHTTYPE DHT11
#define ONE_WIRE_BUS 14
#define RAIN_PIN 34

const char* ssid = "IOT1";
const char* password = "IOT12345";
const char* serverURL =
"https://script.google.com/macros/s/AKfycbxKVfprJHJ899bCz8U4aUK9Rrq0UcKzhkeqjS5iQMwowC4S
E8cBL6jZoIXXxQGaPQMPww/exec";  // e.g., https://script.google.com/macros/s/xxx/exec

DHT dht(DHTPIN, DHTTYPE);
OneWire oneWire(ONE_WIRE_BUS);
DallasTemperature ds18b20(&oneWire);
BH1750 lightMeter;

void setup() {
  Serial.begin(115200);

  WiFi.begin(ssid, password);
  Serial.print("Connecting to WiFi");
  while (WiFi.status() != WL_CONNECTED) {
    delay(500);
    Serial.print(".");
```

```
  }
  Serial.println("\nConnected.");

  dht.begin();
  ds18b20.begin();
  Wire.begin(21, 22);
  lightMeter.begin(BH1750::CONTINUOUS_HIGH_RES_MODE);
}

void loop() {
  float humidity = dht.readHumidity();
  ds18b20.requestTemperatures();
  float temperature = ds18b20.getTempCByIndex(0);
  int rainRaw = analogRead(RAIN_PIN);
  float rain = map(rainRaw, 4095, 0, 0, 100);
  float lux = lightMeter.readLightLevel();

  if (WiFi.status() == WL_CONNECTED) {
    HTTPClient http;
    http.begin(serverURL);
    http.addHeader("Content-Type", "application/json");

    String json = "{\"humidity\":" + String(humidity, 2) +
                  ",\"temperature\":" + String(temperature, 2) +
                  ",\"rain\":" + String(rain, 2) +
                  ",\"lux\":" + String(lux, 2) + "}";

    int httpResponseCode = http.POST(json);
    Serial.print("HTTP Response code: ");
    Serial.println(httpResponseCode);
    http.end();
```

```
  } else {
    Serial.println("WiFi not connected");
  }

  delay(15000); // 30 seconds
}
```