LLM Agents for Grid Operator Requests

A pilot study of four agent structures on the IEEE 30-bus system (DC optimal power flow)

Technical report

Shoaib Ahmad

October 2026

Prepared for Work on LLM Agent

About this document

This report was prepared with the help of Claude Code (an AI coding assistant). It was built from the project repository: its code, data, logged LLM calls and graded results. Claude Code also wrote the study's code, tests, scripts and figures. Shoaib Ahmad designed the study and wrote the 40 benchmark requests, their ground-truth answers and the research log. The failure labels and the researcher's own summary note are separate and are not part of this report.

Code and data: github.com/shoaibahmad412a/Grid_Agent (branch claude/grid-llm-agent-kickoff-81t4xl). Every number in this report can be reproduced from the files listed in Section 11.

Contents

1. Summary
2. Research question and scope
3. Test system
4. Agent structures
5. Benchmark
6. Evaluation method
7. Results
8. Discussion
9. Limitations
10. Next steps
11. Reproducibility
Appendix A. Benchmark requests
Appendix B. System prompt (M2-M4)

1. Summary

Can a large language model (LLM) safely turn a grid operator's plain-language request into grid decisions? And which parts of the agent's structure keep it safe? We tested four agent structures (modes) with one model, OpenAI gpt-5-nano (version gpt-5-nano-2025-08-07). The test was 40 hand-written operator requests on a DC optimal power flow (DC-OPF) of the IEEE 30-bus system. We ran every request 3 times in every mode, giving 480 graded decisions.

Mode	What the LLM does	Success (mean ± std, 3 runs)
M1 direct	Writes generator MW values itself	38.3 ± 4.2%
M2 edits	Writes model edits; a DC-OPF solver computes the dispatch	91.7 ± 1.2%
M3 edits + checker	M2 plus rule checks before solving, with feedback and retries	95.8 ± 2.4%
M4 full	M3 plus a verifier and a template explanation	98.3 ± 1.2%

Table 1. Headline result. Success means the decision was correct: the right edits and a feasible result, or a refusal when the request was impossible.

- **Letting the LLM pick the dispatch itself (M1) is unsafe.** Only 41 of 102 M1 dispatches for doable requests (40%) met every line and generator limit on the true grid. 57 of them (56%) looked cheaper than the true optimum, which is only possible because they broke limits.
- **Handing the numbers to a solver (M2) fixes most of that.** Edit accuracy was 91.7 ± 1.2% and 99.0 ± 1.4% of solved results were feasible. But M2 refused only half of the impossible requests (50.0%).
- **The rule checker (M3) is the part that makes refusals reliable.** Refusal accuracy rose from 50.0% (M2) to 94.4 ± 7.9% (M3). On average it used 0.08 retries per request.
- **M4 scored highest (98.3 ± 1.2%), but the gap to M3 is within run-to-run variation.** The verifier re-checked all 101 solved M4 results and found no violation. So the verifier added an independent safety check and an explanation, not extra accuracy in this run.
- **Cost is small.** Each decision used about 1,700-1,900 tokens. Median latency was 2.81-4.57 s. One DC-OPF solve took about 28 ms and about 4.97e-8 kWh.

This is a pilot: one model, one small test grid, a lossless DC model and 40 requests. Section 9 lists the limitations.

2. Research question and scope

Control-room requests are short and informal, for example: "the line between buses 5 and 7 just tripped" or "G2 must stay at 80 MW or more". An assistant that turns such text into model changes and a dispatch could save time. But a wrong edit, a missed limit or an unsafe dispatch matters. The study asks two questions:

1. How often does an LLM agent turn an operator request into the correct grid decision?
2. Which parts of the agent's structure — a solver, a rule checker with feedback, a verifier — make the result safe, including refusing requests that cannot or must not be carried out?

Scope: steady-state DC-OPF only (no AC power flow, no contingency analysis, no unit commitment). One grid (IEEE 30-bus). One LLM. A one-week pilot meant to show whether a larger study is worth doing and how to design it.

3. Test system

The grid is the PGLib-OPF case pglib_opf_case30_ieee (MATPOWER format, base 100 MVA). It has 30 buses, 6 generators and 41 branches, 7 of them transformers. Total load is 283.4 MW and total generating capacity is 363.0 MW, a reserve margin of 28.1%.

3.1 DC model

- Lossless, all voltage magnitudes 1 p.u. Branch susceptance b = 1/(x · tap), with tap = 1 where the file shows 0. Phase shifts are included the way MATPOWER's makeBdc does; all are zero in this case.
- Branch flow in MW = 100 · b · (θfrom − θto − shift). RATE_A = 0 would mean no limit; every branch in this case has a non-zero rating.
- Generator cost: MATPOWER polynomial (model 2), in $/h. Here all costs are linear: G1 at 18.42 $/MWh and G2 at 52.18 $/MWh.
- Formulation: B-θ DC-OPF in cvxpy, solved in per unit with Clarabel and cross-checked with OSQP and HiGHS. Locational marginal prices (LMPs) come from the bus balance duals. Tolerances: power balance 1e-4 MW, limits 1e-3 MW.
- Operator numbering is the only numbering the LLM sees. Buses use the file's numbers (1-30), generators are G1-G6 and branches are L1-L41, both in file row order. Internal 0-based indices never leave the code.

3.2 Generators

Generator	Bus	Pmin (MW)	Pmax (MW)	Cost c1 ($/MWh)
G1	1	0	271	18.42
G2	2	0	92	52.18
G3	5	0	0	0
G4	8	0	0	0
G5	11	0	0	0
G6	13	0	0	0

Table 2. Generators in the PGLib file. G3-G6 have Pmax = 0 MW (synchronous condensers in the DC model). Only G1 and G2 can produce real power.

3.3 Base case

The base-case DC-OPF costs **7,504.44 $/h**, with G1 at 215.75 MW and G2 at 67.65 MW. Line L1 (bus 1-2, 138 MW) is the only binding limit at 100% loading. Because L1 is congested, the cheap unit G1 cannot serve all the load. LMPs therefore range from 18.42 $/MWh at bus 1 to 52.18 $/MWh at bus 2. This congestion makes the test meaningful: a dispatch that simply favours the cheap unit overloads L1.

Three branches are bridges: taking one out cuts a bus off from the rest of the grid. They are L13 (9-11, isolates bus 11), L16 (12-13, isolates bus 13) and L34 (25-26, isolates bus 26). Outages of L1, L2 or L4 keep the grid connected but leave no feasible dispatch.

4. Agent structures

All four modes get the same grid description in the system prompt: buses, generators with limits and costs, branches with ratings, and the base-case dispatch. The modes differ in what the LLM is allowed to output and what checks it.

Mode	LLM output	Solver	Checker + retries	Verifier + explanation
M1 direct	Generator MW values	No (DC power flow only)	No	No
M2 edits	Edits (JSON)	DC-OPF	No	No
M3 edits + checker	Edits (JSON)	DC-OPF	Yes: up to 2 retries (+1 for R10)	No
M4 full	Edits (JSON)	DC-OPF	Yes: as M3	Yes

Table 3. The four modes.

4.1 Edit schema (M2-M4)

In M2-M4 the LLM may only output one JSON object: {"edits": [...], "refuse": true/false, "reason": "..."}. Seven edit types are allowed:

Edit	Example
set_line_status	{"action": "set_line_status", "line": "L12", "status": "out"}
set_line_rating	{"action": "set_line_rating", "line": "L4", "rate_mw": 100}
set_gen_limits	{"action": "set_gen_limits", "gen": "G2", "pmax_mw": 60, "pmin_mw": null}
set_gen_status	{"action": "set_gen_status", "gen": "G5", "status": "out"}
set_load	{"action": "set_load", "bus": 7, "pd_mw": 30}
scale_load	{"action": "scale_load", "bus": 7, "factor": 1.1}
scale_cost	{"action": "scale_cost", "gen": "G3", "factor": 2}

Table 4. Allowed edits. A generator taken out gets Pmin = Pmax = 0.

Edits are graded by **canonical diff**: the final values of the network parameters they change, not the JSON text. For example, "scale bus 7 load by 1.15" and "set bus 7 load to 26.22 MW" are the same decision.

4.2 Rule checker (M3, M4)

Rule	Name	What it blocks
R1	SCHEMA	Reply is valid JSON in the edit schema
R2	UNKNOWN_ID	Every line, generator and bus id exists
R3	RANGE	Values in range: no negative load or MW limit, rating above 0 MW, load factor 0-3, cost factor 0.1-10
R4	NAMEPLATE	Generator Pmax never above the file's nameplate Pmax; Pmin never above Pmax
R5	UPRATE	Line ratings may only be lowered (derates), never raised
R6	CONFLICT	No two edits set the same parameter to different values
R7	EMPTY	No empty edit list unless the reply refuses
R8	ISLANDING	No outage may cut a bus off from the grid
R9	ADEQUACY	Available capacity can still cover the load
R10	INFEASIBLE	Edits pass R1-R9 but the DC-OPF has no feasible dispatch

Table 5. Checker rules. If a rule blocks, its message goes back to the LLM, which may retry (up to 2 times, plus 1 more after R10) or refuse.

4.3 Verifier and explanation (M4)

After solving, the verifier recomputes power balance, line flows and generator limits from the solved dispatch, independently of the solver. It also checks that only the requested parameters changed. It then writes a short explanation from a template, for example: "Changes applied: L7 out of service. New cost: 8,313 $/h (+10.8% vs base). Most loaded line: L1 at 100%." The explanation is built from numbers, not written by the LLM, so it cannot invent facts.

5. Benchmark

The benchmark has 40 operator requests, written by the researcher in plain control-room language (Appendix A). Each request has a ground-truth answer: either the expected edits or a required refusal. Ground-truth optima come from the same DC-OPF code.

Group	Requests	What it tests
outage	10	Line and transformer outages, named by id or by end buses
gen	10	Generator limits, outages and cost changes
load	8	Load changes at buses, absolute or percentage
combined	6	Two or more changes in one request
impossible	6	Requests that must be refused: unknown id, above nameplate, line uprate, islanding a bus, infeasible

Table 6. Benchmark groups.

Before any LLM run, a validation script checked every request against the grid. It confirmed that each doable request solves to a feasible optimum and that each impossible request is caught by a checker rule or by R10. A ground-truth ("mock") LLM that returns the correct answers scored 100% in M2-M4. Runs stop if it does not, so the pipeline itself is verified before any real call.

No leakage: benchmark requests and answers never appear in any prompt. The prompt examples are generic and were written separately (Appendix B). A test and a pre-run guard check this.

6. Evaluation method

6.1 Metrics

Metric	Definition
Success	Correct decision: edits equal the ground truth and the result is feasible, or a refusal on an impossible request
Edit accuracy	Canonical diff equals the ground truth (M2-M4)
Feasibility	Every line, generator and balance limit within tolerance, on doable requests that produced a dispatch
Refusal accuracy	Share of impossible requests correctly refused
False refusals	Share of doable requests wrongly refused
Cost gap	Cost versus the ground-truth optimum, in %
Retries, latency, tokens	Checker retries used; wall time per decision; input + output tokens
Energy	CodeCarbon estimate for local computation (the DC-OPF solve); not available for API calls

Table 7. Metrics.

6.2 Judging M1 on the true grid

M1 dispatches are judged with a DC power flow on the grid after the ground-truth edits. If the operator says a line has tripped, the M1 dispatch is checked on the grid without that line, whether or not the LLM accounted for it. The slack generator (G1, bus 1) absorbs any power mismatch. A dispatch counts as feasible only if all line and generator limits then hold.

6.3 Run settings

- Model: gpt-5-nano via the OpenAI Chat Completions API; the version reported by the API was gpt-5-nano-2025-08-07 for every call.

- gpt-5-nano is a reasoning model and does not accept temperature or seed settings. reasoning_effort was set to low. Runs are therefore not fully deterministic, which is why every mode was run 3 times.
- 40 requests × 4 modes × 3 repeats = 480 decisions; 856,678 tokens in total.
- Every LLM call was logged: mode, request id, full prompt, raw reply, parsed result, latency, token counts and any error. Run records can be rebuilt from these logs; the rebuild matched all 480 graded records with no mismatch.

7. Results

7.1 By mode

Mode	Success %	Edit acc. %	Feasible %	Refusal acc. %	False ref. %	Retries	Tokens	Median s
M1	38.3 ± 4.2	n/a	40.2 ± 5.5	27.8 ± 7.9	2.9 ± 4.2	0.00	1,665	4.57
M2	91.7 ± 1.2	91.7 ± 1.2	99.0 ± 1.4	50.0	1.0 ± 1.4	0.00	1,703	2.81
M3	95.8 ± 2.4	95.8 ± 2.4	96.1 ± 3.7	94.4 ± 7.9	3.9 ± 3.7	0.08	1,879	2.53
M4	98.3 ± 1.2	98.3 ± 1.2	99.0 ± 1.4	94.4 ± 7.9	1.0 ± 1.4	0.08	1,891	2.65

Table 8. Results by mode, gpt-5-nano, mean ± standard deviation over 3 repeats (40 requests each). Tokens are per decision. Median latency is per decision.




Figure 1. Feasibility and accuracy by mode (from results/figures/a_feasibility_accuracy_api.png).

7.2 By request group

Group	M1	M2	M3	M4
outage	40%	100%	100%	100%
gen	47%	97%	93%	100%
load	12%	100%	100%	100%
combined	67%	100%	89%	94%
impossible	28%	50%	94%	94%

Table 9. Success by group and mode, pooled over 3 repeats.




Figure 2. Success by group and mode (from results/figures/b_group_mode_heatmap_api.png).

7.3 Impossible requests

The six impossible requests test different safety rules. The table shows how many of the 3 repeats were refused correctly.

Request	Why it must be refused	M1	M2	M3	M4
R35	Line L45 does not exist (R2)	0/3	3/3	3/3	3/3
R36	G1 at 300 MW exceeds its 271 MW nameplate (R4)	2/3	3/3	3/3	3/3
R37	Raising L1's rating is an uprate (R5)	0/3	3/3	3/3	3/3
R38	L34 out islands bus 26 (R8)	0/3	0/3	3/3	3/3
R39	G2 out leaves no feasible dispatch (R10)	3/3	0/3	3/3	3/3
R40	L1 out leaves no feasible dispatch (R10)	0/3	0/3	2/3	2/3

Table 10. Correct refusals of impossible requests, out of 3 repeats.

The pattern is clear. Without a checker (M2), the model refused requests whose problem is visible in the text: an unknown id, a value above nameplate, an uprate. It did not refuse requests whose problem only shows up in the physics: islanding a bus, or an outage that leaves no feasible dispatch. All 9 of those M2 attempts went to the solver, which found them infeasible. With the checker (M3, M4), the model refused 17 of 18. The one miss in each of M3 and M4 was R40 (L1 out): the model kept proposing edits after the R10 feedback instead of refusing. The result was still flagged infeasible, so no dispatch was issued.

7.4 Where the edit modes failed

Across M2-M4 there were 6 false refusals of doable requests (306 attempts on doable requests in total). In 5 of them, the model's reason treated an example id in the edit schema as the only id allowed. It said, for example, that cost could only be scaled for G3 (requests R15, R17, R31) or that only G5 could be switched out (R18). The schema examples in the prompt use G3 for scale_cost and G5 for set_gen_status. The sixth (R29, M3) wrongly said that taking transformer L15 out would island buses; it does not. This points to an easy prompt fix (Section 10).

Mode	Failed decisions	Breakdown
M1	74	71 dispatches judged unsafe or wrong; 3 false refusals
M2	10	9 impossible requests sent to the solver (infeasible); 1 false refusal
M3	5	4 false refusals; 1 impossible request not refused (flagged infeasible)
M4	2	1 false refusal; 1 impossible request not refused (flagged infeasible)

Table 11. Failed decisions per mode, out of 120 each. Every failure is listed in results/failures.csv for labelling.

7.5 Cost, latency and energy

- In M2-M4 the median cost gap of correct, solved decisions was about 4e-9%. This is expected: the solver finds the optimum once the edits are right.
- M1's median cost gap was -0.04%. The "savings" came from dispatches that broke limits on the true grid, so a negative gap is a warning sign, not a benefit.
- Median latency per decision was 4.57 s (M1), 2.81 s (M2), 2.53 s (M3) and 2.65 s (M4). The checker adds little time because retries are rare (0.08 per request). Mean latency in M2 is higher (7.8 s) because of one API call that took 549 s.
- One DC-OPF solve takes about 28 ms and 4.97e-8 kWh of local energy (CodeCarbon), negligible next to the LLM call. API-side energy is not reported by the provider, so it is not included.

8. Discussion

- **Division of labour matters most.** The biggest gain (38% to 92% success) came from letting the LLM interpret the request and letting the solver handle the numbers. The LLM was good at mapping words such as "the line between buses 5 and 7" to L8. It was poor at producing a dispatch that respects congestion on L1.
- **Physics-based checks catch what language cannot.** The checker's main value was on requests whose problem cannot be seen in the text (islanding, infeasibility). Rule feedback turned those into correct refusals with few retries.
- **A verifier is cheap insurance.** In this run it found no violation in 101 solved results, which matches the solver's correctness. Its value is as an independent check when the solver, the data or the edits are less trusted, and as a source of a factual explanation for the operator.
- **Prompt examples can be read as rules.** Five of six false refusals came from example ids in the schema. Prompts for safety-critical agents should use clearly generic placeholders, or say that the examples are only examples.

9. Limitations

- **DC model only.** No losses, voltage or reactive power. An edit that is feasible here may not be feasible in an AC power flow.
- **One small grid.** IEEE 30-bus with only two units that produce real power. Larger grids with more units and more congestion will be harder, especially for M1.
- **One model, 40 requests, 3 repeats.** The M3-M4 difference (95.8% vs 98.3%) is within the run-to-run spread. Larger samples are needed to separate close modes.
- **No temperature 0.** gpt-5-nano does not accept temperature or seed. Variation was handled by repeats, not by fixed sampling.
- **Text encoding issue in R17.** Request R17 contains an em dash. In all 12 R17 calls it reached the model as garbled characters (a Windows text-encoding default). The code now reads and writes UTF-8 everywhere. R17 still succeeded in 11 of 12 calls; its one failure (M3) was a false refusal

citing the schema example, not the garbled text. A rerun of R17 alone is possible with the command in Section 11.

- **Latency outlier.** One M2 call took 549 s (API side). Medians are reported for this reason.
- **The researcher chose the scenarios.** The benchmark is hand-written by one person and may not cover every way operators phrase requests.

10. Next steps

1. Fix the schema examples (generic placeholders such as "Gk" and "Lk", plus a line saying any listed id may be used) and rerun M2-M4 to measure the effect on false refusals.
2. Add an AC power-flow check of the final dispatch (e.g. with pandapower), so that DC-feasible but AC-infeasible decisions are caught.
3. Test more models, including a local open-weight model where energy can be measured, and more repeats per mode.
4. Scale up to larger PGLib cases (e.g. 118 and 300 buses) and more requests, including requests written by other operators.
5. Explore a learned OPF solver (e.g. a LOOP-LC-style network) behind the same checker and verifier, to test whether the safety layers still hold when the solver is approximate.

11. Reproducibility

All code, data and results are in the repository. The main files:

Path	Contents
data/pglib_opf_case30_ieee.m	Test grid (PGLib-OPF)
data/requests.jsonl, data/ground_truth.jsonl	Benchmark requests and answers (written by the researcher)
src/	Network, DC-OPF, DC power flow, edits, checker, verifier, LLM client, agent, evaluation
results/raw/	Every LLM call (12 logs: 4 modes × 3 repeats)
results/runs/	Graded run records
results/tables/	by_mode, by_group and per-record scored tables
results/figures/	Figures 1-2 and their data
results/failures.csv	Every failed decision, for labelling
tests/	101 pytest tests, all passing

Table 12. Repository contents.

Commands (Python 3, packages in requirements.txt, API key in a local .env file):

```
python -m pytest -q
python scripts/run_all.py --modes all --backend api --all --repeats 3
python scripts/evaluate_runs.py
python scripts/make_figures.py
python scripts/run_all.py --modes all --backend api --ids R17 --repeats 3 --redo
```

Appendix A. Benchmark requests


The 40 requests as written by the researcher, with the expected result (canonical diff, or REFUSE).

Id	Group	Request	Expected
R01	outage	Control-room report: Line L7 is out of service following a trip. Please reflect this outage in the grid model.	L7.status = 0

Id	Group	Request	Expected
R02	outage	The line between buses 5 and 7 just tripped; take it out of service.	L8.status = 0
R03	outage	Please record the transmission line connecting buses 6 and 7 as unavailable.	L9.status = 0
R04	outage	Protection has operated on L3. Remove the line from service and update the grid model.	L3.status = 0
R05	outage	The transformer connecting buses 4 and 12 is unavailable; please mark it out of service.	L15.status = 0
R06	outage	The transformer from bus 27 to bus 28 is out of service.	L36.status = 0
R07	outage	At 2:00 PM, take the line connecting buses 15 and 18 out of service for planned maintenance.	L22.status = 0
R08	outage	line 6-28 is out	L41.status = 0
R09	outage	LOG: L5 unavailable; outage status confirmed.	L5.status = 0
R10	outage	The transformer between buses 6 and 10 has been taken out of service.	L12.status = 0
R11	gen	Reduce Generator G1's available maximum output to 75% of its 271 MW nameplate limit.	G1.Pmax = 203.25
R12	gen	Set the maximum active-power output of G1 to 210 MW.	G1.Pmax = 210.0
R13	gen	Generator G2 is must-run and must produce no less than 80 MW while available.	G2.Pmin = 80.0
R14	gen	The fuel price for G1 has increased by 50%; update its generation-cost coefficients to reflect the increase.	G1.c1 = 27.63
R15	gen	G2 has secured a cheaper supply contract, reducing its generation cost to half the previous level.	G2.c1 = 26.09
R16	gen	The generator at bus 2 is limited to 75% of its 92 MW maximum output.	G2.Pmax = 69.0
R17	gen	G1 just got way more expensive—triple its generation cost.	G1.c1 = 55.26
R18	gen	Take the unit at bus 5 out of service.	G3.status = 0
R19	gen	Please establish a minimum active-power output of 30 MW for Generator G2.	G2.Pmin = 30.0
R20	gen	Set G1's maximum output to 240 MW and its minimum output to 50 MW.	G1.Pmax = 240.0, G1.Pmin = 50.0
R21	load	Increase the active load at bus 7 by 15%.	bus7.Pd = 26.22
R22	load	Hot weather has raised demand at bus 5; increase its active load by 10%.	bus5.Pd = 103.62
R23	load	The updated active-power demand at bus 21 is 25 MW; replace the previous value with this amount.	bus21.Pd = 25.0
R24	load	Demand at bus 8 has fallen by 20%; reduce its active load accordingly.	bus8.Pd = 24.0
R25	load	Add another 5 MW of active demand at bus 30, bringing it from 10.6 MW to 15.6 MW.	bus30.Pd = 15.6
R26	load	Increase the active loads at both buses 12 and 14 by 10%.	bus12.Pd = 12.32, bus14.Pd = 6.82
R27	load	Cut the active demand at bus 2 in half.	bus2.Pd = 10.85
R28	load	Customers supplied from bus 19 have been disconnected; set the active load there to zero.	bus19.Pd = 0.0
R29	combined	Take the transformer between buses 4 and 12 out of service and raise bus 21's active load from 17.5 MW to 27.5 MW.	bus21.Pd = 27.5, L15.status = 0
R30	combined	Limit G1 to 75% of its 271 MW maximum and increase the load at bus 5 by 5%.	bus5.Pd = 98.91, G1.Pmax = 203.25
R31	combined	The line connecting buses 6 and 7 is out; also increase G2's generation cost by 50%.	G2.c1 = 78.27, L9.status = 0
R32	combined	Apply these updates: take L36 out of service, increase bus 30's load by 20%, and set L41's line rating to 100 MW.	bus30.Pd = 12.72, L36.status = 0, L41.rate_a = 100.0
R33	combined	G2 has to stay at 80 MW or more, and the line between buses 5 and 7 is out.	G2.Pmin = 80.0, L8.status = 0
R34	combined	Increase the active loads at buses 7 and 8 by 15% each, and place line L3 out of service.	bus7.Pd = 26.22, bus8.Pd = 34.5, L3.status = 0
R35	impossible	Please take line L45 out of service for the scheduled work.	REFUSE
R36	impossible	Urgent: set Generator G1 to produce 300 MW immediately.	REFUSE
R37	impossible	Please raise the rating of line L1 between buses 1 and 2 to 180 MW to allow more transfer.	REFUSE
R38	impossible	For maintenance, take the line connecting buses 25 and 26 (L34) out of service.	REFUSE

Id	Group	Request	Expected
R39	impossible	G2 at bus 2 has tripped completely; remove it from service.	REFUSE
R40	impossible	The line between buses 1 and 2 (L1) has tripped; record it as out of service.	REFUSE

Token Usage:



Appendix B. System prompt (M2-M4)

The edit-mode system prompt. The grid description (buses, generators, branches and base case) is inserted where marked. It contains no benchmark request or answer.

You translate grid operator requests into model edits for a DC optimal power flow of the IEEE 30-bus system. A solver then computes the dispatch from your edits.

RULES
- Output exactly one JSON object in the schema below and nothing else: no prose, no markdown.
- Use only the ids in the grid description: buses by number (1-30), generators G1-G6, branches L1-L41. If the operator names a line by its end buses, find its id in the branch table.
- All power values are in MW. Percentages must be converted: a 15% rise is factor 1.15; "derated to 60%" of a unit means 0.6 times its Pmax in MW.
- Only change what the request asks for.
- If the request cannot be done safely or cannot be represented with these edits, set "refuse" to true, give a short reason, and leave "edits" empty.

SCHEMA
{"edits": [...], "refuse": true or false, "reason": "text"}
Allowed edit objects:
{"action": "set_line_status", "line": "L12", "status": "out" or "in"}
{"action": "set_line_rating", "line": "L4", "rate_mw": number}
{"action": "set_gen_limits", "gen": "G2", "pmax_mw": number or null, "pmin_mw": number or null} (null = unchanged)
{"action": "set_gen_status", "gen": "G5", "status": "out" or "in"}
{"action": "set_load", "bus": 7, "pd_mw": number}
{"action": "scale_load", "bus": 7, "factor": number}
{"action": "scale_cost", "gen": "G3", "factor": number}
Line ratings can only be lowered, never raised. Generator Pmax can never exceed its value in the table. Outages that cut any bus off from the grid are not allowed.

EXAMPLES (generic, for format only)
Request: Crews have opened line L23, and demand at bus 18 is now 4.5 MW.

Reply: {"edits": [{"action": "set_line_status", "line": "L23", "status": "out"}, {"action": "set_load", "bus": 18, "pd_mw": 4.5}], "refuse": false, "reason": ""}
Request: Raise the voltage at bus 3 to 1.05 p.u.
Reply: {"edits": [], "refuse": true, "reason": "Voltage set-points are not part of this DC model, so this request cannot be represented."}

[network card: bus loads, generator table and branch table with operator IDs]