

Aliasing-Aware RTNeural-Compatible WaveNet Modeling of Guitar Amplifier and Pedal Captures

Shortwav Labs

RTNeural Trainer Project

<https://github.com/shortwavlabs/rtneural-trainer>

<https://doi.org/10.5281/zenodo.21109537>

July 1, 2026

Abstract

We report an applied study of neural guitar amplifier and pedal modeling under a strict real-time export constraint: trained models must be representable as RTNeural JSON, validate against TensorFlow/Keras reference inference, and run as causal low-latency DSP in a native C++ audio runtime. The study began with dense, recurrent, and convolutional candidates, but the strongest end-to-end evidence in our internal 48 kHz mono paired-capture dataset favored WaveNet-style temporal convolutional networks (TCNs). We evaluate clean, edge-of-breakup, crunch, rhythm, lead, and overdrive-pedal captures using waveform error, residual statistics, native real-time factor, and a probe-based aliasing-to-signal ratio (ASR). The best high-gain result came from an A2-inspired sequential TCN using mixed kernel sizes, non-power-of-two dilations, and PReLU nonlinearities while remaining compatible with current RTNeural dynamic JSON. On a difficult high-gain rhythm capture, this model improved preview error-to-signal ratio (ESR) from 0.0646 for the previous smoothed-tanh quality model to 0.0381 after continuation, while reducing probe-measured average ASR from 0.0419 to 0.0145 and benchmarking at a worst-case native Eigen real-time factor of approximately 6.62 on the reference system. Real hardware captures later produced stronger export packages: clean/edge, overdrive pedal, and rhythm exports reached ESR values of 0.00217, 0.00043, and 0.00355 respectively, all passing native RTNeural validation with low probe ASR. The results support a practical, scoped conclusion: under current RTNeural JSON and product-workflow constraints, WaveNet-family causal TCNs are the best-tested architecture family for this trainer, while exact NAM A2-style residual/skip topology remains future runtime work.

1 Introduction

Neural modeling of guitar amplifiers and pedals is a system-identification problem with unusually unforgiving perceptual constraints. A fixed amp or pedal setting maps a dry direct-input signal $x[n]$ to a processed target $y[n]$, but the mapping is nonlinear, level-dependent, often highly compressive, and sensitive to latency errors of only a few samples. High-gain tones further expose residual energy in the upper bands, where small spectral mistakes can become audible as fizz, foldback, or loss of pick definition.

The goal of RTNeural Trainer is not merely to minimize a training loss. The model must be usable as real-time DSP: it must be causal, streamable, exportable to RTNeural, parity-checked against the training backend, benchmarked in a native runtime, and loadable in a DAW plugin. This engineering constraint rules out treating the training graph as an arbitrary offline model. It also makes runtime validation a first-class part of model evaluation.

This paper summarizes the DSP research performed while building the trainer. Our main contributions are:

- an end-to-end RTNeural-compatible training and export workflow for paired guitar amp/pedal captures;
- a comparison of product-facing WaveNet-style TCN presets across clean, edge, crunch, rhythm, lead, and overdrive-pedal cases;
- an aliasing-to-signal ratio diagnostic for exported RTNeural JSON models;
- an A2-inspired sequential TCN that improves difficult high-gain captures without requiring new RTNeural graph topology; and
- a set of capture and validation lessons for real-time neural audio effects.

The central claim is deliberately scoped. We do not prove that TCNs dominate all recurrent or convolutional models for all amplifier modeling tasks. We show that, in this internal dataset and under the current RTNeural JSON export constraint, WaveNet-family causal TCNs produced the strongest end-to-end product evidence.

2 Related Work

WaveNet introduced dilated causal convolutional stacks for raw audio modeling [1]. Subsequent neural audio-effects and amplifier-modeling work has used recurrent models, convolutional models, spectral losses, pre-emphasis, and finite-memory feed-forward architectures for real-time nonlinear system approximation [2, 3]. PANAMA frames amplifier modeling as a parametric and active-learning problem, where control settings are sampled strategically and the model is conditioned on those settings [4]. That broader parametric setting remains future work here; the present trainer models one fixed capture setting per project.

Neural Amp Modeler (NAM) is an important practical reference for this work [6, 7, 8]. NAM separates training/export from real-time plugin inference and treats the exported model package as a runtime contract. Recent NAM A2 models use WaveNet-like residual and skip structures with specialized C++ runtime paths. Current RTNeural dynamic JSON can host sequential Conv1D and PReLU stacks [9], but it does not directly express A2-style residual fan-out, skip accumulation, layer-array heads, or slimmable submodel selection. This motivated an A2-inspired sequential preset rather than direct NAM conversion.

Aliasing is another relevant thread. Nonlinear models generate harmonics that can fold above Nyquist, and high-gain guitar models stress this behavior. Work on smoothing neural activations for amp modeling suggests that activation shape can trade waveform accuracy against aliasing behavior [5]. We therefore added explicit ASR diagnostics and smoothed-tanh WaveNet variants, but treat ASR as a warning signal rather than a psychoacoustic score.

3 Problem Formulation

Let $x[n]$ be the prepared dry input and $y[n]$ the prepared target. After channel policy, resampling policy, polarity handling, and latency alignment, both are mono 48 kHz floating-point sequences. A causal finite-memory model produces

$$\hat{y}[n] = f_{\theta}(x[n], x[n-1], \dots, x[n-R+1]), \quad (1)$$

where R is the effective receptive field. For a sequential stack of causal Conv1D layers with kernel sizes k_ℓ , dilations d_ℓ , and no striding, the receptive field is

$$R = 1 + \sum_{\ell} (k_\ell - 1) d_\ell. \quad (2)$$

The residual is

$$e[n] = y[n] - \hat{y}[n]. \quad (3)$$

The primary waveform metric is error-to-signal ratio:

$$\text{ESR} = \frac{\sum_n e[n]^2}{\max(\sum_n y[n]^2, \epsilon)}. \quad (4)$$

We also report mean absolute error, root mean square error, peak residual, and correlation. Prediction level is tracked by

$$\rho_{\text{RMS}} = \frac{\text{RMS}(\hat{y})}{\max(\text{RMS}(y), \epsilon)}, \quad (5)$$

which guards against underpowered predictions that appear deceptively stable.

Three metric spans appear in our reports. Window validation is computed on held-out training windows. Stream validation is computed on a longer continuous segment to catch state and continuity failures. Preview or state-continuous metrics are computed on rendered preview WAVs from a saved checkpoint or export and are the main user-facing comparison metrics in this paper unless otherwise noted.

4 Methods

4.1 Capture preparation

The capture contract is a paired dry/processed recording from the same performance. Captures are prepared as 48 kHz mono WAVs, with float32 preserved when available. Stereo or dual-mono sources are mixed to mono for the current trainer. The preparation stage reports clipping, duration, level, channel policy, latency candidates, confidence, and polarity.

Latency is treated as an experimental variable. If the target is shifted by L samples, then the prepared pair is

$$x_{\text{aligned}}[n] = x[n], \quad y_{\text{aligned}}[n] = y[n + L]. \quad (6)$$

For high-gain captures the processed waveform can correlate weakly with the dry DI, producing several plausible offsets separated by only a few samples. The application therefore exposes top candidate offsets and allows manual sample nudging. In practice we found that a short transient preamble at the start of the DI—palm mutes, single-note plucks, and hard/soft attacks—is valuable for alignment.

4.2 Training protocol

Training uses TensorFlow/Keras only. The default optimizer is Adam, with a default seed of 1337 unless overridden. Default batch size is 16 and default sequence length is 1024 samples, though product recipes can override these values. Candidate windows are sampled across the prepared file; validation windows are fixed, while training windows may be resampled between epochs.

Checkpoint selection uses a composite validation score:

$$s = \text{ESR}_{\text{stream}} + 0.25 \text{ESR}_{\text{window}} + p_{\text{under}}, \quad (7)$$

Preset	Layers	Filters	Kernels	Dilations	Activation
Fast	6	12	3	$1, \dots, 32$ powers of two	tanh
Balanced	8	16	3	$1, \dots, 128$ powers of two	tanh
Quality	10	20	3	$1, \dots, 512$ powers of two	tanh
Quality Tanh 1.5	10	20	3	$1, \dots, 512$ powers of two	$\tanh(x/1.5)$
Clean	10	8	7	$1, \dots, 512$ powers of two	linear hidden
Edge	10	8	7	$1, \dots, 512$ powers of two	$\tanh(x/1.8)$
A2 PReLU	12	16	6, 15 mixed	non-power-of-two mixed	PReLU

Table 1: Principal RTNeural-compatible TCN presets. The shorthand $1, \dots, 512$ denotes powers-of-two dilations. The A2 PReLU row uses the mixed sequence 1, 3, 7, 17, 41, 101, 239, 1, 3, 7, 17, 41.

where p_{under} penalizes severely underpowered predictions. Early stopping monitors this score with default patience 5 and minimum improvement 10^{-4} . The learning rate scheduler uses ReduceLROnPlateau with factor 0.5, a minimum learning rate of 10^{-6} , and patience derived from the early-stopping patience.

Losses include waveform ESR/MSE variants, pre-emphasis MSE, and a multi-resolution STFT plus pre-emphasis loss. The pre-emphasis coefficient is 0.95, with pre-emphasis loss weight 0.35. The multi-resolution STFT frame sizes are 256, 1024, and 2048 samples, with STFT weight 0.02 and log-magnitude weight 0.05. These values are implementation settings rather than claimed optima.

4.3 Architectures

The project initially included dense, GRU, LSTM, shallow Conv1D, BatchNorm/PReLU, and hybrid presets. Those paths remain useful as internal export fixtures, but product-facing recipes have moved to WaveNet-family TCNs. The main presets are summarized in Table 1.

These models are intentionally sequential:

$$x \rightarrow [\text{causal Conv1D} \rightarrow \text{activation}]^N \rightarrow \text{output}. \quad (8)$$

They are not full residual/skip WaveNet graphs. That limitation preserves RTNeural dynamic-JSON compatibility, but it also limits how much depth can be added before optimization becomes difficult. A failed high-gain experiment with one additional plain tanh dilation stage suggested that larger receptive field alone does not solve difficult rhythm captures.

4.4 Aliasing-to-signal ratio

For each exported RTNeural JSON model, we render deterministic sine probes at requested frequencies 1250, 2500, and 5000 Hz. The input amplitude is 0.5, with 2048 warmup samples and a 4096-sample analysis window. The actual frequency is snapped to the nearest FFT bin so the fundamental is on-bin. After subtracting the mean, the analyzer computes FFT power and identifies

Family	Duration	Notes
DI2	151.6 s	Same dry DI rendered to clean, crunch, rhythm, edge, lead, and overdrive-pedal targets.
DI3/CLEAN3	613.08 s	Long clean capture with known 13-sample DAW latency.
DI3-B/RHYTHM3-B	444.25 s	Trimmed high-gain rhythm capture; 10-sample estimated latency with low confidence.
DI4/RHYTHM4	158.8 s	Short high-gain rhythm control capture; 9-sample estimated latency.
Hardware trio	focused captures	Real amp clean/edge, real overdrive pedal, and real amp rhythm exports.

Table 2: Capture families used in the internal experiments.

harmonic bins. It then defines

$$E_{\text{harm}} = \sum_{b \in \mathcal{H}} P[b], \quad (9)$$

$$E_{\text{alias}} = \sum_{b > 0} P[b] - E_{\text{harm}}, \quad (10)$$

$$\text{ASR} = \frac{E_{\text{alias}}}{\max(E_{\text{harm}}, \epsilon)}. \quad (11)$$

Worst-case ASR below 0.02 is treated as low aliasing in the current probes; values below 0.08 produce a review warning; larger values produce a stronger warning. These thresholds are not audibility thresholds. They are engineering diagnostics to focus listening tests.

4.5 Native validation and plugin smoke testing

Exports are gated by Keras-to-RTNeural JSON parity, native RTNeural validation, and native benchmark results. The validator tests block sizes 16, 32, 64, 128, 256, and 512 samples, mono and stereo when applicable, and records worst-case real-time factor:

$$\text{RTF} = \frac{\text{audio duration processed}}{\text{wall time elapsed}}. \quad (12)$$

An RTF above one is faster than real time, but product headroom requires a larger margin because DAWs may run multiple instances and small buffers.

A JUCE Audio Unit debug plugin was used for smoke testing [10]. It loads exported RTNeural package folders, stages model objects off the audio thread, and keeps `processBlock()` free of parsing, file I/O, locks, and heap allocation. These plugin tests were performed on a MacBook Pro M5 Max reference machine and should not be interpreted as broad release qualification.

5 Experiments

The main internal capture families are listed in Table 2. All audio was prepared at 48 kHz mono for training.

Preset	ESR	RMSE	Corr.	Worst ASR	Avg. ASR	Native RTF
Balanced	0.6309	0.0740	0.6109	–	–	–
Quality	0.0713	0.0249	0.9640	0.290	0.100	12.17
Quality Tanh 1.5	0.0646	0.0237	0.9674	0.0670	0.0419	11.74
A2 PReLU	0.0440	0.0196	0.9778	0.0354	0.0205	6.54
A2 PReLU continued	0.0381	0.0182	0.9808	0.0201	0.0145	6.62

Table 3: RHYTHM4 high-gain progression. Missing ASR/RTF values indicate runs not used as export candidates in the benchmarked export study.

The DI2 family established tone-dependent difficulty. WaveNet quality achieved preview ESR 0.0052 on clean, 0.0115 on crunch, 0.1100 on rhythm, 0.0045 on edge, and 0.0021 on the overdrive pedal. Lead was the primary outlier: balanced slightly beat quality at ESR 0.0810 versus 0.0821. Shallow stacked Conv/PReLU baselines were fast but trailed WaveNet-family presets across the reported product comparisons.

6 Results

6.1 High-gain RHYTHM4 progression

Table 3 shows the most informative high-gain progression. The plain balanced model plateaued. The quality model fit the waveform much better but produced a strong ASR warning. The smoothed-tanh quality model improved both ESR and probe ASR. The A2-inspired PReLU model then improved both metrics again, at a runtime and model-size cost.

This sequence does not isolate which A2-inspired change caused the improvement. Kernel sizes, dilation pattern, activation type, training dynamics, and continuation all differ. The result should therefore be read as evidence for the combined preset, not as a controlled ablation of individual features.

6.2 Clean and edge-of-breakup behavior

The real clean amp project exposed an architecture mismatch. A2 PReLU initially improved but then diverged from full-stream validation, despite stable 130-sample alignment and polarity handling. A clean long-field linear preset improved the run to ESR 0.0675 and correlation 0.9663. The capture was technically clean for single coils but behaved closer to edge-of-breakup with humbuckers; adding gentle hidden nonlinearity in the edge preset reduced ESR to 0.00362 and correlation to 0.9982. A larger edge-detail variant did not improve this result, suggesting that the key correction was light nonlinearity rather than more capacity.

6.3 Real hardware exports

The hardware export trio is summarized in Table 4. All three exports passed native RTNeural validation and reported low probe ASR.

These hardware captures trained more reliably than several earlier DAW amp-simulation renders. Plausible contributors include the matured capture workflow, float32 preparation, shorter focused material, consistent reamping, and the analog capture path’s natural band limiting. These explanations remain hypotheses; matched experiments would be needed to isolate causes.

Export	Preset	ESR	Worst ASR	Avg. ASR	Native RTF
Clean/edge amp	Edge	0.00217	0.00673	0.00251	20.72
Overdrive pedal	A2 PReLU	0.00043	0.00195	0.00080	6.49
Rhythm amp	A2 PReLU	0.00355	0.00913	0.00359	6.63

Table 4: Real hardware export results. Native RTF values are reference-system Eigen-backend results.

7 Discussion

7.1 Why TCNs fit the product constraint

The successful presets combine three properties: finite memory, causal streaming, and RTNeural compatibility. Dilation expands temporal context without sample-by-sample recurrence, and Conv1D exports naturally to current RTNeural JSON. Smaller Conv models were fast but left residual structure in important tones. Recurrent models were considered during development, but the strongest validated export evidence in this workflow came from TCNs.

The models in this paper are not full WaveNet graphs with residual and skip topology. They are sequential TCNs shaped by export constraints. That constraint is useful: it forces every architecture to survive the same native validation and real-time benchmark path.

7.2 Latency as experimental control

Latency is a major bottleneck. A few samples of error can dominate high-frequency residuals, and high-gain distortion weakens simple correlation between dry and processed signals. The trainer therefore treats latency as an interactive measurement problem, not a hidden preprocessing step. Future work should combine transient alignment, envelope correlation, band-limited scoring, phase methods, and post-training residual-shift diagnostics.

7.3 ESR, ASR, and listening

ESR is necessary but insufficient. A low-ESR model can still alias, mismatch level, or produce unacceptable residual spectra. ASR provides a deterministic probe-specific stress test for nonlinear foldback, but it is not a perceptual model. The appropriate export gate is multi-objective: backend parity, native validation, runtime headroom, preview metrics, probe ASR, residual listening, and user judgment.

7.4 Runtime scope

The A2 PReLU result ran comfortably on the reference machine and in a JUCE debug plugin smoke test, including a four-instance Logic Pro test at a 32-sample buffer. This is encouraging but not production qualification. The next runtime work is controlled plugin benchmarking across weaker systems, release builds, sample rates, block sizes, plugin validation tools [11], and full pedal-plus-amp-plus-IR chains. Static RTNeural `ModelT` specializations or fused residual TCN layers may eventually be necessary.

8 Limitations

This study is an internal applied research report rather than a fully controlled public benchmark. Most comparisons are single-seed product experiments. Dataset diversity is limited to the available captures and hardware. ASR thresholds are engineering heuristics rather than calibrated audibility thresholds. Some high-gain captures have low latency confidence. Runtime evidence is strongest on Apple Silicon with the Eigen backend. Finally, although the A2-inspired sequential preset is effective, it is not equivalent to NAM A2 topology.

9 Future Work

The most immediate research tasks are repeated-seed comparisons for the best WaveNet variants, matched latency-offset ablations, listening-calibrated ASR thresholds, and controlled plugin benchmarks. A day-2 RTNeural runtime extension should add a fused `a2_wavenet` or `residual_tcn` layer with preallocated state, residual/skip accumulation, and constrained JSON schema. Longer-term work includes NAM-teacher distillation, plugin-side oversampling or higher-rate model support, and PANAMA-style parametric active learning for controllable amplifier settings.

10 Conclusion

Under the current 48 kHz mono paired-capture workflow and RTNeural JSON export constraint, WaveNet-family causal TCNs are the best-tested architecture family for RTNeural Trainer. The strongest high-gain evidence is an A2-inspired sequential PReLU TCN that substantially improves RHYTHM4 waveform fit and probe ASR while remaining compatible with current RTNeural exports. The strongest practical evidence is the real hardware clean/drive/rhythm export trio, which passed native validation with low probe ASR and reference-system runtime headroom.

The broader lesson is that neural amp modeling is not just a training problem. Capture discipline, latency alignment, spectral loss, aliasing diagnostics, native validation, and DAW runtime behavior all determine whether a model is musically useful.

Data and Code Availability

The trainer implementation, native validator, documentation, and experimental notes are maintained at <https://github.com/shortwavelabs/rtnneural-trainer>. Some source captures used in this study are not included in the repository because they contain performance audio and third-party tone references.

Acknowledgments

This work builds on the RTNeural, Neural Amp Modeler, JUCE, and audio-ML research communities. We thank the maintainers of those projects for making their code and documentation available.

References

- [1] A. van den Oord, S. Dieleman, H. Zen, K. Simonyan, O. Vinyals, A. Graves, N. Kalchbrenner, A. Senior, and K. Kavukcuoglu. WaveNet: A generative model for raw audio. *arXiv preprint arXiv:1609.03499*, 2016.
- [2] E.-P. Damskäg, L. Juvela, E. Thuillier, and V. Välimäki. Deep learning for tube amplifier emulation. *ICASSP*, 2019. arXiv:1811.00334.
- [3] C. J. Steinmetz and J. D. Reiss. auraloss: Audio-focused loss functions in PyTorch. In *Digital Music Research Network One-day Workshop*, 2020.
- [4] F. Grötschla, L. A. Lanzendörfer, L. Jiao, and R. Wattenhofer. Parametric neural amp modeling with active learning. *arXiv preprint arXiv:2507.02109*, 2025.
- [5] R. Sato and J. O. Smith III. Aliasing reduction in neural amp modeling by smoothing activations. *arXiv preprint arXiv:2505.04082*, 2025.
- [6] S. Atkinson. Neural Amp Modeler. <https://github.com/sdatkinson/neural-amp-modeler>.
- [7] S. Atkinson. NeuralAmpModelerPlugin. <https://github.com/sdatkinson/NeuralAmpModelerPlugin>.
- [8] S. Atkinson. NeuralAmpModelerCore. <https://github.com/sdatkinson/NeuralAmpModelerCore>.
- [9] J. Chowdhury. RTNeural. <https://github.com/jatinchowdhury18/RTNeural>.
- [10] Raw Material Software. JUCE. <https://juce.com/>.
- [11] Tracktion. pluginval. <https://github.com/Tracktion/pluginval>.