

CPRI SCL Transformer Loss Measurement v2.17

Series No : CPRI BLSCL25T1654

Sample No : HV D25S0847

Sample Details :

250kVA, 11000/433V, EEL-1, 3ph, Cu wound, tapping (+5% to -10% : step 2.5%) Distribution Transformer (EEL-1 limits : 980W/2930W)

No Load Loss

	V	I	P	f
BT	433.05	1.689	383.18	49.95
AT	433.02	1.687	383.26	49.99

50% Load Loss

	V	I	P	f
	137.07	6.517	443.04	49.885
	138.24	6.553	448.20	49.968

L V Resistance (milliOhm)

	LVR1	LVR2	LVR3	Temp
	3.8716	3.8650	3.9074	24.7
	3.8970	3.8844	3.9248	25.9

Load Loss Measurement

	V1	V2	V3	I1	I2	I3	P1	P2	P3	f	HVR1	HVR2	HVR3
NTBT	267.85	268.49	263.62	12.706	12.718	12.576	568.91	565.64	542.57	49.886	3.9736	3.9558	3.9690
NTAT	273.45	273.81	269.60	12.936	12.935	12.819	588.76	586.96	568.04	49.959	3.9890	3.9734	3.9844
HTBT	273.45	273.66	269.03	11.607	11.588	11.480	508.05	508.62	490.73	49.876	4.2028	4.1822	4.1874
HTAT	270.67	271.09	266.12	11.452	11.449	11.342	498.22	493.92	482.26	49.944	4.2200	4.1988	4.2092
LTBT	247.35	248.33	242.53	14.175	14.158	13.954	615.33	598.64	579.45	49.878	3.5476	3.5398	3.5458
LTAT	242.61	244.44	238.47	13.866	13.869	13.672	590.73	577.67	557.86	49.955	3.5612	3.5540	3.5622

HV Resistance (Ohm)

Load Loss Results (Ref Temp : 75 degC)

	%Z-75deg	%X-50Hz	%X Change	Rhv-Ohm	Rlv-mOhm	100% Load Loss	X/R-75deg	Isc-pk	Isc-rms	Stray Loss	50% Load Loss	50% Total Loss	100% Total Loss
NTBT	4.380	4.299		7.101	2.317	2102.74	5.112	16.73	7.61	107.62	524.91	908.09	2485.92
NTAT	4.387	4.306	-0.163	7.098	2.318	2101.21				106.21	523.61	906.87	2484.47
HTBT	4.442	4.365		7.504	2.317	2056.03	5.310	16.61	7.50	111.77			2439.21
HTAT	4.446	4.369	-0.092	7.502	2.318	2054.67				110.09			2437.93
LTBT	4.487	4.397		6.346	2.317	2240.03	4.907	16.20	7.43	118.60			2623.21
LTAT	4.496	4.406	-0.205	6.343	2.318	2239.94				118.58			2623.20

TEST ENGINEER

