



LIFT INVERTER

**POWERFUL
QUIET
RELIABLE**

1 TO 100 KVA



**G1 ENERGY SOLUTIONS
PRIVATE LIMITED**

SPECIFICATIONS FOR LIFT INVERTER

INPUT

- Voltage : 415 V, 3 Phase or 230V, 1 Phase
- Voltage Variation : +15% - 20%
- Frequency : 47 to 53 Hz

OUTPUT

- Rating : 1 KVA to 100 KVA
- Voltage : 415 V, 3 Phase or 230 V, 1 Phase
- Voltage Variation : 1% (On Inverter mode)
(During Mains Available Conditions, Mains will be Directly Connected at Output)
- Crest Factor : 3:1
- Frequency : 50Hz
- Frequency Regulation: + 0.1%
- Wave form : Sine wave
- Harmonic Distortion : <3% THD for linear load
<5% THD for non-linear load
<2% THD for optional
- Overload Rating : 110% for 30 minutes
: 125% for 10 minutes
: 150% for 60 seconds
: 200% for 60 seconds
- Transient Rating : for 100% load change,
- Response Time : Recovery to $\pm 1\%$ within 5msec.

DC LINK

- DC Bus volts Ripple : Less than 2%.
- Battery isolation : Circuit Breaker
- Battery type : Sealed Maintenance Free (SMF) Tubular

EFFICIENCY (TYPICAL)

- Inverter Efficiency : Better than 90% above 5 KVA
- Overall Efficiency : Better than 98% on Mains

PROTECTIONS

- | | | |
|----------|---|-------------------|
| Inverter | : | O/P Over Voltage |
| | | O/P Under Voltage |
| | | O/P Over Load |
| | | O/P Short-Circuit |

Range : 1 KVA to 100 KVA

IGBT Technology

High Overload Capability For Motor Starting & Operation of Lifts/Pumps

Led status indicator

Low on load losses

Higher Overall Efficiency Saves on Electricity Bills

Battery Low Alarm and Shut Down For Longer Battery Life



G1 ENERGY SOLUTIONS PRIVATE LIMITED

MANUFACTURER & SUPPLIERS OF POWER ENERGY PRODUCTS &
CUSTOMISED DESIGNED PRODUCTS

204, B. K. APARTMENT, DECCAN COLLEGE ROAD, YERAWADA,
PUNE-411006, INDIA • TEL/FAX: +91 (0) 20 26683974 • Mobile: +91 9322741876 / 9822001119
E-MAIL: info@glenergysolutions.com • www.glenergysolutions.com

DETAILED TECHNICAL DATA SHEETS OF ABOVE PRODUCTS AVAILABLE ON REQUEST

DUE TO OUR CONTINUOUS ENDEAVOUR TO GIVE YOU THE BEST, THE MODELS, DESIGNS AND SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT PRIOR NOTICE.

DIFFERENCE BETWEEN GENERATOR & UPS

	DG-SET	UPS
PRICE	High capital cost per KVA 1. Auto start Panel 2. Sound proof Canopy. 3. Foundation, Installation & Commissioning Cost. 4. Battery & Battery Charger Cost 5. Lisioning Cost for Obtaining MSEB & Pollution Control Board Permission. 6. Exhaust piping for smoke up to top floor. 7. Fuel storage license is required	Cost involves only - 1. UPS Systems Cost. 2. Battery Set Cost
RUNNING COST	1. Diesel Consumption even when working on no-load 2. No Load Consumption is around 80% 3. Attendant required to keep record of diesel requirement, Preventive maintenance schedule, to carry out battery charging once in a day, for keeping DG SET in working condition. 4. To keep DG-SET batter in charged condition, starting of DG SET for 5 to 10 min. a day is recommended for battery charging. This adds to fuel consumption 5. Very high maintenance cost 6. Running cost may increase depending upon fuel price fluctuations	1. Battery replacement cost required after 3 years works out to be cheaper compared to diesel cost required for 3 years. 2. Battery energy is consumed according to load 3. No load consumption is as low as 3% 4. Very low maintenance cost 5. Fixed Running cost a long period (Battery life span)
POLLUTION	1. As it runs on diesel emits smoke Fumes, gases continuously. 2. Very noisy	1. Does not emit smoke, fumes or any gases. No noise. 2. Absolutely Environment Friendly. & noiseless
SIZE	1. Very large space is required to install	1. Very less space is required
LIFE	1. Life of DG-SET depends on regular maintenance. Can get 10 to 15 years life it maintained properly. 2. But since it consists of moving part, regular wear & tear is common factor. Maintenance cost & cost of spare is high.	1. Does not consist of any moving part. So, no wear & tear. 2. Can get life of 20 years if kept in clean environment. 3. Battery life is 3 years to 7 years depending on battery type
OUTPUT POWER QUALITY	1. Power quality, efficiency, Diesel consumption, noise level & pollution will detroite depending on wear & tear. Protection against overload, short circuit, & other such problems which may arise	1. Will get high quality power throughout the life Emergency landing facility Backup history records for easy dignosys & solutions