

QuARC

Quantum Advanced
Research Center



CSIC

CONSEJO SUPERIOR DE INVESTIGACIONES CIENTÍFICAS

Floquet engineering of open quantum systems

Sigmund Kohler

Quantum Advanced Research Center, CSIC
Instituto de Ciencia de Materiales de Madrid, CSIC

- I. Floquet theory for the Schrödinger equation
- II. Dissipation & transport
- III. Applications

<https://sigmundkohler.github.io/download/FloquetTutorial.pdf>



Laser physics since the 1970s

- strong ac fields acting on atoms
 - treatment beyond linear response
- Floquet theory for Schrödinger equation
 - discrete time translation and Floquet ansatz
 - properties of Floquet states
 - relation to Berry phase
 - analytical and numerical techniques
- Floquet-Bloch-Redfield theory
 - dissipation & decoherence
 - Floquet state population
 - efficient computation

~ 2000: qubits + microwaves

~ 2015: Floquet engineering, optical lattices, artificial gauge fields, ...

1 Floquet & Schrödinger equation


- Geometric phases
- Time-periodicity, Floquet ansatz, and all that

2 Quantum dissipation and transport

- System-bath model
- Floquet-Bloch-Redfield formalism

3 Applications & miscellaneous topics

- LZSM Interference
- Floquet-Gibbs states
- Hidden symmetries
- Floquet degeneracies & topology
- Time-dependent Liouvillians
- Two-color Floquet theory
- Adiabatic Floquet theory
- Floquet scattering theory



- Time evolution of an eigenstate ($\hbar = 1$)

$$|\psi(t)\rangle = e^{-iE_n t} |\phi_n\rangle$$

Notation:

ψ : solution of Schrödinger equation

ϕ : other state vector, e.g., eigenstate


- energy $\leftrightarrow$ phase

for (periodically) time-dependent system ?

- Spin in magnetic field

$$\vec{B}(t) = \vec{B}(t + T):$$


$$H(t) = \frac{1}{2} \vec{B}(t) \cdot \vec{\sigma}$$



- Spin in magnetic field


$$\vec{B}(t) = \vec{B}(t + T):$$

$$H(t) = \frac{1}{2} \vec{B}(t) \cdot \vec{\sigma}$$



- Quantum dynamics for $\dot{B} \ll B^2$:
state follows the eigenstate
adiabatically


$$|\psi(t)\rangle \propto |\phi_n(t)\rangle$$



→ $|\psi(t)\rangle$ determined up to phase factor

After one period: $|\psi(T)\rangle = e^{i\varphi}|\psi(0)\rangle$

$$\varphi = - \int_0^T dt E_n(t) + \gamma_C$$




- dynamical phase $\leftrightarrow$ mean energy
- Berry phase γ_C
 - depends only on closed curve C in parameter space

M. Berry, Proc. Roy. Soc. London, Ser. A **392**, 45 (1984)

After one period: $|\psi(T)\rangle = e^{i\varphi} |\psi(0)\rangle$

$$\varphi = - \int_0^T dt E_n(t) + \gamma_C$$



- dynamical phase $\leftrightarrow$ mean energy
- Berry phase γ_C
 - depends only on closed curve C in parameter space

M. Berry, Proc. Roy. Soc. London, Ser. A **392**, 45 (1984)

- Assumptions:
 - 1 $\vec{B}(t)$ changes adiabatically slowly
 - 2 initial state: eigenstate $|\phi_n(0)\rangle$

Different perspective:

State vector undergoes **periodic** time-evolution

- $|\psi(T)\rangle = e^{i\varphi}|\psi(0)\rangle$
- dynamics $|\psi(t)\rangle$ induced by some Hamiltonian $H(t)$

Remarks:

- no adiabatic condition
- $|\psi(t)\rangle$ need not be an eigenstate of $H(t)$
- $H(t)$ is not unique
- only condition: **cyclic time-evolution in Hilbert space**

$$|\psi(t)\rangle = e^{i\varphi(t)}|\phi(t)\rangle, \quad |\phi(t)\rangle = |\phi(t+T)\rangle$$

→ Phase acquired during cyclic evolution: $\varphi = f(T) - f(0)$

$$\frac{d\varphi}{dt} = -\langle \phi | H(t) | \phi \rangle + \langle \phi | i \frac{d}{dt} | \phi \rangle \implies \boxed{\varphi = \varphi_{\text{dyn}} + \gamma}$$

→ Phase acquired during cyclic evolution: $\varphi = f(T) - f(0)$

$$\frac{d\varphi}{dt} = -\langle \phi | H(t) | \phi \rangle + \langle \phi | i \frac{d}{dt} | \phi \rangle \implies \boxed{\varphi = \varphi_{\text{dyn}} + \gamma}$$

Dynamical phase $\varphi_{\text{dyn}} = - \int_0^T dt \langle \phi(t) | H(t) | \phi(t) \rangle$

- depends on choice of $H(t)$
- reflects mean energy

→ Phase acquired during cyclic evolution: $\varphi = f(T) - f(0)$

$$\frac{d\varphi}{dt} = -\langle\phi|H(t)|\phi\rangle + \langle\phi|i\frac{d}{dt}|\phi\rangle \implies \boxed{\varphi = \varphi_{\text{dyn}} + \gamma}$$

Dynamical phase $\varphi_{\text{dyn}} = -\int_0^T dt \langle\phi(t)|H(t)|\phi(t)\rangle$

- depends on choice of $H(t)$
- reflects mean energy

Aharonov-Anandan phase (“non-adiabatic Berry phase”)

$$\gamma = \int_0^T dt \langle\phi|i\frac{d}{dt}|\phi\rangle$$

- depends only on trajectory in Hilbert space — not in parameter space!
- adiabatic limit: $\gamma = \gamma_{\text{C}}$

Aharonov & Anandan, PRL 1987

Goal: propagator $U(t, t')$

- Time-independent system: diagonalize Hamiltonian $\rightarrow |\phi_n\rangle, E_n$

$$U(t, t') = U(t - t') = \sum_n e^{-iE_n(t-t')} |\phi_n\rangle \langle \phi_n|$$

Goal: propagator $U(t, t')$

- Time-independent system: diagonalize Hamiltonian $\rightarrow |\phi_n\rangle, E_n$

$$U(t, t') = U(t - t') = \sum_n e^{-iE_n(t-t')} |\phi_n\rangle \langle \phi_n|$$

- Driven system:

$$i \frac{d}{dt} |\psi\rangle = H(t) |\psi\rangle \rightarrow \text{numerical integration}$$

problem 1: time-integration not efficient for long times

problem 2: no information about structure of U

Goal: propagator $U(t, t')$

- Time-independent system: diagonalize Hamiltonian $\rightarrow |\phi_n\rangle, E_n$

$$U(t, t') = U(t - t') = \sum_n e^{-iE_n(t-t')} |\phi_n\rangle \langle \phi_n|$$

- Driven system:

$$i \frac{d}{dt} |\psi\rangle = H(t) |\psi\rangle \rightarrow \text{numerical integration}$$

problem 1: time-integration not efficient for long times

problem 2: no information about structure of U

- Solution for $H(t) = H(t + T)$: “Bloch theory in time”

cf. $H(x)|\phi\rangle = \epsilon|\phi\rangle$ with $H(x) = H(x + a)$

$\rightarrow$ Bloch waves $\phi(x) = e^{iqx} \varphi(x)$, where $\varphi(x)$ is a -periodic

Gaston Floquet (1883):

Ann. de l'Ecole Norm. Sup. **12**, 47 (1883)

Parametric oscillator (cf. Paul trap)


$$\ddot{x} + (\omega_0^2 + \epsilon \cos \Omega t)x = 0$$

Floquet theorem:
solutions have the structure

$$x(t) = e^{\pm i\mu t} \xi(t)$$

where $\xi(t) = \xi(t + 2\pi/\Omega)$

(undriven limit: $\mu = \omega_0$, $\xi = \text{const}$)



μ real

→ oscillating solutions

μ imaginary

→ one solution unstable

- $H(t) = H(t + T)$
 - $t \rightarrow t + T$ is symmetry operation
 - solutions of Schrödinger equation with $|\psi(t+T)\rangle = e^{i\varphi}|\psi(t)\rangle$
- Floquet ansatz

$$|\psi(t)\rangle = e^{-i\epsilon t}|\phi(t)\rangle = e^{-i\epsilon t} \sum_k e^{-ik\Omega t} |\phi_k\rangle$$

- ϵ quasienergy (cf. quasi momentum) → long-time dynamics
 - $|\phi(t)\rangle = |\phi(t + T)\rangle$, Floquet state → within driving period
- Floquet theorem: complete set of Floquet solutions of this form
- Schrödinger equation $i\partial_t|\psi\rangle = H(t)|\psi\rangle$ yields

$$\left(H(t) - i\frac{d}{dt}\right)|\phi(t)\rangle = \epsilon|\phi(t)\rangle$$

$|\phi(t)\rangle$ Floquet state with quasienergy ϵ


→ $e^{ik\Omega t}|\phi(t)\rangle$ Floquet state with $\epsilon + k\Omega$

→ Equivalent states: all correspond to the same $|\psi(t)\rangle$

$|\phi(t)\rangle$ Floquet state with quasienergy ϵ

→ $e^{ik\Omega t}|\phi(t)\rangle$ Floquet state with $\epsilon + k\Omega$

→ Equivalent states: **all correspond to the same $|\psi(t)\rangle$**



■ all Brillouin zones equivalent, choice arbitrary

→ **quasienergies cannot serve for ordering!**

- Physical quantity / observable: mean energy

$$E = \frac{1}{T} \int_0^T dt \langle \psi(t) | H(t) | \psi(t) \rangle = \frac{1}{T} \int_0^T dt \langle \phi(t) | H(t) | \phi(t) \rangle$$

- All equivalent states have the same mean energy
[proof: insert $e^{ik\Omega t} |\phi(t)\rangle$]
- Floquet states can be ordered by their mean energy

■ Mean energy

$$E = \frac{1}{T} \int_0^T dt \langle \phi(t) | \{ H(t) - i\partial_t + i\partial_t \} | \phi(t) \rangle$$

where $(H - i\partial_t)|\phi(t)\rangle = \epsilon|\phi(t)\rangle$

$$E = \epsilon + \frac{1}{T} \int_0^T dt \langle \phi(t) | i\partial_t | \phi(t) \rangle$$

■ Mean energy

$$E = \frac{1}{T} \int_0^T dt \langle \phi(t) | \{ H(t) - i\partial_t + i\partial_t \} | \phi(t) \rangle$$

where $(H - i\partial_t)|\phi(t)\rangle = \epsilon|\phi(t)\rangle$

$$-\epsilon = -E + \frac{1}{T} \int_0^T dt \langle \phi(t) | i\partial_t | \phi(t) \rangle$$

■ Compare to

$$\varphi = \varphi_{\text{dyn}} + \gamma$$

■ Mean energy

$$E = \frac{1}{T} \int_0^T dt \langle \phi(t) | \{ H(t) - i\partial_t + i\partial_t \} | \phi(t) \rangle$$

where $(H - i\partial_t)|\phi(t)\rangle = \epsilon|\phi(t)\rangle$

$$-\epsilon = -E + \frac{1}{T} \int_0^T dt \langle \phi(t) | i\partial_t | \phi(t) \rangle$$

■ Compare to

$$\varphi = \varphi_{\text{dyn}} + \gamma$$

$(E - \epsilon)T$ is a geometric phase

Floquet equation as function of Ω and Ωt :

$$\epsilon(\Omega)\phi(\Omega t) = \left[H(\Omega t) - i\Omega \frac{\partial}{\partial \Omega t} \right] \phi(\Omega t)$$

Floquet equation as function of Ω and Ωt :

$$\epsilon(\Omega)\phi(\Omega t) = \left[H(\Omega t) - i\Omega \frac{\partial}{\partial \Omega t} \right] \phi(\Omega t)$$

Compute derivative $(\partial/\partial\Omega)|_{\Omega t}$ and apply $\int \frac{dt}{T} \phi^+$ to obtain

$$\frac{\partial \epsilon}{\partial \Omega} = -\frac{\gamma}{2\pi} = \frac{\epsilon - E}{\Omega} \quad \rightarrow \quad \boxed{E = \epsilon - \Omega \frac{\partial \epsilon}{\partial \Omega}}$$

Floquet equation as function of Ω and Ωt :

$$\epsilon(\Omega)\phi(\Omega t) = \left[H(\Omega t) - i\Omega \frac{\partial}{\partial \Omega t} \right] \phi(\Omega t)$$


Compute derivative $(\partial/\partial \Omega)|_{\Omega t}$ and apply $\int \frac{dt}{T} \phi^+$ to obtain

$$\frac{\partial \epsilon}{\partial \Omega} = -\frac{\gamma}{2\pi} = \frac{\epsilon - E}{\Omega} \quad \rightarrow \quad \boxed{E = \epsilon - \Omega \frac{\partial \epsilon}{\partial \Omega}}$$

E.g. for $\gamma = \gamma_{\text{ad}} + \mathcal{O}(\Omega)$


$$\rightarrow \epsilon = \text{const} - (\gamma_{\text{ad}}/2\pi)\Omega + \dots \rightarrow E = E_{\text{ad}} + \mathcal{O}(\Omega^2)$$

Fainshtein, Manakov, Rapoport, J. Phys. B (1978)




Driven **undetuned** two-level system

- exact crossings
(consequence of a symmetry)



Driven **undetuned** two-level system

- exact crossings
(consequence of a symmetry)



... with **small detuning**

- **quasi energies**
 - avoided crossings
- **mean energies**
 - exact crossings remain
 - additional crossings
 - do not follow from any eigenvalue equation

Goal: more formal treatment of $H(t) - i\partial_t$

- $|\phi(t)\rangle \in \mathcal{R} \otimes \mathcal{T}$ composite Hilbert space / Sambe space

Shirley, PR **138**, B979 (1965), Sambe, PRA **7**, 2203 (1973)

$\mathcal{T}$: Hilbert space of T -periodic functions with inner product

$$\langle f|g\rangle = \int_0^T f(t)^* g(t) \frac{dt}{T} = \sum_k f_k^* g_k$$

- extended Dirac notation:

- $|\phi(t)\rangle = \langle t|\phi\rangle$
- Fourier coefficient $|\phi_k\rangle = \langle k|\phi\rangle$

$$\text{e.g.: } |\phi(t)\rangle = \langle t|\phi\rangle = \sum_k \langle t|k\rangle \langle k|\phi\rangle = \sum_k e^{-ik\Omega t} |\phi_k\rangle$$

- $H - i\partial_t$ is hermitian (in Sambe space!)
- Floquet states $|\phi_\alpha\rangle$ orthonormal and complete in $\mathcal{R} \otimes \mathcal{T}$

$$\langle\langle\phi_\alpha^{(k)}|\phi_\beta^{(k')}\rangle\rangle = \delta_{\alpha\beta}\delta_{kk'}$$

? but in $\mathcal{R}$?

- $H - i\partial_t$ is hermitian (in Sambe space!)

→ Floquet states $|\phi_\alpha\rangle$ orthonormal and complete in $\mathcal{R} \otimes \mathcal{T}$

$$\langle\langle\phi_\alpha^{(k)}|\phi_\beta^{(k')}\rangle\rangle = \delta_{\alpha\beta}\delta_{kk'}$$

? but in $\mathcal{R}$?

- Consider $\langle\phi_\alpha(t)|\phi_\beta(t)\rangle = \sum_k \lambda_k e^{-ik\Omega t}$ since T -periodic with the Fourier coefficient

$$\lambda_k = \frac{1}{T} \int_0^T dt e^{ik\Omega t} \langle\phi_\alpha(t)|\phi_\beta(t)\rangle = \langle\langle\phi_\alpha|\phi_\beta^{(k)}\rangle\rangle = \delta_{\alpha\beta}\delta_{k,0}$$

→ Floquet states orthogonal at equal times

- propagator in terms of Floquet states

$$U(t, t') = \sum_{\alpha} |\psi_{\alpha}(t)\rangle \langle \psi_{\alpha}(t')| = \sum_{\alpha} e^{-i\epsilon_{\alpha}(t-t')} |\phi_{\alpha}(t)\rangle \langle \phi_{\alpha}(t')|$$

- long-time dynamics (depends on $t - t'$)
- dynamics within driving period (“micro motion”, depends on t and t')

- propagator in terms of Floquet states

$$U(t, t') = \sum_{\alpha} |\psi_{\alpha}(t)\rangle \langle \psi_{\alpha}(t')| = \sum_{\alpha} e^{-i\epsilon_{\alpha}(t-t')} |\phi_{\alpha}(t)\rangle \langle \phi_{\alpha}(t')|$$

- long-time dynamics (depends on $t - t'$)
- dynamics within driving period (“micro motion”, depends on t and t')

- one-period propagator for kicked systems

$$H(t) = H_0 + K \sum_n \delta(t - nT)$$

$$\rightarrow U(T) = e^{-iH_0 T} e^{-iK}$$

- ✓ easy to compute
- ✓ provides quasienergies
- ✗ only long-time dynamics (stroboscopic)

Solve eigenvalue problem

$$\{H(t) - i\partial_t\}|\phi\rangle = \epsilon|\phi\rangle$$

Solve eigenvalue problem

$$\{H(t) - i\partial_t\}|\phi\rangle = \epsilon|\phi\rangle$$

Straightforward in Fourier representation (“Floquet matrix”)

$$H_0 + H_1 \cos(\Omega t) - i \frac{d}{dt} \leftrightarrow \begin{pmatrix} \ddots & \vdots & \vdots & \vdots & \vdots & \vdots & \\ \cdots & H_0 + 2\Omega & \frac{1}{2}H_1 & 0 & 0 & 0 & \cdots \\ \cdots & \frac{1}{2}H_1 & H_0 + \Omega & \frac{1}{2}H_1 & 0 & 0 & \cdots \\ \cdots & 0 & \frac{1}{2}H_1 & H_0 & \frac{1}{2}H_1 & 0 & \cdots \\ \cdots & 0 & 0 & \frac{1}{2}H_1 & H_0 - \Omega & \frac{1}{2}H_1 & \cdots \\ \cdots & 0 & 0 & 0 & \frac{1}{2}H_1 & H_0 - 2\Omega & \cdots \\ & \vdots & \vdots & \vdots & \vdots & \vdots & \ddots \end{pmatrix}$$

- 1 direct diagonalization of $H(t) - i\partial_t$
 - conceptually simple $\rightarrow$ first choice
 - increasingly difficult with smaller frequency
- 2 analytical tool: **perturbation theory**
strong driving: $H_1 \cos(\Omega t) - i\partial_t$ as zeroth order

- 1 direct diagonalization of $H(t) - i\partial_t$
 - conceptually simple $\rightarrow$ first choice
 - increasingly difficult with smaller frequency
- 2 analytical tool: **perturbation theory**
strong driving: $H_1 \cos(\Omega t) - i\partial_t$ as zeroth order
- 3 numerical propagation: $U(T, 0) \rightarrow e^{-i\epsilon T}$ and $|\phi(0)\rangle \rightarrow |\phi(t)\rangle$
- 4 (t, t') formalism (very efficient propagation scheme)
- 5 matrix-continued fractions (convenient for time-dep. Liouvillians)

Starting point: **Rabi-like Hamiltonian** with $1 \ll \langle a^\dagger a \rangle \approx n_0$

$$H = \Omega a^\dagger a + g(a^\dagger + a)X + \dots$$

Classical field / coherent state

$$a \longrightarrow \langle a \rangle = \sqrt{n_0} e^{-i\Omega t}$$

→ driving: $2g\sqrt{n_0} \cos(\Omega t)X$

✓ intuitive

✗ assumes separability

Starting point: **Rabi-like Hamiltonian** with $1 \ll \langle a^\dagger a \rangle \approx n_0$

$$H = \Omega a^\dagger a + g(a^\dagger + a)X + \dots$$

Classical field / coherent state

$$a \longrightarrow \langle a \rangle = \sqrt{n_0} e^{-i\Omega t}$$

→ driving: $2g\sqrt{n_0} \cos(\Omega t)X$

✓ intuitive

✗ assumes separability

New basis: “phase states”

$$|\theta\rangle = \sum_{k=-n_0}^{\infty} e^{-ik\theta} |n_0 - k\rangle$$

→ $H = \Omega(n_0 - i\partial_\theta) + 2g\sqrt{n_0} \cos(\theta)X$


cf. $\mathcal{H} = H(t) - i\partial_t$

✓ entanglement survives


✓ Anandan phase $\leftrightarrow n_0 - \langle a^\dagger a \rangle$

- 1 role of quasienergy crossings
- 2 perturbation theory (two-level approximation)
- 3 basic example of Floquet engineering

Driven double-well potential $H(t) = H_{\text{DW}} + Sx \cos(\Omega t)$




quasienergies $\epsilon_\alpha(S)$




- ? tunnel oscillations influenced by driving
- ? dynamics at quasienergy crossing

Occupation $P_{\text{left}}(nT)$



far from crossing:

■ tunnel oscillations



at crossing:

■ particle stays in left well

→ “coherent destruction of tunneling” by ac field


Grossmann *et al.*, PRL 1991

Analytical understanding → two-level approximation

Driven two-level system

$$H(t) = -\frac{\Delta}{2}\sigma_x + \frac{A}{2}\cos(\Omega t)\sigma_z$$

quasienergy spectrum



Analytical approach for $\Delta \ll \Omega$: high-frequency limit

$$H(t) = -\frac{\Delta}{2}\sigma_x + \frac{A}{2}\cos(\Omega t)\sigma_z$$

- zeroth order propagator

$$U_{\text{dr}}(t, 0) = \exp\left(-\frac{iA}{2\Omega}\sin(\Omega t)\sigma_z\right)$$

- transformation and rotating-wave approximation (i.e. time-average)


$$H(t) \longrightarrow -\frac{\Delta}{2}U_{\text{dr}}^\dagger(t, 0)\sigma_x U_{\text{dr}}(t, 0) \longrightarrow -\frac{\Delta}{2}J_0(A/\Omega)\sigma_x$$

→ tunnel-matrix element renormalized by Bessel function J_0

$$H_{\text{eff}} = \frac{\tilde{\Delta}}{2} \begin{pmatrix} 0 & 1 \\ 1 & 0 \end{pmatrix}$$

■ quasienergies

$$\epsilon_{\pm} = \pm \frac{\Delta}{2} J_0(A/\Omega)$$



$$H_{\text{eff}} = \frac{\tilde{\Delta}}{2} \begin{pmatrix} 0 & 1 \\ 1 & 0 \end{pmatrix}$$


- quasienergies

$$\epsilon_{\pm} = \pm \frac{\Delta}{2} J_0(A/\Omega)$$

- mean energies $E = \epsilon - \Omega(\partial\epsilon/\partial\Omega)$

$$E_{\pm} = \pm \frac{\Delta}{2} \left[J_0(A/\Omega) - \frac{A}{\Omega} J_1(A/\Omega) \right]$$

no need to compute Floquet states!



Bessel function $J_1(x) = \frac{d}{dx} J_0(x)$

$$H(t) = -\frac{\Delta}{2}\sigma_z + \frac{A}{2}\sigma_x \cos(\Omega t)$$

- close to resonance: $\delta = \Delta - \Omega \ll \Delta$, small amplitude: $A \ll \Delta$

$$H(t) = -\frac{\Delta}{2}\sigma_z + \frac{A}{2}\sigma_x \cos(\Omega t)$$

- close to resonance: $\delta = \Delta - \Omega \ll \Delta$, small amplitude: $A \ll \Delta$

$$\mathcal{H}_0 = \frac{\Omega}{2}\sigma_z - i\frac{\partial}{\partial t} \quad \mathcal{H}_1 = \frac{\delta}{2}\sigma_z + \frac{A}{2}\cos(\Omega t)\sigma_x$$

- 2nd order perturbation theory

$$\mathcal{H} \approx \frac{1}{2} \begin{pmatrix} \delta + \frac{A^2}{16\Omega} & A/2 \\ A/2 & -\delta - \frac{A^2}{16\Omega} \end{pmatrix} \quad \begin{array}{l} \text{Rabi Hamiltonian} \\ \text{beyond RWA} \end{array}$$

- absorption maximum at avoided crossing: $\Delta - \Omega_{\text{res}} + \frac{A^2}{16\Omega_{\text{res}}} = 0$:

$$\Omega_{\text{res}} \approx \Delta + \frac{A^2}{16\Delta} \quad \text{Bloch-Siegert shift}$$

Some standard references

■ Classic work:

- Shirley, Phys. Rev. 138, B979 (1965)
- Sambe, Phys. Rev. A 7, 2203 (1973)

■ Reviews:

- Grifoni, Hänggi, Phys. Rep. 304, 229 (1998)
- Hänggi, Chap.5 of “Quantum transport and dissipation” (1998)
<http://www.physik.uni-augsburg.de/theo1/hanggi/Papers/Chapter5.pdf>
- Eckardt, Rev. Mod. Phys. 89, 011004 (2017)

- 1 Proof the Floquet theorem: A T -periodic Hamiltonian has a fundamental matrix of the form $P(t)e^{-iCt}$ with $P(t) = P(t + T)$.
- 2 Perform the perturbation theory for the TLS at high-frequency, $\Delta \ll \Omega$.
- 3 Derive the Rapoport relation $E = \epsilon - \Omega(\partial\epsilon/\partial\Omega)$.
- 4 Compute the Bloch-Siegert shift to order $\mathcal{O}(A^2)$.
- 5 Discretize the loop integral for the Berry phase.
- 6 Given $H(t)$ and an adiabatic eigenstate $|u(t)\rangle$ with energy $E(t)$.
Write the ansatz for adiabatic following in Floquet form.
Which gauge transformations are still allowed?
- 7 Compute numerically the quasienergies of the driven TLS.
- 8 Compute the stability borders of the Mathieu equation.
Hint: assume integer μ and compute the corresponding ω_0^2

1 Floquet & Schrödinger equation


- Geometric phases
- Time-periodicity, Floquet ansatz, and all that

2 Quantum dissipation and transport

- System-bath model
- Floquet-Bloch-Redfield formalism

3 Applications & miscellaneous topics

- LZSM Interference
- Floquet-Gibbs states
- Hidden symmetries
- Floquet degeneracies & topology
- Time-dependent Liouvillians
- Two-color Floquet theory
- Adiabatic Floquet theory
- Floquet scattering theory



Heuristic approach

coupling of qubit to electromagnetic environment $\rightarrow$ sponaneous decay

$$|\psi\rangle \longrightarrow \begin{cases} \sigma_- |\psi\rangle & \text{decay with probability } \alpha \ll 1 \\ |\psi\rangle + |\delta\psi\rangle & \text{no decay, probability } 1 - \alpha \end{cases}$$

- normalization requires $|\delta\psi\rangle = \frac{\alpha}{2} \sigma_+ \sigma_- |\psi\rangle$

Heuristic approach

coupling of qubit to electromagnetic environment $\rightarrow$ sponaneous decay

$$|\psi\rangle \longrightarrow \begin{cases} \sigma_- |\psi\rangle & \text{decay with probability } \alpha \ll 1 \\ |\psi\rangle + |\delta\psi\rangle & \text{no decay, probability } 1 - \alpha \end{cases}$$

- normalization requires $|\delta\psi\rangle = \frac{\alpha}{2}\sigma_+\sigma_-|\psi\rangle$
- corresponding density operator

$$\rho \longrightarrow \rho + \frac{\alpha}{2} \left(2\sigma_- \rho \sigma_+ - \sigma_+ \sigma_- \rho - \rho \sigma_+ \sigma_- \right)$$

- continuous limit with coherent time-evolution $\rightarrow$ master equation

$$\frac{d}{dt}\rho = -i[H, \rho] + \frac{\gamma}{2} \left(2\sigma_- \rho \sigma_+ - \sigma_+ \sigma_- \rho - \rho \sigma_+ \sigma_- \right)$$

Time evolution must conserve

- hermiticity and trace of ρ
- positivity (all eigenvalues of $\rho \geq 0$)

Time evolution must conserve

- hermiticity and trace of ρ
- positivity (all eigenvalues of $\rho \geq 0$)

Fulfilled by a **Markovian** master equation iff of “**Lindblad form**”

$$\frac{d}{dt}\rho = -i[H, \rho] + \sum_n \gamma_n \left(2Q_n \rho Q_n^\dagger - Q_n^\dagger Q_n \rho - \rho Q_n^\dagger Q_n \right)$$

G. Lindblad, Comm. Math. Phys. **48**, 119 (1976)

V. Gorini, J. Math. Phys. **17**, 821 (1976)

- Interpretation: incoherent transitions $|\psi\rangle \rightarrow Q_n|\psi\rangle$

Time evolution must conserve

- hermiticity and trace of ρ
- positivity (all eigenvalues of $\rho \geq 0$)

Fulfilled by a **Markovian** master equation iff of “**Lindblad form**”

$$\frac{d}{dt}\rho = -i[H, \rho] + \sum_n \gamma_n \left(2Q_n \rho Q_n^\dagger - Q_n^\dagger Q_n \rho - \rho Q_n^\dagger Q_n \right)$$

G. Lindblad, Comm. Math. Phys. **48**, 119 (1976)

V. Gorini, J. Math. Phys. **17**, 821 (1976)


- Interpretation: incoherent transitions $|\psi\rangle \rightarrow Q_n|\psi\rangle$

✗ Critique

- request for Markovian evolution unphysical
- axiomatic, not based on physical model
- high-temperature limit typically wrong
i.e. not the Klein-Kramers or the Smoluchowski equation

Caldeira-Leggett model

Magalinskii 1959; Caldeira, Leggett 1981

Coupling of a **system** to **bath of harmonic oscillators**

$$H = H_{\text{system}}(t) + X \sum_{\nu} \gamma_{\nu} (b_{\nu}^{\dagger} + b_{\nu}) + \sum_{\nu} \omega_{\nu} b_{\nu}^{\dagger} b_{\nu}$$

- eliminate bath
- equation of motion for reduced density operator
 - interpretation: bath “measures” system operator X

Total density operator $R \approx \rho \otimes \rho_{\text{bath,eq}}$

$$\dot{R} = -i[H_{\text{total}}, R]$$

2nd order perturbation theory in system-bath coupling

$$\begin{aligned} \frac{d}{dt}\rho = & -i[H_{\text{sys}}, \rho] - i \int_0^{(t-t_0) \rightarrow \infty} d\tau \mathcal{A}(\tau) [X, [\tilde{X}(-\tau), \rho(t-\tau)]_+] \\ & - \int_0^{(t-t_0) \rightarrow \infty} d\tau \mathcal{S}(\tau) [X, [\tilde{X}(-\tau), \rho(t-\tau)]] \end{aligned}$$

- Heisenberg operator $\tilde{X}(-\tau) = U(\tau) X U^\dagger(\tau)$
- bath correlation functions $\mathcal{A}, \mathcal{S}$
- non-Markovian
- short system-bath correlation time: Markov approximation

- anti-symmetric correlation function

$$\mathcal{A}(\tau) = -i\langle[\xi(\tau), \xi(0)]\rangle$$


- Fourier transformed: spectral density $\longrightarrow$ continuum limit

$$\mathcal{A}(\omega) = \pi \sum_{\nu} |\gamma_{\nu}|^2 \delta(\omega - \omega_{\nu}) \longrightarrow J(\omega)$$

- here: Ohmic with cutoff

$$J(\omega) = 2\pi\alpha\omega e^{-\omega/\omega_{\text{cutoff}}}$$

- dimensionless dissipation strength α




■ symmetric bath correlation function

$$S(\tau) = \frac{1}{2} \langle [\xi(\tau), \xi(0)]_+ \rangle$$

$$S(\omega) = J(\omega) \coth\left(\frac{\omega}{2k_B T}\right)$$

$$= \begin{cases} 4\pi\alpha k_B T & \text{high } k_B T \\ 2\pi\alpha\omega & \text{low } k_B T \end{cases}$$




- symmetric bath correlation function

$$S(\tau) = \frac{1}{2} \langle [\xi(\tau), \xi(0)]_+ \rangle$$

$$S(\omega) = J(\omega) \coth\left(\frac{\omega}{2k_B T}\right)$$

$$= \begin{cases} 4\pi\alpha k_B T & \text{high } k_B T \\ 2\pi\alpha\omega & \text{low } k_B T \end{cases}$$



- $S(\omega)$ evaluated at transition frequencies

→ dissipation strength depends on spectrum / coherent dynamics

- Ohmic, short memory times (e.g. for $\gamma < k_B T$)

→ Bloch-Redfield master equation

$$\dot{\rho} = -i[H_S, \rho] + i\gamma[X, \{[H_S, X], \rho\}] - [X, [Q, \rho]]$$

coherent dynamics dissipation decoherence

coherent dynamics enters via $Q = \int_0^\infty d\tau \mathcal{S}(\tau) \tilde{X}(-\tau)$

- Ohmic, short memory times (e.g. for $\gamma < k_B T$)

→ Bloch-Redfield master equation

$$\dot{\rho} = -i[H_S, \rho] + i\gamma[X, \{[H_S, X], \rho\}] - [X, [Q, \rho]]$$

coherent dynamics dissipation decoherence

coherent dynamics enters via $Q = \int_0^\infty d\tau \mathcal{S}(\tau) \tilde{X}(-\tau)$

- not of Lindblad form
 - ✗ positivity might be violated
 - ✓ happens only on unphysically small time scales
- high-temperature limit: Fokker-Planck equation

- Decomposition into energy basis and rotating-wave approximation
- rate equation for the populations (Pauli master equation)

$$\frac{d}{dt}\rho_{\alpha\alpha} = \sum_{\alpha'} \left[w_{\alpha \leftarrow \alpha'} \rho_{\alpha'\alpha'} - w_{\alpha' \leftarrow \alpha} \rho_{\alpha\alpha} \right]$$

with the golden-rule rates

$$w_{\alpha \leftarrow \alpha'} = J(E_{\alpha} - E_{\alpha'}) \left| \langle \phi_{\alpha} | X | \phi_{\alpha'} \rangle \right|^2 n_{\text{th}}(E_{\alpha} - E_{\alpha'})$$

- notice: $-n_{\text{th}}(-\omega) = n_{\text{th}}(\omega) + 1$

- Decomposition into energy basis and rotating-wave approximation
- rate equation for the populations (Pauli master equation)

$$\frac{d}{dt}\rho_{\alpha\alpha} = \sum_{\alpha'} \left[w_{\alpha \leftarrow \alpha'} \rho_{\alpha'\alpha'} - w_{\alpha' \leftarrow \alpha} \rho_{\alpha\alpha} \right]$$

with the golden-rule rates

$$w_{\alpha \leftarrow \alpha'} = J(E_{\alpha} - E_{\alpha'}) \left| \langle \phi_{\alpha} | X | \phi_{\alpha'} \rangle \right|^2 n_{\text{th}}(E_{\alpha} - E_{\alpha'})$$

– notice: $-n_{\text{th}}(-\omega) = n_{\text{th}}(\omega) + 1$

✓ detailed balance: $\frac{w_{\alpha \leftarrow \alpha'}}{w_{\alpha' \leftarrow \alpha}} = e^{-(E_{\alpha} - E_{\alpha'})/k_B T}$

✓ Lindblad form

✗ high-temperature limit typically wrong

full Bloch-Redfield: golden rule for non-diagonal $\rho_{\alpha\beta}$

Driven system $\rightarrow$ noise term becomes time-dependent

$$\dot{\rho} = \dots - [X, [Q(t), \rho]], \quad Q(t) = \int_0^\infty d\tau S(\tau) \tilde{X}(t - \tau, t)$$

Driven system $\rightarrow$ noise term becomes time-dependent

$$\dot{\rho} = \dots - [X, [Q(t), \rho]], \quad Q(t) = \int_0^\infty d\tau S(\tau) \tilde{X}(t - \tau, t)$$

Central idea:

- 1 adapted basis: Floquet states $|\phi_\alpha(t)\rangle \rightarrow$ captures coherent dynamics
- 2 master equation in Floquet basis

$$\frac{d}{dt} \rho_{\alpha\beta} = -i(\epsilon_\alpha - \epsilon_\beta) \rho_{\alpha\beta} + \sum_{\alpha'\beta'} \mathcal{L}_{\alpha\beta, \alpha'\beta'}(t) \rho_{\alpha'\beta'}$$

where $\mathcal{L}(t) = \mathcal{L}(t + T)$

- 3 rotating-wave approximation

$$\frac{d}{dt}\rho_{\alpha\beta} = -i(\epsilon_{\alpha} - \epsilon_{\beta})\rho_{\alpha\beta} + \sum_{\alpha'\beta'} \mathcal{L}_{\alpha\beta,\alpha'\beta'}(t) \rho_{\alpha'\beta'}$$

$$i(\epsilon_{\alpha} - \epsilon_{\beta} - k\Omega)\rho_{\alpha\beta}^{(k)} = \sum_{\alpha',\beta',k'} \mathcal{L}_{\alpha\beta,\alpha'\beta'}^{(k-k')} \rho_{\alpha'\beta'}^{(k')} \quad (\text{if } \rho \text{ is } T\text{-periodic})$$

	Liouvillian	Density operator	Remark
Full RWA	$\mathcal{L}_{\alpha\alpha,\alpha'\alpha'}^{(0)}$	populations only	efficient, Pauli type, analytic calculations
Moderate RWA	$\mathcal{L}_{\alpha\beta,\alpha'\beta'}^{(0)}$	transients	coherent dynamics, depends on BZ (!)
Convolution	full $\mathcal{L}$	time periodic	best Markovian long-time solution


→ full RWA (Pauli master equation)

$$\frac{d}{dt}\rho_{\alpha\alpha} = \sum_{\alpha'} w_{\alpha \leftarrow \alpha'} \rho_{\alpha'\alpha'} - \sum_{\alpha} w_{\alpha' \leftarrow \alpha} \rho_{\alpha\alpha}$$

with the golden-rule rates

$$w_{\alpha \leftarrow \alpha'} = \sum_k J(\epsilon_{\alpha} - \epsilon_{\alpha'} + k\Omega) \left| \sum_{k'} \langle \phi_{\alpha, k+k'} | X | \phi_{\alpha', k} \rangle \right|^2 n_{\text{th}}(\epsilon_{\alpha} - \epsilon_{\alpha'} + k\Omega)$$

- sidebands contribute to $w_{\alpha \leftarrow \alpha'}$
... but NOT as independent states!
- no detailed balance between forward / backward rates



- (many-body) Floquet states
- evaluate rates $w_{\alpha \leftarrow \alpha'}$
- dc current, counting statistics

	Dissipation	Transport
Environment	harmonic oscillators	electron source / drain
Coupling of mode ν	$X(a_\nu^\dagger + a_\nu)$	$c^\dagger c_\nu + c_\nu^\dagger c$
Absorption / tunnel in	$n_{\text{th}}(\omega)$	$f(\epsilon - \mu)$
Emission / tunnel out	$1 + n_{\text{th}}(\omega)$	$1 - f(\epsilon - \mu)$
“Ohmic”	$J(\omega) \propto \omega$	$\Gamma(\omega) = \text{const}$

1 Floquet & Schrödinger equation


- Geometric phases
- Time-periodicity, Floquet ansatz, and all that

2 Quantum dissipation and transport


- System-bath model
- Floquet-Bloch-Redfield formalism

3 Applications & miscellaneous topics

- LZSM Interference
- Floquet-Gibbs states
- Hidden symmetries
- Floquet degeneracies & topology
- Time-dependent Liouvillians
- Two-color Floquet theory
- Adiabatic Floquet theory
- Floquet scattering theory




Landau-Zener-Stückelberg-Majorana Interference



Experiments: Stefan Ludwig (PDI Berlin)
 Jason Petta (UCLA)
 Gang Cao & Guo-Ping Guo (Hefei)

Quantum system in AC-field, $H(t)$




- non-adiabatic transition probability

$$P_{LZ} = e^{-\pi \Delta^2 / 2 \hbar v}$$

Landau, Zener, Stückelberg,
Majorana, 1932


Quantum system in AC-field, $H(t)$



- non-adiabatic transition probability

$$P_{LZ} = e^{-\pi \Delta^2 / 2 \hbar v}$$

Landau, Zener, Stückelberg,
Majorana, 1932



- beam splitter, interference
- Landau-Zener-(Stückelberg-Majorana) interferometry


$$H(t) = \frac{\Delta}{2}\sigma_x + \frac{g(t)}{2}\sigma_z \quad g(t) = \epsilon + A\cos(\Omega t)$$

1 (avoided) crossing requires $A > |\epsilon|$

$$H(t) = \frac{\Delta}{2}\sigma_x + \frac{g(t)}{2}\sigma_z \quad g(t) = \epsilon + A\cos(\Omega t)$$


- 1 (avoided) crossing requires $A > |\epsilon|$
- 2 relative phase between dominant paths

adiabatic: $P_{LZ} \ll 1$



$$\varphi(T) = \int_0^T dt |g(t)|$$

diabatic: $1 - P_{LZ} \ll 1$




$$\varphi(T) = \int_0^T dt g(t)$$

→ fringes for $\varphi(T) = 2\pi k$

$$H(t) = \frac{\Delta}{2}\sigma_x + \frac{g(t)}{2}\sigma_z \quad g(t) = \epsilon + A\cos(\Omega t)$$

- 1 (avoided) crossing requires $A > |\epsilon|$
- 2 relative phase between dominant paths


adiabatic: $P_{LZ} \ll 1$



$$\varphi(T) = \int_0^T dt |g(t)|$$



→ fringes for $\varphi(T) = 2\pi k$



diabatic: $1 - P_{LZ} \ll 1$




$$\varphi(T) = \int_0^T dt g(t) = \epsilon T$$

$\epsilon = k\Omega$ “ k -photon resonance”







E.g. excitation probability of a TLS:




DC current:

$$I(t) = e_0 \Gamma_R \langle n_R(t) \rangle \rightarrow \overline{\langle n_R(t) \rangle}^T$$




Forster *et al.*, PRL 2014



Dispersive frame:
effective cavity frequency


$$\omega_0 \longrightarrow \omega_0 + \frac{g^2}{\epsilon_{\text{qb}} - \omega_0} \sigma_z$$



Theory for readout of
driven system?

Koski *et al.*, PRL 2018

Qubit-cavity Hamiltonian



$$H = H_{\text{sys}}(t) + gZ(a^\dagger + a) + \omega_0 a^\dagger a$$

- Backaction: cavity $\rightarrow$ qubit $\rightarrow$ cavity
- Cavity equation (input/output formalism)

$$\frac{d}{dt}a = -i\omega_0 a - \frac{\kappa}{2}a - \sum_{\nu=1,2} \sqrt{\kappa_\nu} a_{\text{in},\nu} - igZ$$

- (non equilibrium) Kubo formula $Z(t) = g \int dt' \chi(t-t') a(t')$
with the response function (may depend on the initial state!)

$$\chi(t) = -i \langle [Z(t), Z] \rangle \theta(t-t')$$

$$\rightarrow -i\omega a = -i(\omega_0 + g^2 \chi(\omega)) a - \frac{\kappa}{2} a - \sum_{\nu=1,2} \sqrt{\kappa_\nu} a_{\text{in},\nu}$$

- measured quantity: (non-equilibrium) susceptibility

Response of periodically driven system

$$\chi(t, t') = -i \langle [Z(t), Z(t')] \rangle_{\text{non-eq}} = \chi(t+T, t'+T)$$

such that

$$\chi(t, t - \tau) = \sum_k e^{-ik\Omega t} \int d\omega e^{-i\omega\tau} \chi^{(k)}(\omega)$$


Response of periodically driven system

$$\chi(t, t') = -i \langle [Z(t), Z(t')] \rangle_{\text{non-eq}} = \chi(t+T, t'+T)$$

such that

$$\chi(t, t - \tau) = \sum_k e^{-ik\Omega t} \int d\omega e^{-i\omega\tau} \chi^{(k)}(\omega)$$

- resonant cavity driving, $\omega = \omega_0$
- response $Z(t)$ acquires sidebands
- good cavity limit, $\kappa \ll \omega_0, \Omega$



Relevant component:

$$\chi^{(0)}(\omega_0) = \sum_{\beta, \alpha, k} \frac{(p_\alpha - p_\beta) |Z_{\beta\alpha, k}|^2}{\epsilon_\alpha - \epsilon_\beta + \omega_0 + k\Omega + i\gamma/2}$$

- Floquet theory $\rightarrow$ quasi-energies ϵ_α
- Floquet-Bloch-Redfield $\rightarrow$ populations p_α

Relevant component:

$$\chi^{(0)}(\omega_0) = \sum_{\beta, \alpha, k} \frac{(p_\alpha - p_\beta) |Z_{\beta\alpha, k}|^2}{\epsilon_\alpha - \epsilon_\beta + \omega_0 + k\Omega + i\gamma/2}$$

- Floquet theory $\rightarrow$ quasi-energies ϵ_α
- Floquet-Bloch-Redfield $\rightarrow$ populations p_α

Resonance conditions

cavity response:


$$\Delta\epsilon = \omega_0 + k\Omega$$

cf. population:

$$\Delta\epsilon = k\Omega$$

e.g. Ivakhnenko *et al.*, Phys.Rep. 2023

$\rightarrow$ Agree only for low-frequency oscillator!




Double QD in GaAs

→ two-level system


Koski *et al.*, PRL 2018

(yellow: heuristic theory)




Present theory

SK, PRA 2018




Chen *et al.*, Phys. Rev. B **103**, 205428 (2021)



Experiment (Cao & Guo, Hefei)

- holes in LZSM pattern
- GaAs DQD → two-level sys.



Experiment (Cao & Guo, Hefei)


- holes in LZSM pattern
- GaAs DQD → two-level sys.

Recap: susceptibility (two-level system)

$$\chi^{(0)}(\omega_0) = (p_0 - p_1) \sum_k \frac{|Z_{10,k}|^2}{\epsilon_1 - \epsilon_0 + \omega_0 + k\Omega + i\gamma/2}$$


response determined by

- resonance condition for cavity signal
- Floquet state population




- competing resonance conditions
 - holes in fringes when $p_0 \approx p_1 \approx 1/2$
- cavity response provides information about Floquet state population

Readout for ultra-strong coupling





Gu *et al.*, Phys. Rev. Lett. **120**, 2333602 (2023)



Experiment (Cao & Guo, Hefei)

- two DQDs interacting via cavity
- DQD-cavity coupling large



Experiment (Cao & Guo, Hefei)

- two DQDs interacting via cavity
- DQD-cavity coupling large


Theory


- (too) simple generalization:

$$\chi = \sum_{\text{all DQDs}} \chi_{\text{DQD}}$$

- transmission > 1
- lasing? No!

→ beyond linear response regime





Perturbation: **mirror**

$$H_1 = -i \sum_{\ell=L,R} \sqrt{\kappa_\ell} a_{\text{in},\ell}^\dagger a + \text{H.c.}$$


Corresponding susceptibility



$$\chi(t, t') = -i \langle [a(t), a^\dagger(t')] \rangle \theta(t - t')$$

Transmission amplitude (Fourier component $k = 0$, evaluated at ω_0)

$$S_{12}(\omega) = -i \sqrt{\kappa_1 \kappa_2} \chi^{(0)}(\omega)$$


Gu *et al.*, PRL 2023







Experiment vs. theory

- inhomogeneous broadening
- includes DQD-DQD interaction via cavity



Dissipation at conical intersections



SK, Phys. Rev. A **110**, 052218 (2024)

SK, J. Chem. Phys. **162**, 154101 (2025)

Stationary state of driven dissipative quantum system


mean energy: $p_{\alpha} \propto e^{-E_{\alpha}/kT}$

quasi energy: $p_{\alpha} \propto e^{-q_{\alpha}/kT}$


Stationary state of driven dissipative quantum system

mean energy: $p_\alpha \propto e^{-E_\alpha/kT}$

quasi energy: $p_\alpha \propto e^{-q_\alpha/kT}$




mean-energy state



(anti-) Floquet-Gibbs state

$$H(t) = \frac{\Delta}{2}\sigma_x + \frac{A}{2}\sigma_z \cos(\Omega t)$$




■ spatio-temporal symmetry G :

$$\sigma_x \text{ \& \; } (t \rightarrow t + T/2)$$

→ even / odd states


$$H(t) = \frac{\Delta}{2}\sigma_x + \frac{A}{2}\sigma_z \cos(\Omega t) + \frac{\epsilon}{2}\sigma_z$$



■ spatio-temporal symmetry G :

$$\sigma_x \text{ \& \; } (t \rightarrow t + T/2)$$

→ even / odd states




with detuning


■ quasienergies: **anti-crossing**

■ mean energies: **exact crossing**

quasienergy



mean energy



On circle around tip:

- constant quasienergy
- maximal variation of mean energy


Two-state approximation for ϕ_0

■ basis: φ_- / φ_+ at tip

■ $\vartheta = 0 \longrightarrow \vartheta = \pi$:

$$\phi_0 \longrightarrow \phi_1$$

$$p_0 \longrightarrow p_1 = 1 - p_0$$





Two-state approximation for ϕ_0

■ basis: φ_- / φ_+ at tip

■ $\vartheta = 0 \longrightarrow \vartheta = \pi$:

$$\phi_0 \longrightarrow \phi_1$$

$$p_0 \longrightarrow p_1 = 1 - p_0$$



Population for σ_x -coupling

- angles with $p_0 = p_1 = 1/2$
 - full mixture, max. entropy
- behaves like mean energy of ϕ_0

cf. discontinuity along A -axis

Engelhardt *et al.*, PRL 2019

Golden-rule rate with $S_{01}(t) = \langle \phi_0(t) | S | \phi_1(t) \rangle \rightarrow$ sidebands S_k

Generic

- Ohmic $J(\omega) = \frac{\pi}{2} \alpha \omega$

$\rightarrow k = 0$ suppressed

Golden-rule rate with $S_{01}(t) = \langle \phi_0(t) | S | \phi_1(t) \rangle \rightarrow$ sidebands S_k

Generic


■ Ohmic $J(\omega) = \frac{\pi}{2} \alpha \omega$

$\rightarrow k = 0$ suppressed

Exception: $S = \sigma_z$


■ time-independent for large Ω

$\rightarrow k \neq 0$ suppressed




■ Crossover to Floquet-Gibbs:
two lines with $p_0 = 1/2$ merge
with increasing Ω

$\rightarrow$ Measurable signature of
 σ_z -coupling




Bath coupling via σ_z



→ experimental signature of bath coupling operator


* for DQD and cavity of Chen *et al.*, PRB 2021, $\Omega/2\pi = 10$ GHz

Bath coupling via σ_x



→ experimental signature of bath coupling operator

* for DQD and cavity of Chen *et al.*, PRB 2021, $\Omega/2\pi = 10$ GHz



- zero bias
 - no interaction
 - no spin
- master eq. for populations P_i

$$\frac{d}{dt} \begin{pmatrix} P_L \\ P_R \end{pmatrix} = \begin{pmatrix} -\Gamma_L & \Gamma_R \\ \Gamma_L & -\Gamma_R \end{pmatrix} \begin{pmatrix} P_L \\ P_R \end{pmatrix}$$

(numerics: beyond RWA)

Special case $\Gamma_L = \Gamma_R$:

$$P = \sum_k f(q + k\Omega - \mu) \langle \phi_k | \phi_k \rangle$$


Special case $\Gamma_L = \Gamma_R$:

$$P = \sum_k f(q + k\Omega - \mu) \langle \phi_k | \phi_k \rangle$$

use $f(x) \approx \frac{1}{2} + \frac{x}{2k_B T}$

$$P \approx f(E - \mu)$$

→ mean-energy state




Special case $\Gamma_L = \Gamma_R$:

$$P = \sum_k f(q + k\Omega - \mu) \langle \phi_k | \phi_k \rangle$$

use $f(x) \approx \frac{1}{2} + \frac{x}{2k_B T}$

$$P \approx f(E - \mu)$$

→ mean-energy state




Mean energy state

- dissipation:
(almost) any bath coupling
- intermediate / high
temperature $kT \gtrsim \hbar\Omega$
- open TLS: $\Gamma_L \approx \Gamma_R$

Floquet-Gibbs state


- huge driving frequency,
 $\hbar\Omega \gtrsim 25\Delta$
- coupling to environment
via σ_z or $\Gamma_L \approx \Gamma_R$

Hidden Symmetries in Floquet Systems




SK & Casado-Pascual, Quantum **10**, 2112 (2026)

■ Spectra of classically chaotic systems




Haake, book
on Q. Chaos

→ level repulsion → anti crossings




Bohigas 1983

■ Spectra of classically chaotic systems



Haake, book
on Q. Chaos

→ level repulsion → anti crossings




Bohigas 1983

■ symmetry: Hamiltonian block diagonal (here: even/odd)


$$H = \begin{pmatrix} H_+ & 0 \\ 0 & H_- \end{pmatrix}$$

→ allows exact level crossings

■ Spectra of classically chaotic systems



Haake, book
on Q. Chaos



Bohigas 1983

→ level repulsion → anti crossings

■ symmetry: Hamiltonian block diagonal (here: even/odd)

$$H = \begin{pmatrix} H_+ & 0 \\ 0 & H_- \end{pmatrix}$$

→ allows exact level crossings

→ Exact level crossings indicate symmetries / integrals of motion


TLS Hamiltonian

$$H(t) = \beta\sigma_x + \alpha\sigma_z \cos(\Omega t)$$

generalized parity $G = \sigma_x e^{(T/2)\partial_t}$

→ even / odd states

→ exact crossings Peres, PRL 1991




TLS Hamiltonian

$$H(t) = \beta\sigma_x + \alpha\sigma_z \cos(\Omega t)$$

generalized parity $G = \sigma_x e^{(T/2)\partial_t}$

→ even / odd states

→ exact crossings Peres, PRL 1991



High-frequency approximation

$$q_{\pm} = \pm\beta J_0(2\alpha/\Omega)$$

TLS Hamiltonian



$$H(t) = \beta\sigma_x + \alpha\sigma_z \cos(\Omega t) + \frac{n\Omega}{2}\sigma_z$$

generalized parity $G = \sigma_x e^{(T/2)\partial_t}$

High-frequency approximation

$$q_{\pm} = \pm\beta J_0(2\alpha/\Omega) \longrightarrow \pm\beta J_n(2\alpha/\Omega)$$


■ suggests that crossings are exact



$$H(t) = \beta\sigma_x + \alpha\sigma_z \cos(\Omega t) + \frac{\epsilon}{2}\sigma_z$$

Quasienergy splittings tiny at
isolated points


(intermediate frequency,
beyond Bessel function approx.)



$$H(t) = \beta \sigma_x + \alpha \sigma_z \cos(\Omega t) + \frac{\epsilon}{2} \sigma_z$$

Quasienergy splittings tiny at isolated points

(intermediate frequency, beyond Bessel function approx.)



- crossings exact for integer detuning ?
- underlying symmetry / integral of motion ?

- time-independent: integral of motion $[H, J] = 0$
- for time-dependent system: $[H(t) - i\partial_t, J(t)] = 0$

Lewis & Riesenfeld, J. Math. Phys. 1969

- time-independent: integral of motion $[H, J] = 0$
- for time-dependent system: $[H(t) - i\partial_t, J(t)] = 0$

Lewis & Riesenfeld, J. Math. Phys. 1969

- ansatz for time non-local LR invariant: $J(t) = Q(t)e^{(T/2)\partial_t}$
[motivation: for $\epsilon = 0 \rightarrow Q = \sigma_x$]

$$i\partial_t Q = \left[\frac{\epsilon}{2}\sigma_z + \beta\sigma_x, Q \right] + \{ \alpha\sigma_z, Q \} \cos(\Omega t)$$

- time-independent: integral of motion $[H, J] = 0$
- for time-dependent system: $[H(t) - i\partial_t, J(t)] = 0$

Lewis & Riesenfeld, J. Math. Phys. 1969

- ansatz for time non-local LR invariant: $J(t) = Q(t)e^{(T/2)\partial_t}$
[motivation: for $\epsilon = 0 \rightarrow Q = \sigma_x$]

$$i\partial_t Q = \left[\frac{\epsilon}{2} \sigma_z + \beta \sigma_x, Q \right] + \{ \alpha \sigma_z, Q \} \cos(\Omega t)$$

- trivial (and useless) solution: projector on Floquet state

$$J = |\phi_\ell(t)\rangle\langle\phi_\ell(t)| \rightarrow Q = |\phi_\ell(t)\rangle\langle\phi_\ell(t + T/2)|$$

depends on state $\ell \rightarrow$ cannot be used to classify state


- 1 Fourier ansatz $Q(t) = \sum_k e^{-ikt} Q_k$
 - 2 matrix recurrence relation
 - 3 scalar recurrence
 - 4 $\epsilon/\Omega = n = \text{integer}$: recurrence terminates at $k_{\max} = n$
 - 5 $J^2 = 1$, i.e. $\mathbb{Z}_2$ symmetry
- eigenvalues $j = \pm 1$, “even / odd” Floquet states

- 1 Fourier ansatz $Q(t) = \sum_k e^{-ikt} Q_k$
 - 2 matrix recurrence relation
 - 3 scalar recurrence
 - 4 $\epsilon/\Omega = n = \text{integer}$: recurrence terminates at $k_{\max} = n$
 - 5 $J^2 = 1$, i.e. $\mathbb{Z}_2$ symmetry
- eigenvalues $j = \pm 1$, “even / odd” Floquet states

Such $J = Qe^{(T/2)\partial_t}$ exists for any integer value of ϵ/Ω


For $\epsilon = \Omega$

$$Q(t) = \frac{1}{\sqrt{\alpha^2 + \beta^2}} \begin{pmatrix} \beta & \alpha e^{-i\Omega t} \\ -\alpha e^{i\Omega t} & \beta \end{pmatrix} \quad \text{with} \quad J^2 = QQ^\dagger = 1$$




For $\epsilon = \Omega$

$$Q(t) = \frac{1}{\sqrt{\alpha^2 + \beta^2}} \begin{pmatrix} \beta & \alpha e^{-i\Omega t} \\ -\alpha e^{i\Omega t} & \beta \end{pmatrix} \quad \text{with} \quad J^2 = QQ^\dagger = 1$$




For $\epsilon = \Omega$

$$Q(t) = \frac{1}{\sqrt{\alpha^2 + \beta^2}} \begin{pmatrix} \beta & \alpha e^{-i\Omega t} \\ -\alpha e^{i\Omega t} & \beta \end{pmatrix} \quad \text{with} \quad J^2 = QQ^\dagger = 1$$




→ accidental degeneracy due to hidden symmetry


- numerical iteration: J with eigenvalues $j = +1$ and $j = -1$



Topological charges at Floquet degeneracies




SK & Guéry-Odelin, arXiv:0926.00975



Varying B -field in xz plane

$$H = x(t)\sigma_x + z(t)\sigma_z, \quad E_{\pm} = \pm\sqrt{x^2 + z^2} = \pm|\mathbf{r}|$$

Berry phase = half solid angle: $\pm\pi$ or 0



Varying B -field in xz plane

$$H = x(t)\sigma_x + z(t)\sigma_z, \quad E_{\pm} = \pm\sqrt{x^2 + z^2} = \pm|\mathbf{r}|$$

Berry phase = half solid angle: $\pm\pi$ or 0

Berry curvature and potential

$$\gamma = \oint_C d\mathbf{r} \cdot \langle u | i\partial_{\mathbf{r}} | u \rangle = \int_F d^2\mathbf{f} \cdot \boldsymbol{\Omega}, \quad \Omega_{\kappa} = i\epsilon_{\kappa\mu\nu} \langle \partial_{\mu} u | \partial_{\nu} u \rangle$$

■ For real Hamiltonian: $\boldsymbol{\Omega} = \mathbf{0}$ — unless singular cf. $\Delta \frac{1}{r} = -4\pi\delta(\mathbf{r})$

→ $\boldsymbol{\Omega} = \pi\delta(\mathbf{r})$

→ Dirac cone has topological charge (formally a magnetic monopole)

T -periodic Hamiltonian with
slowly varying parameter

$$H(\mathbf{x}(t), t)$$

T -periodic Hamiltonian with
slowly varying parameter

$$H(\mathbf{x}(t), t)$$

- Floquet adiabatic theorem

$$|\psi(t)\rangle = e^{i\varphi(t)} |\phi(\mathbf{x}(t), t)\rangle$$

Floquet state $|\phi(\mathbf{x}, t)\rangle$ for fixed $\mathbf{x}$

- Equation of motion for phase

$$\dot{\varphi} = -q + \dot{\mathbf{x}} \cdot \langle \phi | i \partial_{\mathbf{x}} | \phi \rangle$$

P. Weinberg *et al.*, Phys. Rep. 2017

T -periodic Hamiltonian with slowly varying parameter

$$H(\mathbf{x}(t), t)$$

- Floquet adiabatic theorem

$$|\psi(t)\rangle = e^{i\varphi(t)} |\phi(\mathbf{x}(t), t)\rangle$$

Floquet state $|\phi(\mathbf{x}, t)\rangle$ for fixed $\mathbf{x}$

- Equation of motion for phase

$$\dot{\varphi} = -q + \dot{\mathbf{x}} \cdot \langle \phi | i\partial_{\mathbf{x}} | \phi \rangle$$

- Dynamical phase $\leftrightarrow$ quasienergy


$$\varphi_{\text{dyn}} = -q(t_f - t_0)$$

- Floquet-Berry phase

$$\gamma_{\text{FB}} = \oint d\mathbf{x} \cdot \langle \langle \phi(\mathbf{x}) | i\partial_{\mathbf{x}} | \phi(\mathbf{x}) \rangle \rangle$$

formally like Berry,
but now in Sambe space


- only difference:
 T_{loop}/T must be integer



- 1 Quasienergies form Dirac cones
- 2 Floquet-Berry phase

→ **Topological charges ?**

Regions with tiny splitting



→ isolated degeneracy points

Two types of degeneracies:

- 1 integer detuning
- 2 m -photon resonance

$$E_e - E_g = m\Omega$$


Floquet states for $A = 0$:

$$|g\rangle \text{ and } e^{im\Omega t}|e\rangle$$

both with quasienergy E_g

- Topological charge?
- How to detect it?

- FB loop integral for circle around (ϵ, A)
- detects topologically non-trivial points



Integer detuning

- perturbation theory like above
- Dirac cones
- topological charge

m -photon resonance


- lowest order perturbation $\propto A^m$

$$\mathbf{B}_{\text{eff}} = (\epsilon - \epsilon_0, 0, \beta_m A^m)$$


winds around degeneracy for odd m only

- topological charge iff m odd

- start at $\epsilon = A = 0$
- loop with $A \rightarrow A_{\max}$
encloses n degeneracies
- ✓ $\gamma_{\text{FB}} = n\pi \pmod{2\pi}$
- ✗ dynamical phase dominates



- start at $\epsilon = A = 0$
- loop with $A \rightarrow A_{\max}$
encloses n degeneracies
- ✓ $\gamma_{\text{FB}} = n\pi \pmod{2\pi}$
- ✗ dynamical phase dominates



Chirality of $\mathcal{H}(t) = \frac{\Delta}{2}\sigma_x + \frac{1}{2}[\epsilon + A\cos(\Omega t)]\sigma_z - i\partial_t$

Unitary mapping in Sambe space

$$S = \sigma_y \otimes (t \rightarrow -t)$$

$$\rightarrow S\mathcal{H}(t)S^{-1} = -\mathcal{H}(-t)$$

links Floquet states




$$\sigma_y|\phi_-(t)\rangle = |\phi_+(-t)\rangle$$

$$\sigma_y|\phi_-(kT)\rangle = |\phi_+(+kT)\rangle$$

$$\blacksquare q_- = -q_+$$

$\rightarrow$ opposite dynamical phase

$$|\psi_{\text{initial}}\rangle = |g\rangle \longrightarrow |\psi_{\text{final}}\rangle = e^{i\gamma} |\psi_{\text{initial}}\rangle$$





$$\rightarrow \gamma_{\text{FB}} = n\pi \pmod{2\pi}$$

■ sufficient fidelity:

$$T_{\text{loop}} \gtrsim 100 T$$

$$|\psi_{\text{initial}}\rangle = |g\rangle \longrightarrow |\psi_{\text{final}}\rangle = e^{i\gamma} |\psi_{\text{initial}}\rangle$$





$$\rightarrow \gamma_{\text{FB}} = n\pi \pmod{2\pi}$$

■ sufficient fidelity:

$$T_{\text{loop}} \gtrsim 100T$$

■ jumps at odd- m resonances only

■ requires larger T_{loop}



Possible measurement: Ramsey interference

Periodically time-dependent Liouvillians

$$\frac{d}{dt}P = L(t)P$$

Master equation of type

$$\frac{d}{dt}P = L(t)P$$

- Floquet-Bloch-Redfield beyond moderate RWA
- time-dependent system with Lindblad dissipator

$$\dot{\rho} = -i[H(t), \rho] + \gamma(2a^\dagger \rho a - a^\dagger a \rho - \rho a^\dagger a)$$

- very weak dissipation
- transport problem with large bias

- long-time solution T -periodic
- Floquet ansatz with “quasienergy” zero

$$P(t) = \sum_k e^{-ik\Omega t} p_k$$

$$\frac{d}{dt}P = L(t)P \text{ with}$$

$$L(t) = L_0 + 2L_1 \cos(\Omega t)$$

→ kernel of tridiagonal Floquet matrix

$$L_0 + 2L_1 \cos(\Omega t) - \partial_t \leftrightarrow \begin{pmatrix} \ddots & \vdots & \vdots & \vdots & \vdots & \vdots & \\ \cdots & L_0 + 2i\Omega & L_1 & 0 & 0 & 0 & \cdots \\ \cdots & L_1 & L_0 + i\Omega & L_1 & 0 & 0 & \cdots \\ \cdots & 0 & L_1 & L_0 & L_1 & 0 & \cdots \\ \cdots & 0 & 0 & L_1 & L_0 - i\Omega & L_1 & \cdots \\ \cdots & 0 & 0 & 0 & L_1 & L_0 - 2i\Omega & \cdots \\ & \vdots & \vdots & \vdots & \vdots & \vdots & \ddots \end{pmatrix}$$

- ansatz $P(t) = \sum_k e^{-ik\Omega t} p_k$ yields

$$L_1 p_{k-1} + (L_0 + ik\Omega) p_k + L_1 p_{k+1} = 0$$

- idea: truncate and iterate $p_{k-1} = -L_1^{-1} \{ (L_0 - ik\Omega) p_k + L_1 p_{k+1} \}$

- ansatz $P(t) = \sum_k e^{-ik\Omega t} p_k$ yields

$$L_1 p_{k-1} + (L_0 + ik\Omega) p_k + L_1 p_{k+1} = 0$$

- idea: truncate and iterate $p_{k-1} = -L_1^{-1} \{ (L_0 - ik\Omega) p_k + L_1 p_{k+1} \}$
✗ fails, L_1 generally singular

- ansatz $P(t) = \sum_k e^{-ik\Omega t} p_k$ yields

$$L_1 p_{k-1} + (L_0 + ik\Omega) p_k + L_1 p_{k+1} = 0$$

- idea: truncate and iterate $p_{k-1} = -L_1^{-1} \{ (L_0 - ik\Omega) p_k + L_1 p_{k+1} \}$
 $\times$ fails, L_1 generally singular
- solution: ansatz $p_k = S_k L_1 p_{k\mp 1}$ ($k \gtrless 0$) leads to

$$S_k = - (L_0 + ik\Omega + L_1 S_{k\pm 1} L_1)^{-1} \longrightarrow S_{\pm 1} \quad (1)$$


$$0 = (L_1 S_{-1} L_1 + L_0 + L_1 S_1 L_1) p_0 \quad (2)$$

- truncate at $\pm k_0$, iterate (1), and solve (2)
- time-averaged $P(t) = p_0 \rightarrow$ time-averaged expectation values

Risken, "The Fokker-Planck Equation"

Appendix of Forster *et al.*, PRB 2015



LZSM Interference for Bichromatic Driving





Forster, Mühlbacher, Blattmann, Schuh, Wegscheider, Ludwig & SK

PRB **92**, 245422 (2015)


- $g(t) = \cos(\Omega t) + \eta \cos(\Omega' t + \phi)$
 Ω', Ω commensurable vs. incommensurable
 $\rightarrow g(t)$ periodic vs. quasi-periodic



- $g(t) = \cos(\Omega t) + \eta \cos(\Omega' t + \phi)$
 Ω', Ω commensurable vs. incommensurable
 $\rightarrow g(t)$ periodic vs. quasi-periodic



- quasi-periodic:
 - dynamical phases (quasi) random
 - ? regular LZSM pattern, symmetries



E.g. Lindblad approach:

- source-to-dot tunneling

$$|\psi\rangle \longrightarrow c_1^\dagger |\psi\rangle$$

$$\rightarrow \dot{\rho} = \dots + \Gamma \left(c_1^\dagger \rho c_1 - \frac{1}{2} c_1 c_1^\dagger \rho - \frac{1}{2} \rho c_1 c_1^\dagger \right)$$

$$\frac{d}{dt} P = L(t)P \quad \text{where} \quad L(t) = -i[H_{\text{DQD}}(t), \cdot] + L_{\text{in}} + L_{\text{out}}$$

Quantum master equation

$$\frac{d}{dt}\rho = L(t)\rho \quad \text{with} \quad L(t) = L_0 + L_1 \cos(n\Omega t) + L'_1 \cos(n'\Omega t)$$

Quantum master equation

$$\frac{d}{dt}\rho = L(t)\rho \quad \text{with} \quad L(t) = L_0 + L_1 \cos(n\Omega t) + L'_1 \cos(n'\Omega t)$$

- long-time solution periodic, “Floquet solution with eigenvalue 0”

$$\rho(t) = \rho(t + 2\pi/\Omega) = \sum_k e^{-ik\Omega t} \rho_k$$

- homogeneous set of equations for ρ_k
- ρ_0 , time-averaged expectation values, e.g. dc current

- $\frac{d}{dt}\rho = L(t)\rho$ with

$$L(t) = L_0 + L_1 \cos(\Omega t) + L'_1 \cos(\omega t)$$

- auxiliary angular coordinate $\omega t \longrightarrow \theta$

$$\frac{d}{dt}\mathcal{P} = \mathcal{L}(t, \theta)\mathcal{P}$$

$$\mathcal{L}(t, \theta) = L_0 + L_1 \cos(\Omega t) + L'_1 \cos(\theta) - \omega \frac{\partial}{\partial \theta}$$

- $2\pi/\Omega$ -periodic time-dependence
- solve by usual Floquet tools — here: **matrix-continued fractions**

- $\frac{d}{dt}\rho = L(t)\rho$ with

$$L(t) = L_0 + L_1 \cos(\Omega t) + L'_1 \cos(\omega t)$$


- auxiliary angular coordinate $\omega t \longrightarrow \theta$

$$\frac{d}{dt}\mathcal{P} = \mathcal{L}(t, \theta)\mathcal{P}$$


$$\mathcal{L}(t, \theta) = L_0 + L_1 \cos(\Omega t) + L'_1 \cos(\theta) - \omega \frac{\partial}{\partial \theta}$$

- $2\pi/\Omega$ -periodic time-dependence
- solve by usual Floquet tools — here: **matrix-continued fractions**
 - connection $\rho(t) = \mathcal{P}(t, \theta)|_{\theta=\omega t}$


cf. t - t' formalism, see Peskin & Moiseyev, J.Chem.Phys. 1993




- $g(t) = \sin(\Omega t) + \eta \sin(2\Omega t + \phi)$
[4.8 GHz, $\eta = 1.25$]
- pattern asymmetric ...



- $g(t) = \sin(\Omega t) + \eta \sin(2\Omega t + \phi)$
[4.8 GHz, $\eta = 1.25$]
- pattern asymmetric ...



- ... and ϕ -dependent
- phase calibration




■ golden ratio $\frac{\Omega_2}{\Omega_1} = \frac{1 + \sqrt{5}}{2}$


→ pattern symmetric
and ϕ -independent

Forster *et al.*, PRB 2015

Dispersive readout of LZSM patterns in Si/SiGe DQDs (under low-frequency driving)




Mi, SK, Petta, Phys. Rev. B **98**, 161404(R) (2018)




Level structure

- strain, confinement
- valley splitting
- valley qubit




P2 (To Cavity)



J. Petta, U Princeton

Si double quantum dots

- position, spin, valley
- coupling to cavity
- “dispersive readout”



Experiment (J.R. Petta, Princeton)

- very slow driving: 50–100 MHz
→ non-eq. population tiny
- heuristic resonance condition:
$$\bar{E}_1 - \bar{E}_0 = \omega_{\text{cavity}} + k\Omega$$

(mean energies!)

Computational problem:

- amplitude: up to 300 GHz
→ Floquet theory requires
 $\gtrsim 10^4$ sidebands

■ adiabatic eigenstates $H(t)|u(t)\rangle = (\bar{E} + \delta E(t))|u(t)\rangle$


→ $|\psi(t)\rangle = e^{-i\bar{E}t} e^{i\varphi(t)} |u(t)\rangle$

→ adiabatic Floquet states

$$|\phi(t)\rangle = e^{i\varphi(t)} |u(t)\rangle \quad \text{with} \quad \varphi(t) = - \int_0^t dt' \delta E(t') \quad T \text{ periodic!}$$

with quasienergies $\epsilon = \bar{E} = \frac{1}{T} \int_0^T dt E(t)$

[here: time-reversal symmetry → $\langle u | \partial_t | u \rangle = 0$, i.e., no Berry phase]





Dressed-state interpretation

■ LZSM between states


$$|g, 1\rangle, |e, 0\rangle$$

→ cavity-assisted LZSM

Mi, SK, Petta, PRB 2018




Floquet scattering theory




SK, Lehmann, Hänggi, Phys. Rep. **406**, 379 (2005)

- Landauer (1957): “conductance is transmission”



- Landauer (1957): “conductance is transmission”



- current

$$I = \frac{e}{h} \int dE \, T(E) [f(E + eV) - f(E)]$$

- transmission of an electron with energy E

$$T(E) = \Gamma_L \Gamma_R |\langle 1 | G(E) | N \rangle|^2$$


Fischer, Lee, PRB 1981; Meir, Wingreen, PRL 1992

- ac bias voltage:

$$V_0 \longrightarrow V_0 + V_{\text{ac}} \cos(\Omega t)$$


- time-dependent energy shift by $eV_{\text{ac}} \cos(\Omega t)$

$$e^{-iEt} \longrightarrow \exp\left(-iEt - i\frac{eV_{\text{ac}}}{\Omega} \sin(\Omega t)\right)$$



- ac bias voltage:

$$V_0 \longrightarrow V_0 + V_{\text{ac}} \cos(\Omega t)$$



- time-dependent energy shift by $eV_{\text{ac}} \cos(\Omega t)$

$$e^{-iEt} \longrightarrow \exp\left(-iEt - i\frac{eV_{\text{ac}}}{\Omega} \sin(\Omega t)\right) = \sum_k J_k(eV_{\text{ac}}/\Omega) e^{-i(E+k\Omega)t}$$

- sidebands occupied with probability $J_k^2(\dots)$
- energy $k\Omega$ corresponds to additional DC bias voltage $k\Omega/e$

$$I(V_0, V_{\text{ac}}) = \sum_k J_k^2\left(\frac{eV_{\text{ac}}}{\Omega}\right) I_0(V_0 + k\Omega/e)$$

DC conductivity determines the current !

- Approach rather heuristic
- Rigorous derivation?
- When is Tien-Gordon theory applicable?

Transport and driving:

Green's function and Landauer formula for time-dependent situation

Transport and driving:

Green's function and Landauer formula for time-dependent situation

■ Floquet equation

with self-energy $\Sigma = |1\rangle \frac{i\Gamma_L}{2} \langle 1| + |N\rangle \frac{i\Gamma_R}{2} \langle N|$

$$\left(H(t) + \Sigma - i \frac{d}{dt} \right) |\varphi_\alpha(t)\rangle = (\epsilon_\alpha - i\gamma_\alpha) |\varphi_\alpha(t)\rangle$$

■ propagator in the presence of the contacts

$$G(t, t - \tau) = \sum_k e^{ik\Omega t} \int dE e^{-iE\tau} \underbrace{\sum_{\alpha, k'} \frac{|\varphi_{\alpha, k+k'}\rangle \langle \varphi_{\alpha, k'}|}{\epsilon - (\epsilon_\alpha + k'\Omega - i\gamma_\alpha)}}_{G^{(k)}(E)}$$


propagation under absorption/emission of $|k|$ photons


■ dc current

$$I = \frac{e}{h} \sum_k \int dE \left\{ T_{LR}^{(k)}(E) f(E - \mu_L) - T_{RL}^{(k)}(E) f(E - \mu_R) \right\}$$

■ transmission under absorption of k photons


$$T_{LR}^{(k)}(E) = \Gamma_L \Gamma_R |\langle 1 | G^{(k)}(E) | N \rangle|^2 \neq T_{RL}^{(\pm k)}(E \pm k\Omega)$$






applicable for


- AC bias voltage



- tunnel barriers
(studied by Tien & Gordon)




- uniform AC gate voltage




applicable for


- AC bias voltage



- tunnel barriers
(studied by Tien & Gordon)




- uniform AC gate voltage



but not for

- non-uniform gating
- dipole force

$$H_{\text{dipole}} \propto x \cos(\Omega t)$$




- 1 time periodicity $t \longrightarrow t + T$ → Floquet theory applicable
- 2 time reversal $t \longrightarrow -t$ → Floquet states real
- 3 generalized parity $(x, t) \longrightarrow (-x, t + T/2)$
e.g. symmetric potential with dipole driving → Floquet states even/odd
- 4 time-reversal parity $(x, t - T/4) \longrightarrow (-x, T/4 - t)$
– combination of the other three

Consequences for scattering probabilities ?

Symmetry-related processes have the same probability


time-reversal

$$t \rightarrow -t$$




generalized parity

$$(x, t \rightarrow -x, t + \frac{T}{2})$$



time-reversal parity

$$(x, t \rightarrow -x, -t)$$



1 Floquet & Schrödinger equation


- Geometric phases
- Time-periodicity, Floquet ansatz, and all that

2 Quantum dissipation and transport

- System-bath model
- Floquet-Bloch-Redfield formalism

3 Applications & miscellaneous topics

- LZSM Interference
- Floquet-Gibbs states
- Hidden symmetries
- Floquet degeneracies & topology
- Time-dependent Liouvillians
- Two-color Floquet theory
- Adiabatic Floquet theory
- Floquet scattering theory



Experimental collaborations

- Stefan Ludwig (PDI Berlin)
- Jason R. Petta (UCLA)
- Guo-Ping Guo & Gang Cao (Hefei)

