

CCD 02 vs. CCD 01 vs. Bid Set: Drawing Comparison & Quantity Takeoff

Directive: Progressive Companies CCD 02, dated 2026-07-30 (Delta 4). **Sheets reissued:** E101, E300, E301, E501, E502, T101. **Compared against:** CCD 01 set (2026-05-28, Delta 3) and the Bid Set (title blocks at Permit Cycle 2, 2025-12-18). **Method:** word-level text diff of every block on each sheet across all three issues, a pixel diff to find graphic changes, and a visual check of every Delta 4 cloud. No other sheet was reissued by CCD 02.

1. Executive summary

#	Change	Division / Trade	Cost direction
1	Digital signs, power (new). 4 new duplex receptacles on 2 existing spare 20A/1P breakers in panel LC1 (LC1-38 feeds 2 at Vestibule 100; LC1-40 feeds 2 on the checkout storefront wall). New keynotes: E101 #22 and E301 #19.	Div 26 Electrical / Electrical sub	Add
2	Digital signs, data (new). 3 new data outlets, T101 keynote #30 (2 at the checkout storefront wall and 1 at Vestibule 100).	Div 27 Communications / Low-voltage sub	Add
3	Bakery ovens split into upper and lower. 2 of 4 oven circuits drop from 60A/3P to 50A/3P, with NEMA 15-60R receptacles changed to 15-50R (upper ovens, BK1-13/15/17 and BK1-25/27/29). Lower ovens stay 60A with 15-60R. The E300 keynote was reworded to match.	Div 26 Electrical / Electrical sub; Div 11 (Owner-furnished ovens) coordination	Small credit (smaller wire on 2 circuits) plus device swap
4	Panel schedules and load calcs updated for items 1 and 3: LC1 +1,440 VA, BK1 55.0 to 57.8 kVA, service connected load 588.5 to 592.7 kVA (demand 690 A to 693 A).	Div 26 Electrical	No separate cost; no feeder or gear changes
5	Title block entity renamed on all 6 sheets: Progressive Architecture Engineering & Planning I, LLC becomes III, Inc. (not clouded).	Admin / record	None

Nothing in CCD 02 touches architectural, structural, mechanical, plumbing, fire protection, fire alarm, BMS or civil sheets. The net effect is a small electrical and low-voltage add for the digital signs, partly offset by the oven-circuit downsizing.

2. Revision history of the six affected sheets

Sheet	Title	Bid Set	CCD 01 set	CCD 02 set
E101	Ground Floor: Electrical Power Plan	Rev 1 PC2 12/18/25	Rev 2 PC3 01/14/26; Rev 3 CCD 01 05/28/26	Rev 4 CCD 02 07/30/26
E300	Enlarged Electrical Drawings	Rev 1 PC2 12/18/25	No change (PC2)	Rev 4 CCD 02 07/30/26
E301	Enlarged Electrical Drawings	Rev 1 PC2 12/18/25	Rev 2 PC3; Rev 3 CCD 01	Rev 4 CCD 02 07/30/26
E501	Panel Schedules	Rev 1 PC2 12/18/25	Rev 3 CCD 01	Rev 4 CCD 02 07/30/26
E502	Panel Schedules	Rev 1 PC2 12/18/25	Rev 2 PC3; Rev 3 CCD 01	Rev 4 CCD 02 07/30/26
T101	Ground Floor: Technology Plan	Rev 1 PC2 12/18/25	Rev 2 PC3; Rev 3 CCD 01	Rev 4 CCD 02 07/30/26

Baseline flag: The Bid Set predates Permit Cycle 3 (01/14/2026). The CCD 01 set carries Permit Cycle 3 revisions that neither narrative lists. Among E and T sheets, PC3 appears on E001, E101, E201, E203, E301, E502, T101 and T201. Confirm which issue the contract sum is based on. If it is the Bid Set, the PC3 changes are an unpriced delta separate from CCD 01 and CCD 02.

3. Changes by division and trade

Division 26: Electrical (Electrical subcontractor)

Item	Bid Set	CCD 01	CCD 02 (current)	Net vs. Bid
Digital sign power, Vestibule 100	None	None	2 duplex receptacles, home run on LC1-38 (E101 keynote 22: confirm final location with Fit Out Manager)	Added
Digital sign power, checkout storefront wall	None	None	2 duplex receptacles, home run on LC1-40 (E301 keynote 19)	Added
Panel LC1, circuits 38 and 40	Spare 20A/1P	Spare 20A/1P	"DIGITAL SIGNAGE" REC, 20A/1P, 720 VA each	Spares used; no new breaker
Bakery oven circuits, BK1-13/15/17 and BK1-25/27/29	20A/3P (bid schedule error); 3,200 / 5,367 VA/phase	60A/3P; 3,200 / 5,367 VA/phase	UPPER oven, 50A/3P, 3,667 VA/phase each	Breakers 60A to 50A
Bakery oven circuits, BK1-19/21/23 and BK1-31/33/35	20A/3P (bid schedule error); 3,200 / 5,367 VA/phase	60A/3P; 3,200 / 5,367 VA/phase	LOWER oven, 60A/3P, 5,367 VA/phase each	Breakers unchanged; BK1-19 load up
Oven receptacles, E300 keynote	4 x NEMA 15-60R	4 x NEMA 15-60R	2 x 15-60R (lower) + 2 x 15-50R (upper)	2 receptacles swapped
Panel BK1 totals	55.0 kVA / 152.6 A	55.0 kVA / 152.6 A	57.8 kVA / 160.4 A connected; 115.6 A demand	Within the 225A feeder
Panel LC1 totals	See bid E502	24.9 kVA / 69.2 A	26.4 kVA / 73.2 A connected	Within capacity
Service (MDP) totals	582.2 kVA / 700 A	588.5 kVA / 708 A	592.7 kVA / 713 A connected; 693 A demand	No gear change

Division 27: Communications (Low-voltage subcontractor)

Item	Bid Set	CCD 01	CCD 02 (current)	Net vs. Bid
Digital sign data outlets (keynote 30)	None	None	3 outlets: 2 at checkout storefront wall (clouded) + 1 at Vestibule 100 (not clouded)	Added
Digital advertisement data outlets (keynote 28)	29 tags	29 tags	29 tags	Unchanged (existing scope)

Owner-furnished items and coordination (no GC material)

Item	Responsibility	Note
Digital signs (displays, mounts, content players)	Lidl / Fit Out Manager	The keynotes say to confirm the final location and connection with the Fit Out Manager. GC provides power and data rough-in only.
Bakery ovens (Div 11)	Lidl-furnished	The upper-oven cord caps must be NEMA 15-50P. Get the oven cut sheets before buying devices.

4. Sheet-by-sheet: Added / Removed / Modified (CCD 01 to CCD 02)

Sheet	Type	Change	Location / reference
E101	Added	2 duplex receptacles for digital signs, circuit LC1-38, Delta 4 clouds	Vestibule 100, grid B: one on the west exterior wall, one on the vestibule wall between the entry doors
E101	Added	Keynote 22: "Power for digital signs. Confirm final location and connection with Fit Out Manager."	Sheet keynotes
E300	Modified	Bakery oven keynote: "four NEMA 15-60R" changed to "two 15-60R for lower oven power and two 15-50R for upper oven power"	Sheet keynotes; 4/E300 Bakery Enlarged Power Plan
E301	Added	2 duplex receptacles for digital signs, circuit LC1-40	West storefront wall at the checkout lanes (E301 enlarged plan), about 18 ft apart
E301	Added	Keynote 19: "Power for digital signs. Confirm final location..."	Sheet keynotes
E501	Modified	BK1-13 and BK1-25 renamed UPPER BAKERY OVEN, 60A/3P to 50A/3P; load 3,200 (BK1-13) and 5,367 (BK1-25) become 3,667 VA/phase	Panel BK1 schedule
E501	Modified	BK1-19 and BK1-31 renamed LOWER BAKERY OVEN, 60A/3P unchanged; BK1-19 load 3,200 to 5,367 VA/phase (BK1-31 unchanged at 5,367)	Panel BK1 schedule
E501	Modified	BK1 totals 55.0 to 57.8 kVA; feeding panels and MDP load summaries recalculated	Panel BK1 and MDP/LDP summaries
E502	Modified	LC1-38 and LC1-40 changed from SPARE BREAKER to DIGITAL SIGNAGE, 720 VA each	Panel LC1 schedule
T101	Added	3 data outlets, keynote 30 (2 clouded at checkout storefront; 1 at Vestibule 100 not clouded)	Grid D storefront and Vestibule 100
T101	Added	Keynote 30: "Data for digital signs. Confirm final location and connection with Fit Out Manager."	Sheet keynotes
All 6	Modified	Title block: Delta 4 CCD 02 07/30/2026 added; firm entity I, LLC changed to III, Inc.	Title block / copyright note
All 6	Removed	Nothing removed beyond the superseded oven ratings and spare-breaker labels above	

5. Quantity takeoff by material (CCD 02 scope only)

Lengths are scaled from E101/T101 at 1/8" = 1'-0" using orthogonal routing. Panels LC1 and BK1 and IT rack R1B are in the Technical room (E300 enlarged plan). Each run adds about 12 LF for the panel rise and about 12 LF per device drop (mounting height is not shown on the drawings), plus 10% waste. Wire includes 10 LF of makeup per conductor. Treat these as order-of-magnitude quantities for pricing review. They are not a substitute for the subcontractors' own takeoff.

5a. Digital sign power (Div 26)

Material	Size / type	Qty	Unit	Basis
EMT conduit	3/4"	480	LF	LC1-38 about 200 LF (Tech room to Vestibule, 2 devices); LC1-40 about 280 LF (Tech room to checkout wall, 2 devices)
THHN Cu, phase (black)	#12 AWG	500	LF	1 per run, E000 note sets #12 minimum
THHN Cu, neutral (white)	#12 AWG	500	LF	1 per run
THHN Cu, ground (green)	#12 AWG	500	LF	1 per run
Alternate: upsize for voltage drop	#10 AWG in lieu of #12	1,500	LF	At about 280 LF, #12 exceeds 3% drop at a full 16A load. Confirm against spec 26 05 19
Junction / device box	4" sq x 2-1/8" deep	4	EA	1 per receptacle
Device ring	1-gang	4	EA	
Duplex receptacle	20A 125V NEMA 5-20R, spec grade	4	EA	E101 x2, E301 x2
Cover plate	1-gang duplex, per spec finish	4	EA	
Pull box	6x6x4 NEMA 1	2	EA	1 per run (more than 360 degrees of bends expected)
EMT couplings / connectors	3/4" set-screw	48 / 12	EA	1 coupling per 10 LF; 2 connectors per box
Straps / beam clamps	3/4" 1-hole + clamp	55	EA	1 per 8-10 LF
Circuit breaker	20A/1P	0	EA	Uses existing spares LC1-38 and LC1-40; update panel directory
Labels	Panel/circuit ID	4	EA	Per spec

5b. Bakery oven circuits (Div 26), change vs. CCD 01

Material	Size / type	Add	Deduct	Unit	Basis
Circuit breaker	50A/3P (BK1)	2		EA	BK1-13 and BK1-25
Circuit breaker	60A/3P (BK1)		2	EA	
Receptacle	NEMA 15-50R 250V 3-pole 4-wire	2		EA	Upper ovens
Receptacle	NEMA 15-60R 250V		2	EA	
THHN Cu, phase	#8 AWG (50A at 75°C)	510		LF	2 circuits x 3 conductors x about 85 LF (Tech room to Bakery, about 75 LF + makeup)
THHN Cu, phase	#6 AWG (60A at 75°C)		510	LF	
THHN Cu, ground	#10 AWG	0	0	LF	No change; NEC 250.122 gives #10 for both 50A and 60A
EMT conduit	1" (could drop to 3/4")	0	0	LF	Keep 1" unless the EC wants the credit
Receptacle box / plate	Per 15-50R device	2	2	EA	Swap only if the box differs

5c. Digital sign data (Div 27)

Material	Size / type	Qty	Unit	Basis
Data cable	Cat 6 plenum (confirm vs. Lidl LV standard)	700	LF	Checkout #1 about 265 LF, checkout #2 about 245 LF, vestibule about 175 LF, to rack R1B via cable tray (1 cable per outlet assumed)
EMT conduit stub	1" (T000: 1" minimum to tray)	60	LF	About 20 LF per outlet, box to cable tray
Device box + ring	4" sq x 2-1/8" deep, 1-gang mud ring	3	EA	T000 note
Jack	Cat 6 RJ45	3	EA	
Faceplate	1-port	3	EA	
Patch panel port / patch cords	Cat 6	3 / 6	EA	Rack R1B
Bushings / pull string / labels / test		3	Lot	Per outlet

Flag: the checkout-wall cable runs of about 265 LF are close to the 295 LF (90 m) TIA channel limit. The LV sub should confirm the actual route.

6. Issues, RFIs and downstream tracker actions

#	Issue	Suggested action	Log
1	Power and data don't match. E101/E301 show 4 sign receptacles, but T101 shows only 3 data outlets. Only one vestibule location has data, and the T101 vestibule tag is not clouded.	Ask which signs need data and whether the unclouded vestibule outlet is part of CCD 02.	RFI Log (new RFI)
2	No mounting heights or dimensions for sign receptacles or data. Both keynotes say to "confirm final location ... with Fit Out Manager".	Ask for sign elevations and mounting heights before rough-in (storefront glazing and brick at the vestibule).	RFI Log (combine with #1)
3	Upper-oven plug type. 15-50R works only if the Lidl-furnished upper ovens ship with 15-50P cords.	Request the oven cut sheets. Add the wiring-device change to the electrical submittal.	Submittal Log; Material Tracker
4	Bid Set error: the bid E501 listed the oven breakers as 20A/3P, while the bid E300 note already called for 60A receptacles. CCD 01 corrected this to 60A.	Confirm the EC priced 60A circuits in the bid. If not, it is part of the CCD 01 price, not CCD 02.	Change Order Log (note)
5	Permit Cycle 3 not in the Bid Set (see Section 2).	Confirm the contract-document baseline.	Owner Contract Key Terms / Risk Register
6	CCD 02 has no PCO yet. The Change Order Log has PCO-001 and PCO-002 only. CCD 01 also has no PCO logged.	Open PCO-003 (CCD 02: digital sign power and data plus oven circuit revision). Request pricing from the electrical and LV subs, using this takeoff for the review.	Change Order Log
7	CCD 02 narrative clerical error: the footer file path points to the "2026 07 30 CCD 01" folder.	None (record only).	n/a

Drawing Log one-liner (CCD 02): "2026-07-30 (CCD 02 / Delta 4): digital sign power (LC1-38/40, 4 receptacles) and data (3 outlets, keynote 30); bakery upper ovens 50A/3P with 15-50R; panel loads updated."

Sources: documents/drawings/CCD2/E-DWGs_CCD2.pdf; T101-CCD2.pdf; CCD-02 Narrative; documents/drawings/CCD1/E-DWGs_CCD1.pdf, T-DWGs_CCD1.pdf, CCD1 Narrative.pdf; documents/drawings/bid set/Lidl 1517 - E-DWGs_Bid Set.pdf, T-DWGs_Bid Set.pdf.