OSDP ACU PKOC Card Processing

Contents

Introduction **3**
Identifying PD Configuration . . . 3
Data Format Conventions . . . 3
Error TLV Contents . . . 4

Message Flow **5**
Reader-Generated Challenge . . . 5
ACU-Generated Challenge . . . 6
Message Flow . . . 7
Transaction ID in PD . . . 8

Manufacturer-specific commands **8**
Commands for use within MFG and MFGREP . . . 8

osdp_RAW as 'Card Present' **9**
Format of osdp_RAW for PKOC "Card Present" . . . 9

osdp_PKOC_AUTH_REQUEST **10**
MFG payload . . . 10

osdp_PKOC_AUTH_RESPONSE **11**
MFGREP payload . . . 11

osdp_PKOC_NEXT_TRANSACTION **12**
MFG payload . . . 12

osdp_PKOC_READER_ERROR **13**
MFGREP payload . . . 13

osdp_PKOC_TRANSACTION_REFRESH **14**
MFGREP payload . . . 14

osdp_PKOC_CARD_PRESENT **15**
MFGREP payload . . . 15

Appendix **16**
Colophon . . . 16
Security Considerations . . . 16
OSDP Considerations . . . 16
Assigned Numbers . . . 16
References . . . 16

Change Log **17**

Version 1.40

Introduction

This document describes alternatives to process PKOC cards for access control. It is assumed that these would be considered as an alternative to a reader that handles the complete PKOC operation and just returns a cardholder number to the ACU. This document describes processing PKOC cards with the work "on-loaded" (not off-loaded) to the ACU.

These all assume the standard OSDP manufacturer specific command format. This specification further adopts the multi-part message format proposed by Integrated Engineering for PIV.

Use of a PKOC card will require multiple card operations and so the osdp_KEEPACTIVE command is recommended to ensure the reader maintains the link to the card during the entire card processing operation. Since these messages are likely larger than the minimum size OSDP message it is recommended the ACU send an osdp_ACURXSIZE command with a size of at least 1024 bytes.

This work is licensed under a Creative Commons Attribution-ShareAlike 4.0 International License. See http://creativecommons.org/licenses/by-sa/4.0/ for license details.

Identifying PD Configuration

- if the PD handles the entire PKOC NFC card processing, it will send osdp_RAW responses with format "unspecified" (0x00) and a PKOC identifier as the cardholder field. The ACU can infer it need not process PKOC operations.
- if the PD provides the reader identifier it will return an empty (tag, length 0) reader identifier in the OSDP_PKOC_CARD_PRESENT response. The ACU should send an empty reader identifier in the subsequent OSDP_PKOC_AUTH_REQUEST command.
- if the PD provides the transaction identifier it will return an empty (tag, length 0) transaction identifier in the OSDP_PKOC_CARD_PRESENT response. The ACU should send an empty transaction identifier in the subsequent OSDP_PKOC_AUTH_REQUEST command.
- when the ACU constructs the OSDP_PKOC_AUTH_REQUEST it uses the current context to identify if it is to send the transaction identifier or the reader identifier.

Data Format Conventions

In the following tables when two or more TLV items are listed they are meant to be "stacked" one after the other. They are not wrapped with an outer TLV. These are meant to be in sync with the PKOC base specification's notation.

If a field is meant to be not present it may be omitted or simply sent as 'present' it must use the format (tag, length=0.)

Three new tags are introduced, for error responses and transaction id tracking:

Tag	Contents
0xFC	Card Present Payload
0xFE	Manufacturer-specific smartcard error response, Length 1-64 bytes
0xFD	Transaction Sequence, Length 1 byte

Error TLV Contents

- Tag: 0xFD
- Length: Per table
- Error Code
- Error Details (depends on code)

Error Code (1 octet)	Meaning
0x00	No error
0x01	ISO 7816 status (SW1/SW2.)
0x02	Problem accessing card.
0x03-0x7F	Reserved for future use.
0x80-0xFF	Reserved for private use.

Message Flow

Reader-Generated Challenge

In this case the reader creates the PKOC Authentication Request, the ACU is responsible only for the crypto. The ACU receives the request and response TLV values and validates the values.

- ACU initializes secure channel connection with PD. Initialization includes osdp_ACURXSIZE of at least 1024 bytes and osdp_KEEPACTIVE.
- ACU and PD exchange conventional osdp_POLL/osdp_ACK steady-state traffic.
- cardholder presents card
- PD sends OSDP_CARD_PRESENT to the ACU, including the select response payload.
- ACU sends OSDP_AUTH_REQUEST. Some fields may be omitted due to pre-processing or PD-side values being provided.
- PD sends Authentication Request to card
- card provides Authentication Response [pkoc]
- PD sends osdp_MFGREP("OSDP_AUTH_RESPONSE") in response to osdp_POLL
- ACU processes the Authentication Response, including necessary EC crypto operations.
- ACU extracts cardholder number from osdp_AUTH_RESPONSE and proceeds with access control processing.

ACU-Generated Challenge

In this case the reader notifies the ACU that the card is present and the ACU creates the PKOC Authentication Request.

- ACU initializes secure channel connection with PD. Initialization includes osdp_ACURXSIZE of at least 1024 bytes and osdp_KEEPACTIVE.
- Optionally, ACU sends osdp_PKOC_NEXT_TRANSACTION to pre-load a transaction identifier in the PD to reduce message traffic. This may include a sequence number.
- ACU and PD exchange conventional osdp_POLL/osdp_ACK steady-state traffic.
- cardholder presents card
- PD identifies the card is a PKOC card and initiates PKOC card dialog.
- (if the transaction ID has not been pre-loaded) PD sends (osdp_RAW or osdp_PKOC_CARD_PRESENT); ACU creates transaction id; ACU sends osdp_PKOC_AUTH_REQUEST
- PD generates Authentication Request
- card provides Authentication Response [1]
- PD sends osdp_MFGREP("OSDP_AUTH_RESPONSE") in response to osdp_POLL. This optionally includes a transaction id sequence to correlate it with the appropriate previously supplied transaction id.
- ACU processes the Authentication Response, including necessary EC crypto operations.
- ACU extracts cardholder number from osdp_AUTH_RESPONSE and proceeds with access control processing.
- optionally PD sends OSDP_PKOC_TRANSACTION_REFRESH
- optionally ACU sends OSDP_PKOC_NEXT_TRANSACTION

Message Flow

Note this uses osdp_RAW as the card-present indication.

```
EAC ACU     PD    CARD
--- ---    ---    ----
 |   |      |      |
 |   |      |      |
             <-----
             card is presented
 |   |      |      |
 |   |      |      |
      <-----
      osdp_RAW, new format, pkoc card version string
 |   |      |      |
 |   |      |      |
      ----->
Auth Request
 |   |      |      |
 |   |      |      |
             ----->
       Auth Request
 |   |      |      |
 |   |      |      |
      ...
      Poll/Ack Traffic
      ...
 |   |      |      |
 |   |      |      |
             <-----
             Auth Response
 |   |      |      |
 |   |      |      |
      <-----
      Auth Response
 |   |      |      |
 |   |      |      |
  <-----
  Card data
```

Transaction ID in PD

The PD needs the transaction id to perform the Authentication Request. This value can be provided by the PD, or provided by the ACU in response to an osdp_PKOC_CARD_PRESENT response, or provided in advance of a card reader using the osdp_PKOC_NEXT_TRANSACTION command. The PD may request a pre-defined transaction id by using the osdp_PKOC_TRANSACTION_REFRESH response. A sequence number may also be provided with the transaction ID. This is useful for case where the ACU is periodically sending transaction identifiers and there is a need to know which one the PD is using.

Manufacturer-specific commands

To implement these operations OSDP's manufacturer-specific command mechanism is used. Six commands are defined. At this time individual vendors are expected to use their own OUI value or a locally defined value.

Commands for use within MFG and MFGREP

Name	Value
osdp_PKOC_CARD_PRESENT	0xE0
osdp_PKOC_AUTH_REQUEST	0xE1
osdp_PKOC_AUTH_RESPONSE	0xE2
osdp_PKOC_NEXT_TRANSACTION	0xE3
osdp_PKOC_TRANSACTION_REFRESH	0xE4
osdp_PKOC_READER_ERROR	0xFE

osdp_RAW as 'Card Present'

The card present event can be represented two ways. One is to use the new OSDP_PKOC_CARD_PRESENT response defined below. Alternatively, an osdp_RAW message can be used. Note the payload for osdp_RAW must fit within a minimum-sized OSDP message (total 128 bytes in the response.)

Format of osdp_RAW for PKOC "Card Present"

Fields in osdp_RAW response

Field	Value
Format	0x80 - Note this value is defined in OSDP 2.2.1(Draft.)
Bits LSB	Number of bits in TLV field (LSB)
Bits MSB	Number of bits in TLV field (MSB)
Data	Tag 0xFC - Card Present Payload, contains: Reader ID TLV (returns empty if PD generated) Transaction Identifier TLV (returns empty if PD generated) Error TLV (optional)

osdp_PKOC_AUTH_REQUEST

This REQUEST is sent by the ACU so that the PD may issue an Authentication Request to the card. This contains the protocol version, transaction ID, and "reader" identifier. The order of these fields does not matter, the TLV tags identify them. If the Transaction ID has been previously provided the "Transaction ID TLV" field will be omitted or encoded as omitted.

MFG payload

Contents of the osdp_MFG payload:

Offset	Contents
0	Manufacturer OUI (3 octets)
3	0xE1 (Mfg Request Code)
4	Total request payload size (Least Significant Octet)
5	Total request payload size (Most Significant Octet)
6	Offset in request (Least Significant Octet)
7	Offset in request (Most Significant Octet)
8	Request length (Least Significant Octet)
9	Request length (Most Significant Octet)
10	Auth Command Parameter 1 ("P1") - 1 octet
11	Auth Command Parameter 2 ("P2") - 1 octet
12	Protocol Version TLV Transaction ID TLV (or indicated to be omitted) Reader Identifer TLV (or indicated to be omitted) Transaction ID Sequence (optional)

osdp_PKOC_AUTH_RESPONSE

This RESPONSE consists of an osdp_MFGREP response. It is sent in response to an osdp_POLL command. This response is sent after the Authentication Response is received from the card by the reader.

MFGREP payload

Contents of the osdp_MFGREP payload:

Offset	Contents
0	Manufacturer OUI (3 octets)
3	0xE2 (Mfg Response Code)
4	Total response payload size (Least Significant Octet)
5	Total response payload size (Most Significant Octet)
6	Offset in response (Least Significant Octet)
7	Offset in response (Most Significant Octet)
8	Response length (Least Significant Octet)
9	Response length (Most Significant Octet)
10	PKOC Authentication Response TLV (contais Public Key and Digital Signature TLV) Error TLV

osdp_PKOC_NEXT_TRANSACTION

This COMMAND consists of an osdp_MFG command. It is sent to provide the PD with a transaction ID to be used in the next Authentication Request. This command may be sent at any time. Optionally, a sequence number can be added so the ACU and the PD can track which transaction ID is being used.

MFG payload

Contents of the osdp_MFG payload:

Offset	Contents
0	Manufacturer OUI (3 octets)
3	0xE3 (Mfg Command Code)
4	Total command payload size (Least Significant Octet)
5	Total command payload size (Most Significant Octet)
6	Offset in command (Least Significant Octet)
7	Offset in command (Most Significant Octet)
8	Command length (Least Significant Octet)
9	Command length (Most Significant Octet)
10	Transaction ID TLV
11	Transaction Sequence TLV (optional)

osdp_PKOC_READER_ERROR

This RESPONSE consists of an osdp_MFGREP command and associated payload. It is sent in response to a poll when there is an error reading the card. The code 0xFE was selected as the format corresponds to response 0xFE in [2].

MFGREP payload

Contents of the osdp_MFGREP payload:

Offset	Contents
0	Manufacturer OUI (3 octets)
3	0xFE (Mfg Response Code)
4-n	Error TLV (see above for description.)

osdp_PKOC_TRANSACTION_REFRESH

This RESPONSE consists of an osdp_MFGREP response. It is sent in response to an osdp_POLL command.
This response is sent when the PD wants to pre-load a transaction id for the next card read. It is expected this would be generated within a few poll cycles after an osdp_PKOC_AUTH_RESPONSE. Note there is no payload beyond the OUI and the response code.

MFGREP payload

Contents of the osdp_MFGREP payload:

Offset	Contents
0	Manufacturer OUI (3 octets)
3	0xE4 (Mfg Response Code)

osdp_PKOC_CARD_PRESENT

This RESPONSE is sent by the reader to the ACU so that the ACU may specify the Authentication Request transaction ID. It returns the "supported protocol versions" TLV structure as received by the reader in the select response. It can optionally include a transaction sequence value, so that the ACU can maintain sync with respect to ACU-supplied transaction id's.

Note is expected the osdp_PKOC_AUTH_REQUEST command will be sent soon after the osdp_PKOC_CARD_PRESENT response is received by the ACU, but not necessarily as the next command. In general the next command after osdp_PKOC_CARD_PRESENt is expected to be a poll.

Note this has no multipart header as the response will never exceed the minimum OSDP packet size. In addition, it does use an outer TLV to make PD-side processing easier.

MFGREP payload

Contents of the osdp_MFGREP payload:

Offset	Contents
0	Manufacturer OUI (3 octets)
3	0xE0 (Mfg Response Code)
4-n	Tag 0xFC - Card Present Payload, contains: Supported Protocol Versions TLV Transaction Sequence TLV (optional) Error TLV (optional)

Appendix

Colophon

This work is licensed under a Creative Commons Attribution-ShareAlike 4.0 International License. See http://creativecommons.org/licenses/by-sa/4.0/ for license details.

This document was written in 'markdown', using pandoc. PDF converter assistance provided by latex. Linux command line to create the PDF is

```
pandoc --toc -o pkoc-osdp-acu.pdf pkoc-osdp-acu.md
```

Document source is in github.

PKOC as used here refers to the card format specificed by PSIA.

This is version 1.31 of this document.

This document originated by Rodney Thayer (Smithee Solutions), Mike Zercher (Secure Element Solutions), and Mark de Olde (Integrated Engineering.) Additional instigation provided by Ed Chandler (Security By Design.)

Security Considerations

It is assumed all of this message traffic happens inside a proper OSDP secure channel using a unique paired (not the default) key.

OSDP Considerations

If you perform PKOC operations on an OSDP "chain" (RS-485 bus with more than one PD) it is possible that long delays will be introduced between the time the PD sends an osdp_PKOC_CARD_PRESENT response and when the ACU sends an osdp_PKOC_AUTH_REQUEST. It is recommended you use a chain with a minimal number of PD's (preferrably only one) and/or a higher line speed (38,400) and/or use a PD that connects over TCP/IP.

Assigned Numbers

This specification assumes certain numbers will be registered.

OUI value (3-byte) - to be registerered with IEEE by (PSIA?.)

Tags FD, FE to be registered in the tag space for PKOC.

References

[pkoc] PKOC NFC Card Specification, Version 1.0 Rev0, 6/13/2023. Physical Security Interoperability Alliance.

[2] Integrated Engineering OSDP extensions, document 100-01G-PS-01-INID "Vendor Specific OSDP Extensions v10c".

[3] OSDP, IEC 60839-11-5

[4] ISO 7816-4-2020

Change Log

```
1.23 - shared at GSX 2023
1.24 - fixed typo's in 1.23
1.30 - added transaction id sequence number, sorted messages, corrected "blah" typo.
1.31 - minor formatting changes, removed multi-part header from osdp_PKOC_CARD_PRESENT respo
1.40 - updated error TLV description and use; reused tag 0xFC for card present payload, adde
```