


## Configure Layer 3 Switching and Inter-VLAN Routing



### Addressing Table

Device	Interface	IP Address / Prefix
MLS	VLAN 10	192.168.10.254 /24
	VLAN 20	192.168.20.254 /24
	VLAN 30	192.168.30.254/24
	VLAN 99	192.168.99.254/24
	G0/2	209.165.200.225
PC0	NIC	192.168.10.1
PC1	NIC	192.168.20.1
PC2	NIC	192.168.30.1

Device	Interface	IP Address / Prefix
PC3	NIC	192.168.10.2/24
PC4	NIC	192.168.20.2/24
PC5	NIC	192.168.30.2/24
S1	VLAN 99	192.168.99.1
S2	VLAN 99	192.168.99.2
S3	VLAN 99	192.168.99.3

### Objectives

#### Part 1: Configure Layer 3 Switching

#### Part 2: Configure Inter-VLAN Routing

### Background / Scenario

A multilayer switch like the Cisco Catalyst 3650 is capable of both Layer 2 switching and Layer 3 routing. One of the advantages of using a multilayer switch is this dual functionality. A benefit for a small to medium-sized company would be the ability to purchase a single multilayer switch instead of separate switching and routing network devices. Capabilities of a multilayer switch include the ability to route from one VLAN to another using multiple switched virtual interfaces (SVIs), as well as the ability to convert a Layer 2 switchport to a Layer 3 interface.

### Instructions

#### Part 1: Configure Layer 3 Switching

In Part 1, you will configure the GigabitEthernet 0/2 port on switch MLS as a routed port and verify that you can ping another Layer 3 address.

- On MLS, configure G0/2 as a routed port and assign an IP address according to the Addressing Table.

```
MLS(config)# interface g0/2
MLS(config-if)# no switchport
MLS(config-if)# ip address 209.165.200.225 255.255.255.252
```

- Verify connectivity to **Cloud** by pinging 209.165.200.226.

```
MLS# ping 209.165.200.226
```

Type escape sequence to abort.

Sending 5, 100-byte ICMP Echos to 209.165.200.226, timeout is 2 seconds:

!!!!

Success rate is 100 percent (5/5), round-trip min/avg/max = 0/0/0 ms

### Part 2: Configure Inter-VLAN Routing

#### Step 1: Add VLANs.

Add VLANs to MLS according to the table below.

VLAN Number	VLAN Name
10	Staff
20	Student
30	Faculty

#### Step 2: Configure SVI on MLS.

Configure and activate the SVI interfaces for VLANs 10, 20, 30, and 99 according to the Addressing Table. The configuration for VLAN 10 is shown below as an example.

```
MLS(config)# interface vlan 10
MLS(config-if)# ip address 192.168.10.254 255.255.255.0
```

Run similar commands for SVI's for vlan 20, 30 and 99.

#### Step 3: Configure Trunking on MLS.

Trunk configuration differs slightly on a Layer 3 switch. On the Layer 3 switch, the trunking interface needs to be encapsulated with the dot1q protocol, however it is not necessary to specify VLAN numbers as it is when working with a router and subinterfaces.

- On MLS, configure interface **g0/1**.
- Make the interface a static trunk port.

```
MLS(config-if)# switchport mode trunk
```

- Specify the native VLAN as 99.

```
MLS(config-if)# switchport trunk native vlan 99
```

- Encapsulate the link with the dot1q protocol.

```
MLS(config-if)# switchport trunk encapsulation dot1q
```

#### Step 4: Configure trunking on S1.

- Configure interface **g0/1** of S1 as a static trunk.
- Configure the native VLAN on the trunk.

#### Step 5: Enable routing.

- Use the **show ip route** command. Are there any active routes?

**No.**

- Enter the **ip routing** command to enable routing in global configuration mode.

```
MLS(config)# ip routing
```

- Use the **show ip route** command to verify routing is enabled.

MLS# **show ip route**

Codes: C - connected, S - static, I - IGRP, R - RIP, M - mobile, B - BGP  
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area  
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2  
E1 - OSPF external type 1, E2 - OSPF external type 2, E - EGP  
i - IS-IS, L1 - IS-IS level-1, L2 - IS-IS level-2, ia - IS-IS inter area  
\* - candidate default, U - per-user static route, o - ODR  
P - periodic downloaded static route

Gateway of last resort is not set

```
C   192.168.10.0/24 is directly connected, Vlan10
C   192.168.20.0/24 is directly connected, Vlan20
C   192.168.30.0/24 is directly connected, Vlan30
C   192.168.99.0/24 is directly connected, Vlan99
    209.165.200.0/30 is subnetted, 1 subnets
C       209.165.200.224 is directly connected, GigabitEthernet0/2
```

### Step 6: Verify end-to-end connectivity.

- From PC0, ping PC3 or MLS to verify connectivity within VLAN 10.
- From PC1, ping PC4 or MLS to verify connectivity within VLAN 20.
- From PC2, ping PC5 or MLS to verify connectivity within VLAN 30.
- From S1, ping S2, S3, or MLS to verify connectivity with VLAN 99.
- To verify inter-VLAN routing, ping devices outside the sender's VLAN.
- From any device, ping this address inside **Cloud**, 209.165.200.226.

The Layer 3 switch is now routing between VLANs and providing routed connectivity to the cloud.