

Elision API Document



Document Revision History

Version	Date	Author	Description of change
1.0	08/08/2018	Khemchand Agrawal	APIDocument

Table of Contents

TABLE OF CONTENTS.....	3
1. ADD MULTI LEAD API.....	4
2. X-MARK API.....	7

1. Add Multi Lead API

This API use to add multiple leads into dialer.

- Below are the parameters with their description to pass to Add Multilead API:

Parameter	Description
source*	Description of what originated the API call (minimum 2 character)
action *	Add_multi_lead
multi_leads*	multiple leads in JSON format Of array of multiple lead.check below sample

* Required parameters.

- Below is Sample array which contains of list of parameters as we discussed in 'API Parameters' section:

```
[{"phone_code":"111","phone_number":"1111111111","list_id":"1111","user":"elision",
"vendor_lead_code":"test","source_id":"tets","title":"elision","first_name":"elision",
"middle_initial":"WEB","last_name":"WEB","address1":"ahemdabad","address2":"ahemdabad",
"address3":"ahemdabad","city":"nehrunagar","state":"ahemdabad","province":"1524",
"postal_code":"385125","country_code":"101","alt_phone":"852","email":"ahemdabad@gmail.com",
"security_phrase":"xyz","comments":"ahemdabad gujrat","owner":"12","postal_code":"385125"}]
```

- Below are the parameters with their description to pass to multi_leads Array Parameters:

Parameter	Description
phone_number*	Must be all numbers, 6-16 digits
list_id *	Must be all numbers, 3-12 digits, defaults to 999 if not set

* Required parameters.

- **Below is Sample URL which contains of list of parameters as we discussed in 'API Parameters' section:**

[http://220.227.5.73/elision-dialer/elision-api/main.php?action=add_multi_lead&source=external&multi_leads=\[{"phone_code":"11","phone_number":"1234567894","list_id":"5555","user":"elision","vendor_lead_code":"test","source_id":"tets","title":"elision","first_name":"elision","middle_initial":"WEB","last_name":"WEB","address1":"ahemdabad","address2":"ahemdabad","address3":"ahemdabad","city":"nehrunagar","state":"ahemdabad","province":"1524","postal_code":"385125","country_code":"101","alt_phone":"852","email":"ahemdabad@gmail.com","security_phrase":"xyz","comments":"ahemdabad gujrat","owner":"12","postal_code":"385125"},{"phone_code":"111","phone_number":"1111111111","list_id":"5555","user":"elision","vendor_lead_code":"test","source_id":"tets","title":"elision","first_name":"elision","middle_initial":"WEB","last_name":"WEB","address1":"ahemdabad","address2":"ahemdabad","address3":"ahemdabad","city":"nehrunagar","state":"ahemdabad","province":"1524","postal_code":"385125","country_code":"101","alt_phone":"852","email":"ahemdabad@gmail.com","security_phrase":"xyz","comments":"ahemdabad gujrat","owner":"12","postal_code":"385125"}\]](http://220.227.5.73/elision-dialer/elision-api/main.php?action=add_multi_lead&source=external&multi_leads=[{)

- **Below are the SUCCESS Responses:**

```
{
  "lead 1": {
    "success": "true",
    "message": "add_multi_lead RECORD(S) CREATED",
    "data": {
      "Phone Number": "1234567894",
      "List ID": "5555",
      "Lead ID": "1556176",
      "Status": "NEW"
    }
  },
  "lead 2": {
    "success": "true",
    "message": "add_multi_lead RECORD(S) CREATED",
    "data": {
      "Phone Number": "1111111111",
      "List ID": "5555",
      "Lead ID": "1556177",
      "Status": "NEW"
    }
  }
}
```

- **Below are the ERROR Responses:**

1. If action is blank then,

```
{
  "status": "false",
  "message": "PLEASE ENTER ACTION VALUE"
}
```
2. If action is wrong then,

```
{
  "status": "false",
  "message": "ENTERED ACTION IS NOT VALID"
}
```
3. If source is blank,

```
{
  "success": "false",
  "message": "add_multi_lead SOURCE IS REQUIRED"
}
```
4. If source is less than 2 charcter ,

```
{
  "success": "false",
  "message": "add_multi_lead PLEASE ENTER TWO DIGIT SOURCE VALUE"
}
```
5. If multi_lead is blank,

```
{
  "success": "false",
  "message": "add_multi_lead MULTI_LEAD IS REQUIRED FIELDS"
}
```

-
6. If multi_lead JSON syntax is wrong,

```
{"success":"false","message":"add_multi_lead PLEASE CHECK YOUR JSON SYNTAX"}
```
 7. If Phone number is blank ,

```
{"lead 1":{"success":"false","message":"add_multi_lead PHONE NUMBER IS REQUIRED"}}
```
 8. If Phone number have alphabetic value,

```
{"lead 1":{"success":"false","message":"add_multi_lead PHONE NUMBER IS NOT VALID"}}
```
 9. If phone number less than 6 and more than 16 digit,

```
{"lead 1":{"success":"false","message":"add_multi_lead PHONE NUMBER MINIMUM 6 DIGIT AND MAXIMUM 16 DIGIT"}}
```
 10. If list_id blank then,

```
{"lead1":{"success":"false","message":"add_multi_lead LIST ID IS REQUIRED"}}
```
 11. If list_id less than 3 and more than 14 character ,

```
{"lead 1":{"success":"false","message":"add_multi_lead LIST ID MINIMUM 3 DIGIT AND MAXIMUM 14 DIGIT"}}
```
 12. If list_id is not exist,

```
{"lead 1":{"success":"false","message":"add_multi_lead LIST ID 1445 DOES NOT EXISTS"}}
```
 13. If Api user do not have permission of Modify lead ,

```
{"success":"false","message":"add_multi_lead USER DOES NOT HAVE PERMISSION TO ADD LEADS TO THE SYSTEM"}
```
 14. If Api user login fails ,

```
{"success":"false","message":"Login incorrect, please try again"}
```

2. X-MARK API

Change status X using list_id and phone number.

- Below are the parameters with their description to pass to X-mark API:

Parameter	Description
phone_number*	Must be all numbers, 6-16 digits
list_id *	Must be all numbers, 3-12 digits, defaults to 999 if not set

* Required parameters.

- Below is Sample URL which contains of list of parameters as we discussed in 'API Parameters' section:

http://220.227.5.73/elision-dialer/elision-api/main.php?action=x-mark&list_id=5555&phone_number=1111111111

- Below are the SUCCESS Responses:

```
{"success":"true","message":"UPDATED STATUS SUCCESSFULLY"}
```

- Below are the ERROR Responses:

- If action is blank than,
{"status":"false","message":"PLEASE ENTER ACTION VALUE"}
- If action is wrong than,
{"status":"false","message":"ENTERED ACTION IS NOT VALID"}
- If list_id blank than,
{"success":"false","message":"x-mark LIST ID REQUIRED"}
- If list_id less than 3 and more than 14 character,
{"success":"false","message":"x-mark LIST ID MINIMUM 3 DIGIT AND MAXIMUM 14 DIGIT"}
- If phone_number blank than,
{"success":"false","message":"x-mark PHONE NUMBER IS REQUIRED"}
- If phone_number less than 6 and more than 16 character,
{"success":"false","message":"x-mark PHONE NUMBER MINIMUM 6 DIGIT AND MAXIMUM 16 DIGIT"}
- If list ID not exist,
{"success":"false","message":"x-mark LIST ID 44544 DOES NOT EXISTS"}

8. If list_id and phone_number data not match than,
{"success":"false","message":"x-mark NOT FOUOD DATA IN LIST ID AND
PHONE NUMBER"}

Products

- Call Center Dialer
- IP / PBX
- Voice Broadcasting
- IVR System
- Click2Call
- Live Chat
- SoftSwitch
- Voice logger
- Video Telephony



Elision TechnoLab LLP

India Office :

3B, 4th Floor, Sumeru Center, Nr. Parimal Bridge, Paldi,
Ahmedabad-380007 Gujarat, India. Tel.: +91 704 164 9394

USA Office :

2419 # E Piper Lane, Charlotte,
NC. 28208-7325, USA, Tel.: +1 305 328 9898

www.elisiontec.com