

Elision API Document



Document Revision History

Version	Date	Author	Description of change
1.0	06/09/2018	Khemchand Agrawal	APIDocument

Table of Contents

TABLE OF CONTENTS	3
1. ADD LEAD API WITH 2 PARAMETER.....	4
2. ADD LEAD API WITH 3 PARAMETER.....	6

1. Add Lead API with 2 Parameter

This API adds single lead and multiple lead to the table with several fields and options

- Below are the parameters with their description to pass to Add lead API:

Parameter	Description
source *	Description of what originated the API call (minimum 2 character)
action *	add_multi_lead
multi_leads*	multiple leads in JSON format Of array of multiple lead.check below sample

- Below are the parameters with their description to pass to multi_leads Array Parameters:

Parameter	Description
phone_number*	Must be all numbers, 6-16 digits
list_id*	Must be all numbers, 3-12 digits, defaults to 999 if not set
language	User can pass language

- Below is Sample URL For Single lead:

[https://swadhaar.rightside.co.in/rightside/rightside-api/main.php?action=add_multi_lead&source=12&multi_leads=\[{"phone_number":"9516589658","language":"Hindi","list_id":"1111"}\]](https://swadhaar.rightside.co.in/rightside/rightside-api/main.php?action=add_multi_lead&source=12&multi_leads=[{)

- Below is Sample URL For Multiple lead:

[https://swadhaar.rightside.co.in/rightside/rightside-api/main.php?action=add_multi_lead&source=12&multi_leads=\[{"phone_number":"9516589658","language":"Hindi","list_id":"1111"},{"phone_number":"9516589658","language":"Hindi","list_id":"1111"}\]](https://swadhaar.rightside.co.in/rightside/rightside-api/main.php?action=add_multi_lead&source=12&multi_leads=[{)

- Below are the SUCCESS Responses:

```
{
  "lead 1": {
    "success": "true",
    "message": "add_multi_lead RECORD(S)CREATED",
    "data": {
      "Phone Number": "9516589658",
      "List ID": "1001",
      "Lead ID": 1926,
      "Status": "NEW"
    }
  }
}
```

- Below are the ERROR Responses:

- If action is blank then,
{ "status": "false", "message": "PLEASE ENTER ACTION VALUE" }
- If action is wrong then,
{ "status": "false", "message": "ENTER ACTION IS WRONG" }
- If source is blank,
{ "status": "false", "message": "add_multi_lead SOURCE IS REQUIRED" }

4. If source is less than 2 character ,
{"status":"false","message":"add_multi_lead PLEASE ENTER TWO DIGIT SOURCE VALUE","data":{"source":"t"}}
5. If multi_lead is blank,
{"success":"false","message":"add_multi_lead MULTI_LEAD IS REQUIRED FIELDS"}
6. If multi_lead JSON syntax is wrong,
{"success":"false","message":"add_multi_lead PLEASE CHECK YOUR JSON SYNTAX"}
7. If Phone number is blank ,
{"lead 1":{"success":"false","message":"add_multi_lead PHONE NUMBER IS REQUIRED"}}
8. If phone number less than 6 and more than 16 digit,
{"lead 1":{"success":"false","message":"add_multi_lead PHONE NUMBER MINIMUM 6 DIGIT AND MAXIMUM 16 DIGIT","data":{"phone_number":"95"}}
9. If list_id blank then,
{"lead 1":{"success":"false","message":"add_multi_lead LIST ID IS REQUIRED"}}
10. If list_id less than 3 and more than 14 character ,
{"lead 1":{"success":"false","message":"add_multi_lead LIST ID MINIMUM 3 DIGIT AND MAXIMUM 14 DIGIT","data":{"list_id":"11"}}
11. If list_id is not exist,
{"lead 1":{"success":"false","message":"add_multi_lead LIST ID 11585 DOES NOT EXISTS","data":{"list_id":"11585"}}

2. Add Lead API with 3 Parameter

This API adds single lead and multiple lead to the table with several fields and options

- Below are the parameters with their description to pass to Add lead API:

Parameter	Description
source *	Description of what originated the API call (minimum 2 character)
action *	add_multi_lead
multi_leads*	multiple leads in JSON format Of array of multiple lead.check below sample

- Below are the parameters with their description to pass to multi_leads Array Parameters:

Parameter	Description
phone_number*	Must be all numbers, 6-16 digits
list_id*	Must be all numbers, 3-12 digits, defaults to 999 if not set
language	User can pass language
productid	User can pass product id

- Below is Sample URL for single lead:

[https://swadhaar.rightside.co.in/rightside/rightside-api/main.php?action=add_multi_lead&source=12&multi_leads=\[{"phone_number":"9516589658","language":"Hindi","productid":"123456","list_id":"1111"}\]](https://swadhaar.rightside.co.in/rightside/rightside-api/main.php?action=add_multi_lead&source=12&multi_leads=[{)

- Below is Sample URL for multiple lead:

[https://swadhaar.rightside.co.in/rightside/rightside-api/main.php?action=add_multi_lead&source=12&multi_leads=\[{"phone_number":"9516589658","language":"Hindi","productid":"123456","list_id":"1111"},{"phone_number":"9516589658","language":"Hindi","productid":"123456","list_id":"1111"}\]](https://swadhaar.rightside.co.in/rightside/rightside-api/main.php?action=add_multi_lead&source=12&multi_leads=[{)

- Below are the SUCCESS Responses:

```
{ "lead 1": { "success": "true", "message": "add_multi_lead RECORD(S)
  CREATED", "data": { "Phone Number": "9516589658", "List ID": "1001", "Lead
  ID": 1926, "Status": "NEW" } } }
```

- Below are the ERROR Responses:

- If action is blank then,
{ "status": "false", "message": "PLEASE ENTER ACTION VALUE" }
- If action is wrong then,
{ "status": "false", "message": "ENTER ACTION IS WRONG" }

3. If source is blank,
{"status":"false","message":"add_multi_lead SOURCE IS REQUIRED"}
4. If source is less than 2 character,
{"status":"false","message":"add_multi_lead PLEASE ENTER TWO DIGIT SOURCE
VALUE","data":{"source":"t"}}
5. If multi_lead is blank,
{"success":"false","message":"add_multi_lead MULTI_LEAD IS REQUIRED
FIELDS"}
6. If multi_lead JSON syntax is wrong,
{"success":"false","message":"add_multi_lead PLEASE CHECK YOUR JSON
SYNTAX"}
7. If Phone number is blank ,
{"lead 1":{"success":"false","message":"add_multi_lead PHONE NUMBER IS
REQUIRED"}}
8. If phone number less than 6 and more than 16 digit,
{"lead 1":{"success":"false","message":"add_multi_lead PHONE NUMBER
MINIMUM 6 DIGIT AND MAXIMUM 16 DIGIT ","data":{"phone_number":"95"}}
9. If list_id blank then,
{"lead 1":{"success":"false","message":"add_multi_lead LIST ID IS
REQUIRED"}}
10. If list_id less than 3 and more than 14 character ,
{"lead 1":{"success":"false","message":"add_multi_lead LIST ID MINIMUM 3 DIGIT
AND MAXIMUM 14 DIGIT","data":{"list_id":"11"}}
11. If list_id is not exist,
{"lead 1":{"success":"false","message":"add_multi_lead LIST ID 11585 DOES NOT
EXISTS","data":{"list_id":"11585"}}

Products

- Call Center Dialer
- IP / PBX
- Voice Broadcasting
- IVR System
- Click2Call
- Live Chat
- SoftSwitch
- Voice logger
- Video Telephony



Elision TechnoLab LLP

India Office :

3B, 4th Floor, Sumeru Center, Nr. Parimal Bridge, Paldi,
Ahmedabad-380007 Gujarat, India. Tel.: +91 704 164 9394

USA Office :

2419 # E Piper Lane, Charlotte,
NC. 28208-7325, USA, Tel.: +1 305 328 9898

www.elisiontec.com