Elision API Document

Document Revision History

Version	Date	Author	Description of change
1.0	06/09/2018	Khemchand Agrawal	APIDocument

Table of Contents

1. Add Lead API with 2 Parameter

This API adds single lead and multiple lead to the table with several fields and options

- **Below are the parameters with their description to pass to Add lead API:**

Parameter	Description
source *	Description of what originated the API call (minimum 2 character)
action *	add_multi_lead
multi_leads*	multiple leads in JSON format Of array of multiple lead.check below sample

- **Below are the parameters with their description to pass to multi_leads Array Parameters:**

Parameter	Description
phone_number*	Must be all numbers, 6-16 digits
list_id*	Must be all numbers, 3-12 digits, defaults to 999 if not set
language	User can pass language

- **Below is Sample URL For Single lead:**

  https://swadhaar.rightside.co.in/rightside/rightside-api/main.php?action=add_multi_lead&source=12&multi_leads=[{"phone_number":"9516589658","language":"Hindi","list_id":"1111"}]

- **Below is Sample URL For Multiple lead:**

  https://swadhaar.rightside.co.in/rightside/rightside-api/main.php?action=add_multi_lead&source=12&multi_leads=[{"phone_number":"9516589658","language":"Hindi","list_id":"1111"},{"phone_number":"9516589658","language":"Hindi","list_id":"1111"}]

- **Below are the SUCCESS Responses:**

  {"lead 1":{"success":"true","message":"add_multi_lead RECORD(S)CREATED","data":{"Phone Number":"9516589658","List ID":"1001","Lead ID":1926,"Status":"NEW"}}}

- **Below are the ERROR Responses:**
  1. If action is blank then,
     {"status":"false","message":"PLEASE ENTER ACTION VALUE"}

  2. If action is wrong then,
     {"status":"false","message":"ENTER ACTION IS WRONG"}

  3. If source is blank,
     {"status":"false","message":"add_multi_lead SOURCE IS REQUIRED"}

4. If source is less than 2 character ,
{"status":"false","message":"add_multi_lead PLEASE ENTER TWO DIGIT SOURCE VALUE","data":{"source":"t"}}

5. If multi_leadis blank,
{"success":"false","message":"add_multi_lead MULTI_LEAD IS REQUIRED FIELDS"}

6. If multi_lead JSON syntax is wrong,
{"success":"false","message":"add_multi_lead PLEASE CHECK YOUR JSON SYNTAX"}

7. If Phone number is blank ,
{"lead 1":{"success":"false","message":"add_multi_lead PHONE NUMBER IS REQUIRED"}}

8. If phone number less than 6 and more than 16 digit,
{"lead 1":{"success":"false","message":"add_multi_lead PHONE NUMBER MINIMUM 6 DIGIT AND MAXIMUM 16 DIGIT","data":{"phone_number":"95"}}}

9. If list_id blank then,
{"lead 1":{"success":"false","message":"add_multi_lead LIST ID IS REQUIRED"}}

10. If list_id less than 3 and more than 14 character ,
{"lead 1":{"success":"false","message":"add_multi_lead LIST ID MINIMUM 3 DIGIT AND MAXIMUM 14 DIGIT","data":{"list_id":"11"}}}

11. If list_id is not exist,
{"lead 1":{"success":"false","message":"add_multi_lead LIST ID 11585 DOES NOT EXISTS","data":{"list_id":"11585"}}}

2. Add Lead API with 3 Parameter

This API adds single lead and multiple lead to the table with several fields and options

- **Below are the parameters with their description to pass to Add lead API:**

Parameter	Description
source *	Description of what originated the API call (minimum 2 character)
action *	add_multi_lead
multi_leads*	multiple leads in JSON format Of array of multiple lead.check below sample

- **Below are the parameters with their description to pass to multi_leads Array Parameters:**

Parameter	Description
phone_number*	Must be all numbers, 6-16 digits
list_id*	Must be all numbers, 3-12 digits, defaults to 999 if not set
language	User can pass language
productid	User can pass product id

- **Below is Sample URL for single lead:**

  https://swadhaar.rightside.co.in/rightside/rightside-api/main.php?action=add_multi_lead&source=12&multi_leads=[{"phone_number":"9516589658","language":"Hindi","productid":"123456","list_id":"1111"}]

- **Below is Sample URL for multiple lead:**

  https://swadhaar.rightside.co.in/rightside/rightside-api/main.php?action=add_multi_lead&source=12&multi_leads=[{"phone_number":"9516589658","langauge":"Hindi","productid":"123456","list_id":"1111"},{"phone_number":"9516589658","language":"Hindi","productid":"123456","list_id":"1111"}]

- **Below are the SUCCESS Responses:**

  {"lead 1":{"success":"true","message":"add_multi_lead RECORD(S) CREATED","data":{"Phone Number":"9516589658","List ID":"1001","Lead ID":1926,"Status":"NEW"}}}

- **Below are the ERROR Responses:**

1. If action is blank then,
   {"status":"false","message":"PLEASE ENTER ACTION VALUE"}

2. If action is wrong then,
   {"status":"false","message":"ENTER ACTION IS WRONG"}

3. If source is blank,
{"status":"false","message":"add_multi_lead SOURCE IS REQUIRED"}

4. If source is less than 2 character,
{"status":"false","message":"add_multi_lead PLEASE ENTER TWO DIGIT SOURCE VALUE","data":{"source":"t"}}

5. If multi_leadis blank,
{"success":"false","message":"add_multi_lead MULTI_LEAD IS REQUIRED FIELDS"}

6. If multi_lead JSON syntax is wrong,
{"success":"false","message":"add_multi_lead PLEASE CHECK YOUR JSON SYNTAX"}

7. If Phone number is blank ,
{"lead 1":{"success":"false","message":"add_multi_lead PHONE NUMBER IS REQUIRED"}}

8. If phone number less than 6 and more than 16 digit,
{"lead 1":{"success":"false","message":"add_multi_lead PHONE NUMBER MINIMUM 6 DIGIT AND MAXIMUM 16 DIGIT ","data":{"phone_number":"95"}}}

9. If list_id blank then,
{"lead 1":{"success":"false","message":"add_multi_lead LIST ID IS REQUIRED"}}

10. If list_id less than 3 and more than 14 character ,
{"lead 1":{"success":"false","message":"add_multi_lead LIST ID MINIMUM 3 DIGIT AND MAXIMUM 14 DIGIT","data":{"list_id":"11"}}}

11. If list_id is not exist,
{"lead 1":{"success":"false","message":"add_multi_lead LIST ID 11585 DOES NOT EXISTS","data":{"list_id":"11585"}}}

3. Add Lead API

This API adds single lead and multiple lead to the table with several fields and options

- **Below are the parameters with their description to pass to Add lead API:**

Parameter	Description
source *	Description of what originated the API call (minimum 2 character)
action *	add_multi_lead
multi_leads*	multiple leads in JSON format Of array of multiple lead.check below sample

- **Below are the parameters with their description to pass to multi_leads Array Parameters:**

Parameter	Description
phone_number*	Must be all numbers, 6-16 digits
list_id*	Must be all numbers, 3-12 digits, defaults to 999 if not set

- **Below is Sample URL for single lead:**

https://swadhaar.rightside.co.in/rightside/rightside-api/main.php?action=add_multi_lead&source=12&multi_leads=[{"phone_code":"111","phone_number":"1111111111","list_id":"5555","user":"elision","vendor_lead_code":"test","source_id":"tets","title":"elision","first_name":"elision","middle_initial":"WEB","last_name":"WEB","address1":"ahemdabad","address2":"ahemdabad","address3":"ahemdabad","city":"nehrunagar","state":"ahemdabad","province":"1524","postal_code":"385125","country_code":"101","alt_phone":"852","email":"ahemdabad@gmail.com","security_phrase":"xyz","comments":"ahemdabad gujrat","owner":"12","postal_code":"385125"}]

- **Below is Sample URL for multiple lead:**

https://swadhaar.rightside.co.in/rightside/rightside-api/main.php?action=add_multi_lead&source=12&multi_leads=[{"phone_code":"111","phone_number":"1111111111","list_id":"5555","user":"elision","vendor_lead_code":"test","source_id":"tets","title":"elision","first_name":"elision","middle_initial":"WEB","last_name":"WEB","address1":"ahemdabad","address2":"ahemdabad","address3":"ahemdabad","city":"nehrunagar","state":"ahemdabad","province":"1524","postal_code":"385125","country_code":"101","alt_phone":"852","email":"ahemdabad@gmail.com","security_phrase":"xyz","comments":"ahemdabad gujrat","owner":"12","postal_code":"385125"},{"phone_code":"111","phone_number":"1111111111","list_id":"5555","user":"elision","vendor_lead_code":"test","source_id":"tets","title":"elision","first_name":"elision","middle_initial":"WEB","last_name":"WEB","address1":"ahemdabad","address2":"ahemdabad","address3":"ahemdabad","city":"nehrunagar","state":"ahemdabad","province":"1524","postal_code":"385125","country_code":"101","alt_phone":"852","email":"ahemdabad@

gmail.com","security_phrase":"xyz","comments":"ahemdabad gujrat","owner":"12","postal_code":"385125"}]

- **Below are the SUCCESS Responses:**

  {"lead 1":{"success":"true","message":"add_multi_lead RECORD(S) CREATED","data":{"Phone Number":"9516589658","List ID":"1001","Lead ID":1926,"Status":"NEW"}}}

- **Below are the ERROR Responses:**

1. If action is blank then,
   {"status":"false","message":"PLEASE ENTER ACTION VALUE"}

2. If action is wrong then,
   {"status":"false","message":"ENTER ACTION IS WRONG"}

3. If source is blank,
   {"status":"false","message":"add_multi_lead SOURCE IS REQUIRED"}

4. If source is less than 2 character,
   {"status":"false","message":"add_multi_lead PLEASE ENTER TWO DIGIT SOURCE VALUE","data":{"source":"t"}}

5. If multi_leadis blank,
   {"success":"false","message":"add_multi_lead MULTI_LEAD IS REQUIRED FIELDS"}

6. If multi_lead JSON syntax is wrong,
   {"success":"false","message":"add_multi_lead PLEASE CHECK YOUR JSON SYNTAX"}

7. If Phone number is blank ,
   {"lead 1":{"success":"false","message":"add_multi_lead PHONE NUMBER IS REQUIRED"}}

8. If phone number less than 6 and more than 16 digit,
   {"lead 1":{"success":"false","message":"add_multi_lead PHONE NUMBER MINIMUM 6 DIGIT AND MAXIMUM 16 DIGIT ","data":{"phone_number":"95"}}}

9. If list_id blank then,
   {"lead 1":{"success":"false","message":"add_multi_lead LIST ID IS REQUIRED"}}

10. If list_id less than 3 and more than 14 character ,
    {"lead 1":{"success":"false","message":"add_multi_lead LIST ID MINIMUM 3 DIGIT AND MAXIMUM 14 DIGIT","data":{"list_id":"11"}}}

11. If list_id is not exist,
    {"lead 1":{"success":"false","message":"add_multi_lead LIST ID 11585 DOES NOT EXISTS","data":{"list_id":"11585"}}}

Products

- Call Center Dialer
- IP / PBX
- Voice Broadcasting
- IVR System
- Click2Call
- Live Chat
- SoftSwitch
- Voice logger
- Video Telephony

elision
Next Gen Telecom Solutions

Elision TechnoLab LLP

India Office :
3B, 4th Floor, Sumeru Center, Nr. Parimal Bridge, Paldi,
Ahmedabad-380007 Gujarat, India. Tel.: +91 704 164 9394

USA Office :
2419 # E Piper Lane, Charlotte,
NC. 28208-7325, USA, Tel.: +1 305 328 9898

www.elisiontec.com