

BedLog Browser Reset Guide

Return the Raspberry Pi BedLog kiosk to the fresh onboarding screen

Use this procedure when: BedLog has already been configured for a hospital/ward and you want the kiosk to behave like a new installation again. This guide uses the dedicated Chromium profile `/home/pi/.config/bedlog-chromium`.

1. Stop the BedLog kiosk

Stop Chromium before changing its profile. This prevents the browser from writing old state back to disk while the profile is being reset.

```
sudo systemctl stop bedlog-kiosk.service
```

2. Rename the current Chromium profile

Rename the existing profile instead of deleting it immediately. This keeps a backup in case you need to recover the previous browser state.

```
mv /home/pi/.config/bedlog-chromium \
    /home/pi/.config/bedlog-chromium-backup
```

3. Start the BedLog kiosk again

Start the kiosk service. Chromium will automatically create a new, clean profile because the original profile path no longer exists.

```
sudo systemctl start bedlog-kiosk.service
```

4. Confirm the onboarding screen

BedLog should now open without its previous browser `localStorage` configuration and return to the onboarding/setup screen. Complete onboarding only when you are ready to assign this Raspberry Pi to its hospital and ward.

```
systemctl status bedlog-kiosk.service --no-pager
```

Important: browser reset does not clear PostgreSQL

Resetting the Chromium profile removes the browser-side BedLog configuration, but it does not erase records already stored in the local PostgreSQL database. If this Raspberry Pi is being prepared as a clean master for cloning, clear the BedLog database records separately.

5. Open the BedLog PostgreSQL database

```
PGPASSWORD=pi psql -h localhost -U bedlog -d bedlog
```

6. Clear BedLog application records

Run the following inside the `bedlog=> PostgreSQL` prompt. The transaction removes device-specific data while leaving the tables/schema in place.

```
BEGIN;
```

```
DELETE FROM patients;
DELETE FROM beds;
DELETE FROM wards;
DELETE FROM backup_log;
DELETE FROM device_config;
```

```
COMMIT;
```

7. Verify that all five tables are empty

```
SELECT 'wards' AS table_name, COUNT(*) FROM wards
UNION ALL
SELECT 'beds', COUNT(*) FROM beds
UNION ALL
SELECT 'patients', COUNT(*) FROM patients
UNION ALL
SELECT 'device_config', COUNT(*) FROM device_config
UNION ALL
SELECT 'backup_log', COUNT(*) FROM backup_log;
```

The expected result is a count of **0** for wards, beds, patients, device_config, and backup_log.

8. Exit PostgreSQL

```
\q
```

Final clean-master checklist

Check	Expected state
Chromium profile	New / clean profile created
BedLog screen	Onboarding/setup screen
Old browser profile	Preserved as bedlog-chromium-backup
PostgreSQL tables	0 records if preparing a clean master
bedlog-kiosk.service	Active

Note: If a folder named bedlog-chromium-backup already exists, choose another backup name before running the rename command, for example bedlog-chromium-backup-2.