Ip representation:D2-01-17

IP KEY	Valid range	Step size	Unit	IP Meaning
Command ID	1			ID 01
Dim value	0			Switch to new output value
	1			Dim to new output value dim timer 1
	2			Dim to new output value dim timer 2
	3			Dim to new output value dim timer 3
	4			Stop dimming
IOChannel	0...29	1		IOChannel key
	30			All output channels supported by the device
	31			Input channel (from mains supply)
Output value	1...99	1	%	Output value key
	0			Output value 0% or OFF100:Output value 100% or ON
	127			Output value not valid or not applicable
Taught in devices	0			Disable taught-in devices (with different EEP)
	1			Enable taught-in devices (with different EEP)
Over current shut down	0			static off
	1			automatic restart
reset over current shut down	0			not active
	1			trigger signal
LocalControl	0			Disable
	1			Enable
Dim timer 2	1...15	0.50	s	Dim timer 2
	0			Not used
Dim timer 3	1...15	0.50	s	Dim timer 3
	0			Not used
UserInterfaceIndication	0			User interface indication day operation
	1			User interface indication night operation
Power Failure	0			Disable Power Failure Detection

IP KEY	Valid range	Step size	Unit	IP Meaning
	1			Enable Power Failure Detection
DefaultState	0			0% or off
	1			100% or on
	2			remember previous state
Dim timer 1	0			Not used
Power Failure Detection	0			Power Failure not detected / not supported / disabled
	1			Power Failure Detected
Over current switch off	0			ready / not supported
	1			executed
Error level	0			hardware OK
	1			hardware warning
	2			hardware failure
	3			Not supported
ReportMeasurement	0			Query only
	1			Query / Auto reporting
ResetMeasurement	0			Not active
	1			trigger signal
Measurement Mode	0			Energy measurement
	1			Power measurement
MeasurementDeltaToBeReportedLsb	0...15	1		MeasurementDeltaToBeReportedLsb
Unit	0			Ws
	1			Wh
	2			kWh
	3			W
	4			kW
MeasurementDeltaToBeReportedMsb	0...255	1		MeasurementDeltaToBeReportedMsb
MaximumTimeBetweenTwoSubsequentActuator	1...255	10	s	MaximumTimeBetweenTwoSubsequentActuator
MinimumTimeBetwee	1...255	1	s	MinimumTimeBetweenTwoSubsequentA

IP KEY	Valid range	Step size	Unit	IP Meaning
nTwoSubsequentActuator				ctuator
query	0			Query energy
	1			Query power
Measurement value	0...4294967295	1	N/A	Power / Energy
Auto OFF Timer	1...65534	0.10	s	Auto OFF Timer
	0			Timer deactivated
	65535			Does not modify saved value
Delay OFF Timer	1...65534	0.10	s	DelayOFFTimer
	0			Timer deactivated
	65535			Does not modify saved value
External Switch/Push Button	0			Not applicable
	1			External Switch
	2			External Push Button
	3			Auto detect
2-state switch	0			Change of key state sets ON or OFF
	1			Specific ON/OFF positions. ON when contacts are closed. OFF when contacts are open.
Delay Off Timer	1...65534	0.10		Delay OFF Timer
	0			Timer deactivated
	65535			Does not modify saved value