Direction "from": Sensor Values

Key	Value	Meaning
battery	0 ... 100 [%], step 5	State of the battery charge
burglaryAlarm	off	Burglary Alarm not triggered
	on	Burglary Alarm Triggered
buttonLeft	pressed	Button pressed
	released	Button released
buttonRight	pressed	Button pressed
	released	Button released
handle	closed	Handle Down
	open	Handle Left
	open	Handle Right
	undefined	Handle Position Undefined
	up	Handle Up
humidity	0 ... 100 [%], step 0.5	Relative Humidity (linear)
illumination	0 ... 60000 [lx], step 1	Illumination (linear)
	overRange	Illumination is over sensor range
motionDetected	false	No motion detected
	true	Motion detected
protectionPlusAlarm	off	Protection Plus Alarm not Triggered
	on	Protection Plus Alarm Triggered
state	notTilted	Window notTilted
	tilted	Window tilted
	undefined	Window State Undefined
temperature	-20 ... 60 [°C], step 0.32	Temperature (linear)
vacationMode	off	Locally switched off
	on	Locally switched on

Direction "from": Configuration Report

Key	Value	Meaning
batteryLowClick	off	Battery low click feature is off
	on	Battery low click feature is on
handleClosedClick	off	Handle closed click feature is off
	on	Handle closed click feature is on
sensorUpdateInverval	5 ... 65535 [s], step 1	Interval between the update of the environmental sensors
vacationBlinkInverval	3 ... 255 [s], step 1	Interval between the LED blinks when vacation mode is active
vacationMode	off	Vacation mode is off
	on	Vacation mode is on

Direction "from": Log Data 01

Key	Value	Meaning
alarmCounter	0 ... 4294967295, step 1	Number of alarms
powerOnCounter	0 ... 4294967295, step 1	Number of power ons

Direction "from": Log Data 02

Key	Value	Meaning
handleClosedCounter	0 ... 4294967295, step 1	Number of handle movements closed
handleOpenedCounter	0 ... 4294967295, step 1	Number of handle movements opened
handleTiltedCounter	0 ... 4294967295, step 1	Number of handle movements tilted

Direction "from": Log Data 03

Key	Value	Meaning
windowTiltedCounter	0 ... 4294967295, step 1	Number of window tilted

Direction "from": Log Data 04

Key	Value	Meaning
buttonLeftPressedCounter	0 ... 4294967295, step 1	Number of button left presses
buttonRightPressedCounter	0 ... 4294967295, step 1	Number of button right presses

Direction "to": Control and Settings

Key	Value	Meaning
batteryLowClick	noChange (default)	Do not change battery low click feature
	off	Set battery low click feature off
	on	Set battery low click feature on
handleClosedClick	noChange (default)	Do not change handle closed click feature
	off	Set handle closed click feature off
	on	Set handle closed click feature on
query	all	Query configuration and log data
	configReport	Query configuration report
	logData	Query log data
	noQuery (default)	Do not query
sensorUpdateInverval	5 ... 65535 [s], step 1	Set the sensor update interval
	noChange (default)	Do not change the sensor update interval
vacationBlinkInterval	3 ... 255 [s], step 1	Set the vacation blink interval
	noChange (default)	Do not change the vacation blink interval
vacationMode	off	Set vacation mode off
	on	Set vacation mode on