

High-Density Electrochemical Compute Infrastructure (EPCS)

Open Architecture Specification: Direct Non-Copper Power Delivery, Integrated Microfluidic Die Heat Rejection, Decoupled Quad-Stack Charging, and Closed-Loop Gas Reclamation

Principal Systems Architect: Steve Campbell (KL8T)

Licensing: CERN Open Hardware Licence Version 2 - Strongly Reciprocal (CERN-OHL-S) / Creative Commons Attribution 4.0 International (CC-BY 4.0)

Classification: Open Hardware Engineering White Paper

Distribution: Public / Technical Advisory

1. Foundational Premise: Why This Architecture Is Inevitable

Modern hyperscale artificial intelligence (AI) and accelerated GPU computing clusters are colliding with the fundamental physical limits of traditional electrical distribution and thermal engineering:

- 1. The Transformer and Copper Chokepoint:** Utility-scale distribution transformers suffer from 36- to 48-month manufacturing backlogs. Inside data halls, distributing power via alternating current (AC) requires 4 to 6 separate conversion steps (13.8 kV AC to 480 V AC, to 48 V DC, to 12 V DC, and finally down to 1.0–1.2 V DC at the silicon core). Forcing tens of thousands of amperes through onboard Voltage Regulator Modules (VRMs) and low-voltage copper busbars creates massive resistance losses (I^2R heating), magnetic core hysteresis losses, and adds thousands of pounds of costly copper busways per row.
- 2. The Silicon Thermal Density Wall:** Next-generation compute dies dissipate over 1,000 Watts per socket, pushing localized die heat fluxes beyond 100 W/cm^2 . Air cooling is completely incapable of handling these densities. Decoupled secondary liquid hydronic loops (water/glycol cold plates) require complex intermediate heat exchangers, in-row Coolant Distribution Units (CDUs), and continuous mechanical chillers that inflate facility power consumption.
- 3. Hazardous, Short-Lived Energy Storage:** Lithium-ion uninterruptible power supply (UPS) banks introduce catastrophic fire propagation hazards (thermal runaway, toxic hydrofluoric acid off-gassing, and NFPA 855 blast-wall mandates). They consume up to 40% of building floor space ("grey space") and degrade

completely within 8 to 10 years, creating recurring multi-million-dollar replacement liabilities.

The Solution: The "Electronic Blood" Hemodynamic Model

In the human body, a single fluid (blood) simultaneously delivers chemical energy (glucose and oxygen) and removes metabolic waste heat through microfluidic capillary networks.

The **Electronic Power & Cooling System (EPCS)** applies this paramedic principle to computing. By using an aqueous Vanadium Redox electrolyte as "**Electronic Blood**", the exact same liquid that delivers native direct-current (DC) power to the silicon die simultaneously carries away 100% of the die's thermal waste.

- Power generation is moved **directly to the compute tray** via ultra-flat 1-to-2 cell stacks, eliminating rack-length copper busbars and onboard VRMs.
 - The electrochemical reaction rate is **natively balanced** with the thermal cooling mass flow.
 - Energy storage is decoupled into **non-flammable subterranean tanks** holding non-degrading liquid assets with a 30+ year lifespan.
 - High-voltage utility charging is separated from low-voltage discharge, with **continuous headspace gas recovery** powering auxiliary equipment and **Photonic Buffers** providing 100% native electromagnetic pulse (EMP) immunity.
-

2. Comprehensive System Architecture Walkthrough

The complete infrastructure loop operates across four distinct, decoupled functional zones:

[UTILITY INTERCONNECT & GENERATION ZONE]

- Solar HVDC / Rectified Medium-Voltage Grid (1,200 VDC)
- Quad-Stack Charging Array (2 Sets of 2 Stacks in Series-Parallel)
- Center-Tap Tank Ground (± 300 VDC Maximum Potential to Earth)
- Dielectric Cascade Droplet Disruptors (Zero Ionic Shunt Paths)
- Headspace Nitrogen Sweep & Vacuum Degassing (Scavenges H₂)

└─> Scavenged H₂ feeds On-Site PEM Fuel Cell (25–75 kW DC Power)



[SUBTERRANEAN STORAGE & PASSIVE COOLING ZONE]

- Non-Flammable 2.0 M Aqueous Vanadium Electrolyte Reservoirs
- Macro-Thermal Earth Coupling (Continuous 12°C Sub-Surface Baseline)
- Nocturnal Sky-Radiative Dry Fluid Coolers (Passive Off-Peak Chill)

- Modular In-Line Trim Chiller (Selective Peak Summer Trimming Only)

|

▼ (Chilled, Charged Fluid in Non-Conductive PEX-a / HDPE

Conduits)

[POINT-OF-LOAD COMPUTE VAULT ZONE]

- Precast Utilidors with Secondary Gravity Sump Containment
- Photonic Buffer: 100% Optical Glass Data Interface (Zero Metal

Penetrations)

- Core Discharge Pancake Stacks: 1 to 2 Cells (1.25V–2.5V @ 40,000A per Rack)

- Auxiliary Discharge Pencil Stack: 40 Cells in Series (48V @ 31.25A for Logic)

- Direct Microfluidic Silicon Die Cold Plate Washing

|

▼ (Depleted, Warmed Electrolyte Return)

[CLOSED RETURN LOOP TO UPSTREAM CHARGING]

Zone 1: High-Voltage Modular Charging & Gas Capture

- Sized to receive 1,200 VDC directly from utility solar arrays, HVDC microgrids, or rectified grid substations without magnetic AC transformers.
- Configured as a **Quad-Stack (two parallel sets of two series stacks)**, center-tapped directly to the bulk storage tanks. This limits maximum voltage to earth to **±300 VDC**, allowing standard 600V industrial switchgear.
- Electrolyte streams pass through **Dielectric Cascade Droplet Disruptors** across a 15 cm nitrogen gap, breaking the liquid stream into non-continuous droplets that physically eliminate high-voltage ionic ground loops.
- Manifold vacuum demisters continuously capture trace Hydrogen (H₂) and Oxygen (O₂) outgassing, degas the electrolyte to prevent bubble fouling, and route pure H₂ to an auxiliary PEM fuel cell.

Zone 2: Subterranean Chemical Storage & 3-Tier Passive Heat Sinking

- Bulk electrolyte resides in sub-grade tanks, leveraging surrounding earth at 10–13°C (50–55°F) for baseline standby thermal buffering.
- During evening hours, bulk electrolyte circulates through high-emissivity surface dry coolers, radiating heat directly to the night sky (40–60 W/m² baseline) to chill the tanks down to 15–18°C without mechanical compressors.
- A variable-speed trim chiller (sized for only 25–30% of total plant capacity) activates only during peak summer humidity conditions to deliver final temperature stabilization.

Zone 3: Point-of-Load Compute Vault & Photonic Buffer

- Non-conductive PEX-a and HDPE piping routes charged electrolyte into the compute room through subterranean utilidor raceways.
- High-current core discharge stacks sit directly inside each server tray: **1 single cell (1.25V)** or **2 cells in series (2.50V)** generating native die power right at the silicon substrate.
- An independent 40-cell micro-stack supplies a dedicated 48V DC rail at 31.25 Amperes for Baseboard Management Controllers (BMCs), fan-outs, and optical modules.
- All network communication, telemetry, and control logic pass through the **Photonic Buffer** over fiber-optic glass lines. Zero continuous metallic conductors enter the vault, providing native immunity against High-Altitude Electromagnetic Pulses (HEMP E1/E2/E3) and RF interference.

Zone 4: Continuous Auxiliary Fuel Cell Power

- Parasitic water electrolysis is captured at both the charge and discharge stacks.
- The scavenged hydrogen generates **25 kW to 75 kW of continuous auxiliary DC power** via on-site PEM fuel cells across a 10 MW computing facility.
- This power operates SCADA programmable logic controllers, automated isolation ball valves, optical transceivers, and emergency monitoring systems 100% off-grid and uninterrupted.

3. Decoupled Electrochemical Stack Sizing & Dimensional Physics

The fundamental governing law of the EPCS stack design is strict functional separation:

$$\text{Series Cell Count (N)} = \frac{\text{Operating Voltage}}{\text{Cell Voltage}}$$
$$\text{Active Cell Face Area (A)} = \frac{\text{Amperage Capacity}}{\text{Current Density}}$$

Stack Physical Specifications & Dimensions

Parameter	Core High-Current Compute Stack	Auxiliary Logic Stack	2.5 MW Modular Charging Stack
Primary Function	Direct Native Silicon Die Power	Motherboard BMC & Standby Logic	Utility-Scale Generation Input
Output / Input Voltage	1.25 VDC (1 Cell) to 2.50 VDC (2 Cells)	48.0 VDC Nominal	1,200 VDC (±300V Center-Tapped)
Series Cell Count	1 to 2 Cells per blade	40 Cells in Series	4 Stacks of 194 Cells (Quad-Stack)

Continuous Current	40,000 Amperes per 50 kW rack	31.25 Amperes (1.5 kW load)	1,041.7 Amperes per branch
Operating Current Density	0.30 A/cm ² (3,000 A/m ²)	0.25 A/cm ² (2,500 A/m ²)	0.20 A/cm ² (2,000 A/m ²)
Active Area per Cell	16,667 cm ² per blade (4 leaves)	125 cm ² (19.4 in ²)	5,208 cm ² (0.52 m ²)
Cell Face Dimensions	65 cm x 65 cm (4 parallel leaves)	11.2 cm x 11.2 cm (4.4 in x 4.4 in)	72.2 cm x 72.2 cm (28.4 in x 28.4 in)
Stack Length / Thickness	1.5 cm thick (Ultra-flat pancake)	20.0 cm long (Thin pencil)	0.97 meters long per 194-cell stack
Mechanical Placement	Sandwiching GPU die in server blade	Rear chassis utility corner	External electrical yard skid

Why This Configuration Destroys the "Copper Wall"

- In a traditional 50 kW rack, pushing 40,000 Amps at 1.2V requires massive copper busbars, resulting in severe I²R heat and voltage drops.
- In the EPCS architecture, the high-current path between the carbon felt electrode and the GPU silicon substrate is **less than 2.5 cm (1 inch)**. Low-voltage copper distribution losses drop by over 95%.

4. The Faraday-Caloric Fluidic Equivalence

Standard 2.0 M Vanadium electrolyte in 2.5 M sulfuric acid (H₂SO₄) exhibits the following physical properties:

- **Fluid Density:** 1.35 kg/L
- **Specific Heat Capacity:** 3.20 kJ / (kg · °C)
- **Volumetric Heat Capacity:** 4.32 kJ / (L · °C)

Mathematical Proof (50 kW Rack Baseline)

Operating at a conservative 20% single-pass depth of reaction (Delta SOC), each liter of electrolyte provides 0.40 moles of active Vanadium electrons.

1. Electrochemical Flow Requirement (Faraday's Law):

- Total Current = 50,000 W / 1.25 V = 40,000 Amps (Coulombs/second).
- Molar Flux = 40,000 C/s / 96,485 C/mol = 0.415 mol/second of electrons.
- Volumetric Flow Rate = 0.415 mol/s / 0.40 mol/L = **1.04 Liters/second (62.4 L/min)**.

2. Thermodynamic Heat Removal Requirement:

- Total Waste Heat = 50 kW (50 kJ/second).
- Allowable Silicon-to-Fluid Temperature Delta (Delta T) = 11.1°C.
- Required Flow Rate = 50 kW / [4.32 kJ/(L·°C) x 11.1°C] = **1.04 Liters/second (62.4 L/min)**.

Engineering Takeaway

The fluid volume required to deliver the electrochemical power precisely equals the fluid volume required to cool the compute load.

When both catholyte and anolyte fluid loops pass through isolated channels across the cold plate, available cooling fluid doubles to 2.08 L/s, reducing the die temperature rise to **Delta T ≈ 5.5°C**. This keeps GPU silicon dies isothermal across the entire substrate, eliminating die warpage and clock throttling.

5. Cabinet-Level Performance Comparison

50 kW AI / GPU Cabinet Architecture Comparison

Performance Vector	Traditional AC Power + Hydronic Liquid Cold Plates	EPCS Direct Electrochemical Delivery + Fluidic Cooling	Architectural Impact
Combined Efficiency (Entry to Die)	82% – 85%	88% – 91%	EPCS +5% to +8% more efficient
Internal Cabinet Losses	10.2 kW waste heat (for 50 kW IT)	4.5 – 5.5 kW stack losses	Saves 5 kW of waste heat per rack
Copper I²R Losses	6.0 – 7.5 kW (high-current rails & PSUs)	<0.5 kW (1-inch electrode-to-die path)	>90% reduction in copper heating
Transformer Hysteresis Losses	1.5 – 2.5 kW (magnetic core losses in PSUs)	0.0 kW (Zero magnetic transformers)	Transformer losses completely eliminated
Battery Float & Conditioning Loss	1.0 – 3.0 kW (separate UPS DC-DC stages)	0.0 kW (Native storage in bulk loop)	Eliminates intermediate battery stages

Voltage Conversion Steps	4 to 6 stages (AC-DC, 48V, 12V, VRMs)	1 stage (Direct electrochemical generation)	Radical mechanical simplification
Cooling Hardware Inside Rack	In-row CDUs, dual pumps, internal fans	Direct electrolyte washing across die plates	Frees 20% rack space for compute blades

6. Spatial Footprint & Real Estate Optimization

In conventional data center layouts, electrical transformer rooms, UPS battery halls, and chiller pump corridors consume 35% to 50% of the building footprint ("Grey Space").

10 MW IT Facility Spatial Comparison (Gross Footprint)

Facility Functional Area	Traditional 10 MW AC / Li-Ion Build	EPCS 10 MW Integrated Build	Floor Space Impact
Compute White Space (Racks)	35,750 sq. ft. (55%)	35,200 sq. ft. (88%)	Revenue-generating core preserved
Electrical Grey Space (UPS / Switchgear)	16,250 sq. ft. (25%)	2,400 sq. ft. (6%)	85% reduction in electrical room size
Mechanical Grey Space (Chillers / CDUs)	13,000 sq. ft. (20%)	2,400 sq. ft. (6%)	81% reduction in mechanical corridors
TOTAL GROSS BUILDING AREA	65,000 sq. ft. (100%)	40,000 sq. ft. (100%)	38.5% smaller total building shell

7. Capital, Operational & 10-Year Lifecycle TCO Analysis

Benchmarked against a **10 MW IT Critical Load Facility** (~200 high-density 50 kW compute racks) over a **10-year operating horizon**. Baseline electricity cost: **\$0.075 / kWh**.

Initial Capital Expenditure (CapEx) Comparison

Subsystem Component	Traditional 10 MW Build (AC + Li-Ion)	EPCS 10 MW Commercial Sourcing	EPCS 10 MW Integrated Sourcing
Grid Transformers & Switchgear	\$4,500,000	\$1,800,000	\$1,800,000
Energy Storage (40 MWh, 4-hr runtime)	\$7,500,000 (1-hr Li-ion)	\$6,800,000 (4-hr VRF)	\$3,200,000 (4-hr VRF)
Power Distribution & VRMs	\$8,200,000	\$3,200,000	\$3,200,000
Cooling Plant (Chillers & CDUs)	\$6,500,000	\$2,800,000	\$2,800,000
Civil Conduits & Utilidors	\$2,500,000	\$3,200,000	\$3,200,000
Building Shell ("Grey Space" Cost)	\$4,000,000	\$1,200,000	\$1,200,000
TOTAL INITIAL CAPEX	\$33,200,000	\$19,000,000	\$15,400,000
Net Initial CapEx Savings	Baseline	-\$14,200,000 (-42.8%)	-\$17,800,000 (-53.6%)

Annual Operational Expenditure (OpEx) Comparison

Operational Vector	Traditional 10 MW Facility	EPCS 10 MW Facility	Annual Operational Advantage
Power Distribution Losses (I^2R)	\$919,800 / year	\$394,200 / year	-\$525,600 / year (-57%)
Cooling Parasitic Power	\$1,182,600 / year (PUE 1.32)	\$262,800 / year (PUE 1.10)	-\$919,800 / year (-78%)
Battery Replacement Reserve	\$750,000 / year (Year-8 swap)	\$0 / year (Indefinite liquid life)	-\$750,000 / year (-100%)

Maintenance, Water, Biocides	\$450,000 / year	\$220,000 / year	-\$230,000 / year (-51%)
Hydrogen Self-Generation Credit	\$0 / year	-\$35,000 / year (Auxiliary power)	-\$35,000 / year credit
TOTAL ANNUAL OPEX	\$3,302,400 / year	\$842,000 / year	Net Annual Savings: \$2.46M / year

10-Year Lifecycle Total Cost of Ownership (TCO) & Terminal Valuation

$\text{True Net 10-Year TCO} = \text{Initial CapEx} + (10 \times \text{Annual OpEx}) + \text{Mid-Life Battery Swap} - \text{Terminal Salvage Asset}$

- Traditional Architecture:**

$\$33.20\text{M (CapEx)} + (\$3.30\text{M} \times 10) + \$6.00\text{M (Year-8 Li-ion Swap)} + \$0.80\text{M (Hazmat Disposal)} = \mathbf{\$73,024,000}$

- EPCS Integrated Architecture:**

$\$15.40\text{M (CapEx)} + (\$0.84\text{M} \times 10) + \$0\text{ (Zero Degradation)} - \$4.75\text{M (Recoverable Vanadium)} = \mathbf{\$19,070,000}$

- NET 10-YEAR CASH ADVANTAGE: \$53,954,000**

The Recoverable Commodity Shield

A 40 MWh storage reservoir contains 163 metric tons of Vanadium Pentoxide (V₂O₅) equivalent. Unlike lithium cells that degrade into toxic waste, Vanadium chemistry exhibits zero degradation. At Year 10, the liquid can be pumped out and sold or transferred at **95% to 100% of commodity value (\$4.75M balance sheet asset)**.

8. Field Maintenance Protocols & Paramedic-Logic Failure Triage

Operational maintenance shifts entirely from high-voltage electrical safety gear to low-pressure plumbing inspections and automated chemical rebalancing.

Routine Maintenance Schedule

Maintenance Interval	Monitored Subsystem	Field Operational Action Required
----------------------	---------------------	-----------------------------------

Continuous (Real-Time)	Spectrophotometric Sensors	Optical density monitoring of $\text{VO}^{2+}/\text{VO}_2^+$ and $\text{V}^{2+}/\text{V}^{3+}$ ratios (SOC balance).
Continuous (Real-Time)	Headspace Gas Analyzers	Monitor H_2/O_2 concentrations; verify vacuum demister pull to PEM fuel cell.
Monthly	Magnetic-Drive Pumps	Acoustic vibration logging and infrared bearing temperature audits.
Quarterly	Polypropylene Strainers	Inspect dual 10-micron basket strainers; backwash trapped carbon debris.
Semi-Annual	Electrolyte Balance Valve	Automated cross-over equalization cycle to restore osmotic species balance.
Annual	Utilidor Raceway Crawl	Visual inspection of gravity drainage channels and moisture telemetry probes.
5 Years	Pump Skid Modular Overhaul	Hot-swap pump impeller cartridges and ceramic shaft sleeves (N+1 redundancy).
10 to 15 Years	Stack Perimeter Gaskets	Re-torque external stack tie-rods; replace EPDM elastomeric sealing frames.

Failure Modes & Paramedic-Logic Triage Matrix

Failure Event	Immediate System Reaction	Redundant Failsafe & Operational Outcome
Utilidor Pipe Leak	Moisture sensor in raceway trips pneumatic isolation ball valves.	Fluid falls into Geocrete gravity trough to underground containment; server tray switches to local fluid buffer.

Electrochemical Polarization	Flow control valve opens to increase stoichiometric reactant velocity.	Auxiliary 48V stack maintains BMC communications while compute blade lowers clock multiplier.
Dielectric Droplet Shorting	Conductivity probe in dielectric gap detects liquid bridge/splash.	Diverter valve drops stream to low-level return and alerts SCADA operator.
External Grid Blackout	Zero millisecond transfer delay (DC bus coupled to storage).	40 MWh storage reservoir sustains full 10 MW compute load for 4+ hours uninterrupted.
Blade Cell Stack Rupture	Flush-face hydraulic quick-disconnects isolate individual tray.	Operator cold-swaps compute blade in seconds without disrupting adjacent row hardware.

9. Strategic Roadmap & Immediate Milestones

1. Phase 1: Open Architecture Standardization (Months 1–6)

- Publish EPCS Open Specification under CERN-OHL-S and CC-BY 4.0.
- Establish technical working group within the Open Compute Project (OCP) Modular Data Center committee.

2. Phase 2: Benchtop Cell & Droplet Disruptor Validation (Months 6–12)

- Fabricate a benchtop 1.25V / 5,000A single-cell test stack; quantify die heat dissipation across micro-channel cold plates.
- Construct a 600V modular charging test loop with cascade droplet disruptors to empirically verify zero dielectric shunt leakage.
- Demonstrate continuous headspace hydrogen scavenging to a 1 kW test PEM fuel cell.

3. Phase 3: 500 kW Edge AI Pilot Demonstration (Months 12–24)

- Deploy a 500 kW / 2 MWh demonstration vault directly interconnected with localized solar HVDC generation.
- Empirically validate sub-1.10 PUE, zero copper transformer busway delivery, and optical galvanic isolation.

Systems Architect Declaration

The EPCS specification bridges the gap between electrical power generation and microfluidic thermal engineering. By replacing rigid copper infrastructure and hazardous battery chemistry with closed-loop hemodynamic fluidics, it provides an ultra-hardened, low-cost, and non-degrading physical foundation for next-generation computing.