		Bytes Used									
Message ID	Description	0	1	2	3	4	5	6	7	Max Refresh Rate	Notes
600	Calculated VSS speed in MPH	■	■							8hz	Divide by 10 when decoding
600	VSS pulse count			■	■	■	■			8hz	
601	Hour	■								10hz	24 hour format
601	Minute		■							10hz	
601	Second			■						10hz	
601	Month				■					10hz	
601	Day					■				10hz	
601	Year						■	■		10hz	4 digit
602	GPS Latitude sign bit	■								10hz	0 is postive, 1 is negative
602	GPS Latitude		■	■	■	■				10hz	degrees * 10^-7
603	GPS Longitude sign bit	■								10hz	0 is positive, 1 is negative
603	GPS Longitude		■	■	■	■				10hz	degrees * 10^-7
604	GPS Altitude sign bit	■								10hz	0 is positive, 1 is negative
604	GPS Altitude		■	■	■	■				10hz	mm
604	GPS satellites in view						■			10hz	
605	Fuel Pressure	■								50hz	0-100 psi
605	Fuel Pressure analog value		■	■						50hz	0-1023
605	Oil Pressure				■					50hz	0-100 psi
605	Oil Pressure analog value					■	■			50hz	0-1023
606	Accelerometer X axis	■								20hz	Divide by 10 when decoding, result is in m/s^2
606	Accelerometer Y axis		■							20hz	Divide by 10 when decoding, result is in m/s^2
606	Accelerometer Z axis			■						20hz	Divide by 10 when decoding, result is in m/s^2
607	Compass heading	■	■							5hz	0-360 degrees
607	Compass direction			■						5hz	array index, points to text: N, NW, W, etc...
608	Ambient Temperature sign bit	■								1hz	0 is positive, 1 is negative
608	Ambient Temperature (F)		■	■						1hz	Divide by 10 when decoding, result in fahrenheit