

BIOS Hot Keys

Donnerstag, 19. Januar 2023 19:34

Gerät	Boot Menü	BIOS
Acer Aspire V5-571	ESC halten und F12	F2
Microsoft Surface	<ul style="list-style-type: none">• Halten Sie die Leiser-Taste von Surface gedrückt. Drücken Sie währenddessen die Ein/Aus-Taste und lassen Sie sie los.• Die Microsoft- oder Surface-Logo wird auf dem Bildschirm angezeigt. Halten Sie die Leiser-Taste weiterhin gedrückt. Lassen Sie die Schaltfläche los, wenn sich drehende Punkte unter dem Logo angezeigt werden. <p>Aus <https://support.microsoft.com/de-de/surface/starten-des-surface-von-einem-usb-ger%C3%A4t-fe7a7323-8d1d-823d-be17-9aec89c4f9f5></p>	<ul style="list-style-type: none">• Halten Sie die Lauter-Taste Ihres Surface gedrückt, und drücken Sie gleichzeitig die Netztaste.• Lassen Sie die Lauter-Taste los, wenn das Surface-Logo angezeigt wird. Das UEFI-Menü wird innerhalb weniger Sekunden angezeigt.
MSI	F11	[Entf]

Hot keys for BootMenu / BIOS Settings

How to get to your Boot Menu or your BIOS settings? Every PC has different hot-keys that go to these settings.

Below is a list of PC brands with their corresponding hot-keys.

Manufacturer	Type	Models	Boot Menu	Boot Once	BIOS Key	Change Priority
ACER			Esc, F12, F9		Del, F2	
ACER	netbook	Aspire One, Aspire Timeline	F12		F2	
ACER	netbook	Aspire v3, v5, v7	F12	The "F12 Boot Menu" must be enabled in BIOS. It is disabled by default.	F2	
APPLE		After 2006	Option			
ASUS	desktop		F8		F9	
ASUS	laptop		Esc		F9	
ASUS	laptop	R503C	F8		DEL	
ASUS	netbook	Eee PC 1025c	Esc		F2	Boot Tab, Boot Device Priority, 1st Boot Device, Removable Device, F10
COMPAQ		Presario	Esc, F9		F10	BIOS "Advanced Tab", Boot Order
DELL	desktop	Dimension, Inspiron, Latitude	F12	Select "USB Flash Drive"	F2	
DELL	desktop	Inspiron One 2020, 2305, 2320, 2330 All-In-One	F12	Select "USB Flash Drive"	F2	
DELL	laptop	Inspiron	F12	Select "USB Flash Drive"	F2	Settings->General->Boot Sequence->"USB Storage Device", then up arrow, [Apply]--[Exit]
DELL	laptop	Precision	F2	Select "USB Storage Device" from boot menu	F12	
EMACHINES			F12		Tab, Del	
Fujitsu	Laptop		F12		F2	
HP	generic		Esc, F9		Esc, F10, F1	
HP	desktop	Media Center	Esc		F10	BIOS "Advanced" tab, Boot Order, Move "USB Device" before "Hard Drive"
HP	desktop	Pavilion 23 All In One	Esc	Select boot media from the menu	F10	Move "USB Device" before "Hard Drive". For non-UEFI media, disable secure boot and enable legacy support
HP	desktop	Pavilion g6 and g7	Esc		F10	BIOS "Advanced" tab, Boot Order, Move "USB Device" before "Hard Drive"
HP	desktop	Pavilion HPE PC, h8-1287c	Esc	Then F9 for "Boot Menu"	Esc, F10	Storage tab, Boot Order, Legacy Boot Sources
HP	desktop	Pavilion PC, p6 2317c	Esc	Then F9 for "Boot Menu"	Esc, F10	Storage tab, Boot Order, Legacy Boot Sources
HP	desktop	Pavilion PC, p7 1297cb	Esc	Then F9 for "Boot Menu"	Esc, F10	Storage tab, Boot Order, Legacy Boot Sources
HP	desktop	TouchSmart 520 PC	Esc	Then F9 for "Boot Menu"	Esc, F10	Storage tab, Boot Order, Legacy Boot Sources
HP	laptop	2000	Esc	Select "Patriot Memory" on the Boot Option Menu	Esc	
HP	notebook	Pavilion	Esc	Select "Patriot Memory" on the Boot Option Menu	F10	BIOS "Advanced" tab, Boot Order, Move "USB Device" before "Hard Drive"
HP	notebook	ENVY dv6 and dv7 PC	Esc	Then F9 for "Boot Menu"	Esc	F10 Storage tab, Boot Order, Legacy Boot Sources
INTEL			F10			
LENOVO	desktop		F12, F8, F10		F1, F2	
LENOVO	laptop		F12		F1, F2	
LENOVO	laptop	IdeaPad P500	F12 or Fn +		F2	

			F11			
NEC			F5		F2	
PACKARD BELL			F8		F1, Del	
SAMSUNG			F12, Esc			
SAMSUNG	netbook	NC10	Esc		F2	Boot Tab, Select "Boot Device Priority", Press Return, Up/Down to Highlight, F6/F5 to change priority
SAMSUNG	ultrabook	Series 5 Ultra and Series 7 Chronos	Esc		F2	Boot Tab, Select "Boot Device Priority", Press Return, Up/Down to Highlight, F6/F5 to change priority
SHARP					F2	
SONY		VAIO, PCG, VGN	F11		F1, F2, F3	
SONY		VGN Esc	F10		F2	BIOS "BOOT" section, "External Device Boot" enabled
TOSHIBA		Protege, Satellite, Tecra	F12		F1, Esc	
TOSHIBA		Equium F12	F12		F12	

Ausgeschnitten aus: https://www.boot-disk.com/quest_bootmenu.htm