Title

No File System Usage Events Happening (usually for File Systems Under 1 GB in Size)

Summary

Help Summary

A filesystem is above threshold percentage but the no alert is being generated. This is usually related to File Systems with 1GB or less total space.

Article Details

Problem Statement:

No event is triggered when a file system on a monitored device exceeds its threshold.

This may only affect some file systems (usually ones with less than 1 GB total space). Other File Systems on the same device may create events normally.

Version Affected:

All

Diagnostic Steps:

Verify the event is not triggered on the Event Page when the FS exceeds its threshold.

Root Cause:

By default, SL1's Internal Collections monitoring for File Systems only created events for FS greater than 1GB (1048576 KB) in total size.

Resolution:

The minimum size can be changed in the Database settings. To change the default value for fs_alert_min size of 1GB to other values where an event is required to be generated. For example, in the update query below the default min size has been changed to 200MB:

Step 1: The current value can be verified using the following query on the Database appliance (or DB Tool in UI):

```
SELECT fs_alert_min_size FROM master.system_settings_thresholds;
```

Step 2: Before making any changes with the UPDATE query below, ensure that a recent Config Backup has been created so it can be restored in case there is a failure.

Step 3: To update it to a smaller min size, i use the UPDATE query below on the Database appliance (or DB Tool in UI):

```
UPDATE master.system_settings_thresholds SET fs_alert_min_size=204800;
```

Note: the value is in KB, in this example 204800 KB = 200 MB, If ALL File Systems need to be alerted on, set this value to 1 instead.