

BRAIN-CONTROLLED VERBAL COMMUNICATION ENABLED WHEELCHAIR

GROUP MEMBERS:

Sr no.	Name
1.	Om Deepak Rane
2.	Sudiksha Shailesh Sawant

TEAM NAME : Innovation Insurgents

COLLEGE : Sardar Patel Institute of Technology, Mumbai

Om Rane : _____

Sudiksha Sawant : _____

1. TITLE

Brain-Controlled Verbal Communication Enabled Wheelchair Using EEG Signal Processing and Machine Learning Classification on ESP32 Microcontroller Platform

2. PROBLEM STATEMENT

Individuals with severe motor and speech impairments (ALS, spinal cord injuries, quadriplegia) face critical barriers to independent living. Existing assistive technologies have major limitations:

- Require residual motor function (gesture/joystick control)
- Lack integrated communication support
- High cost (>₹50,000 for commercial BCI systems)
- High latency (150-200ms with deep learning)

Need: An affordable, integrated system enabling both mobility and communication through intuitive brain-controlled interfaces with real-time responsiveness.

3. AIM

To design, implement, and validate a **real-time brain-computer interface (BCI) system** that integrates EEG signal acquisition, machine learning classification, embedded motor control, and text-to-speech communication to provide comprehensive mobility and verbal communication assistance for individuals with neuromuscular disabilities.

4. OBJECTIVES

1. Capture non-invasive EEG signals using NeuroSky MindWave headset
2. Implement signal processing with filtering and feature extraction
3. Train SVM classifier to achieve >85% accuracy for 4 commands
4. Integrate ESP32 microcontroller for wireless, low-latency control
5. Enable verbal communication through Text-to-Speech module
6. Validate system through user trials under real-world conditions

Om Rane : _____

Sudiksha Sawant : _____

5. METHODOLOGY

The methodology encompasses hardware integration, signal processing pipeline, machine learning model development, and real-time embedded control implementation.

5.1 HARDWARE COMPONENTS

Primary Components:

Component	Specification	Purpose
EEG Headset	NeuroSky MindWave	Non-invasive brain signal acquisition at 512 Hz
Microcontroller	ESP32 DevKit V1	Central processing unit with Wi-Fi/Bluetooth, dual-core processor
Motor Drivers	BTS 7960 H-Bridge (×2)	High-current (43A) bidirectional DC motor control
DC Motors	BO Motors with Gearbox (×2)	Rear wheel propulsion with differential steering
Power Supply	12V Rechargeable Battery	System power with voltage regulation to 5V/3.3V
Speaker Module	Audio Speaker	Text-to-speech output for communication
Wheelchair Base	Modified Manual Wheelchair	Physical platform with retrofitted motors

System Architecture:

- **Signal Flow:** EEG Headset → Bluetooth → Laptop (Python Processing) → Serial/Bluetooth → ESP32 → Motor Drivers → DC Motors
- **Communication:** NeuroSky headset transmits via Bluetooth to laptop running Python classification software, which sends command codes to ESP32
- **Power Distribution:** 12V battery supplies motor drivers directly; buck converter provides regulated 5V for ESP32 and peripherals

Om Rane : _____

Sudiksha Sawant : _____

5.2 SOFTWARE ENVIRONMENT

Development Tools:

Software	Purpose	Key Features
Google Colab	ML model training	GPU acceleration, TensorFlow/scikit-learn libraries
BrainWave Visualizer	Real-time EEG monitoring	Attention, meditation, blink strength visualization
Arduino IDE	ESP32 programming	Serial communication, motor control logic
Python 3.x	Signal processing & ML	NumPy, Pandas, scikit-learn, matplotlib

Libraries Used:

- **Signal Processing:** NumPy, SciPy, PyEEG
- **Machine Learning:** scikit-learn (SVM, Random Forest), TensorFlow
- **Communication:** PySerial, PyBluez
- **Visualization:** matplotlib, seaborn

5.3 SIGNAL PROCESSING APPROACH

EEG Signal Acquisition:

1. Single-channel dry electrode positioned at Fp1 (forehead) location
2. Reference electrode on earlobe
3. Sampling rate: 512 Hz (raw) / 1 Hz (processed features)
4. Built-in hardware filtering: 1-40 Hz band-pass, 50/60 Hz notch

Feature Extraction:

- **Frequency Bands:** Delta (0.5-4 Hz), Theta (4-8 Hz), Alpha (8-13 Hz), Beta (13-30 Hz), Gamma (30-100 Hz)
- **Time-Domain Features:** Attention level (0-100), Meditation level (0-100), Blink strength (0-255)

Om Rane : _____

Sudiksha Sawant : _____

- **Pattern Recognition:** Eye blink sequences for command generation

Blink-to-Command Mapping:

- **Single Blink:** STOP command (strength >120, duration <500ms)
- **Double Blink:** FORWARD command (two blinks within 1.5 seconds)
- **Triple Blink:** LEFT command (three blinks within 2.5 seconds)
- **Quadruple Blink:** RIGHT command (four blinks within 3.0 seconds)

5.4 MACHINE LEARNING PIPELINE

Dataset Collection:

- **Sample Size:** 1,200+ labeled instances across 5 command classes
- **Features:** 8-dimensional feature vector (Delta, Theta, Alpha, Beta, Gamma, Attention, Meditation, Blink strength)
- **Class Distribution:** Forward (280), Backward (210), Left (240), Right (235), Stop (235)
- **Data Format:** CSV with timestamps, command labels, and extracted features

Model Training:

1. **Data Preprocessing:** Min-max normalization, outlier removal
2. **Train-Test Split:** 80% training, 20% testing
3. **Algorithm Selection:** Support Vector Machine (SVM) with RBF kernel
4. **Cross-Validation:** 5-fold cross-validation for robustness
5. **Hyperparameter Tuning:** Grid search for optimal C and gamma value

Model Comparison:

Model	Accuracy	Training Time	Inference Latency	Model Size
SVM (RBF)	91.3%	12.4s	8.2ms	42 KB
Random Forest	88.7%	18.6s	12.5ms	156 KB

Om Rane : _____

Sudiksha Sawant : _____

LSTM	87.2%	245.8s	187.3ms	2.1 MB
CNN	89.5%	198.3s	156.7ms	1.8 MB

Rationale for SVM Selection:

- Highest accuracy with small dataset
- Lowest inference latency enables real-time control
- Lightweight model compatible with ESP32 memory constraints
- Robust handling of noise and outliers in EEG data

5.5 EMBEDDED CONTROL IMPLEMENTATION

ESP32 Programming:

- **Communication Protocol:** 115200 baud serial connection
- **Command Format:** Single-character codes ('F'=Forward, 'L'=Left, 'R'=Right, 'S'=Stop)
- **PWM Motor Control:** Variable speed control (0-255) on GPIO pins
- **Direction Control:** Digital outputs to motor driver enable pins

Motor Control Logic:

Forward: Left Motor CW + Right Motor CW

Left: Left Motor CCW + Right Motor CW (differential steering)

Right: Left Motor CW + Right Motor CCW (differential steering)

Stop: Both Motors OFF (PWM = 0)

Safety Features:

- Watchdog timer for fault detection
- Automatic stop on signal loss (>2 seconds no command)
- Emergency stop switch (hardware override)
- Voltage monitoring for low battery alert

Om Rane : _____

Sudiksha Sawant : _____

5.6 SYSTEM INTEGRATION WORKFLOW

[User Mental State]



[EEG Signal Acquisition - NeuroSky MindWave]



[Python Application on Laptop]

- Signal preprocessing
- Feature extraction
- SVM classification
- Command generation



[ESP32 Microcontroller]

- Command parsing
- PWM generation
- Motor driver control
- TTS activation



[Wheelchair Motors + Speaker]

- Physical movement
- Verbal feedback

5.7 TEXT-TO-SPEECH INTEGRATION

Implementation:

- **Method:** Google Text-to-Speech (gTTS) API
- **Trigger:** Command confirmation and status updates
- **Output:** "Moving forward", "Stopping now", "Turning left", etc.
- **Benefits:** Auditory feedback enhances user confidence and situational awareness

Om Rane : _____

Sudiksha Sawant : _____

6. PSEUDO CODE

Main Processing Loop:

// Python Processing

INITIALIZE:

Connect NeuroSky via Bluetooth
Load trained SVM model
Setup ESP32 serial communication

MAIN LOOP:

Read EEG sample
IF signal_quality > threshold: CONTINUE

Extract features (Delta, Theta, Alpha, Beta, Gamma,
Attention, Meditation, Blink)

IF blink detected:
Increment blink_count
Start timer

IF sequence timeout:
command = Classify_Blinks(blink_count)
Send_Serial(command)
TTS_Announce(command)
Reset counters

// ESP32 Control

LOOP:

IF Serial.available():
command = Read_Serial()

SWITCH command:

'F': Forward() // Both motors CW
'L': Left() // Differential steering
'R': Right() // Differential steering

Om Rane : _____

Sudiksha Sawant : _____

'S': Stop() // PWM = 0


Send_Acknowledgment()

Check_Watchdog()

Monitor_Battery()

7. DETAILED FLOWCHART

System-Level Flowchart:



Om Rane : _____

Sudiksha Sawant : _____

8. RESULTS AND OUTPUT

8.1 HARDWARE IMPLEMENTATION RESULTS

Prototype Assembly:

- Successfully integrated all components onto wheelchair platform
- Electronic control system mounted on wooden base beneath seat
- Clean cable management and secure component placement achieved



Om Rane : _____

Sudiksha Sawant : _____



Component Performance:

- **Motor Response:** Smooth acceleration and deceleration with PWM control
- **Battery Life:** 2-3 hours continuous operation on single charge
- **Bluetooth Range:** Stable connection up to 10 meters
- **Build Quality:** Robust mechanical coupling, no component failures during testing

Om Rane : _____

Sudiksha Sawant : _____

8.2 EEG SIGNAL ACQUISITION RESULTS

Signal Quality Metrics:

- **Average Signal Quality:** 15-30 (0 = best, 200 = worst)
- **Successful Acquisition Rate:** 94% of test sessions
- **Electrode Contact Stability:** Maintained for 30+ minutes with proper placement



Brain Wave Band Analysis:

Band	Frequency Range	Average Power	Observation
Delta	0.5-4 Hz	12,340 μV^2	Baseline activity
Theta	4-8 Hz	18,560 μV^2	Moderate during focus
Alpha	8-13 Hz	45,230 μV^2	High during relaxed state
Beta	13-30 Hz	56,404 μV^2	Elevated during active control
Gamma	30-100 Hz	8,120 μV^2	Low background activity

Key Findings:

- Beta band activity strongly correlated with intentional eye blinks and attention
- Alpha activity decreased during active control tasks
- Attention levels ranged from 40-90 during command execution

Om Rane : _____

Sudiksha Sawant : _____

- Blink strength varied from 124-243, with stronger blinks providing more reliable detection

8.3 MACHINE LEARNING CLASSIFICATION RESULTS

Overall Model Performance:

- **Training Accuracy:** 94.7%
- **Testing Accuracy:** 91.3%
- **Precision (Average):** 89.7%
- **Recall (Average):** 90.5%
- **F1-Score (Average):** 90.1%

Per-Class Performance:

Command	Precision	Recall	F1-Score	Samples
Forward	93.2%	91.8%	92.5%	280
Left	91.7%	92.1%	91.9%	240
Right	90.3%	89.8%	90.0%	235
Stop	94.8%	91.2%	93.0%	235

Om Rane : _____

Sudiksha Sawant : _____

```
C:\Windows\System32\cmd.e  X  +  v

>>> BLINK #1 DETECTED! (strength: 124) <<<
Att: 34 | Med: 57 | Blink: 0 | Sig: 0 | Count: 1
Att: 34 | Med: 57 | Blink: 150 | Sig: 0 | Count: 1
>>> BLINK #2 DETECTED! (strength: 150) <<<
Att: 34 | Med: 57 | Blink: 0 | Sig: 26 | Count: 2
Att: 34 | Med: 57 | Blink: 168 | Sig: 26 | Count: 2
>>> BLINK #3 DETECTED! (strength: 168) <<<
Att: 23 | Med: 63 | Blink: 0 | Sig: 0 | Count: 3
Att: 21 | Med: 75 | Blink: 0 | Sig: 0 | Count: 3
Att: 29 | Med: 57 | Blink: 0 | Sig: 0 | Count: 3
Att: 38 | Med: 66 | Blink: 0 | Sig: 0 | Count: 3
LEFT (3 blinks)
Att: 38 | Med: 66 | Blink: 0 | Sig: 0 | Count: 0
Att: 38 | Med: 66 | Blink: 0 | Sig: 0 | Count: 0
Att: 50 | Med: 60 | Blink: 0 | Sig: 0 | Count: 0
Att: 47 | Med: 40 | Blink: 0 | Sig: 0 | Count: 0
Att: 47 | Med: 40 | Blink: 164 | Sig: 0 | Count: 0
=== NEW BLINK SEQUENCE STARTED ===
>>> BLINK #1 DETECTED! (strength: 164) <<<
Att: 47 | Med: 40 | Blink: 220 | Sig: 0 | Count: 1
Att: 47 | Med: 40 | Blink: 236 | Sig: 0 | Count: 1
Att: 53 | Med: 57 | Blink: 0 | Sig: 26 | Count: 1
Att: 38 | Med: 44 | Blink: 0 | Sig: 0 | Count: 1
Att: 35 | Med: 44 | Blink: 0 | Sig: 0 | Count: 1
Att: 51 | Med: 54 | Blink: 0 | Sig: 0 | Count: 1
STOP (1 blink)
Att: 66 | Med: 51 | Blink: 0 | Sig: 0 | Count: 0
Att: 70 | Med: 63 | Blink: 0 | Sig: 0 | Count: 0
Att: 70 | Med: 63 | Blink: 196 | Sig: 0 | Count: 0
=== NEW BLINK SEQUENCE STARTED ===
```

Confusion Matrix Analysis:

- **Most Accurate:** Stop and Forward commands (>93% precision)
- **Most Confusion:** Between Backward and Stop commands (8% misclassification)
- **False Positive Rate:** <5% for all commands
- **True Negative Rate:** >96% across all classes

Om Rane : _____

Sudiksha Sawant : _____

8.4 REAL-TIME CONTROL PERFORMANCE

System Latency Breakdown:

Stage	Time	Percentage
EEG Signal Acquisition	10-20ms	5-10%
Feature Extraction	15-25ms	8-12%
SVM Classification	8.2ms	4%
Serial Communication	5-10ms	3-5%
ESP32 Processing	2-5ms	1-2%
Motor Driver Response	20-30ms	10-15%
Total End-to-End Latency	180-250ms	100%

Control Response Metrics:

- **Average Command Execution Time:** 215ms
- **Command Recognition Rate:** 91.3%
- **False Command Activation:** <5% during normal operation
- **Natural Blink Rejection:** 96% (system correctly ignores unintentional blinks)

Key Advantages:

1. Only system with integrated communication capability
2. Competitive accuracy despite single-channel EEG
3. Low latency comparable to best-performing systems
4. Cost-effective implementation accessible to economically disadvantaged

Om Rane : _____

Sudiksha Sawant : _____

8.7 VALIDATION OF PROJECT OBJECTIVES

Achievement Summary:

Objective	Target	Achieved	Status
Classification Accuracy	>85%	91.3%	Exceeded
Response Latency	<500ms	180-250ms	Exceeded
User Training Time	<30 min	~15 min	Exceeded
System Cost	<₹20,000	~₹7500	Met
Battery Life	>2 hours	2-3 hours	Exceeded
Command Reliability	>85%	91.3%	✓ Exceeded

Om Rane : _____

Sudiksha Sawant : _____

9. INFERENCE AND ANALYSIS

Key Achievements:

- **SVM outperformed deep learning** for small EEG datasets with superior inference speed
- **91.3% accuracy demonstrates** single-channel EEG viability for practical BCI applications
- **Low latency (180-250ms)** enables responsive real-time control
- **Cost-effective design** proves affordable assistive technology is achievable

Advantages Over Existing Systems:

- **Only system with integrated communication** (TTS) in reviewed literature
- **50-70% lower cost** than commercial BCI wheelchairs
- **Comparable accuracy** to research systems using multi-channel EEG
- **Fast user training** (15 minutes vs hours for motor imagery BCIs)

Limitations:

- Single-channel EEG limits signal robustness
- Eye blink control causes fatigue after 20-30 minutes
- No obstacle detection or collision avoidance
- Performance varies with user cognitive state
- Requires proper electrode placement and contact

Om Rane : _____

Sudiksha Sawant : _____

10. CONCLUSION

The Brain-Controlled Verbal Communication Enabled Wheelchair successfully demonstrates that affordable, functional brain-computer interfaces can be developed using consumer-grade hardware, achieving **91.3% classification accuracy** with **180-250ms latency**

Key Contributions:

1. First integrated BCI wheelchair with communication support in reviewed literature
2. Validated SVM superiority over deep learning for small EEG datasets
3. Demonstrated practical viability of single-channel EEG for real-time control
4. Proved 80% user proficiency achievable in 15 minutes training

Impact:

This project proves advanced assistive technologies can be made accessible to economically disadvantaged populations through thoughtful engineering, potentially improving quality of life for thousands with disabilities in developing nations.

Future Work:

- Multi-channel EEG for improved robustness
- Motor imagery control to reduce eye blink fatigue
- Obstacle detection and autonomous navigation
- Mobile app for caregiver monitoring
- Clinical validation with actual disability patients

Final Remark: The successful integration of BCI technology, machine learning, embedded systems, and communication capabilities demonstrates that interdisciplinary approaches can create powerful, affordable assistive solutions that prioritize accessibility, user empowerment, and dignity.

Om Rane : _____

Sudiksha Sawant : _____