

Publishing Your LED Mask Website to GitHub Pages

This guide walks you through publishing your single-file website to **GitHub Pages** so anyone on the internet can view and interact with it.

You can complete this entire process directly inside your web browser in **under 5 minutes** without installing Git, Node.js, or using the terminal.

Prerequisites

1. A free GitHub account (sign up at `github.com` if you don't already have one).
2. Your website file saved on your computer with the exact name: `index.html`.

(Note: Naming the file exactly `index.html` in lowercase is mandatory so GitHub automatically recognizes it as your homepage).

Step 1: Prepare Your `index.html` File

If you have not saved the code onto your computer yet:

1. Open a basic text editor on your computer:
 - **Windows:** Open **Notepad** (or Notepad++ / VS Code).
 - **Mac:** Open **TextEdit** (go to *Format > Make Plain Text*).
2. Copy the complete HTML code from the LED mask prototype.
3. Paste the code into the text editor.
4. Save the file as:

`index.html`

(Ensure the file type is "All Files" in Windows Notepad so it does not save as `index.html.txt`).

Step 2: Create a New GitHub Repository

1. Log in to your account at `github.com`.
2. Look at the top-right corner of the page and click the **+** icon, then select **New repository**.

3. Fill in the repository details:
 - **Repository name:** Enter a short name such as `led-mask-showcase` or `led-skincare-mask`.
 - **Description (optional):** "Interactive LED therapy face mask product showcase".
 - **Visibility:** Choose **Public** (*Free GitHub Pages requires a public repository unless you have GitHub Pro*).
 - **Initialize this repository with:** Check the box next to **Add a README file** (this makes uploading through the browser easier).
 4. Click the green **Create repository** button at the bottom.
-

Step 3: Upload `index.html` via the Browser

1. Inside your newly created repository, click the **Add file** dropdown button near the top right.
 2. Select **Upload files**.
 3. Drag and drop your `index.html` file into the upload box (or click **choose your files** and select it from your computer).
 4. Scroll down to the **Commit changes** box:
 - In the commit summary box, you can leave it as default or type: `Add index.html`.
 5. Click the green **Commit changes** button. Your `index.html` file will now appear in your repository file list.
-

Step 4: Enable GitHub Pages

1. In your repository menu bar, click on **Settings** (represented by the gear icon on the far right).
 2. On the left sidebar, scroll down to the **Code and automation** section and click on **Pages**.
 3. Under **Build and deployment**:
 - **Source:** Ensure it is set to **Deploy from a branch**.
 - **Branch:** Click the dropdown that says **None** and change it to **main** (or **master**).
 - Leave the folder set to **/(root)**.
 4. Click **Save**.
-

Step 5: View Your Live Website

1. Wait approximately **1 to 2 minutes** while GitHub deploys your site.
2. Refresh the **Settings > Pages** screen.
3. You will see a banner at the top of the page that says:

"Your site is live at https://

4. Click the **Visit site** button or open the link in any browser tab to see your interactive LED mask website live.

Quick Troubleshooting & Tips

Problem	Cause	Quick Fix
404 Not Found error	The file is not named <code>index.html</code> or deployment is still processing.	Double-check that your file is named exactly <code>index.html</code> (all lowercase) in the main root directory. Wait 2 minutes and refresh.
Code displays as plain text	The file was saved as <code>index.html.txt</code> .	Rename the file locally to <code>index.html</code> , re-upload, and commit changes.
Light toggle buttons not glowing	CSS or SVG styles blocked.	The provided code is 100% self-contained without external CDNs, so it will work immediately upon load.
Updating your site	You made changes to the code.	Click on <code>index.html</code> inside GitHub, click the pencil icon (Edit this file), paste your new code, and click Commit changes . GitHub Pages will automatically update within 1–2 minutes.