

OPI_CM5_CORE JP1 100PIN						
Description	Pin Name	Pin Net	PIN NO.		Signal	Description
Ground (0V)		GND	1	2	GND	Ground (0V)
Floating		Reserved	3	4	Reserved	Floating
Floating		Reserved	5	6	Reserved	Floating
Ground (0V)		GND	7	8	GND	Ground (0V)
Floating		Reserved	9	10	Reserved	Floating
Floating		Reserved	11	12	Reserved	Floating
Ground (0V)		GND	13	14	GND	Ground (0V)
Floating		Reserved	15	16	Reserved	Floating
Floating		Reserved	17	18	Reserved	Floating
Floating		Reserved	19	20	Reserved	Floating
GPIO Typically a 3.3V	CIF_D4/BT1120_D4/DDRPHY_CH1_DT8_0/I2C3_SCL_M2/UART0_RX_M2/SPI2_MISO_M1/GPIO4_A4_d	GPIO4_A4	21	22	GND	Ground (0V)
Ground (0V)		GND	23	24	GPIO1_C0	GPIO Typically a 3.3V , 3.3V or 1.8V
GPIO Typically a 3.3V , 3.3V or 1.8V	PDM1_SDI1_M1/SPI2_CS1_M0/GPIO1_B0_u	GPIO1_B0	25	26	GPIO1_C1	GPIO Typically a 3.3V , 3.3V or 1.8V
GPIO Typically a 3.3V , 3.3V or 1.8V	PDM1_SDI2_M1/SPI0_MISO_M2/GPIO1_B1_d	GPIO1_B1	27	28	GPIO1_A2	GPIO Typically a 3.3V , 3.3V or 1.8V
GPIO Typically a 3.3V , 3.3V or 1.8V	PDM1_SDI3_M1/UART4_RX_M2/SPI0_MOSI_M2/GPIO1_B2_d	GPIO1_B2	29	30	GPIO1_A3	GPIO Typically a 3.3V , 3.3V or 1.8V
GPIO Typically a 3.3V , 3.3V or 1.8V	PDM1_CLK1_M1/SATA0_ACT_LED_M1/UART4_TX_M2/SPI0_CLK_M2/GPIO1_B3_d	GPIO1_B3	31	32	GND	Ground (0V)
Ground (0V)		GND	33	34	GPIO1_A4	GPIO Typically a 3.3V , 3.3V or 1.8V
GPIO Typically a 3.3V	MIPI_CAMERA3_CLK_M0/I2C8_SCL_M2/UART1_RTSN_M1/PWM14_M2/GPIO1_D6_u	GPIO1_D6	35	36	GPIO1_D7	GPIO Typically a 3.3V
GPIO Typically a 3.3V , 3.3V or 1.8V	PDM1_CLK0_M1/UART7_RX_M2/SPI0_CS0_M2/GPIO1_B4_u	GPIO1_B4	37	38	GPIO1_A5	GPIO Typically a 3.3V , 3.3V or 1.8V
GPIO Typically a 3.3V , 3.3V or 1.8V	UART7_TX_M2/SPI0_CS1_M2/GPIO1_B5_u	GPIO1_B5	39	40	GPIO1_A6	GPIO Typically a 3.3V , 3.3V or 1.8V
GPIO Typically a 3.3V , 3.3V or 1.8V	MIPI_CAMERA1_CLK_M0/SPDIF0_TX_M0/I2C5_SCL_M3/UART1_TX_M1/GPIO1_B6_u	GPIO1_B6	41	42	GND	Ground (0V)
Ground (0V)		GND	43	44	GPIO1_A7	GPIO Typically a 3.3V , 3.3V or 1.8V
GPIO Typically a 3.3V , 3.3V or 1.8V	MIPI_CAMERA2_CLK_M0/SPDIF1_TX_M0/SATA2_ACT_LED_M1/I2C5_SD_A_M3/UART1_RX_M1/PWM13_M2/GPIO1_B7_u	GPIO1_B7	45	46	GPIO1_C4	GPIO Typically a 3.3V , 3.3V or 1.8V
GPIO Typically a 3.3V , 3.3V or 1.8V	PMIC_SLEEP4/GPIO0_C2_d	GPIO0_C2	47	48	GPIO1_C6	GPIO Typically a 3.3V , 3.3V or 1.8V
GPIO Typically a 3.3V , 3.3V or 1.8V	PDM0_SDI0_M0/SPI1_CS1_M2/GPIO1_D5_d	GPIO1_D5	49	50	GPIO1_D0	GPIO Typically a 3.3V , 3.3V or 1.8V
GPIO Typically a 3.3V , 3.3V or 1.8V	I2S1_SCLK_M1/JTAG_TMS_M2/I2C1_SDA_M0/UART2_RX_M0/PCIE2_0X1_1_WAKEN_M0/GPIO0_B6_d	UART2_RX_M0	51	52	GND	Ground (0V)
Ground (0V)		GND	53	54	GPIO1_D1	GPIO Typically a 3.3V , 3.3V or 1.8V
GPIO Typically a 3.3V , 3.3V or 1.8V	I2S1_MCLK_M1/JTAG_TCK_M2/I2C1_SCL_M0/UART2_TX_M0/PCIE2_0X1_1_CLKREQN_M0/GPIO0_B5_d	UART2_TX_M0	55	56	GPIO1_D2	GPIO Typically a 3.3V , 3.3V or 1.8V
SDCARD CLK signal	SDMMC_CLK/PDM1_CLK0_M0/TEST_CLKOUT_M0/MCU_JTAG_TMS_M0/CAN0_RX_M1/UART5_TX_M0/GPIO4_D5_d	SDMMC_CLK	57	58	GPIO1_D3	GPIO Typically a 3.3V , 3.3V or 1.8V
Ground (0V)		GND	59	60	GND	Ground (0V)
SDCARD Data3 signal	SDMMC_D3/PDM1_SDI0_M0/JTAG_TMS_M0/I2C8_SDA_M0/UART5_RT_SN_M0/PWM10_M1/GPIO4_D3_u	SDMMC_D3	61	62	SDMMC_CMD	SDCARD CMD signal
SDCARD Data0 signal	SDMMC_D0/PDM1_SDI3_M0/JTAG_TCK_M1/I2C3_SCL_M4/UART2_TX_M1/PWM8_M1/GPIO4_D0_u	SDMMC_D0	63	64	Reserved	Do not Connect anything to this pin.
Ground (0V)		GND	65	66	GND	Ground (0V)
SDCARD Data1 signal	SDMMC_D1/PDM1_SDI2_M0/JTAG_TMS_M1/I2C3_SDA_M4/UART2_RX_M1/PWM9_M1/GPIO4_D1_u	SDMMC_D1	67	68	SARADC_IN1	RECOVERY signal , Internally pulled up via 10K to1.8V
SDCARD Data2 signal	SDMMC_D2/PDM1_SDI1_M0/JTAG_TCK_M0/I2C8_SCL_M0/UART5_CTS_N_M0/GPIO4_D2_u	SDMMC_D2	69	70	Reserved	Floating
Ground (0V)		GND	71	72	Reserved	Floating
Do not Connect anything to this pin.		Reserved	73	74	GND	Ground (0V)
Output to Power switch for the SDCARD GPIO4_B4 For 3.3V GPIO.	SPI2_CLK_M2/SDMMC_PWREN/PMU_DEBUG/GPIO0_A5_d	SDMMC_PWREN	75	76	GPIO0_A4	SDMMC_DET GPIO0_A4,For 1.8V GPIO.
4.75V-5.25V Main power input	Main power input	VBUS	77	78	GPIO_VREF	Power for 3.3V GPIO or for 1.8V
4.75V-5.25V Main power input	Main power input	VBUS	79	80	I2C6_SCL_M3	IIC Clock pin GPIO4_B1, for 3.3V
4.75V-5.25V Main power input	Main power input	VBUS	81	82	I2C6_SDA_M3	IIC Data pin GPIO4_B0, for 3.3V
4.75V-5.25V Main power input	Main power input	VBUS	83	84	VCC_3V3_S3	3.3V +/-2.5% Power Output max 300mA per pin for a total of 600mA.
4.75V-5.25V Main power input	Main power input	VBUS	85	86	VCC_3V3_S3	3.3V +/-2.5% Power Output max 300mA per pin for a total of 600mA.

4.75V-5.25V Main power input	Main power input	VBUS	87	88	VCC_1V8_S3	POWER VCC_1V8 Out	1.8V +/-2.5% Power Output max 300mA per pin for a total of 600mA.
Floating		Reserved	89	90	VCC_1V8_S3	POWER VCC_1V8 Out	1.8V +/-2.5% Power Output max 300mA per pin for a total of 600mA.
Floating		Reserved	91	92	PMIC_RESET_L	RESET,PMU IN And RK3588S	Bidirectional pin. Can be driven low to Reset the CM5 CPU.
A low on this pin forces booting , Internally pulled up via IO to1.8V	SARADC_IN0_BOOT	SARADC_IN0	93	94	SARADC_IN3	SARADC_IN3	12-bit ADC in signal,MAX 1.8V
GPIO4_B6, for 3.3V	BT1120_D12/SATA0_ACT_LED_M0/DDRPHY_CH3_DTB2/I2C5_SCL_M1/PWM13_M1/SPI3_MOSI_M1/GPIO4_B6_d	GPIO4_B6	95	96	SARADC_IN2	SARADC_IN2	12-bit ADC in signal,MAX 1.8V
GPIO4_A7, for 3.3V	CIF_D7/BT1120_D7/I2S1_SDI2_M0/DDRPHY_CH1_DTB3/I2C5_SDA_M2/SPI2_CS0_M1/GPIO4_A7_d	GPIO4_A7	97	98	GND		Ground (0V)
Input. Drive low to power off or power on .CM5. Internally pulled up with a 45K to VBUS	POWER KEY(PWRON_L To GND).	PWRON_L	99	100	GPIO4_A5	CIF_D5/BT1120_D5/I2S1_SDI0_M0/DDRPHY_CH1_DTB_1/I2C3_SD_A_M2/UART3_TX_M2/SPI2_MOSI_M1/GPIO4_A5_d	GPIO4_A5, for 3.3V

OPI_CM5_CORE JP2 100PIN

Description		Signal	PIN NO.	Signal		Description
TYPEC0_USB20_OTG_ID	TYPEC0_USB20_OTG_ID	TYPEC0_USB20_OTG_ID	1 2	GPIO1_A0	PCIE20X1_1_CLKREQN_M2/DP0_HPDI0_M2/I2C2_SDA_M4/UART6_RX_M1/SPI4_MISO_M2/GPIO1_A0_d	PCIE_CLKREQN GPIO1_A0 for 3.3V
TYPEC0_USB20_OTG_DM	TYPEC0_USB20_OTG_DM	TYPEC0_USB20_OTG_DM	3 4	GPIO1_A1	PCIE20X1_1_WAKEN_M2/I2C2_SCL_M4/UART6_TX_M1/SPI4_MOSI_M2/GPIO1_A1_d	PCIE_WAKEN GPIO1_A1 for 3.3V
TYPEC0_USB20_OTG_DP	TYPEC0_USB20_OTG_DP	TYPEC0_USB20_OTG_DP	5 6	GPIO4_A6	CIF_D6/BT1120_D6/I2S1_SDI1_M0/DDRPHY_CH1_DTB2/I2C5_SCL_M2/UART3_RX_M2/SPI2_CLK_M1/GPIO4_A6_d	GPIO4_A6 for 3.3V
Ground (0V)		GND	7 8	GND		Ground (0V)
PCIE20_PERSTn_3V3_L GPIO4_A2 for 3.3V	CIF_D2/BT1120_D2/I2S1_LRCK_M0/PCIE20X1_1_PERSTN_M1/DDRPHY_CH0_DTB2/SPI0_CLK_M1/GPIO4_A2_d	GPIO4_A2	9 10	PCIE20_2_REFCLKP	PCIE20_2_REFCLKP	PCIE20_2_REFCLKP,
Floating		Reserved	11 12	PCIE20_2_REFCLKN	PCIE20_2_REFCLKN	PCIE20_2_REFCLKN
Ground (0V)		GND	13 14	GND		Ground (0V)
MIPI_CSI0_RX_D0N	MIPI_CSI0_D0N	MIPI_CSI0_D0N	15 16	PCIE20_2_RXP/ SATA30_2_RXP		PCIE20_2_RXP SATA30_2_RXP
MIPI_CSI0_RX_D0P	MIPI_CSI0_D0P	MIPI_CSI0_D0P	17 18	PCIE20_2_RXN/ SATA30_2_RXN		PCIE20_2_RXN SATA30_2_RXN
Ground (0V)		GND	19 20	GND		Ground (0V)
MIPI_CSI0_RX_D1N	MIPI_CSI0_D1N	MIPI_CSI0_D1N	21 22	PCIE20_2_TXP/ SATA30_2_TXP		PCIE20_2_TXP SATA30_2_TXP
MIPI_CSI0_RX_D1P	MIPI_CSI0_D1P	MIPI_CSI0_D1P	23 24	PCIE20_2_TXN/ SATA30_2_TXN		PCIE20_2_TXN SATA30_2_TXN
Ground (0V)		GND	25 26	GND		Ground (0V)
MIPI_CSI0_RX_CLK0N	MIPI_CSI0_CLK0N	MIPI_CSI0_CLK0N	27 28	MIPI_DPHY0_RX_D0N	MIPI_DPHY0_RX_D0N/MIPI_CPHY0_RX_TRIO0_A	MIPI_DPHY0_RX_D0N
MIPI_CSI0_RX_CLK0P	MIPI_CSI0_CLK0P	MIPI_CSI0_CLK0P	29 30	MIPI_DPHY0_RX_D0P	MIPI_DPHY0_RX_D0P/MIPI_CPHY0_RX_TRIO0_B	MIPI_DPHY0_RX_D0P
Ground (0V)		GND	31 32	GND		Ground (0V)
MIPI_CSI0_RX_D2N	MIPI_CSI0_D2N	MIPI_CSI0_D2N	33 34	MIPI_DPHY0_RX_D1N	MIPI_DPHY0_RX_D1N/MIPI_CPHY0_RX_TRIO0_C	MIPI_DPHY0_RX_D1N
MIPI_CSI0_RX_D2P	MIPI_CSI0_D2P	MIPI_CSI0_D2P	35 36	MIPI_DPHY0_RX_D1P	MIPI_DPHY0_RX_D1P/MIPI_CPHY0_RX_TRIO1_A	MIPI_DPHY0_RX_D1P
Ground (0V)		GND	37 38	GND		Ground (0V)
MIPI_CSI0_RX_D3N	MIPI_CSI0_D3N	MIPI_CSI0_D3N	39 40	MIPI_DPHY0_RX_CLKN	MIPI_DPHY0_RX_CLKN/MIPI_CPHY0_RX_TRIO1_B	MIPI_DPHY0_RX_CLKN
MIPI_CSI0_RX_D3P	MIPI_CSI0_D3P	MIPI_CSI0_D3P	41 42	MIPI_DPHY0_RX_CLKP	MIPI_DPHY0_RX_CLKP/MIPI_CPHY0_RX_TRIO1_C	MIPI_DPHY0_RX_CLKP
Floating		Reserved	43 44	GND		Ground (0V)
MIPI_CSI0_RX_CLK1N	MIPI_CSI0_CLK1N	MIPI_CSI0_CLK1N	45 46	Reserved		Floating
MIPI_CSI0_RX_CLK1P	MIPI_CSI0_CLK1P	MIPI_CSI0_CLK1P	47 48	Reserved		Floating
HDMI0_TX_ON_H GPIO4_B5 for 3.3V	BT1120_D11/DDRPHY_CH3_DTB1/UART9_RX_M1/PWM12_M1/SPI3_MISO_M1/GPIO4_B5_d	GPIO4_B5	49 50	GND		Ground (0V)
HDMI0_TX_CEC_M0 GPIO4_C1 for 3.3V	BT1120_D15/SPDIF1_TX_M2/PCIE20X1_2_PERSTN_M1/HDMI_TX0_CEC_M0/I2C8_SDA_M3/PWM6_M1/SPI3_CS1_M1/GPIO4_C1_d	HDMI_TX0_CEC_M0	51 52	Reserved		Floating
V2.1 HDMI0_HPD for HDMI V2.0	HDMI_TX0_SBDN/EDP_TX0_AUXN	HDMI_TX0_SBDN	53 54	Reserved		Floating
Ground (0V)		GND	55 56	GND		Ground (0V)
MIPI_DPHY0_TX_D0N	MIPI_DPHY0_TX_D0N/MIPI_CPHY0_TX_TRIO0_A	MIPI_DPHY0_TX_D0N	57 58	HDMI_TX0_SBDP	HDMI_TX0_SBDP/EDP_TX0_AUXP	HDMI0_SBDP,for HDMI V2.1
MIPI_DPHY0_TX_D0P	MIPI_DPHY0_TX_D0P/MIPI_CPHY0_TX_TRIO0_B	MIPI_DPHY0_TX_D0P	59 60	Reserved		Floating
Ground (0V)		GND	61 62	GND		Ground (0V)
MIPI_DPHY0_TX_D1N	MIPI_DPHY0_TX_D1N/MIPI_CPHY0_TX_TRIO0_C	MIPI_DPHY0_TX_D1N	63 64	Reserved		Floating
MIPI_DPHY0_TX_D1P	MIPI_DPHY0_TX_D1P/MIPI_CPHY0_TX_TRIO1_A	MIPI_DPHY0_TX_D1P	65 66	Reserved		Floating
Ground (0V)		GND	67 68	GND		Ground (0V)
MIPI_DPHY0_TX_CLKN	MIPI_DPHY0_TX_CLKN/MIPI_CPHY0_TX_TRIO1_B	MIPI_DPHY0_TX_CLKN	69 70	HDMI_TX0_D2P	HDMI_TX0_D2P/EDP_TX0_D2P	HDMI0_TX2P
MIPI_DPHY0_TX_CLKP	MIPI_DPHY0_TX_CLKP/MIPI_CPHY0_TX_TRIO1_C	MIPI_DPHY0_TX_CLKP	71 72	HDMI_TX0_D2N	HDMI_TX0_D2N/EDP_TX0_D2N	HDMI0_TX2N

Ground (0V)		GND	73	74	GND		Ground (0V)
MIPI_DPHY1_TX_D0N	MIPI_DPHY1_TX_D0N/MIPI_CPHY1_TX_TRIO0_A	MIPI_DPHY1_TX_D0N	75	76	HDMI_TX0_D1P	HDMI_TX0_D1P/EDP_TX0_D1P	HDMI0_TX1P
MIPI_DPHY1_TX_D0P	MIPI_DPHY1_TX_D0P/MIPI_CPHY1_TX_TRIO0_B	MIPI_DPHY1_TX_D0P	77	78	HDMI_TX0_D1N	HDMI_TX0_D1N/EDP_TX0_D1N	HDMI0_TX1N
Ground (0V)		GND	79	80	GND		Ground (0V)
MIPI_DPHY1_TX_D1N	MIPI_DPHY1_TX_D1N/MIPI_CPHY1_TX_TRIO0_C	MIPI_DPHY1_TX_D1N	81	82	HDMI_TX0_D0P	HDMI_TX0_D0P/EDP_TX0_D0P	HDMI0_TX0P
MIPI_DPHY1_TX_D1P	MIPI_DPHY1_TX_D1P/MIPI_CPHY1_TX_TRIO1_A	MIPI_DPHY1_TX_D1P	83	84	HDMI_TX0_D0N	HDMI_TX0_D0N/EDP_TX0_D0N	HDMI0_TX0N
Ground (0V)		GND	85	86	GND		Ground (0V)
MIPI_DPHY1_TX_CLKN	MIPI_DPHY1_TX_CLKN/MIPI_CPHY1_TX_TRIO1_B	MIPI_DPHY1_TX_CLKN	87	88	HDMI_TX0_D3P	HDMI_TX0_D3P/EDP_TX0_D3P	HDMI0_TX3P
MIPI_DPHY1_TX_CLKP	MIPI_DPHY1_TX_CLKP/MIPI_CPHY1_TX_TRIO1_C	MIPI_DPHY1_TX_CLKP	89	90	HDMI_TX0_D3N	HDMI_TX0_D3N/EDP_TX0_D3N	HDMI0_TX3N
Ground (0V)		GND	91	92	GND		Ground (0V)
MIPI_DPHY1_TX_D2N	MIPI_DPHY1_TX_D2N/MIPI_CPHY1_TX_TRIO2_A	MIPI_DPHY1_TX_D2N	93	94	MIPI_DPHY1_TX_D3N	MIPI_DPHY1_TX_D3N/MIPI_CPHY1_TX_TRIO2_C	MIPI_DPHY1_TX_D3N
MIPI_DPHY1_TX_D2P	MIPI_DPHY1_TX_D2P/MIPI_CPHY1_TX_TRIO2_B	MIPI_DPHY1_TX_D2P	95	96	MIPI_DPHY1_TX_D3P	MIPI_DPHY1_TX_D3P/NO_USE	MIPI_DPHY1_TX_D3P
Ground (0V)		GND	97	98	GND		Ground (0V)
HDMI_TX0_SDA_M0	BT1120_D14/PCIE20X1_2_WAKEN_M1/HDMI_TX0_SDA_M0/I2C8_SCL_M3/SPI3_CS0_M1/GPIO4_C0_u	HDMI_TX0_SDA_M0	99	100	HDMI_TX0_SCL_M0	BT1120_D13/PCIE20X1_2_CLKREQN_M1/HDMI_TX0_SCL_M0/DP0_PHY_CH3_DTB3/I2C5_SDA_M1/SPI3_CLK_M1/GPIO4_B7_u	HDMI_TX0_SCL_M0
GPI04_C0, for 3.3V							GPI04_B7, for 3.3V
OPI_CM5_CORE JP3 100PIN							
Description		Signal	PIN NO.		Signal		Description
USB20_HOST1_DP	USB20_HOST1_DP	USB20_HOST1_DP	1	2	TYPEC0_SSTX2P	TYPEC0_SSTX2P/DP0_TX3P	TYPEC0_SSTX2P
USB20_HOST1_DM	USB20_HOST1_DM	USB20_HOST1_DM	3	4	TYPEC0_SSTX2N	TYPEC0_SSTX2N/DP0_TX3N	TYPEC0_SSTX2N
Ground (0V)		GND	5	6	GND		Ground (0V)
TYPEC_SBU1	TYPEC0_SBU1/DP0_AUXP	TYPEC0_SBU1	7	8	TYPEC0_SSRX2P	TYPEC0_SSRX2P/DP0_TX2P	TYPEC0_SSRX2P
TYPEC_SBU2	TYPEC0_SBU2/DP0_AUXN	TYPEC0_SBU2	9	10	TYPEC0_SSRX2N	TYPEC0_SSRX2N/DP0_TX2N	TYPEC0_SSRX2N
Ground (0V)		GND	11	12	GND		Ground (0V)
USB20_HOST0_DP	USB20_HOST0_DP	USB20_HOST0_DP	13	14	TYPEC0_SSTX1N	TYPEC0_SSTX1N/DP0_TX1N	TYPEC0_SSTX1N
USB20_HOST0_DM	USB20_HOST0_DM	USB20_HOST0_DM	15	16	TYPEC0_SSTX1P	TYPEC0_SSTX1P/DP0_TX1P	TYPEC0_SSTX1P
Ground (0V)		GND	17	18	GND		Ground (0V)
TYPEC0_SSRX1N	TYPEC0_SSRX1N/DP0_TX0N	TYPEC0_SSRX1N	19	20	GPI03_C6	CIF_D10/SPI3_MISO_M3/GPIO3_C6_u	GPI03_C6 for 1.8V
TYPEC0_SSRX1P	TYPEC0_SSRX1P/DP0_TX0P	TYPEC0_SSRX1P	21	22	GPI03_C7	CIF_D11/PCIE20X1_2_CLKREQN_M0/HDMI_TX0_SCL_M2/I2C5_SCL_M0/SPI3_MOSI_M3/GPIO3_C7_u	PCIE20x1_2_CLKREQn_M0 GPI03_C7, for 1.8V
Ground (0V)		GND	23	24	GPI03_D1	PCIE20x1_2_PERSTn_M0/SPI0_MISO_M3/GPIO3_D1_d	PCIE20x1_2_PERSTn_M0 GPI03_D1, for 1.8V
MIPI_DPHY1_RX_CLKP	MIPI_DPHY1_RX_CLKP/MIPI_CPHY1_RX_TRIO1_C	MIPI_DPHY1_RX_CLKP	25	26	GPI03_D5	MCU_JTAG_TMS_M1/UART9_TX_M2/PWM11_IR_M3/SPI0_CS1_M3/GPIO3_D5_d	UART9_TX_M2_BT GPI03_D5, for 1.8V
MIPI_DPHY1_RX_CLKN	MIPI_DPHY1_RX_CLKN/MIPI_CPHY1_RX_TRIO1_B	MIPI_DPHY1_RX_CLKN	27	28	GPI03_D2	CIF_D14/I2C7_SCL_M2/UART9_RTSN_M2/SPI0_MOSI_M3/GPIO3_D2_d	UART9_RTSN_M2_BT GPI03_D2, for 1.8V
Ground (0V)		GND	29	30	GPI03_D4	HDMI_TX0_HPD_M1/MCU_JTAG_TCK_M1/UART9_RX_M2/SPI0_CS0_M3/GPIO3_D4_d	UART9_RX_M2_BT GPI03_D4, for 1.8V
MIPI_DPHY1_RX_D1P	MIPI_DPHY1_RX_D1P/MIPI_CPHY1_RX_TRIO1_A	MIPI_DPHY1_RX_D1P	31	32	GND		Ground (0V)
MIPI_DPHY1_RX_D1N	MIPI_DPHY1_RX_D1N/MIPI_CPHY1_RX_TRIO0_C	MIPI_DPHY1_RX_D1N	33	34	GPI03_B7	GMAC1_PTP_REF_CLK/I2C3_SCL_M1/SPI1_MOSI_M1/GPIO3_B7_d	GPI03_B7, for 1.8V
Ground (0V)		GND	35	36	GPI03_C5	CIF_D9/FSPI_CS1N_M2/CAN2_TX_M0/UART5_RX_M1/SPI3_CS1_M3/GPIO3_C5_u	GPI03_C5, for 1.8V
MIPI_DPHY1_RX_D0P	MIPI_DPHY1_RX_D0P/MIPI_CPHY1_RX_TRIO0_B	MIPI_DPHY1_RX_D0P	37	38	GPI03_C4	CIF_D8/FSPI_CS0N_M2/CAN2_RX_M0/UART5_TX_M1/SPI3_CS0_M3/GPIO3_C4_u	GPI03_C4, for 1.8V
MIPI_DPHY1_RX_D0N	MIPI_DPHY1_RX_D0N/MIPI_CPHY1_RX_TRIO0_A	MIPI_DPHY1_RX_D0N	39	40	GPI03_D3	CIF_D15/I2C7_SDA_M2/UART9_CTSN_M2/PWM10_M2/SPI0_CLK_M3/GPIO3_D3_d	UART9_CTSN_M2_BT GPI03_D3, for 1.8V
Ground (0V)		GND	41	42	GPI03_A1	GMAC1_TXD3/SDIO_D1_M1/I2S3_SCLK/AUDDSM_LN/FSPI_D2_M2/I2C6_SCL_M4/PWM11_IR_M0/SPI4_MOSI_M1/GPIO3_A1_u	GMAC_TXD3/SDIO_D1 GPI03_A1, for 1.8V
PCIE20x1_2_WAKEn_M0	CIF_D12/PCIE20X1_2_WAKEN_M0/HDMI_TX0_SDA_M2/I2C5_SDA_M0/GPI03_D0, for 1.8V	GPI03_D0	43	44	GND		Ground (0V)
Ground (0V)		GND	45	46	GPI03_B3	GMAC1_TXD0/I2S2_SDO_M1/UART2_RTSN/GPIO3_B3_u	GMAC_TXD0 GPI03_B3, for 1.8V
GMAC_TXD2/SDIO_D0	GMAC1_TXD2/SDIO_D0_M1/I2S3_MCLK/FSPI_D0_M2/I2C6_SDA_M4/PWM10_M0/SPI4_MISO_M1/GPIO3_A0_u	GPI03_A0	47	48	GPI03_B2	GMAC1_TXER/I2S2_SDI_M1/UART2_RX_M2/PWM3_IR_M1/GPIO3_B2_d	GMAC_TXER/PWM3_IR GPI03_B2, for 1.8V
GMAC_TXD1	GMAC1_TXD1/I2S2_MCLK_M1/UART2_CTSN/GPIO3_B4_u	GPI03_B4	49	50	GPI03_C1	GMAC1_PPSCCLK/UART7_RX_M1/SPI1_CLK_M1/GPIO3_C1_d	GPI03_C1, for 1.8V
GPI03_B4, for 1.8V							
GMAC_TXEN/PWM12	GMAC1_TXEN/I2S2_SCLK_M1/CAN1_RX_M0/UART3_TX_M1/PWM12_M0/GPIO3_B5_u	GPI03_B5	51	52	GPI03_A6	ETH1_REFCLK0_25M/MIPI_CAMERA1_CLK_M1/I2C4_SCL_M0/GPI03_A6_d	MIPI_CLK1 GPI03_A6, for 1.8V
GPI03_B5, for 1.8V							
GMAC_MDIO	GMAC1_MDIO/MIPI_TE1/I2C8_SDA_M4/UART7_CTSN_M1/PWM15_IR_M0/SPI1_CS1_M1/GPIO3_C3_d	GPI03_C3	53	54	GND		Ground (0V)
GPI03_C3, for 1.8V							
Ground (0V)		GND	55	56	GPI03_B0	GMAC1_RXD1/MIPI_CAMERA3_CLK_M1/PWM9_M0/GPIO3_B0_u	GMAC_RXD1/MIPI_CLK3/PWM9 GPI03_B0, for 1.8V
GMAC_MCLK/PWM13	GMAC1_MCLKINOUT/I2S2_LRCK_M1/CAN1_TX_M0/UART3_RX_M1/PWM13_M0/GPIO3_B6_d	GPI03_B6	57	58	GPI03_A5	GMAC1_RXCLK/SDIO_CLK_M1/MIPI_CAMERA0_CLK_M1/FSPI_CLK_M2/I2C4_SDA_M0/UART8_CTSN_M1/GPIO3_A5_d	GMAC_RXCLK/SDIO_CLK GPI03_A5, for 1.8V
GPI03_B6, for 1.8V							
GMAC_RXDV/MIPI_CLK4/PWM2	GMAC1_RXDV_CRS/MIPI_CAMERA4_CLK_M1/UART2_TX_M2/PWM2_M1/GPIO3_B1_d	GPI03_B1	59	60	GPI03_A7	GMAC1_RXD0/MIPI_CAMERA2_CLK_M1/PWM8_M0/GPIO3_A7_u	GMAC_RXD0/MIPI_CLK2/PWM8 GPI03_A7, for 1.8V
GPI03_B1, for 1.8V							

GMAC_RXD2/SDIO_D2 GPIO3_A2, for 1.8V	GMAC1_RXD2/SDIO_D2_M1/I2S3_LRCK/AUDDSM_LP/FSPL_D2_M2/UA RT8_TX_M1/SPI4_CLK_M1/GPIO3_A2_u	GPIO3_A2	61	62	GPIO3_A4	GMAC1_TXCLK/SDIO_CMD_M1/I2S3_SDI/AUDDSM_RP/UART8_RT SN_M1/SPI4_CS1_M1/GPIO3_A4_d	GMAC_TXCLK/SDIO_CMD GPIO3_A4, for 1.8V
GMAC_RXD3/SDIO_D3 GPIO3_A3, for 1.8V	GMAC1_RXD3/SDIO_D3_M1/I2S3_SDO/AUDDSM_RN/FSPL_D3_M2/UA RT8_RX_M1/SPI4_CS0_M1/GPIO3_A3_u	GPIO3_A3	63	64	GND		Ground (0V)
Ground (0V)		GND	65	66	GPIO0_B0	SPI2_CS1_M2/I2C1_SCL_M1/UART0_RX_M1/GPIO0_B0_z	GPIO0_B0, for 1.8V
REFCLK_OUT/GPIO0_A0 , for 1.8V	REFCLK_OUT/GPIO0_A0_d	GPIO0_A0	67	68	I2S0_MCLK	I2S0_MCLK/I2C6_SDA_M1/UART3_RTSN/PWM3_IR_M2/SPI4_CLK M0/GPIO1_C2_d	I2S0_MCLK GPIO1_C2, for 1.8V
I2S0_LRCK GPIO1_C5, for 1.8V	I2S0_LRCK/I2C2_SCL_M3/UART4_RTSN/GPIO1_C5_d	I2S0_LRCK	69	70	I2S0_SDO0	I2S0_SDO0/I2C4_SCL_M4/UART4_CTSN/GPIO1_C7_d	I2S0_SDO0 GPIO1_C7, for 1.8V
I2S0_SCLK GPIO1_C3, for 1.8V	I2S0_SCLK/I2C6_SCL_M1/UART3_CTSN/PWM7_IR_M2/SPI4_CS0_M0 /GPIO1_C3_d	I2S0_SCLK	71	72	GPIO3_C0	GMAC1_PPSTRIG/I2C3_SDA_M1/UART7_TX_M1/SPI1_MISO_M1/G PIO3_C0_d	GPIO3_C0, for 1.8V
I2S0_SDI0 GPIO1_D4, for 1.8V	I2S0_SDI0/GPIO1_D4_d	I2S0_SDI0	73	74	GND		Ground (0V)
Ground (0V)		GND	75	76	PCIE20_0_REFCLKP	PCIE20_0_REFCLKP	PCIE20_0_REFCLKP
GPIO0_D5, for 1.8V	I2S1_SDO3_M1/CPU_BIG1_AVS/I2C1_SDA_M2/CAN2_TX_M1/HDMI_TX 0_SCL_M1/SPI3_CS1_M2/SATA_MP_SWITCH/GPIO0_D5_u	GPIO0_D5	77	78	PCIE20_0_REFCLKN	PCIE20_0_REFCLKN	PCIE20_0_REFCLKN
GPIO0_C7, for 1.8V	I2S1_SDI2_M1/PDM0_SDI0_M1/I2C6_SDA_M0/UART1_RTSN_M2/PWM 6_M0/SPI0_MISO_M0/GPIO0_C7_d	GPIO0_C7	79	80	GND		Ground (0V)
GPIO0_D4, for 1.8V	I2S1_SDO2_M1/PDM0_SDI2_M1/PWM3_IR_M0/I2C1_SCL_M2/CAN2_R X_M1/HDMI_TX0_SDA_M1/SPI3_CS0_M2/SATA_CPDET/GPIO0_D4_u	GPIO0_D4	81	82	PCIE20_0_TXP	PCIE20_0_TXP/SATA30_0_TXP	PCIE20_0_TXP
GPIO0_C4, for 1.8V	PDM0_CLK1_M1/PWM2_M0/UART0_RX_M0/I2C4_SDA_M2/DP0_HPDI N_M1/GPIO0_C4_d	GPIO0_C4	83	84	PCIE20_0_TXN	PCIE20_0_TXN/SATA30_0_TXN	PCIE20_0_TXN
GPIO0_D3, for 1.8V	LITCPU_AVS/SPI3_CLK_M2/GPIO0_D3_u	GPIO0_D3	85	86	GND		Ground (0V)
Ground (0V)		GND	87	88	PCIE20_0_RXN	PCIE20_0_RXN/SATA30_0_RXN	PCIE20_0_RXN
GPIO0_D0, for 1.8V	I2S1_SDI3_M1/PDM0_SDI1_M1/I2C6_SCL_M0/UART1_CTSN_M2/PWM 7_IR_M0/SPI3_MISO_M2/GPIO0_D0_d	GPIO0_D0	89	90	PCIE20_0_RXP	PCIE20_0_RXP/SATA30_0_RXP	PCIE20_0_RXP
GMAC_MDC GPIO3_C2, for 1.8V	GMAC1_MDC/MIPI_TE0/I2C8_SCL_M4/UART7_RTSN_M1/PWM14_M0/ SPI1_CS0_M1/GPIO3_C2_d	GPIO3_C2	91	92	GND		Ground (0V)
GPIO4_A3, for 3.3V	CIF_D3/BT1120_D3/I2S1_SCLK_M0/DDRPHY_CH0_DTB_3/UART0_TX_M 2/GPIO4_A3_d	GPIO4_A3	93	94	GPIO0_C5	I2S1_SDI0_M1/GPU_AVS/UART0_TX_M0/I2C4_SCL_M2/PWM4_M0 /GPIO0_C5_u	GPIO0_C5, for 1.8V
CAN1_TX_M1/GPIO4_B3, for 3.3V	CIF_VSYNC/BT1120_D9/I2S1_SDO2_M0/PCIE20X1_2_BUTTON_RSTN/D DRPHY_CH2_DTB3/I2C7_SDA_M3/UART8_CTSN_M0/PWM15_IR_M1/C AN1_TX_M1/GPIO4_B3_u	GPIO4_B3	95	96	GPIO0_B2	CLK32K_IN/CLK32K_OUT0/GPIO0_B2_u	CLK32K_IN/GPIO0_B2, for 1.8V
CAN1_RX_M1/GPIO4_B2, for 3.3V	CIF_HREF/BT1120_D8/I2S1_SDO1_M0/PCIE20X1_1_BUTTON_RSTN/DD RPHY_CH2_DTB2/I2C7_SCL_M3/UART8_RTSN_M0/PWM14_M1/SPI0_C S0_M1/CAN1_RX_M1/GPIO4_B2_u	GPIO4_B2	97	98	GPIO0_C6	I2S1_SDI1_M1/NPU_AVS/UART0_RTSN/PWM5_M1/SPI0_CLK_M0/ SATA_CP_POD/GPIO0_C6_u	GPIO0_C6, for 1.8V
Ground (0V)		GND	99	100	GND		Ground (0V)