

How to connect different types of laptops and troubleshoot connection issues

Your laptop port type determines your connection method. So understand what ports your laptop has and decide what cable combination to use.

Connection Methods		
Laptop interface	Screen 1	Screen 2
2 full function Type-C ports (supports video output & power supply)	Type-C to Type-C cable*1	Type-C to Type-C cable*1
1 full function Type-C port 1 HDMI port (support video output) 1 USB-A or 1 Non-functional Type-C port (Support power supply).	Type-C to Type-C cable*1	HDMI to Type-C cable*1 USB-A to Type-C cable*1
2 HDMI ports 2 USB-A ports (or 2 Non-functional Type-C port)	HDMI to Type-C cable*1 USB-A to Type-C cable*1	HDMI to Type-C cable*1 USB-A to Type-C cable*1
Other special circumstances	Need to purchase adapter H5	

Note: Each type of cable must be connected to the corresponding port on the back of the expansion screen.



Common problem - "No signal" or "Enter power-saving mode" message appears on my screen.

1. Thunderbolt 3 / USB-C with DisplayPort ports+USB-A+HDMI Connection

Ensure that each screen has video and power. Confirm that your laptop has a USB-C interface with a display port or Thunderbolt 3 port, an HDMI interface, and a USB-A interface.

2. Thunderbolt 3 / USB-C Connection

If you use two USB-C/Thunderbolt 3 ports and two USB-C to C cables on your laptop for power supply and video, please ensure that the USB-C ports of your laptop support video transmission (full-function interface).

3. H5 adapter+USB-A+HDMI Connection

If your laptop does not have a USB-C/Thunderbolt 3 display port, but has one HDMI and two USB-A ports, you can use an H5 adapter to convert one of the USB-A ports to an HDMI port and connect it to the laptop expansion screen, then connect an external adapter to power that side screen. In other words, each screen is connected using a USB-A+HDMI cable.

4. I have connected the cable to the screen, but the screen is still black

If you connect the cable correctly and the screen is still black, the power supply of the laptop interface may be insufficient or unstable for the product. To ensure its normal operation, please use an adapter (5V/2A or above) to provide external power.