

8.UPLOAD

```
#include <ThingSpeak.h>

#include <ESP8266WiFi.h>

#include <SoftwareSerial.h>

#include <DHT.h>

#define DHTTYPE DHT11

#define DHTPin D5 DHT dht(DHTPin, DHTTYPE);

unsigned long ch_no =1932043;

const char * write_api = "6IN7SREAJYU1H1RY";

char ssid[] = "powerakk";

char pass[] = "kumaranil";

volatile float temperature=0, humidity=0;

WiFiClient client;

void setup(){

    pinMode(DHTPin,INPUT);

    Serial.begin(9600);

    WiFi.begin(ssid, pass);

    while (WiFi.status() != WL_CONNECTED)

    {

        delay(500);

        Serial.print(".");

    }

    Serial.println("WiFi connected");

    Serial.println(WiFi.localIP());

    ThingSpeak.begin(client);

}

void loop()

{
```

```
temperature = dht.readTemperature();  
  
humidity= dht.readHumidity();  
  
Serial.print("Temperature ="),Serial.print(temperature),Serial.println( "Degree  
Celcius");  
  
Serial.print("Humidity ="),Serial.print(humidity),Serial.println( "%RH");  
ThingSpeak.setField(1,humidity);  
  
ThingSpeak.setField(2,temperature);  
  
ThingSpeak.writeFields(ch_no, write_api);  
  
delay(15000);  
  
}
```