

MITSUBISHI INTELLIGENT POWER MODULES


PM25RSB120

FLAT-BASE TYPE
INSULATED PACKAGE



1. V_{UPC} 11. W_P
2. UF_O 12. V_{WPI}
3. U_P 13. V_{NC}
4. V_{UPI} 14. V_{NI}
5. V_{VPC} 15. B_R
6. VF_O 16. U_N
7. V_P 17. V_N
8. V_{VPI} 18. W_N
9. V_{WPC} 19. F_O
10. WF_O






Outline Drawing and Circuit Diagram

Dimensions	Inches	Millimeters
A	3.96 ± 0.04	100.5 ± 1.0
B	3.48 ± 0.02	88.5 ± 0.5
C	2.76 ± 0.04	70.0 ± 1.0
D	2.30 ± 0.02	58.5 ± 0.5
E	1.191 ± 0.02	30.25 ± 0.5
F	0.83	21.0
G	0.75	19.0
H	0.73	18.5
J	0.71	18.0
K	0.69	17.5
L	0.67	17.0
M	0.581	14.76
N	0.541	13.75
P	0.541	13.74

Dimensions	Inches	Millimeters
Q	0.41	10.5
R	0.39	10.0
S	0.394 ± 0.010	10.00 ± 0.25
T	0.39 Dia.	Dia. 10.0
U	0.364	9.25
V	0.24	6.0
W	0.18 Dia.	Dia. 4.5
X	0.16	4.0
Y	0.12	3.0
Z	0.88 ± 0.02	2.25 ± 0.5
AA	0.086 ± 0.02	2.18 ± 0.5
AB	0.079 ± 0.010	2.00 ± 0.25
AC	0.06	1.5
AD	0.01 ± 0.02	0.25 ± 0.5



Description:
Mitsubishi Intelligent Power Modules are isolated base modules designed for power switching applications operating at frequencies to 20 kHz. Built-in control circuits provide optimum gate drive and protection for the IGBT and free-wheel diode power devices.

Features:
- ☐ Complete Output Power Circuit
- ☐ Gate Drive Circuit
- ☐ Protection Logic
  - – Short Circuit
  - – Over Current
  - – Over Temperature
  - – Under Voltage

Applications:
- ☐ Inverters
- ☐ UPS
- ☐ Motion/Servo Control
- ☐ Power Supplies

Ordering Information:
Example: Select the complete part number from the table below -i.e. PM25RSB120 is a 1200V, 25 Ampere Intelligent Power Module.

Type	Current Rating Amperes	V_{CES} Volts (x 10)
PM	25	120

MITSUBISHI ELECTRIC

This datasheet has been downloaded from http://www.digchip.com at this page

Absolute Maximum Ratings, T_j = 25°C unless otherwise specified

	Symbol	Ratings	Units
Power Device Junction Temperature	T_j	-20 to 150	°C
Storage Temperature	T_{stg}	-40 to 125	°C
Case Operating Temperature	T_C	-20 to 100	°C
Mounting Torque, M4 Mounting Screws	—	0.98 ~ 1.47	N · m
Module Weight (Typical)	—	330	Grams
Supply Voltage Protected by OC and SC (V_D = 13.5 - 16.5V, Inverter Part, T_j = 125°C)	$V_{CC(prot.)}$	800	Volts
Isolation Voltage (Main Terminal to Baseplate, AC 1 min.)	V_{iso}	2500	Vrms

Control Sector

Supply Voltage (Applied between V_{UP1}-V_{UPC}, V_{VP1}-V_{VPC}, V_{WP1}-V_{WPC}, V_{N1}-V_{NC})	V_D	20	Volts
Input Voltage (Applied between U_P-V_{UPC}, V_P-V_{VPC}, W_P-V_{WPC}, U_N · V_N · W_N · B_r-V_{NC})	V_{CIN}	20	Volts
Fault Output Supply Voltage Applied between (U_{FO}-V_{UPC}, V_{FO}-V_{VPC}, W_{FO}-V_{WPC}, F_O-V_{NC})	V_{FO}	20	Volts
Fault Output Current (Sink Current at U_{FO}, V_{FO}, W_{FO} and F_O Terminal)	I_{FO}	20	mA

IGBT Inverter Sector

Collector-Emitter Voltage (V_D = 15V, V_{CIN} = 15V)	V_{CES}	1200	Volts
Collector Current, (T_C = 25°C)	I_C	25	Amperes
Peak Collector Current, (T_C = 25°C)	I_{CP}	50	Amperes
Supply Voltage (Applied between P - N)	V_{CC}	900	Volts
Supply Voltage, Surge (Applied between P - N)	$V_{CC(surge)}$	1000	Volts
Collector Dissipation	P_C	132	Watts

Brake Sector

Collector-Emitter Voltage	V_{CES}	1200	Volts
Collector Current, (T_C = 25°C)	I_C	10	Amperes
Peak Collector Current, (T_C = 25°C)	I_{CP}	20	Amperes
Supply Voltage (Applied between P - N)	V_{CC}	900	Volts
Supply Voltage, Surge (Applied between P - N)	$V_{CC(surge)}$	1000	Volts
Collector Dissipation	P_C	62	Watts
Diode Forward Current	I_F	10	Amperes
Diode DC Reverse Voltage	$V_{R(DC)}$	1200	Volts

Electrical and Mechanical Characteristics, T_j = 25°C unless otherwise specified

Characteristics	Symbol	Test Conditions	Min.	Typ.	Max.	Units
Control Sector						
Over Current Trip Level Inverter Part	OC	-20°C ≤ T ≤ 125°C, V_D = 15V	32	62	—	Amperes
Over Current Trip Level Brake Part			15	30	—	Amperes
Short Circuit Trip Level Inverter Part	SC	-20°C ≤ T ≤ 125°C, V_D = 15V	—	101	—	Amperes
Short Circuit Trip Level Brake Part			—	41	—	Amperes
Over Current Delay Time	$t_{off(OC)}$	V_D = 15V	—	10	—	µs
Over Temperature Protection	OT	Trip Level	111	118	125	°C
	OT_r	Reset Level	—	100	—	°C
Supply Circuit Under Voltage Protection	UV	Trip Level	11.5	12.0	12.5	Volts
	UV_r	Reset Level	—	12.5	—	Volts
Supply Voltage	V_D	Applied between V_{UP1}-V_{UPC}, V_{VP1}-V_{VPC}, V_{WP1}-V_{WPC}, V_{N1}-V_{NC}	13.5	15	16.5	Volts
Circuit Current	I_D	V_D = 15V, V_{CIN} = 15V, V_{N1}-V_{NC}	—	44	60	mA
		V_D = 15V, V_{CIN} = 15V, V_{XP1}-V_{XPC}	—	13	18	mA
Input ON Threshold Voltage	$V_{th(on)}$	Applied between	1.2	1.5	1.8	Volts
Input OFF Threshold Voltage	$V_{th(off)}$	U_P-V_{UPC}, V_P-V_{VPC}, W_P-V_{WPC}, U_N · V_N · W_N · B_r-V_{NC}	1.7	2.0	2.3	Volts
PWM Input Frequency	f_{PWM}	3-ϕ Sinusoidal	—	15	20	kHz
Fault Output Current	$I_{FO(H)}$	V_D = 15V, V_{FO} = 15V	—	—	0.01	mA
	$I_{FO(L)}$	V_D = 15V, V_{FO} = 15V	—	10	15	mA
Minimum Fault Output Pulse Width	t_{FO}	V_D = 15V	1.0	1.8	—	ms

Electrical and Mechanical Characteristics, T_j = 25°C unless otherwise specified

Characteristics	Symbol	Test Conditions	Min.	Typ.	Max.	Units
IGBT Inverter Sector						
Collector Cutoff Current	I_{CES}	$V_{CE} = V_{CES}$, T_j = 25°C	—	—	1.0	mA
		$V_{CE} = V_{CES}$, T_j = 125°C	—	—	10	mA
Emitter-Collector Voltage	V_{EC}	$-I_C$ = 25A, V_D = 15V, V_{CIN} = 5V	—	2.5	3.5	Volts
Collector-Emitter Saturation Voltage	$V_{CE(sat)}$	V_D = 15V, V_{CIN} = 0V, I_C = 25A	—	2.5	3.5	Volts
		V_D = 15V, V_{CIN} = 0V, I_C = 25A, T_j = 125°C	—	2.2	3.2	Volts
Inductive Load Switching Times	t_{on}	V_D = 15V, V_{CIN} = 0 ↔ 15V, V_{CC} = 600V, I_C = 25A, T_j = 125°C	0.5	1.0	2.5	µs
	t_{rr}		—	0.15	0.3	µs
	$t_{C(on)}$		—	0.4	1.0	µs
	t_{off}		—	2.0	3.0	µs
	$t_{C(off)}$		—	0.7	1.2	µs
Brake Sector						
Collector-Emitter Saturation Voltage	$V_{CE(sat)}$	V_D = 15V, V_{CIN} = 0V, I_C = 10A, T_j = 25°C	—	2.8	3.8	Volts
		V_D = 15V, V_{CIN} = 0V, I_C = 10A, T_j = 125°C	—	2.5	3.5	Volts
Diode Forward Voltage	V_{FM}	$-I_C$ = 10A, V_D = 15V, V_{CIN} = 5V	—	2.5	3.5	Volts
Collector Cutoff Current	I_{CES}	$V_{CE} = V_{CES}$, T_j = 25°C	—	—	1	mA
		$V_{CE} = V_{CES}$, T_j = 125°C	—	—	10	mA

Thermal Characteristics

Characteristic	Symbol	Condition	Min.	Typ.	Max.	Units
Junction to Case Thermal Resistance	$R_{th(j-c)Q}$	Each Inverter IGBT	—	—	0.95	°C/Watt
	$R_{th(j-c)F}$	Each Inverter FWDi	—	—	2.5	°C/Watt
	$R_{th(c-f)Q}$	Each Brake IGBT	—	—	2.0	°C/Watt
	$R_{th(c-f)F}$	Each Brake FWDi	—	—	2.5	°C/Watt
Contact Thermal Resistance	$R_{th(c-f)}$	Case to Fin Per Module, Thermal Grease Applied	—	—	0.036	°C/Watt

Recommended Conditions for Use


Characteristic	Symbol	Condition	Value	Units
Supply Voltage	V_{CC}	Applied across P-N Terminals	0 ~ 800	Volts
	V_D	Applied between V_{UP1}-V_{UPC}, V_{N1}-V_{NC}, V_{VP1}-V_{VPC}, V_{WP1}-V_{WPC}	15 ± 1.5	Volts
Input ON Voltage	$V_{CIN(on)}$	Applied between	0 ~ 0.8	Volts
Input OFF Voltage	$V_{CIN(off)}$	U_P, V_P, W_P, U_N, V_N, W_N, B_r	4.0 ~ V_D	Volts
PWM Input Frequency	f_{PWM}	Using Application Circuit	5 ~ 20	kHz
Minimum Dead Time	t_{dead}	Input Signal	≥ 2.5	µs

PM25RSB120


FLAT-BASE TYPE
INSULATED PACKAGE

Inverter Part


SATURATION VOLTAGE CHARACTERISTICS (TYPICAL)




COLLECTOR-EMITTER SATURATION VOLTAGE CHARACTERISTICS (TYPICAL)




OUTPUT CHARACTERISTICS (TYPICAL)




SWITCHING TIME VS. COLLECTOR CURRENT (TYPICAL)




SWITCHING TIME VS. COLLECTOR CURRENT (TYPICAL)




REVERSE RECOVERY CURRENT VS. EMITTER CURRENT (TYPICAL)




DIODE FORWARD CHARACTERISTICS



OVER CURRENT TRIP LEVEL VS. SUPPLY VOLTAGE (TYPICAL)




OVER CURRENT TRIP LEVEL VS. TEMPERATURE (TYPICAL)




MITSUBISHI ELECTRIC

Inverter Part


FAULT OUTPUT PULSE WIDTH VS. TEMPERATURE (TYPICAL)




CONTROL SUPPLY VOLTAGE TRIP-RESET LEVEL TEMPERATURE DEPENDENCY (TYPICAL)



TRANSIENT THERMAL IMPEDANCE CHARACTERISTICS (Each IGBT)




TRANSIENT THERMAL IMPEDANCE CHARACTERISTICS (Each FWDi)




Brake Part


SATURATION VOLTAGE CHARACTERISTICS (TYPICAL)




COLLECTOR-EMITTER SATURATION VOLTAGE CHARACTERISTICS (TYPICAL)




OUTPUT CHARACTERISTICS (TYPICAL)



DIODE FORWARD CHARACTERISTICS



TRANSIENT THERMAL IMPEDANCE CHARACTERISTICS (Each IGBT)



TRANSIENT THERMAL IMPEDANCE CHARACTERISTICS (Each FWDi)

