
Load Center, ReliaHome PCC4022R

Catalog No.	PCC4022R
Enclosure	Outdoor Type 3R
Rating	225 A convertible, 1-ph 3-W, 120/240
Spaces / circuits	40 / 80
Interrupt	22 kAIC, fully rated
Main wire	#1-300 Cu/Al
Ground kit	TGK42, TNLK20
Dimensions	39.29 x 14.88 x 5.29 in
Modification	175A ReliaHome P-Series main breaker kit - THQMV175F

Substitution / Deviation - engineer confirmation required

Offered in place of a 42-space recessed NEMA 3R panel: ABB's nearest size is 40 spaces, and the NEMA 3R unit is surface-mount only. Requires engineer confirmation.



Representative Image

Catalog No. **PCC4022**

Description: LD CTR CONV 225A 40/80 CU N1 GR PON UL

UPC No 783164692730

Home > Load Center & Meter Combos > Load Centers

ABB ReliaHome makes homes reliable, with ease. We designed our ReliaHome load centers to be installed as fast as possible - and reliable so your customers can leave a job with confidence. They work seamlessly with all our residential circuit breakers, optimizing your stock.

Descriptors

Category	Load Centers
GO Schedule	RV
Grouping	Single Phase - USA

Specifications

# Branch Circuit 250A	40
1" Space	40
1/2" Space	0
Amperage	225 A
Circuit Breaker Style	Plug-On Neutral
Door	Yes
Enclosure	Indoor
Enclosure Type	Indoor, Combination
Factory Installed Ground Kit	YES
Feed	Either
Input/Output Voltage	120/240V ac
Interrupt Rating	22kAIC
Interrupting Capacity Rating	22kAIC
Load Center Type	P-Series+ (PON)
Meter Socket Options: 200 Amp Main Breaker Installed	No
Meter Socket Options: High Amp Mode	None
NEMA Rating	NEMA 1
No of Circuits	80
Phase	1 Phase
Service & Voltage	1 Phase, 3 Wire, 120/240V ac
Wires	3 Wire

Classifications

UL/CUL Listing	UL
----------------	----


by ABB

RESIDENTIAL MAIN CIRCUIT BREAKERS



100 to 225A. THQMV Main breakers are configured to allow top or bottom modification and can be added to ReliaHome™ P-Series, P-Series+, T-Series, PowerMark™ Gold and PowerMark Pro convertible load centers.

FEATURES AND BENEFITS

- Every breaker exceeds UL, NEMA, ANSI, CSA requirements
- 65° C/75° C Conductor Rating
- Handle trips to center position, giving a clear indication of a tripped breaker
- Handle requires reasonable effort to operate
- Handle's vertical orientation allows it to be mounted for top or bottom feed applications
- 22KAIC interrupting capacity

APPLICATIONS

- 200 amp ReliaHome P-Series and P-Series+
- 200 amp legacy PowerMark Gold Pro convertible load centers
- For 125 amp P-Series and P-Series+ convertible load centers. use TQMH000F and desired plug-on breaker (THHQL21XX)
- For 125 amp legacy PowerMark Gold Pro convertible load centers. Use TQMH000 and desired plug on breaker (THHQL21XX)