

Post-Visit Report

Summary of onsite work completed, current risk status for each finding, and your Month 1 remote team action plan.

PREPARED FOR

Tom — 11611 Heathcliff Drive

11611 Heathcliff Drive · Prepared May 2026

VISIT DATE

May 1, 2026

TECHNICIAN

Sai

HOURS ONSITE

9.5 hrs

OVERALL RISK

HIGH

POST-VISIT RISK RATING

HIGH RISK

Significant progress achieved on credentials, device hardening, and remote support setup. Network-layer security tasks remain open pending Orbi admin access recovery. Two CRITICAL items require immediate Month 1 attention.

Visit Summary

TASKS COMPLETED 28 of ~50 scoped items	DEVICES MIGRATED 10 to ORBI-68 Trusted	2FA ACCOUNTS 6 / 9 3 deferred	CRITICAL OPEN ITEMS 2 Orbi + HikVision
--	--	---	--

Your technician Sai was onsite on **May 1, 2026** (8:15 AM–5:45 PM) for the Home Cybersecurity Remediation engagement. The authorization form was signed and on file before any configuration work began.

The visit covered credentials and account security, a complete device-by-device audit, endpoint hardening on your Dell XPS, and full remote support setup. The primary blocker for the day was the Orbi RBR50 admin portal — credentials were not accepted, which prevented network segmentation, firewall rule configuration, and full HikVision hardening. Those tasks have been escalated as the top priority items for your remote team in Month 1.

What Was Accomplished on May 1

ITEM	STATUS
CREDENTIALS & ACCOUNT SECURITY	
Password manager confirmed active on all devices (Microsoft Edge on Dell XPS, iOS)	✓ Completed
New Orbi WiFi password generated (20+ chars) — stored in password manager only	✓ Completed
Orbi admin password changed — stored in password manager only	✓ Completed
AT&T gateway admin — carrier-locked; Device Access Code is ISP-managed	✓ Documented
2FA confirmed on 6 accounts (primary email ×2, Apple ID, Amazon/Ring, bank, password manager)	✓ Completed
2FA on brokerage and AT&T account — deferred	✗ Month 1
DEVICE AUDIT & FIRMWARE	
AT&T Gateway 5268AC FXN — firmware audited (ISP-managed, current)	✓ Audited
Vizio TV (Kitchen) — firmware updated from 3.710 to 3.720	✓ Updated
Samsung TVs, Apple TV, Dell XPS, Ring, NVR, STBs, printers — all inventoried	✓ Inventoried
Orbi RBR50 — admin portal inaccessible (all credentials rejected)	✗ CRITICAL — Month 1
HikVision cameras — firmware 4.17.0.1224564 noted; hardening deferred	✗ CRITICAL — Month 1
Unknown Ethernet device (MAC: cc:0d:ec:5e:ec:9a) — identity not confirmed	✗ HIGH — Month 1

ITEM	STATUS
NETWORK MIGRATION & SEGMENTATION	
Dell XPS, client phones, Apple TV migrated to ORBI-68 Trusted	✓ Completed
All smart TVs, HP printers migrated to ORBI-68 Trusted	✓ Completed
Ring doorbell reconnected to ORBI-68 after password change — Live View confirmed	✓ Completed
All connectivity tests passed (printing, casting, streaming, Ring, NVR, STBs)	✓ All passed
IoT SSID creation — client preferred single network; Orbi admin also unavailable	✗ HIGH — Month 1
AT&T gateway Wi-Fi still broadcasting Orbi68 (dual-broadcast risk) — deferred	✗ HIGH — Month 1
DELL XPS ENDPOINT HARDENING	
Windows 11 fully updated; automatic updates confirmed enabled	✓ Completed
Microsoft Defender active with cloud protection enabled	✓ Confirmed
Dell firmware updated via Dell Update utility	✓ Updated
OneDrive backup confirmed active (initial scope: machine-level)	✓ Confirmed
BitLocker (disk encryption) — found DISABLED; enabling deferred to Month 1	✗ HIGH — Month 1
Browser password migration to password manager — deferred	✗ Month 1
REMOTE SUPPORT HANDOFF	
Technician remote access tool installed on Dell XPS and tested working	✓ Completed
Technician admin account created (RMG-Barbara-Win7-Dell) — separate from your account	✓ Completed
Client briefed on 24/7 remote support model, notifications, and escalation path	✓ Completed
Technician welcome email and portal login delivered	✓ Completed

Current Risk Status — All Findings

The table below shows the post-visit risk rating for every finding from the original assessment. Ratings reflect work completed on May 1 plus residual risk from open items.

FINDING	POST-VISIT RATING	STATUS & RESIDUAL RISK
F-01 — WiFi Credentials	MEDIUM	New Orbi WiFi and admin passwords set and stored in password manager only. Residual: Orbi admin portal access not yet confirmed working; AT&T gateway also still broadcasting the same SSID (Orbi68), creating a bypass path.
F-02 — AT&T Gateway	MEDIUM	Firmware is ISP-managed and current. WPA2-AES in use. Residual: WPA3 not supported on this hardware model (5268AC FXN). WPS still enabled — should be disabled. AT&T Wi-Fi broadcasting on both bands.
F-03 — HikVision Cameras	CRITICAL	No hardening completed during visit. Cloud relay (Hik-Connect) appears active on client phone. Credentials on NVR unverified. No firewall isolation implemented. CVE-2025-66177 patch status unconfirmed on firmware 4.17.0.1224564. Highest single priority for remote team.
F-04 — Network Segmentation	HIGH	IoT SSID not created (client preferred single network; Orbi admin also unavailable). Firewall rules not configured or verified. All devices currently on a single flat network. AT&T dual-broadcast creates additional bypass risk.
F-05 — NetworX Alarm	LOW	No IP-based management interface found. Alarm is operational. Network exposure is minimal. No action required.
F-06 — Smart TVs	MEDIUM	Vizio Kitchen TV firmware updated. All accessible TVs migrated to ORBI-68 Trusted. Residual: Master BR Vizio TV was not accessible — status unknown. TVs remain on Trusted (not isolated IoT) pending segmentation.
F-07 — HP Printers	MEDIUM	Printing from Dell XPS confirmed working. Firmware versions noted; updates not attempted. Admin credential status on both printers unknown — remote team to verify and change defaults.
F-08 — Dell XPS Hardening	HIGH	OS updates applied, Defender active, Dell firmware updated, remote access installed. Residual: BitLocker (disk encryption) is DISABLED — all data on the laptop is at risk if the device is lost or stolen. Browser password migration incomplete. OneDrive backup active but encryption passphrase not configured.
F-09 — Ring Doorbell	MEDIUM	Ring successfully reconnected after WiFi password change. Live View confirmed working. Residual: firmware version not captured; Ring remains on Trusted network and should move to IoT when segmentation is created.
F-10 — AT&T Redundant AP	HIGH	AT&T Motorola AP (MAC: f8:8b:37:9a:6e:e9, SSID: ATT_Motorola_AP_9A6EE9) identified on AT&T gateway Port 4. Login not possible during visit. Purpose and necessity not confirmed — may be redundant once Orbi is fully configured. Remote team to assess and disable if not needed.

FINDING	POST-VISIT RATING	STATUS & RESIDUAL RISK
F-11 — Orbi WiFi	CRITICAL	Admin portal (http://10.0.0.1) was reachable but all credentials were rejected throughout the visit. Orbi firmware, UPnP, remote management, and port-forward audit all remain unverified. This is the single biggest blocker for full security implementation. Recovery of Orbi admin access is the top Month 1 priority.
F-12 — Unknown Ethernet Device	HIGH	An active Ethernet device (MAC: cc:0d:ec:5e:ec:9a) was found connected to the network. Identity was not confirmed during the visit. This device must be identified before network segmentation is finalized — an unknown device on a home network is a meaningful risk.
F-13 — Laptop Backup	MEDIUM	OneDrive is active and running. Residual: OneDrive does not use a client-set encryption passphrase. Specific folder scope not confirmed. Remote team to review backup coverage and encryption options.

Month 1 Remote Team Action Plan

The items below will be worked by your assigned Technijian remote support team in your first month of service. Items are listed in priority order. You do not need to take any action on these — the remote team will contact you to schedule sessions as needed.

Two CRITICAL items require action before anything else: (1) Recovering the Orbi admin credentials unlocks the network-layer security work; (2) HikVision camera hardening addresses the highest single risk in the home. Both are scheduled for Month 1.

PRIORITY	ACTION ITEM	NOTES
CRITICAL	Recover Orbi RBR50 admin credentials and complete all Orbi configuration: UPnP disable, remote management disable, port-forward audit, firmware verification, firewall rule implementation, IoT SSID (if client agrees)	Everything in the network-layer plan depends on this. Remote team will attempt credential recovery via Netgear account reset; factory reset is the fallback if recovery fails.
CRITICAL	Complete all HikVision / NVR hardening: verify Hik-Connect cloud relay status and discuss replacement access method with client; check Platform Access, DDNS, NAT/UPnP on NVR; block outbound internet from camera IPs at firewall; document camera MACs and model numbers; verify CVE-2025-66177 patch	All 4 cameras have unverified credential and network exposure status. Cloud relay is likely active. This is F-03 CRITICAL from the original assessment.
HIGH	Enable BitLocker disk encryption on the Dell XPS primary drive; provide recovery key in sealed envelope	BitLocker was found disabled. All laptop data is unprotected against physical theft until this is enabled.
HIGH	Disable AT&T gateway Wi-Fi (2.4 GHz and 5 GHz) after confirming Orbi coverage; disable WPS on AT&T gateway	Requires Orbi admin first. AT&T dual-broadcast currently allows devices to bypass any Orbi segmentation.
HIGH	Identify unknown Ethernet device (MAC: cc:0d:ec:5e:ec:9a) connected to AT&T Port 4	Identity must be confirmed before finalizing network segmentation. Could be a smart home hub, game console, or unrecognized device.
HIGH	Assess AT&T Motorola AP (MAC: f8:8b:37:9a:6e:e9) — confirm purpose or disable if redundant	Device is connected to AT&T gateway Port 4. Purpose unknown; likely redundant once Orbi is properly configured.
HIGH	Add all credentials to Technijian shared vault: Orbi admin, Dell XPS admin account (RMG-Barbara-Win7-Dell), HP Officejet, HP Deskjet, NVR	Remote team can only provide effective support when credentials are in the shared vault. Orbi and NVR pending; HP printers pending verification.
MEDIUM	Enable IoT network segmentation (once Orbi access restored): create IoT SSID; migrate HikVision NVR, Ring, smart TVs, and printers to isolated segment; implement firewall rules	Client preferred a single WiFi network during the visit. Remote team will re-present the security case for segmentation. Implementation requires Orbi admin access.
MEDIUM	Enable 2FA on brokerage and AT&T accounts	Both accounts were deferred during the visit. Remote team to follow up with client.

PRIORITY	ACTION ITEM	NOTES
MEDIUM	Complete browser password migration: export from iCloud Keychain to current password manager; disable browser password saving; run password audit	Client had passwords in iCloud Keychain. Migration to be assisted by remote team at next scheduled session.
MEDIUM	Verify HP printer credentials and firmware (OfficeJet Pro 9015e and DeskJet 3755)	Default credential status unknown. Firmware not updated. Remote team to access admin portals and apply updates.
MEDIUM	HikVision camera replacement planning — present client with replacement options; coordinate with preferred installer	Replacement within 90 days strongly recommended. See next section for details.
MEDIUM	Confirm and document client preferences: preferred contact method, best hours for remote sessions, confirm backup encryption options (OneDrive), confirm backup folder scope	To be captured at Month 1 handoff call.
LOW	Verify Master Bedroom Vizio TV connectivity and firmware	Device was inaccessible on visit day. Remote team to verify when client makes it accessible.
LOW	Confirm technician laptop (TE-HQ-LPT-41, MAC: 98:fc:84:e6:16:51) was removed from AT&T network device list	Likely Sai's laptop from the visit. Should not appear in permanent device inventory.

Decisions We Need From You

The following items are your decisions to make. We will support whichever path you choose, but a decision allows us to schedule the right work. No urgency required — your remote team will discuss each of these at the Month 1 call.

1. HikVision Camera Replacement — Recommended within 90 Days

This is our strongest recommendation from the visit. HikVision cameras are actively being targeted at internet scale due to known vulnerabilities. All four exterior cameras (front south, back north, front north, pool area) and a fifth patio camera are affected.

Even after we harden the current cameras (cloud relay off, firewall isolation, credentials changed), HikVision's risk profile remains elevated due to the company's ownership structure and its placement on the U.S. FCC Covered List. Our recommendation is to plan a replacement within 90 days.

What you need to decide: Would you like Technijian to recommend replacement cameras and coordinate with an installer, or do you have a preferred vendor or installer you'd like to use? We can work with either approach.

2. Network Segmentation (IoT SSID)

During the visit, you indicated you preferred a single WiFi network rather than separate Trusted/IoT/Guest segments. We understand the appeal — one network is simpler to manage day to day.

Our recommendation is still to create an IoT segment, for one specific reason: the HikVision cameras and NVR need to be isolated from your laptop and phones. Even after the cameras are replaced, the principle of putting surveillance equipment and smart TVs on a separate network from your financial and personal devices is a meaningful security improvement.

What you need to decide: Would you like us to set up a separate IoT-only SSID (hidden from normal view, so it's not cluttering your WiFi list)? Or would you prefer we proceed only with isolating the cameras at the firewall level without creating additional SSIDs? Either approach is achievable once we have Orbi admin access back.

3. Brokerage and AT&T Account 2FA

Two accounts didn't get 2FA enabled during the visit. Both are straightforward — the remote team can walk through either one in a 10-minute phone or screen-share session.

- **Brokerage account:** Client preferred to handle this independently. If you'd like the remote team to walk through it with you, just let them know at the Month 1 call.
- **AT&T account:** Login wasn't available during the visit. Remote team can assist when you have AT&T account credentials available.

Network Configuration as of May 1, 2026

For reference, this is the confirmed network topology and device list as of the end of the visit.

Network Topology

LAYER	DEVICE	IP / MAC	NOTES
Internet Gateway	AT&T Gateway 5268AC FXN	192.168.1.254 / E0:22:03:67:91:18	Primary active router. Carrier-locked firmware. AT&T Wi-Fi broadcasting Orbi68 — to be disabled.
Mesh Router	Orbi RBR50 (Primary)	10.0.0.1 / BC:A5:11:20:E3:04	Downstream of AT&T in router mode. Admin access BLOCKED — top Month 1 priority.
Mesh Node	Orbi Satellite	—	Managed via Orbi primary. Pending admin access recovery.
NVR	Northern NVR	10.0.0.2 / 08:41:89:0C:FE:6E	Internal camera subnet: 192.168.254.1/24. All 4+ camera feeds confirmed visible.
Unknown	Unknown Ethernet Device	MAC: CC:0D:EC:5E:EC:9A	Active on network. Identity not confirmed. Must be identified.

Active SSIDs Post-Visit

SSID	SOURCE	STATUS	NOTES
ORBI-68	Orbi (5 GHz)	Active	Trusted network. New strong password set and stored in password manager.
ORBI68-guest	Orbi (2.4 GHz)	Active	Guest network. Client isolation enabled.
Orbi68 (both bands)	AT&T Gateway	Risk — to be disabled	AT&T broadcasting same SSID as Orbi. Devices may connect here and bypass any Orbi segmentation. To be disabled once Orbi admin access is restored and device migration confirmed complete.
ATT_Motorola_AP_9A6EE9	AT&T Motorola AP	Assess — likely redundant	Separate AP on AT&T Port 4. Purpose to be confirmed by remote team.

Device Network Assignments Post-Visit

DEVICE	NETWORK	STATUS
TRUSTED DEVICES (ORBI-68)		
Dell XPS Laptop	ORBI-68	✓ Migrated — printing confirmed
Client's phone	ORBI-68	✓ Migrated — internet confirmed
Spouse's phone	ORBI-68	✓ Migrated

DEVICE	NETWORK	STATUS
Apple TV (Family Room)	ORBI-68	✓ Migrated — streaming confirmed
Samsung TV (Family Room)	ORBI-68	✓ Migrated — casting confirmed
Vizio TV (Kitchen)	ORBI-68	✓ Migrated — firmware updated
Samsung TV (Tom's Office)	ORBI-68	✓ Migrated
HP OfficeJet Pro 9015e	ORBI-68	✓ Migrated — printing confirmed
HP DeskJet 3755	ORBI-68	✓ Migrated
Ring Doorbell	ORBI-68	✓ Reconnected — Live View confirmed
WIRED / CARRIER-MANAGED (NO ACTION REQUIRED)		
HikVision Cameras ×4+	Wired to NVR (192.168.254.x)	Hardening deferred — CRITICAL Month 1
AT&T U-verse STBs (×4)	HomePNA / Coax (carrier-managed)	✓ Video signal confirmed all units
NetworX NX8V2 Alarm	No IP interface	✓ Operational — no action required
DEFERRED / NOT ACCESSIBLE		
Vizio TV (Master Bedroom)	Unknown — not accessible	Deferred to Month 1
Unknown Ethernet Device (cc:0d:ec:5e:ec:9a)	Unknown — on AT&T LAN	Must be identified before segmentation

What Happens Next

Your Month 1 Remote Support Schedule

TIMEFRAME	ACTION	WHO
Within 24 hours of visit	Technician (Sai) logs all deferred items as tickets in Technijian ticketing system	Sai (Technician)
Within 5 business days	Your assigned remote pod contacts you to schedule Month 1 handoff call	Technijian Remote Team
Month 1 — Session 1	Orbi admin recovery; BitLocker enablement; disable AT&T Wi-Fi; identify unknown device	Remote Team
Month 1 — Session 2	HikVision / NVR hardening; browser password migration; printer credential verification	Remote Team
Month 1 — Ongoing	Windows updates (monthly), backup verification, security log review	Remote Team (proactive)
Months 1-3	HikVision replacement planning and coordination (pending your decision)	Remote Team + installer

How to Reach Us

CHANNEL	CONTACT	BEST FOR
Phone	949.379.8501	Urgent issues, anything requiring live conversation
Email	billing@technijian.com	Non-urgent requests, questions, documentation
Client Portal	See welcome email for link	Ticket status, session scheduling, report archive

One thing to keep in mind: when you see a remote-access notification pop up on your Dell XPS, it means the Technijian remote team is starting a scheduled support session. This is expected and normal. If you ever see a notification at a time you didn't expect or schedule, call us immediately at 949.379.8501 — that's the right response even if it turns out to be a false alarm.

This report was prepared by Technijian, Inc. based on the onsite visit completed May 1, 2026 by technician Sai. All work performed was within the scope authorized by the client-signed authorization form. For questions about this report, contact your Technijian account manager at 949.379.8501 or billing@technijian.com.