

Description

The 6002+ analogue addressable control and indicating equipment forms the central part of a fire detection and alarm system. The 6002+ is compatible with Numens addressable devices and supports up to 125 devices per loop. The 6002+ is fitted with 2-loops.

Default configuration programming facilitates out-of-box installation and rapid commissioning. A powerful and versatile cause-and-effect PC-based programming tool enables rapid customization with software for sites that require special operating features.

The 6002+ control and indicating equipment provides fire detection and alarm system designers with a premium product for life safety and property protection applications.

Features

- Two addressable loops default
 - Supports 125 addressable devices per loop
 - Supports wireless detection devices
 - Automatic device detection on start-up
 - Automatic device type-code verification
 - 128 configurable zones
 - 32 zone fire alarm LED indicators, expandable to 128 zone indicators
 - 32 addressable audio/visual alarm devices per loop
 - 2 independently programmable non-addressable sounder output circuits
 - Manual activation of alarm devices
 - Configurable timer to delay Fire Alarm Condition output activation
 - 2 programmable unmonitored Fire Alarm Condition relay outputs
 - 1 programmable unmonitored Fault Condition relay output
 - Supervised auxiliary DC 24 V output
 - 3 Access Levels
 - Configurable day/night mode
 - Backlit LCD display providing 4 rows of 40 characters
 - 3000 event history log
 - Multiple language support
 - Attractive designer enclosure available in cream or red
 - Surface mounting
 - Easy installation
- Supports up to 16 repeater panels

Compliance

The 6002+ control and indicating equipment has the following compliance ^a.

	EN 54-2 ^b	EN 54-4 ^c	CE ^d
6002+ -01	✓	✓	✓

^a Third-party conformance assessment has not been undertaken.

^b EN 54-2 Control and indicating equipment

^c EN 54-4 Power supply equipment

^d Conformité Européenne



6002+ addressable control and indicating equipment

Accessories

The following accessories are compatible with 6002+ control and indicating equipment.

Description	Part Number	Datasheet
Addressable repeater panel, LCD display, 24V	6002-06	31-0070
Addressable repeater panel, LCD display, AC	6002-07	31-0071
Programming tool	—	—

Specifications

	6002* -01 6002*-11
Power Supply	
Operating voltage	AC (100 ~ 260) V / 50/60 Hz
Mains supply current limit	1.5 A @ AC 230 V
Mains supply fuse	4 A / AC 250 V slow blow (20 mm)
Mains supply fault threshold voltage	≤ AC 60 V
Power supply	4.3 A @ DC 28.5 V
Quiescent current (I_{min})	200 m A @ DC 28.5 V
Maximum continuous output current ($I_{a, max}$)	550 mA
Maximum short-duration output current ($I_{b, max}$)	2.3 A
Standby battery maximum capacity (2 × DC 12 V)	7.2 Ah
Maximum battery current draw @ maximum operating temperature	1.5 A
Battery fuse	10 A resettable (electronic fuse)
Battery fault threshold voltage	< DC 20 V
Battery fault threshold internal resistance ($R_{i, max}$)	0.5 Ω
Addressable Loops	
Addressable loops	2
Number of connected devices per loop	125
Loop current (max)	400 mA
Loop monitoring	Open- and short-circuit
Audio/Visual Alarms	
Configurable audio/visual alarm groups (max)	512
Non-addressable audio/visual alarm device driver	700 mA
Non-addressable audio/visual alarm end-of-line resistor	10 kΩ
Alarm zone monitoring	Open- and short-circuit
Alarm zone voltage (max)	DC 29 V
Alarm zone fuse	1.1 A resettable (electronic fuse)
Wireless Transmission Path	
Maximum number of wireless nodes (per loop)	62
Wireless node ID range	1 ~ 124
Wireless radio interconnection operating frequencies	433 MHz, 868 MHz, 915 MHz
Number of selectable radio channels	125
Ancillary Outputs	
Number of programmable output relays	2
Ancillary fire C/O relay	2 x (1.0 A @ DC 30 V / 1 A @ AC 240 V)
Ancillary fault N/C relay	1.0 A @ DC 30 V / 1 A @ AC 240 V
Auxiliary supply	DC (19 ~ 30) V @ 200 mA
Miscellaneous	
Event history log	3000 events
Number of networked repeaters	16
Terminal wiring	(0.4 ~ 2.5) mm ²
Operating temperature	(-5 ~ +40) °C
Operating humidity	(0 ~ 95) % RH, non-condensing
Storage temperature	(-25 ~ +80) °C
Storage humidity	(0 ~ 98) % RH, non-condensing
Dimensions (h × w × d)	(485 × 465 × 155) mm
Weight (excluding batteries)	10.0 kg

Ordering Information

	Cream Enclosure	Red Enclosure
6002*-01	✓	—
6002*-11	—	✓

View the complete range of products at www.numens.com

