Message 5: GET_PANEL_RANGE_INFO

The GET_PANEL_RANGE_INFO message retrieves panel capability and range information. This message helps determine what features a panel supports.

Note: This message is currently not implemented in the C++ backend.

Overview

Action: `GET_PANEL_RANGE_INFO` (5) **Direction:** Frontend → Backend **Location:** Not implemented
Purpose: Query panel capabilities and supported ranges **Status:** ⚠️ Not implemented

Expected Request Format

JSON Structure:

```JSON
{
  "action": "GET_PANEL_RANGE_INFO",
  "panelId": 0
}
```

Expected Response Format

JSON Structure:

JSON


```
{
  "action": "GET_PANEL_RANGE_INFO_RES",
  "panelId": 0,
  "data": {
    "inputCount": 64,
    "outputCount": 64,
    "variableCount": 64,
    "programCount": 16,
    "pidCount": 16,
    "scheduleCount": 32,
    "holidayCount": 32,
    "monitorCount": 12,
    "graphicCount": 20
  }
}
```


Implementation Status

This message type is defined in the WEBVIEW_MESSAGE_TYPE enum but does not have a corresponding case handler in BacnetWebView.cpp HandleWebViewMsg function.

To implement:

1. Add case handler for GET_PANEL_RANGE_INFO
2. Read panel configuration from g_Device_Basic_Setting
3. Return count limits for each entry type

Workaround

Until implemented, use hardcoded constants:

```typescript
const PANEL_RANGES = {
  inputs: 64,
  outputs: 64,
  variables: 64,
  programs: 16,
  controllers: 16,
  schedules: 32,
  holidays: 32,
  monitors: 12,
  graphics: 20
};
```

See Also

- Platform Overview - Architecture
- Data Structures - Entry type constants