

SMU

System Management Unit

Beta release | Open-source RTL | Apache 2.0

HIGHLIGHTS

- Composes OCAH management, debug/test, and optional security subsystems
- Full reference configuration integrates SMC, SEP, DTP, and a 3-by-3 AXI4 fabric
- Alternate no-SEP configuration preserves SMC, DTP, and external AXI interfaces
- Runtime-programmed SMC/SEP apertures with fixed, loop-free connectivity
- Integrated reset, clock-stop, lifecycle, mailbox, interrupt, and debug handoffs
- Technology-neutral core plus an open reference wrapper for macro substitution

SYSTEM ROLE


SMU is the composed management boundary between the chiplet system fabric, external debug and test equipment, adopter implementation resources, and the OCAH SMC, DTP, and optional SEP. It supplies their integration wiring and control handoffs; the adopter owns chiplet-level address assignment, clocks, power/reset sequencing, pads, technology macros, firmware policy, and product security authorization.

OVERVIEW

The System Management Unit (SMU) is a composite module providing a standardized OCAH compliant chiplet interface combining SEP, SMC, and DTP sub-blocks into a single instantiable subsystem with standardized interfaces to a user defined subsystem. The SMU provides chiplet functions such as clock, voltage and reset management in addition to Root of Trust (RoT) services in a physically isolated environment.

SEP inclusion is selected independently for each SMU instance. A multi-chiplet system may contain SEP-equipped primary and secondary chiplets, together with secondary chiplets that omit SEP. The integrator defines the security hierarchy and the propagation of lifecycle and debug controls between chiplets.

SYSTEM CONTEXT



AT A GLANCE

Feature	Defaults
Main configuration	4-core SMC + SEP + DTP
Alternate configuration	4-core SMC + DTP
Full-config fabric	3 AXI4 inputs by 3 outputs; 2 runtime address rules
AXI4 boundary	56-bit address, 64-bit data, 12-bit user
AXI IDs	8-bit input; 10-bit crossbar output; 6-bit SMC/SEP target
External interrupts to SMC	256
Mailbox instances	32 SMC; 8 SEP when present
External trigger interfaces	16 CTPs; 8 internal CTs; 8 clock-stop requests

CAPABILITIES

Composition and control

- SMC and DTP always instantiated; SEP selected at elaboration
- Internal wiring for DTP-to-SMC debug fabric and OTP, DTP-to-SEP debug and OTP, SEP-to-SMC mailbox/reset/security status, and SMC-to-DTP cross-trigger control
- SMC-owned primary reset sequencing, 32 subsystem reset/isolation slots, external boot/repair gate, watchdog handoffs, and DTP clock-stop output
- The SEP lifecycle controller enables or disables DTP debug and test paths

Full-configuration fabric

- SEP can target SMC or the external output; SMC can target SEP or the external output; the external input can target SEP or SMC
- Runtime SMC and SEP aperture base/size rules; no same-port loops and no external-input-to-external-output path
- Unmatched SMC/SEP outbound traffic uses the external output; unmatched external inbound traffic receives a decode error
- AXI ID-width conversion at SMC/SEP targets; atomic operations disabled
- Fixed 1 GiB SEP-to-SMC local-alias window in the checked-in RTL

No-SEP behavior

- Direct external-to-SMC and SMC-to-external AXI paths retain the public widths
- DTP and its primary JTAG interface remain present; DTP debug and test paths are not lifecycle-disabled
- SEP memory, entropy, I/O, mailbox, lifecycle-error, and status ports are tied to defined inactive values; the SEP aperture reports zero size
- SEP OTP debug accesses receive DECERR and the SEP secondary TAP has no target

INTERFACES AND CONFIGURATION

Feature	Integration options
Clocks and resets	SMU, reference, peripheral, telemetry, SEP watchdog, and entropy-sample clocks; cold reset, power-good, boot/repair, DFT, and reset outputs
System fabric	Inbound and outbound 56-address/64-data AXI4; programmable SMC and SEP aperture status; adopter AXI/AXI4-Lite extensions
Debug and triggers	Primary JTAG, boundary/ijTAG/secondary scan chains, external reset-control slice, 16 CTPs, 8 local trigger paths, and 8 clock-stop requests
Management	256 external interrupts, 32 reset/isolation slots, 32 SMC mailbox interrupts, GPIO/UART events, telemetry, timer, straps, and RAS status
Technology interfaces	SMC/SEP ROM and SRAM, eFuse/OTP, I3C table memory, trace memory, GPIO pads, PLL/PVT, entropy, and SEP crypto-memory boundaries
Build-time	SEP configuration, external entropy sources, JTAG functions/identity, SMC CPU selection, and SEP memory/Adams Bridge options

INTEGRATION DEPENDENCIES

- Decide whether or not to include SEP.
- Assign non-overlapping chiplet envelopes and program non-overlapping SMC/SEP memory apertures. Change memory apertures only after outstanding transactions have completed.
- If SEP is not configured, the default tie-offs do not provide security authorization; define a no-SEP debug and security policy. Omitting SEP does not automatically place the chiplet under another SEP’s protection.
- Replace zero-valued JTAG identity and SEP security-token fields; supply reviewed firmware, provisioning, recovery, and update policy.
- Provide production clocks, reset/CDC constraints, power sequencing, pads, memories, OTP/eFuse, sensors, entropy, I/O, and physical implementation. Reference-wrapper models and error-slave terminations are examples only.
- Connect or terminate every external fabric, scan, trigger, interrupt, mailbox, reset/isolation, macro, and adopter-extension interface.

VERIFICATION AND MATURITY

The OCAH documentation website publishes the current verification and maturity status. Hosted cocotb/PyUVM smoke and regression use the bare `smu` DUT with `SEP=0`; the 53-test `sep0_all` group exercises SMC/DTP composition, direct external AXI, filters, ID conversion, atomic rejection, JTAG-to-AXI/OTP, reset, mailbox, cross-trigger, and clock-stop scenarios. This does not credit the full 3-by-3 fabric or live SEP interoperability.

A separate `smu_wrapper` catalog has four smoke entries spanning no-SEP and real-SEP profiles, including firmware and SEP boot-readiness observations. Additional real-SEP groups are separately enrolled or blocked and are not part of hosted SMU signoff. Wrapper results are not combined with bare-SMU results.

There is no agreed functional-coverage closure target or SMU RTL code-coverage configuration. No standards certification, silicon characterization, product security assessment, or portable frequency, area, power, latency, or throughput result is claimed.

DELIVERABLES

- `smu` RTL, packages, crossbar, and Bender manifests
- `smu_wrapper` and open IP-integration examples
- SystemRDL/generated registers and interface documentation
- Integrator guidance, specification, and synthesis constraints
- cocotb/PyUVM core/wrapper environments, firmware, and VLANs
- Apache License 2.0 repository distribution

RESOURCES

Documentation: tenstorrent.github.io/tt-oca-harness
SMU specification: hw/sys/smu/doc/SMU_SPEC.md
Core / reference wrapper: hw/sys/smu/rtl/, hw/top/smu_wrapper.sv
Verification: hw/sys/smu/dv/
Integrator Guide: doc/integrator/
Project: github.com/tenstorrent/tt-oca-harness